



# Service Chain Configuration Mode Commands

The Service Chain configuration mode is a sub-mode of the Global Configuration mode. This sub-mode associates nsh-format to service-chain.

## Command Modes

Exec > Global Configuration > Service Chain Configuration

**configure > service-chain**

Entering the above command sequence results in the following prompt:

```
[local]host_name(config-service-chain) #
```



## Important

The commands or keywords/variables that are available are dependent on platform type, product version, and installed license(s).

- [end, on page 1](#)
- [exit, on page 1](#)
- [nsh-format, on page 2](#)

## end

Exits the current configuration mode and returns to the Exec mode.

## Product

All

## Privilege

Security Administrator, Administrator

## Syntax Description

**end**

## Usage Guidelines

Use this command to return to the Exec mode.

## exit

Exits the current mode and returns to the parent configuration mode.

<b>Product</b>	All
<b>Privilege</b>	Security Administrator, Administrator
<b>Syntax Description</b>	<b>exit</b>
<b>Usage Guidelines</b>	Use this command to return to the parent configuration mode.

## nsh-format

This command associates nsh format with service-chain.

<b>Product</b>	P-GW SAEGW
<b>Privilege</b>	Security Administrator, Administrator
<b>Command Modes</b>	Exec > Global Configuration > Service Chain Configuration <b>configure &gt; service-chain</b>
	Entering the above command sequence results in the following prompt:

```
[local]host_name(config-service-chain)#
```

<b>Syntax Description</b>	<b>[ no ] nsh-format</b> <nsh_format_name>
---------------------------	--

### **no**

Disassociates nsh format with the service-chain configuration.

### **nsh-format**

Associates nsh format with service chain.

### **nsh\_format\_name**

Specifies the name of nsh-format. This is entered as an alphanumeric string of 1 through 63 characters.

<b>Usage Guidelines</b>	Use this command to associate nsh-format with service-chain.
-------------------------	--

### **Example**

The following commands associates a nsh-format to service-chain:

```
nsh-format ns1
```

The following commands disassociates the nsh-format with service-chain:

```
no nsh-format
```