



Attaching Tags to an AP

- Attaching Policy Tag and Site Tag to an AP (CLI), on page 1
- Attaching a Policy Tag and Site Tag to an AP (GUI), on page 2

Attaching Policy Tag and Site Tag to an AP (CLI)

Follow the procedure given below to attach a policy tag and a site tag to an AP:

SUMMARY STEPS

1. **configure terminal**
2. **ap *mac-address***
3. **policy-tag *policy-tag-name***
4. **site-tag *site-tag-name***
5. **rf-tag *rf-tag-name***
6. **end**
7. **show ap tag summary**
8. **show ap name <*ap-name*> tag info**
9. **show ap name <*ap-name*> tag detail**

DETAILED STEPS

	Command or Action	Purpose
Step 1	configure terminal Example: Device# configure terminal	Enters global configuration mode.
Step 2	ap <i>mac-address</i> Example: Device(config)# ap F866.F267.7DFB	Configures a Cisco AP and enters AP profile configuration mode. Note The <i>mac-address</i> should be a wired mac address.
Step 3	policy-tag <i>policy-tag-name</i> Example: Device(config-ap-tag)# policy-tag rr-xyz-policy-tag	Maps a policy tag to the AP.

	Command or Action	Purpose
Step 4	site-tag site-tag-name Example: Device(config-ap-tag)# site-tag rr-xyz-site	Maps a site tag to the AP.
Step 5	rf-tag rf-tag-name Example: Device(config-ap-tag)# rf tag rf-tag1	Associates the RF tag.
Step 6	end Example: Device(config-ap-tag)# end	Saves the configuration, exits configuration mode, and returns to privileged EXEC mode.
Step 7	show ap tag summary Example: Device# show ap tag summary	(Optional) Displays AP details and the tags associated to it.
Step 8	show ap name <ap-name> tag info Example: Device# show ap name ap-name tag info	(Optional) Displays the AP name with tag information.
Step 9	show ap name <ap-name> tag detail Example: Device# show ap name ap-name tag detail	(Optional) Displays the AP name with tag details.

Attaching a Policy Tag and Site Tag to an AP (GUI)

Step 1 Choose Configuration > Wireless > Access Points.

The All Access Points section displays details of all the APs on your network.

Step 2 To edit the configuration details of an AP, select the row for that AP.

The Edit AP window is displayed.

Step 3 In the General tab and Tags section, specify the appropriate policy, site, and RF tags, that you created on the Configuration > Tags & Profiles > Tags page.

Step 4 Click Update & Apply to Device.
