



Release Notes for Cisco Connected Mobile Experiences (CMX) Release 11.1.1

First Published: 2025-11-05

Introduction

Cisco Connected Mobile Experiences (Cisco CMX) Release 11.1.1 is a high-performing scalable software solution that addresses the mobility services requirements of high-density Wi-Fi deployments. Unless otherwise noted, Cisco Connected Mobile Experiences is referred to as Cisco CMX in this document.

What's New in Cisco CMX Release 11.1.1

This release includes deployment of a new image version of Cisco CMX 11.1.1-111. This release is packed with an AlmaLinux operating system upgrade.

Cisco CMX Release 11.1.1 supports migration of your data from Cisco CMX Release 10.6.3-146 to the latest Cisco CMX Release 11.1.1-111. To upgrade from Cisco CMX Release 11.1.0 release to the latest CMX 11.1.1 release, use the **cmxos upgrade** command.

You cannot directly upgrade to CMX 11.1.1 from CMX 11.0.0 or CMX 11.0.1. Upgrade should be done only from CMX 11.1.0 release.

To install Cisco CMX OVA, follow these steps:

- 1. Download the CISCO_CMX-11.1.1-111.ova file available on the [Software Download](#) page.
- 2. Install the Cisco CMX Release 11.1.1-111 OVA build on the primary and secondary servers.
- 3. Migrate data from Cisco CMX Release 10.6.3-146 to Cisco CMX Release 11.1.1-111.

Cisco CMX Release 11.1.1 is not supported on Cisco Mobility Services Engine (MSE) 3365 Appliance.

Table 1: What's New in Cisco CMX Release 11.1.1

Feature	Description
AlmaLinux Upgrade	This release upgrades OS from AlmaLinux 8.10 to AlmaLinux 9.6. The upgrade is only supported from Cisco CMX Release 11.1.0 (with AlmaLinux 8.10).
Data migration	Data migration from Cisco CMX Release 10.6.3-146 to Cisco CMX Release 11.1.1 is supported.

Feature	Description
Audit Logging Enhancements	<p>This release supports these enhancements to audit logging:</p> <ul style="list-style-type: none"> • Comprehensive Action Logging: Actions performed on Cisco CMX through CLI, UI, and API interfaces are now logged to the local syslog for improved auditability and system monitoring. • Audit Message Format Update: Audit messages now utilize a new colon-separated (:) format for improved readability and structured log parsing. Audit messages now include these new fields apart from existing fields: <ul style="list-style-type: none"> • IP address from where the user is logged in • Module in the Cisco CMX system where the audit message is generated (for example, Location/Configuration) • Location in the Cisco CMX system where the audit message is generated (source file/script or referring URL in case of API related audit log) • Audit Message Log Level: Audit log messages have log level from one to three, one being lowest (and default) and three being the highest. You can modify the log level to generate desired level of logs. • Audit Logging View and Filter: Run the cmxctl config audit view command to filter and view logs of specific modules.
Support for two Remote Syslog servers	<p>This release introduces support for two new remote syslog servers to collect and store system event logs generated by the Cisco CMX system.</p> <p>You can configure up to two remote syslog servers using the cmxctl config audit settings command in Cisco CMX. This allows CMX logs to be transmitted to two different syslog servers. Both TLS and IPSEC protocols are supported for communication with these remote syslog servers. However, both servers must be configured to use the same protocol simultaneously—either both use TLS or both use IPSEC.</p>
Support for two Unauthenticated NTP Server	<p>This release supports configuration of up to two unauthenticated NTP servers in Cisco CMX using the cmxos ntp type command by selecting the “unauthenticated” type.</p>
User Session Management	<p>This release includes enhancements to improves session management by providing administrators with greater visibility and control over user sessions in the Cisco CMX environment. On the Cisco CMX UI, administrators can now view a list of active user sessions, including both GUI and SSH sessions.</p>
SSH Multi-Factor Authentication (SSH MFA) for External Authentication Server	<p>This release extends the External Authentication Server feature in Cisco CMX to allow SSH access for AAA/RADIUS users, complementing the existing support for GUI access. With this enhancement, AAA/RADIUS users can log in to the CMX SSH terminal using multi-factor authentication (MFA) that involves user certificates and RADIUS server authentication. Use the cmxctl config authserver settings command to configure SSH MFA.</p>

Feature	Description
Certificate Management: Support for 2048-bit RSA key	This release supports configuring the RSA key length for Cisco CMX certificates to enhance security flexibility. When generating new certificates—whether self-signed or CA-signed—administrators can select the RSA key length to be either 2048 bits or 4096 bits, with 4096 bits set as the default. Use the cmxctl config certs keytype command to configure and select RSA as the key type.
Firewall updates	<p>This release introduces conditional opening of port 4242, which is used for High Availability (HA) in Cisco CMX. By default, port 4242 remains closed and is only opened in these scenarios:</p> <ul style="list-style-type: none"> When a CMX server with the Primary role is converted to the Secondary role using the cmxha secondary convert command. When High Availability is enabled on the Primary CMX using the cmxha config enable command. When the cmxha web enable command is executed by the cmxadmin user on a CMX server with either Primary or Secondary role. <p>Port 4242 remains open as long as High Availability is active.</p>
HTTP/2 Support on port 4242	This release allows the HTTP/2 protocol on port 4242 when UCAPL mode is enabled using the cmxctl config fips ucaplmode enable command. When UCAPL mode is disabled, port 4242 continues to support the HTTP/1.1 protocol.
Password Policy updates	This release allows all GUI user passwords to include all printable special characters, including whitespace. However, the backslash character (\) is explicitly not allowed in the password.
License Type Updates	<p>This release introduces updates to the Cisco CMX license names.</p> <ul style="list-style-type: none"> Cisco CMX Essentials (formerly called Cisco CMX Base) is now included in Cisco Spaces Essentials. Cisco CMX Advantage (formerly called Cisco CMX Advanced) is now included in Cisco Spaces Advanatge. <p>Note DNA Advantage customers with a Cisco Spaces Extend license continue to have access to Cisco CMX Essentials (formerly known as Cisco CMX Base) along with CMX Partner Stream capability.</p>
Inclusion Zone updates	This release introduces a new parameter: location.perimetercheckon.floorutil . By default, the value is false .

Feature	Description
Component upgrades	<p>This release supports these component version updates:</p> <ul style="list-style-type: none"> • csm-toolkit: Version 1.19.2 • ciscossl: Version 1.1.1zb.7.2.593 • ciscossh: Version 1.18.80 (OpenSSH_10.0p2) • nodejs: Version 22.16.0 • npm: Version 10.9.2 • PostgreSQL: Version 16.9
Patch merges	<p>This release supports these patch merges:</p> <ul style="list-style-type: none"> • cmx-patch-rel-20250902-11.1.0-1 <ul style="list-style-type: none"> • cmx-cmxpartner-cli-fix-patch-11.1.0-1 • cmx-notification-deletion-fix-patch-11.1.0-1 • cmx-fix-cassandra-perm-patch-11.0.1-1 • cmx-fix-diag-perm-patch-11.0.1-1
Critical issue fixes	This release includes critical security vulnerability fixes.

System Requirements

Supported Hardware

Cisco CMX can be installed as a virtual Cisco MSE appliance, that requires a version VMware ESXi 7.0. The OVA deployment using a VMware vCenter is supported on VMware ESXi 7.0 and above. The VMware vCenter version must be 7.x or above and earlier versions are not supported.

The vSphere Hypervisor ESXi 6.0 is End of General Support.

For information about installing a virtual Cisco MSE appliance, see the Cisco MSE Virtual Appliance Installation Guide for this release at:

<https://www.cisco.com/c/en/us/support/wireless/mobility-services-engine/products-installation-guides-list.html>.

- Data migration support is only available from Cisco CMX Release 10.6.3-146 to Cisco CMX Release 11.1.1 .
- If you are on Cisco CMX releases earlier than Release 10.6.3-146, you need to upgrade to Cisco CMX Release 10.6.3-146 and then install the cmx-11-migration-readiness-patch patch release, and then migrate the data.
- Cisco CMX does not support VMware tools.

The following table lists the Cisco CMX hardware guidelines for a virtual Cisco MSE appliance on VMware. For complete requirements, see the *Cisco Connected Mobile Experiences Data Sheet* at:

<https://www.cisco.com/c/en/us/products/wireless/mobility-services-engine/datasheet-listing.html>.

Table 2: Hardware Guidelines

Hardware Platform	Low-End Appliance	Standard Appliance	High-End Appliance
CPU	8 vCPU 4 physical cores	16 vCPU 8 physical cores	20 vCPU 10 physical cores
RAM	24 GB RAM	48-GB RAM	64-GB RAM
HDD¹	550 GB	550 GB	1 TB

¹ For Cisco CMX OVA installation, 250 GB is the default hard disk drive (HDD) on all virtual machines. We strongly recommend that immediately after deploying the OVA file and before powering on the VM, you should increase the disk space to the recommended amount specified in this table, so that the HDD resource does not run low while using Cisco CMX. If you do not know how to increase the disk space before powering on the VM, see the [VMWare guidelines](#) on how to increase disk space.

If you do not select the recommended disk space, the basic installation defaults to 160 GB of the disk space.

- Cisco CMX Release 11.1.1 is not supported on Cisco Mobility Services Engine (MSE) 3365 Appliance.
- For compatibility information, see the “Cisco Connected Mobile Experiences (CMX) Compatibility Matrix” section in the *Cisco Wireless Solutions Software Compatibility Matrix* at:
<https://www.cisco.com/c/en/us/td/docs/wireless/compatibility/matrix/compatibility-matrix.html>.
- Cisco Hyperlocation is only supported on the High-End Cisco CMX appliances for Cisco Connected Mobile Experiences. By default, Cisco Hyperlocation is disabled on Low-End appliances.

Software Requirements

Before you deploy Cisco CMX, we strongly recommend that you see the following documents:

- For scaling information, see the *Cisco Connected Mobile Experiences Data Sheet* at:
<https://www.cisco.com/c/en/us/products/collateral/wireless/mobility-services-engine/datasheet-c78-734648.html>
- Cisco CMX Release 10.6.0 and later is required to support Cisco Spaces.
- Cisco CMX (which includes Cisco CMX Location and Configuration APIs) has been tested using Google Chrome up to Version 63.



Note If you are using Google Chrome Version 72 or later, we recommend that you use Mozilla Firefox as your browser, or downgrade to Google Chrome Version 63.

- Cisco CMX supports only English input and output.

- Cisco Prime Infrastructure, when paired with Cisco CMX, displays client information and location, but not client history.

For more information about Cisco CMX feature parity with Cisco Prime Infrastructure and Cisco MSE appliance, see the “Cisco CMX Feature Parity” section in the Chapter “Getting Started” in the *Cisco CMX Configuration Guide* for this release at:

<https://www.cisco.com/c/en/us/support/wireless/connected-mobile-experiences/products-installation-and-configuration-guides-list.html>.

- For compatibility information, see the “Cisco Connected Mobile Experiences (CMX) Compatibility Matrix” section in the *Cisco Wireless Solutions Software Compatibility Matrix* at:

<https://www.cisco.com/c/en/us/td/docs/wireless/compatibility/matrix/compatibility-matrix.html>.

- See the following table for system memory details:

Table 3: System Memory for Cisco MSE

Cisco MSE Appliance Model	RAM Allocated
Standard vMSE	48 GB
High-end vMSE	64 GB



Note High Availability pairing checks are done for software versions and hardware specifications. High Availability pairs should have matching CPU count, memory size, and hard drive size. They should also have the same software versions for Cisco CMX, Redis, Cassandra, and Postgres databases.

Licensing Information

Table 4: Cisco CMX License

Cisco CMX License	Features
Cisco CMX Essentials (formerly called Cisco CMX Base) Cisco Spaces Essentials	<ul style="list-style-type: none"> • Cisco CMX RSSI-based location calculation of clients, interferers, and rogues for Cisco products such as Cisco Spaces, Cisco Prime Infrastructure, and Cisco Identity Services Engine • Use of Cisco CMX location data in Cisco Spaces • Use of Cisco CMX location data in Cisco Prime Infrastructure • Tethering of Cisco CMX to Cisco Spaces • Access to the DETECT, MANAGE, and SYSTEMS tabs in the Cisco CMX

Cisco CMX License	Features
Cisco CMX Advantage (formerly called Cisco CMX Advanced) Cisco Spaces Advantage	<ul style="list-style-type: none"> • All functionalities under Cisco CMX Essentials license • Cisco CMX advanced location calculation capabilities, including Cisco FastPath, Cisco Hyperlocation, and CMX Partner Streams • CMX Partner Stream for RSSI streaming for Wi-Fi RFID Tags to third parties <p>Use of CMX location data for third party applications using APIs and Webhooks from cloud or on premise</p>



Note DNA Advantage customers with a Cisco Spaces Extend license continue to have access to Cisco CMX Essentials (formerly known as Cisco CMX Base) along with CMX Partner Stream capability.

Key features and requirements apply to Cisco CMX licensing:

- **Evaluation license:** The Cisco CMX Evaluation License provides full functionality for a period of 120 days. The countdown starts when you start Cisco CMX and enable a service.

Two weeks prior to expiration, a daily alert is sent, prompting you to obtain a permanent license. If the evaluation license expires, you will not be able to access the Cisco CMX GUI or APIs. Cisco CMX will continue to run in the background and collect data until you add a permanent license and regain access to it.

- **Cloud connectivity:** A Cisco Spaces license (Advantage) is required to connect Cisco CMX to a cloud. The cloud license includes the Cisco CMX license required to enable Cisco CMX.
- **Advanced features:** Cisco CMX now includes license changes that warn that the use of Cisco Hyperlocation capabilities requires the Cisco CMX Advanced License. If you have any questions about licensing, contact your Cisco account team.
- **High availability:** The High-Availability feature on Cisco CMX is part of the Cisco CMX Base license, which you should install on the primary HA server. The secondary HA server automatically receives a copy of the Cisco CMX license during synchronization. There is no HA-specific license to install.
- **Certificate management:** When a third-party certificate is installed in an HA setup, the certificate must be installed separately on both the primary and secondary Cisco CMX servers. For additional information and procedures, see the “Installing a CA-Signed Certificate for High Availability in Cisco CMX” section in the *Cisco CMX Configuration Guide* at:

https://www.cisco.com/c/en/us/td/docs/wireless/mse/10-6/cmx_config/b_cg_cmx106/getting_started_with_cisco_cmx.html#id_122557.

For information about procuring Cisco CMX licenses, see the *Cisco Connected Mobile Experiences (CMX) Version 10 Ordering and Licensing Guide* for this release at:

<https://www.cisco.com/c/en/us/solutions/collateral/enterprise-networks/connected-mobile-experiences/guide-c07-734430.html>.

For information about adding and deleting licenses, see the “Managing Licenses” section in the *Cisco CMX Configuration Guide* for this release at:

<https://www.cisco.com/c/en/us/support/wireless/connected-mobile-experiences/products-installation-and-configuration-guides-list.html>.

Installation and Upgrade Information

- Cisco CMX Release 11.1.1 is a new OVA installation for Cisco CMX.
- Inline upgrade from Cisco CMX Release 11.1.0 to Cisco CMX Release 11.1.1 is supported.
- Inline upgrade from releases earlier than Cisco CMX Release 11.1.0 to Cisco CMX Release 11.1.1 is not supported.
- Data migration is supported only from Cisco CMX Release 10.6.3-146 and later releases to Cisco CMX Release 11.1.1.
- Downgrading from any Cisco CMX release is not supported.

Limitations, Restrictions, and Important Notes

- (CSCve28851) The following error message is displayed because MATLAB only counts heavy walls for location calculation, while Java counts all the obstacles on the floor map. Ignore this message because the heat maps are now correctly generated and stored:

```
ERROR com.cisco.mse.matlabengine.heatmap.BaseMatlabHeatmapBuilder -
MatlabHeatmapBuilder#createApInterfaceHeatmap Number of heavy walls used by Matlab:
<nn> not equal to count reported by Java: <nn> during heatmap calculation for AP
Interface: 88:f0:31:08:06:70-5.0-2.
```

- (CSCve37513) Cisco CMX detects the same sources of interferences as the Cisco CleanAir system. For more information, see the “Configuring Cisco CleanAir on the Cisco Wireless LAN Controller (GUI)” section in the Chapter “Wireless Quality of Service” of the *Cisco Wireless Controller Configuration Guide*, Release 8.4 at:

https://www.cisco.com/c/en/us/td/docs/wireless/controller/8-4/config-guide/b_cg84/wireless_quality_of_service.html#ID51.

The sources of interference are:

- Bluetooth Paging Inquiry: A Bluetooth discovery (802.11b/g/n only)
- Bluetooth Sco Acl: A Bluetooth link (802.11b/g/n only)
- Generic DECT: A digital, enhanced cordless communication-compatible phone
- Generic TDD: A time division duplex (TDD) transmitter
- Generic Waveform: A continuous transmitter
- Jammer: A jamming device
- Microwave: A microwave oven (802.11b/g/n only)
- Canopy: A canopy bridge device
- Spectrum 802.11 FH: An 802.11 frequency-hopping device (802.11b/g/n only)
- Spectrum 802.11 inverted: A device using spectrally inverted Wi-Fi signals
- Spectrum 802.11 non std channel: A device using nonstandard Wi-Fi channels
- Spectrum 802.11 SuperG: An 802.11 SuperAG device

- Spectrum 802.15.4vAn 802.15.4 device (802.11b/g/n only)
 - Video Camera: An analog video camera
 - WiMAX Fixed: A WiMAX fixed device (802.11a/n/ac only)
 - WiMAX Mobile: A WiMAX mobile device (802.11a/n/ac only)
 - Xbox: A Microsoft Xbox (802.11b/g/n only)
- (CSCvg10317) Cisco MSE virtual machine (VM) appliance running Cisco CMX might not function properly after being powered on after a power outage. If this occurs:
 1. Use the **cmxos date** command to make sure that the Cisco CMX system date matches the current date. If the dates do not match, use the NTP server to synchronize the dates.
 2. Enter the **cmxctl stop -a** command to shut down Cisco CMX services.
 3. Enter the **cmxctl start** command to restart the services.
 - (CSCvg28274) If NMSP tunnel flapping occurs, ping an external address to check if the DNS resolution is slow. If it is slow, delete all the external DNS server entries in the `/etc/resolv.conf` file, except for the entry that maps to the localhost.
 - (CSCvg79749) In Cisco CMX Release 10.4.0, the v3 client API was introduced, and the v2 client API was deprecated. We recommend that you use the v3 API instead of the v2 API. High CPU usage by the Cisco CMX Location service occurs when the v2 API is used for a long duration. Restart the Cisco CMX Location service to correct the condition.
 - (CSCvi07385) With VMware vSphere ESXi 6.5 Update 2, you can successfully deploy the Cisco CMX OVA file. Update 2 displays the deployment options (Low-end, Standard, and High-end). Minor erroneous text such as [object Object] is also displayed.

With VMware vSphere ESXi 6.5 and VMware vSphere ESXi 6.5 Update 1, the deployment options are not displayed.
 - (CSCvi84935) High CPU usage of the Cisco CMX Analytics and Location services might occur during initial HA synchronization, causing incomplete synchronization. If this occurs, remove the Cisco controller from the system to decrease the CPU usage of the Cisco CMX Analytics service. This provides enough memory for the initial HA synchronization to get completed.
 - (CSCvj52515) There is significant overhead in maintaining the compact history, which allows you to query the unique clients seen on a floor or zone per day. This does not affect the regular clients history that is stored in the Cassandra database.

**Note**

From Cisco CMX Release 10.4.1-15, the Feature Flags setting for compact location history is disabled by default. If your system is running an earlier release of Cisco CMX, we recommend that you disable the Feature Flags setting.

To disable the Feature Flags setting, enter these commands:

1. **cmxctl config featureflags location.compactlocationhistory false**
2. **cmxctl agent restart**

3. `cmxctl location stop`

4. `cmxctl location start`

- (CSCvn98927) We recommend that you assign an IP address to a single interface (ens32). Assigning IP addresses to two interfaces allows data to go to both the interfaces, which causes Cisco CMX to drop packets, which in turn, leads to issues related to client tracking.
- (CSCvo14248) Generating scheduled reports in PDF format is not supported on Cisco CMX Release 10.5.0 and later. Use the **PrtSc** option instead. This feature set will be removed from the product.
- (CSCvo60319) On Cisco CMX, using OAuth with Instagram might not always display the Log In portal. If the portal is not displayed, refresh your browser.
- (CSCvp00432) As of Cisco CMX Release 10.6.0, Cisco CMX no longer supports the Historylite (/api/location/v1/historylite) API. The API requires the collection of the compact location history, which causes performance issues.
- (CSCvp11685) If FIPS mode is enabled on Cisco CMX, the Maps online sync (Import from Cisco Prime Infrastructure) fails for Cisco Prime Infrastructure Release 3.5.

To import maps from Cisco Prime Infrastructure Release 3.5 to Cisco CMX with FIPS mode enabled, you must download the tar file of Cisco Prime Infrastructure, and then upload the tar file to Cisco CMX, as described in the “Importing Maps” section in the Cisco CMX Configuration Guide at:

<https://www.cisco.com/c/en/us/support/wireless/connected-mobile-experiences/products-installation-and-configuration-guides-list.html>

- (CSCvp19413) If you need to use round brackets (such as parentheses) in a Cisco CMX API regex expression, use a backslash (\) to escape the next character. For example, instead of this string:

```
Global->System Campus>1212 Deming Way (TTD)>Floor 1
```

 use this string:

```
Global->System Campus>1212 Deming Way \ (TTD\)>Floor 1
```
- (CSCvp31400) Cisco CMX in FIPS mode does not support the aes128-ctr and aes256-ctr ciphers (while Cisco CMX in non-FIPS mode supports them). If a Cisco Catalyst 9800 wireless controller is using either of these ciphers, it will not be able to communicate with Cisco CMX in FIPS mode.
 Cisco CMX in FIPS mode supports only the aes128-cbc, aes256-cbc, aes128-gcm@openssh.com, and aes256-gcm@openssh.com ciphers.
- (CSCvp25049) The **Repeat Devices** API does not provide all the required information because it requires information from history location data, which is managed by the **compacthistory** feature flag. The feature flag causes performance issues and is disabled by default.
- (CSCvp92688) Cisco CMX might not be able to process a large amount of history data from the Cassandra database if the duration between locatedAfterTime and locatedBeforeTime for the **All Client History** API is either 1 hour or 20 minutes. We recommend that you use the Cassandra export tool to extract history data.
- (CSCvq81962) When the Cisco CMX session idle timeout period is reached, users are logged out of their Cisco CMX UI session whether the session is idle or is actively being used. Users must then log in to Cisco CMX again.

Use the `cmxctl config auth settings` command to configure the **Session idle timeout in minutes** setting. The time range is 1 to 720 minutes. The default value is 30 minutes.

This timeout period does not apply to Cisco CMX CLI sessions.

- (CSCvq82147) Cisco CMX supports VMware Snapshot.
- (CSCvq82305) Location data is poor when too few Angle of Arrival (AoA) measurements are reported in a network, with both hyperlocation and nonhyperlocation access points.
- (CSCvr16016) The issue of the Cisco CMX Analytics Service not processing data is now fixed in Cisco CMX Release 10.6.2-72 but for the fix to come into effect, you must reboot Cisco CMX.
- (CSCvr26395 and CSCvr26398) The Cisco CMX Troubleshooting Tool supports only Cisco Hyperlocation-capable access points.
- (CSCvs57713) With Cisco CMX Release 10.5 and later and Cisco WLC Release 8.7 and later, the Cisco CMX Group Subscription feature allows one Cisco Hyperlocation-enabled wireless controller to connect to multiple Cisco CMX servers.
- (CSCvs68618) When collecting client data from the Cisco CMX v3 Location API, the last seen time stamp is different from the time stamp displayed on the Cisco CMX GUI.
- In Cisco CMX Release 10.6.2-89, the `floorRefId` component is replaced with `floorId`.
- (CSCvs89951) If your network has a Cisco Catalyst 9800 wireless controller, do not check the **Exclude Probing Only Clients** check box located in the **Settings > Filtering** section on the **System > Dashboard** window on Cisco CMX. Checking the **Exclude Probing Only Clients** check box causes all the clients (probing and associated clients) to be excluded from the controller, and hence will not be displayed on Cisco CMX.
- (CSCvt83715) We recommend that you disable the Cisco CMX Analytics service if you are not using the service.
 - If you are running Cisco CMX Release 10.6.2-72 or earlier, install the **cmx-disableanalytics-patch-10.6.2-1.cmxp** patch file. Contact Cisco Customer Support (<https://www.cisco.com/c/en/us/support/index.html>) for the patch file.
 - If you are running Cisco CMX Release 10.6.2-89 or later, use the **cmxctl disable analytics** command.



Note The **cmxctl disable analytics** command is supported only on Cisco CMX Release 10.6.2-89 and later.

- (CSCvt83902) Cisco CMX displays an authentication error during SSO login if the SAML response from the IDP does not include the **User.email**, **User.FirstName**, and **User.LastName** attributes.
- (CSCvu18413) Due to FIPS/CC/UCAPL compliance, root access is no longer available as of Cisco CMX Release 10.6.0. Only Cisco Customer Support has access to a root patch for troubleshooting. Contact Cisco Customer Support (<https://www.cisco.com/c/en/us/support/index.html>) for assistance.

Issues

Issues describe unexpected behavior in the Cisco CMX application. The Open Issues and Resolved Issues sections list the issues in this release.

Open Issues

This section lists the open issues in this release of Cisco CMX 11.1.1.

Table 5: Cisco CMX 11.1.1

Bug ID	Description
CSCwr95922	Cert Management: CMX services are not coming up for setting key type as ECDSA for certificates generation

Resolved Issues

This section lists the issues that have been resolved in this release of Cisco CMX 11.1.0.

Table 6: Cisco CMX 11.1.1 Resolved Issues

Bug ID	Description
CSCwo74982	CMX marks Clients outside the Inclusion Zone
CSCwq11782	Catalyst Center fails to fetch Client positions from CMX 11.0+ when site name has '-' or other special characters
CSCwp27482	Adjust CMX Certificate CSR Key Length to 2048 Bits Instead of 4096 Bits
CSCwn61036	Allow 2 unauthenticated NTP servers
CSCwp67314	cmxpartner Cli not working on 11.1.0
CSCwp67386	Giving Exception while deleting the Notification from CMX UI
CSCwi14096	Needed a CMX failover/failback stop mechanism

Documentation and Support

Related Documentation

- Cisco Spaces product information:
<https://www.cisco.com/c/en/us/solutions/enterprise-networks/connected-mobile-experiences/index.html>
- Cisco Spaces documentation:
<https://www.cisco.com/c/en/us/support/wireless/dna-spaces/tsd-products-support-series-home.html>
- Cisco CMX documentation:
<https://www.cisco.com/c/en/us/support/wireless/connected-mobile-experiences/tsd-products-support-series-home.html>
- Cisco CMX Cloud documentation:
<https://www.cisco.com/c/en/us/support/wireless/connected-mobile-experiences-cmx-cloud/tsd-products-support-series-home.html>

- Cisco Mobility Services Engine documentation:

<https://www.cisco.com/c/en/us/support/wireless/mobility-services-engine/tsd-products-support-series-home.html>

Cisco Aironet Access Point Modules documentation:

<https://www.cisco.com/c/en/us/support/interfaces-modules/aironet-access-point-modules/products-installation-guides-list.html>

Cisco Support Community

Cisco Support Community is a forum for you to ask and answer questions, share suggestions, and collaborate with your peers. Join the forum at [Cisco Community](#).

Communications, services, and additional information

- To receive timely, relevant information from Cisco, sign up at [Cisco Profile Manager](#).
- To get the business impact you're looking for with the technologies that matter, visit [Cisco Services](#).
- To submit a service request, visit [Cisco Support](#).
- To discover and browse secure, validated enterprise-class apps, products, solutions, and services, visit [Cisco DevNet](#).
- To obtain general networking, training, and certification titles, visit [Cisco Press](#).
- To find warranty information for a specific product or product family, access [Cisco Warranty Finder](#).

Cisco Bug Search Tool

[Cisco Bug Search Tool](#) (BST) is a gateway to the Cisco bug-tracking system, which maintains a comprehensive list of defects and vulnerabilities in Cisco products and software. The BST provides you with detailed defect information about your products and software.

Documentation feedback

To provide feedback about Cisco technical documentation, use the feedback form available in the right pane of every online document.