Mobile Policy Infrastructure Commands

- db balance, on page 1
- db global-settings, on page 1
- db global-settings timers, on page 2
- db spr, on page 3

db balance

Configures the Balance database.

Privilege

Security Administrator, Administrator

Command Modes

Exec > Global Configuration

Syntax Description

`db balance shard-count` *`balance_db_shard_count`*

shard-count *balance_db_shard_count*

Specify the Balance database's shard count.

Must be an integer.

Default Value: 1.

Usage Guidelines

Use this command to configure the Balance database.

Example

The following command configures the Balance database's shard count to 1:

```
db balance shard-count 1
```

db global-settings

Configures global DB settings.

Privilege Security Administrator, Administrator

Command Modes Exec > Global Configuration

Syntax Description **`global-settings db-replica`** *`replica_count`*

db-replica *replica_count*

Specify the global DB replica count.

Must be an integer.

Default Value: 3.

Usage Guidelines Use this command to configure the global DB settings.

db global-settings timers

Configures global MongoDB timers.

Privilege Security Administrator, Administrator

Command Modes Exec > Global Configuration

Syntax Description **`db global-settings timers { catchup-timeout-millis`** *`catchup_timeout`* **`| election-timeout-millis`** *`election_timeout`* **`| heartbeat-interval-millis`** *`heartbeat_interval`* **`}`**

heartbeat-interval-millis *heartbeat_interval*

Specify the global heartbeat interval period, in milliseconds.

Must be an integer.

Default Value: 300.

catchup-timeout-millis *catchup_timeout*

Specify the global catchup timeout period, in milliseconds.

Must be an integer.

Default Value: 2000.

election-timeout-millis *election_timeout*

Specify the global election timeout period, in milliseconds.

Must be an integer.

Default Value: 2000.

Usage Guidelines Use this command to configure the global MongoDB timers.

db spr

Configures the SPR database.

Privilege

Security Administrator, Administrator

Command Modes

Exec > Global Configuration

Syntax Description

`db spr shard-count` *`shard_count`*

shard-count *shard_count*

Specify the SPR database's shard count.

Must be an integer.

Default Value: 1.

Usage Guidelines

Use this command to configure the SPR database.

Example

The following command configures the SPR database's shard count to 20:

```
db spr shard-count 20
```