



Monitor Subscriber and Monitor Protocol

- [Feature Summary and Revision History, on page 1](#)
- [Feature Description, on page 1](#)
- [Configuring the Monitor Subscriber and Monitor Protocol Feature, on page 2](#)

Feature Summary and Revision History

Summary Data

Table 1: Summary Data

Applicable Product(s) or Functional Area	SMF
Applicable Platform(s)	SMI
Feature Default Setting	Enabled – Always-on
Related Changes in this Release	Not Applicable
Related Documentation	Not Applicable

Revision History

Table 2: Revision History

Revision Details	Release
First introduced.	Pre-2020.02.0

Feature Description

The SMF supports the Monitor Subscriber and Monitor Protocol on the Kubernetes environment. This feature allows to capture messages of subscribers and protocols.

Configuring the Monitor Subscriber and Monitor Protocol Feature

Monitoring the Subscriber

Use the following CLI command to monitor the subscriber in the SMF.

```
monitor subscriber supi supi_id [ capture-duration duration_sec |
internal-messages { yes } | transaction-logs { yes } ]
```

NOTES:

- **supi *supi_id***: Specifies the subscriber identifier. For example, imsi-123456789, imsi-123*
- **capture-duration *duration_sec***: Specifies the duration in seconds during which the monitor subscriber is enabled. The default is 300 seconds (5 minutes).
- **internal-messages { yes }**: Enables internal messages. By default, internal messages are disabled.
- **transaction-logs { yes }**: Enables transaction logs. By default, transaction logs are disabled.

The **monitor subscriber** CLI command can be run simultaneously on multiple terminals. For example, run the CLI simultaneously in two SMF Ops Center terminals for two subscribers (for example, imsi-123456789012345 and imsi-456780123456789) to implement the following:

- Monitor the duration when the monitor subscriber is enabled.
- View internal messages for the specified subscriber.
- View transaction logs for the specified subscriber

Terminal 1: The following command monitors and displays subscriber messages for the specified subscriber.

```
monitor subscriber supi imsi-123456789012345 capture-duration 1000 internal-messages yes
```

Terminal 2: The following command monitors and displays transaction logs for the specified subscriber.

```
monitor subscriber supi imsi-456780123456789 capture-duration 500 internal-messages yes
transaction-logs yes
```

After the capture-duration is over or to stop the CLI, use the **Ctrl+C** keys. The captured messages are reordered and stored in a file. To retrieve the list of stored files, use the **monitor subscriber list** CLI command.

For example:

```
monitor subscriber list
RELEASE_NAMESPACE: 'smf'
'monsublogs/subscriberID_imsi-*_AT_2019-10-22T09:19:05.586237087.txt.sorted'
monsublogs/subscriberID_imsi-123456789012345_AT_2019-10-22T09:20:11.122225534.txt.sorted
```

Enabling or Disabling the Transaction Messages

Use the following CLI command to enable or disable the presence of request response messages in the transaction logs.

```
configure
 logging transaction message [ enable | disable ]
 commit
end
```

NOTES:

- **logging transaction message:** Specifies the transaction messages in the transaction logs.
- **enable:** Enables the presence of transaction messages in the transaction logs.
- **disable:** Disables the presence of transaction messages in the transaction logs.

Viewing the Sorted File on SMF Ops Center

Use the following CLI command to view the sorted file on the SMF Ops Center screen.

```
monitor subscriber dump filename filename
```

For example:

```
monitor subscriber dump filename
monslogs/subscriberID_imsi-123456789012345_AT_2019-10-22T09:20:11.122225534.txt.sorted
```

Monitoring the Interface Protocol

Use the following CLI command to monitor the interface protocol on the SMF.

```
monitor protocol interface endpoint_name capture-duration duration_sec
```

NOTES:

- **interface *endpoint_name*:** Specifies the endpoint name on which PCAP is captured. This CLI allows the configuration of multiple endpoint names in a single CLI command.
- **capture-duration *duration_sec*:** Specifies the duration in seconds during which the monitor subscriber is enabled. The default is 300 seconds (5 minutes).
- The configured endpoint names can be retrieved using the **show endpoint** CLI command.

The **monitor protocol** CLI can be run simultaneously on multiple terminals. Also, the **interface *endpoint_name*** CLI allows the configuration of multiple endpoint names in a single CLI command. For example:

```
monitor protocol interface sbi,N4:10.86.73.161:8805,gtpc capture-duration
1000
```

Viewing Transaction History Logs

Use the following CLI command to view the transaction history on an OAM pod shell. On another terminal, use the **kubectf** command to tail the logs of the OAM pod and then run the following CLI from the Ops Center.

```
dump transactionhistory
```



Note In this release, the most recent transaction logs are stored in a circular queue of size 1024 transaction logs.

Sample Transaction Log

The following is an example of transaction log collected in Monitor Subscriber during SMF PDU session establishment.

Transaction Log received from Instance: smf.smf-rest-ep.unknown.smf.0

***** TRANSACTION: 00010 *****

TRANSACTION SUCCESS:

```
Txn Type      : N10RegistrationRequest(33)
Priority      : 1
Session State : No_Session
```

LOG MESSAGES:

```
2020/03/03 05:31:39.345 [DEBUG] [infra.transaction.core] Processing transaction Id: 10
Type: 33 SubscriberID: imsi-123456789012345 Keys: []
2020/03/03 05:31:39.345 [DEBUG] [infra.transaction.core] Trace is disabled
2020/03/03 05:31:39.346 [TRACE] [infra.message_log.core] >>>>>>
```

IPC message

```
Name: N10RegistrationRequest
MessageType: N10RegistrationRequest
```

Key:

--body--

```
{"regInfo":{"ueId":"imsi-123456789012345","pduSessionId":5},"regReq":{"dnn":"intershat",
"pduSessionId":5,"pgwFqdn":"cisco.com.apn.epc.mnc456.mcc123","plmnId":{"mcc":"123","mnc":"456"},
"smfInstanceId":"c388eec5-e2ff-4bda-8154-b5dd9f10ad97","supportedFeatures":"0","singleNssai":{"sd":"Abf123","sst":2}},
"regReq":{"Type":2,"ServiceName":4,"Versions":{"v1"},"ProfileName":"UP1","FailureProfile":"FH1","SvcMsgType":3,"Filter":{"BitmapFields":2,"Dnn":"intershat"}}}
```

```
2020/03/03 05:31:39.346 [DEBUG] [nrfClient.Discovery.nrf] Message send Metadata [Type:UDM
ServiceName:nudm-uecm
Method:"Register"
Payload:"\022\030\n\024imsi-123456789012345\020\005\032o\n\tintershat\030\005\037cisco.com.apn.epc.mnc456.
```

```
mcc123*\n\n\003123\022\0034562$c388eec5-e2ff-4bda-8154-b5dd9f10ad97:\0010B\n\n\006Abf123\020\002\010\002\030\004J\002v1b\
003UP1j\r\010\002\022\tintershat\272\001\003FH1\300\001\003" Versions:"v1" MsgType:33
ProfileName:"UP1" FailureProfile:"FH1"
```

```
SvcMsgType:UdmUecmRegistersSMF Filter:<BitmapFields:2 Dnn:"intershat" > ] client
locality [] Preferred locality [], Geo Locality []
2020/03/03 05:31:39.347 [DEBUG] [nrfClient.generic.Int] GetAvailableSLAInMS returned
timeoutInMS [0]
```

```
2020/03/03 05:31:39.347 [DEBUG] [infra.transaction.core] Requested host Setname: Name:
http://10.86.73.209:9020/nudm-uecm/v1 Version: ApiRoot:
2020/03/03 05:31:39.347 [DEBUG] [infra.transaction.core] Exact match found. Selected
remote host is Id 2
```

```
Name: http://10.86.73.209:9020/nudm-uecm/v1 Setname: Host: Port: 0 Url:
http://10.86.73.209:9020/nudm-uecm/v1
```

```
2020/03/03 05:31:39.347 [INFO] [infra.transaction.core] Calling RPC UDM on host
http://10.86.73.209:9020/nudm-uecm/v1 proc-name UDM proc-method: Register
```

```
2020/03/03 05:31:39.348 [DEBUG] [rest_ep.app.n10] Sending registration request to udm:
/imsi-123456789012345/registrations/
smf-registrations/5 with payload
```

```
{"dnn":"intershat","pduSessionId":5,"pgwFqdn":"cisco.com.apn.epc.mnc456.mcc123",
"plmnId":{"mcc":"123","mnc":"456"},"singleNssai":{"sd":"Abf123","sst":2},"smfInstanceId":"c388eec5-e2ff-4bda-8154-b5dd9f10ad97","supportedFeatures":"0"}
```

```
2020/03/03 05:31:39.348 [DEBUG] [infra.rest_client.core] Sending rest message to
http://10.86.73.209:9020/nudm-uecm/v1/imsi-123456789012345/registrations/smf-registrations/5
```

```

2020/03/03 05:31:39.348 [TRACE] [infra.message_log.core] <<<<<<<<
Request
Name: UdmRegistrationRequest
Host:
http://10.86.73.209:9020/nudm-uecm/v1/imsi-123456789012345/registrations/smf-registrations/5
Method: PUT
RequestURI:
--- Headers ---
Content-Type: application/json
RequestURI: http://10.86.73.209:9020/nudm-uecm/v1/imsi-123456789012345/registrations/smf-registrations/5
2020/03/03 05:31:39.376 [TRACE] [infra.message_log.core] >>>>>>>
Response
Name:
Response Status 201
--- Headers ---
Location:
http://10.86.73.209:9020/nudm-uecm/v1/imsi-123456789012345/registrations/smf-registrations/5
Content-Length: 225
Content-Type: application/json
Body:{"pgwFqdn": "cisco.com.apn.epc.mnc456.mcc123", "plmnId": {"mcc": "123", "mnc": "456"},
"dnn": "intershat",
"smfInstanceId": "524f5f8a-b584-47b8-86f5-a5292eabcdef", "pduSessionId": 5, "singleNssai":
{"sd": "Abf123", "sst": 2}}
2020/03/03 05:31:39.377 [INFO] [rest_ep.app.n10] Received registration success response
with status = 201 and body =
{"pgwFqdn": "cisco.com.apn.epc.mnc456.mcc123", "plmnId": {"mcc": "123", "mnc": "456"},
"dnn": "intershat",
"smfInstanceId": "524f5f8a-b584-47b8-86f5-a5292eabcdef", "pduSessionId": 5,
"singleNssai": {"sd": "Abf123", "sst": 2}}
2020/03/03 05:31:39.377 [DEBUG] [infra.transaction.core] Last stage ( init_done ) ->
Next stage ( finished )
2020/03/03 05:31:39.378 [TRACE] [infra.message_log.core] <<<<<<<<
IPC message
Name: N10RegistrationSuccess
MessageType: N10RegistrationSuccess
Key:
--body--
{"regRes":{"dnn":"intershat","pduSessionId":5,"pgwFqdn":"cisco.com.apn.epc.mnc456.mcc123","plmnId":{"mcc":"123","mnc":"456"},
"smfInstanceId":"c388eec5-e2ff-4bda-8154-b5dd9f10ad97","supportedFeatures":"0","singleNssai":{"sd":"Abf123","sst":2}},
"msgRsp":{"Type":2,"Http2_Status":201,"MsgType":34,"ServiceName":4,"SelectedVersion":"v1","SelectedEndPoint":
{"ipv4Address":"10.86.73.209","port":9020,"transport":1},"SelectedProfileName":"UP1","SelectedEndPointName":"EP1",
"SelectedEndPointProfile":"EP1","SelectedLocality":"LOC1","FailureProfile":"FH1","GroupID":"UDM-dnn=intershat;"}
2020/03/03 05:31:39.378 [DEBUG] [infra.transaction.core] no response message sent for
10
*****
Transaction Log received from Instance: smf.smf-rest-ep.unknown.smf.0
***** TRANSACTION: 00011 *****
TRANSACTION SUCCESS:
Txn Type : N10SubscriptionFetchReq(36)
Priority : 1
Session State : No_Session
LOG MESSAGES:
2020/03/03 05:31:39.384 [DEBUG] [infra.transaction.core] Processing transaction Id: 11
Type: 36 SubscriberID: imsi-123456789012345 Keys: []

```

Sample Transaction Log

```

2020/03/03 05:31:39.384 [DEBUG] [infra.transaction.core] Trace is disabled
2020/03/03 05:31:39.384 [TRACE] [infra.message_log.core] >>>>>>
IPC message
Name: N10SubscriptionFetchReq
MessageType: N10SubscriptionFetchReq
Key:
--body--
{"subInfo":{"ueId":"imsi-123456789012345"},"uriParams":{"supportedFeatures":"0","singleNssai":{"sd":"Abf123","sst":2},
"dnn":"intershat","plmnId":{"mcc":"123","mnc":"456"},"msgReq":{"Type":2,"ServiceName":3,"Versions":["v1"],"ProfileName":
"UP1","FailureProfile":"FH1","SvcMsgType":1,"Filter":{"Bitmapfeilds":2,"Dnn":"intershat"}}}

2020/03/03 05:31:39.384 [DEBUG] [nrfClient.Discovery.nrf] Message send Metadata [Type:UDM
ServiceName:nudm-sdm Method:"Subscription"

Payload:"\022\026\n\024imsi-123456789012345\032&\n\0010\022\n\n\006Abf123\020\002\032\tintershat\n\n\n\003123\022\003456
\n\n\010\002\030\003J\002v1b\003UP1j\r\010\002\022\tintershat\272\001\003FH1\300\001\001"
Versions:"v1" MsgType:36
ProfileName:"UP1" FailureProfile:"FH1" SvcMsgType:UdmSdmGetUESMSSubscriptionData
Filter:<Bitmapfeilds:2 Dnn:"intershat" > ]
client locality [] Preferred locality [], Geo Locality []
2020/03/03 05:31:39.385 [DEBUG] [nrfClient.generic.Int] GetAvailableSLAINMS returned
timeoutInMS [0]
2020/03/03 05:31:39.385 [DEBUG] [infra.transaction.core] Requested host Setname: Name:
http://10.86.73.209:9020/nudm-sdm/v1 Version: ApiRoot:
2020/03/03 05:31:39.385 [DEBUG] [infra.transaction.core] Exact match found. Selected
remote host is Id 1 Name: http://10.86.73.209:9020/
nudm-sdm/v1 Setname: Host: Port: 0 Url: http://10.86.73.209:9020/nudm-sdm/v1
2020/03/03 05:31:39.385 [INFO] [infra.transaction.core] Calling RPC UDM on host
http://10.86.73.209:9020/nudm-sdm/v1 proc-name
UDM proc-method: Subscription
2020/03/03 05:31:39.385 [DEBUG] [rest_ep.app.n10] Sending sm subscription request to
udm: /imsi-123456789012345/sm-data?

dnn=intershat&plmn-id=%7B%22mcc%22%3A%22123%22%2C%22mnc%22%3A%22456%22%7D&single-nssai=%7B%22sd%22%3A%22Abf123%22%2C%22sst%22%3A%2
7D&supported-features=0
2020/03/03 05:31:39.385 [DEBUG] [infra.rest_client.core] Sending rest mesage to
http://10.86.73.209:9020/nudm-sdm/v1/

imsi-123456789012345/sm-data?dnn=intershat&plmn-id=%7B%22mcc%22%3A%22123%22%2C%22mnc%22%3A%22456%22%7D&single-nssai=%7B%22sd%22
%3A%22Abf123%22%2C%22sst%22%3A%22%7D&supported-features=0
2020/03/03 05:31:39.385 [TRACE] [infra.message_log.core] <<<<<<<<
Request
Name: UdmSubscriptionRequest
Host:
http://10.86.73.209:9020/nudm-sdm/v1/imsi-123456789012345/sm-data?dnn=intershat&plmn-id=%7B%22mcc%22%3A%22123%22%2C%22mnc%22%3A%2
2456%22%7D&single-nssai=%7B%22sd%22%3A%22Abf123%22%2C%22sst%22%3A%22%7D&supported-features=0
Method: GET
RequestURI:
--- Headers ---
Content-Type: application/json
2020/03/03 05:31:39.400 [TRACE] [infra.message_log.core] >>>>>>
Response
Name:
Response Status 200
--- Headers ---
Content-Length: 812
Content-Type: application/json

```

```

Body:[{"sharedDnnConfigurationsIds": "012345", "internalGroupIds": ["1aAbB00866564",
"dhsjdha67673AA"], "singleNssai": {"sd": "Abf123",
"sst": 2}, "dnnConfigurations": {"intershat": {"3gppChargingCharacteristics": "1",
"5gQosProfile": {"5qi": 5, "arp": {"preemptVuln":
"NOT_PREEMPTABLE", "preemptCap": "NOT_PREEMPT", "priorityLevel": 15}, "priorityLevel":
1}, "sscModes": {"allowedSscModes": ["SSC_MODE_1",
"SSC_MODE_2"], "defaultSscMode": "SSC_MODE_1"}, "ladnIndicator": true, "pduSessionTypes":
{"defaultSessionType": "IPV4",
"allowedSessionTypes": ["IPV6", "IPV4V6", "UNSTRUCTURED", "ETHERNET"]}, "staticIpAddress":
[{"ipv4Addr": "1.1.1.1"}, {"ipv6Addr": "::1"}],
"upSecurity": {"upIntegr": "REQUIRED", "upConfid": "PREFERRED"}, "sessionAmbr": {"downlink":
"125 Mbps", "uplink": "100 Mbps"},
"iwkEpsInd": false}}]}
2020/03/03 05:31:39.400 [INFO] [rest_ep.app.n10] Received sm subscription success
response with status = 200 and body =
[{"sharedDnnConfigurationsIds": "012345", "internalGroupIds": ["1aAbB00866564",
"dhsjdha67673AA"], "singleNssai": {"sd":
"Abf123", "sst": 2}, "dnnConfigurations": {"intershat": {"3gppChargingCharacteristics":
"1", "5gQosProfile": {"5qi": 5, "arp":
{"preemptVuln": "NOT_PREEMPTABLE", "preemptCap": "NOT_PREEMPT", "priorityLevel": 15},
"priorityLevel": 1}, "sscModes":
{"allowedSscModes": ["SSC_MODE_1", "SSC_MODE_2"], "defaultSscMode": "SSC_MODE_1"},
"ladnIndicator": true, "pduSessionTypes":
{"defaultSessionType": "IPV4", "allowedSessionTypes": ["IPV6", "IPV4V6", "UNSTRUCTURED",
"ETHERNET"]}, "staticIpAddress":
[{"ipv4Addr": "1.1.1.1"}, {"ipv6Addr": "::1"}], "upSecurity": {"upIntegr": "REQUIRED",
"upConfid": "PREFERRED"}, "sessionAmbr":
{"downlink": "125 Mbps", "uplink": "100 Mbps"}, "iwkEpsInd": false}}]}
2020/03/03 05:31:39.401 [INFO] [rest_ep.app.n10] Unmarshalled smData:
smData:<dnnConfiguration:<key:"intershat" value:
<_3gppChargingCharacteristics:"1" ladnIndicator:true
pduSessionTypes:<allowedSessionTypes:IPV6 allowedSessionTypes:IPV4V6
allowedSessionTypes:UNSTRUCTURED allowedSessionTypes:ETHERNET defaultSessionType:IPV4
> sessionAmbr:<downlink:"125 Mbps"
uplink:"100 Mbps" > sscModes:<allowedSscModes:SSC_MODE_1 allowedSscModes:SSC_MODE_2
defaultSscMode:SSC_MODE_1 >
upSecurity:<upConfid:PREFERRED > subsQosProfile:<_5qi:5 arp:<preemptCap:NOT_PREEMPT
preemptVuln:NOT_PREEMPTABLE priorityLevel:15 >
priorityLevel:1 > staticIpAddress:<ipv4Addr:"1.1.1.1" > staticIpAddress:<ipv6Addr:::1"
> > > singleNssai:<sd:"Abf123" sst:2 >
internalGroupIds:"1aAbB00866564" internalGroupIds:"dhsjdha67673AA"
sharedDnnConfigurationsIds:"012345" >
2020/03/03 05:31:39.402 [DEBUG] [infra.transaction.core] Last stage ( init_done ) ->
Next stage ( finished )
2020/03/03 05:31:39.403 [TRACE] [infra.message_log.core] <<<<<<<<<
IPC message
Name: N10SubscriptionFetchSuccess
MessageType: N10SubscriptionFetchSuccess
Key:
--body--
{"subInfo":{"ueId":"imsi-123456789012345"},"uriParams":{"supportedFeatures":"0","singleNssai":{"sd":"Abf123","sst":2},"dnn":{"intershat",
"plmnId":{"mcc":"123","mnc":"456"}}, "smData":{"dnnConfiguration":{"intershat":{"_3gppChargingCharacteristics":"1","ladnIndicator":true,
"pduSessionTypes":{"allowedSessionTypes": [2,3,4,5], "defaultSessionType":1}, "sessionAmbr":{"downlink":"125
Mbps", "uplink":"100 Mbps"},
"sscModes":{"allowedSscModes": [1,2], "defaultSscMode":1}, "upSecurity":{"upConfid":2}, "subsQosProfile":{"_5qi":5, "arp":{"preemptCap":1,
"preemptVuln":1, "priorityLevel":15}, "priorityLevel":1}, "staticIpAddress":{"ipv4Addr":"1.1.1.1"}, {"ipv6Addr":"::1"}}, "singleNssai":

```

```
{"sd":"Abf123","sst":2,"internalGroupIds":["1aAb00866564","dhsjcha67673AA"],"sharedDnnConfigurationsIds":"012345"},"msgRsp":  
  
{"Type":2,"Http2_Status":200,"MsgType":37,"ServiceName":3,"SelectedVersion":"v1","SelectedEndPoint":{"ipv4Address":"10.86.73.209",  
  
"port":9020,"transport":1},"SelectedProfileName":"EPI","SelectedEndPointName":"EPI","SelectedEndPointProfile":"EPI","SelectedLocality":  
  
"LOC1","FailureProfile":"FH1","GroupID":"UDM-dnn=intershat;"}  
2020/03/03 05:31:39.403 [DEBUG] [infra.transaction.core] no response message sent for  
11  
*****  
*
```