



SMF Metrics

- [chf-service Metrics Reference, on page 1](#)
- [diameter-ep statistics Category, on page 8](#)
- [dns-proxy Metrics Reference, on page 21](#)
- [gtpc-ep Metrics Reference, on page 22](#)
- [gtp-ep Metrics Reference, on page 23](#)
- [nodemgr Metrics Reference, on page 31](#)
- [oam Metrics Reference, on page 46](#)
- [protocol Metrics Reference, on page 46](#)
- [radius-ep Metrics Reference, on page 47](#)
- [rest-ep Metrics Reference, on page 51](#)
- [smf-service Metrics Reference, on page 64](#)
- [udp-proxy Metrics Reference, on page 133](#)

chf-service Metrics Reference

CCF Data Consistency Check Category

ccf_datacheck_stats

Description: Total number of sessions checked for consistency

Sample Query: 'ccf_datacheck_stats{rat_type="NR", status="failed"}'

Labels:

- Label: `procedure_type`

Label Description: Procedure Name

Example: N40 Charging Data Request Create, N40 Charging Data Request Release SMF Initiated, N40 Session Modify SMF Initiated, N40 Session Notify - Abort, N40 Session Notify - Reauth, N28 Spending Limit Subscribe, N28 Spending Limit Subscribe Update, N28 Spending Limit UnSubscribe, N28 Spending Limit Notify Status, N28 Spending Limit Terminate Status, N28 Next Reval Notify, N40 Next Reval Notify

- Label: `rat_type`

Label Description: Type of the radio access associated

Example: EUTRA, NR, WLAN, VIRTUAL, rat_type_unknown

- Label: pdu_type

Label Description: Type of PDU session

Example: ipv4, ipv6, ipv4v6, unknown

- Label: status

Label Description: Procedure status after data consistency check

Example: success, failed

- Label: reason

Label Description: Failure reason of data inconsistency

Example: String format for failed reason

CCF Procedure Category

ccf_service_stats

Description: CCF call flow procedure counters

Sample Query: 'ccf_service_stats{procedure_type="pdu_sess_create"}'

Labels:

- Label: procedure_type

Label Description: The procedure type associated with an call flow procedure

Example: pdu_sess_create, smf_req_pdu_sess_mod, smf_req_pdu_sess_rel, pdu_sess_notify_abort, pdu_sess_notify_reauth, spending_limit_notify_terminate, spending_limit_notify_status, spending_limit_create, spending_limit_update, spending_limit_delete

- Label: status

Label Description: call flow procedure counter

Example: attempted, success, failures

- Label: dnn

Label Description: Dnn configured in dnn-policy, also can have virtual_dnn if configured, separated by #

Example: intershat, intershat#cisco.com

- Label: reason

Label Description: Reason for failure status. For sucessess and attempted it will be Empty

Example: proc_pdu_not_established, proc_pdu_ctx_not_found, internal_error, reason_unknown, pdn_create_over_created_pdn, auth_grpc_failed, maintenance_mode, quota_grpc_failed, auth_failed, cc_relay_failed

- Label: rat_type

Label Description: RAT Type of the Session

Example: EUTRA, NR, WLAN, rat_type_unknown

- Label: `roaming_status`

Label Description: Roaming status of the subscriber session

Example: IN_BOUND, OUT_BOUND, none

- Label: `ccf_current_procedure`

Label Description: Current Procedure Name for Message Level Stats

Example:

CCF Procedure Collision Category

`ccf_procedure_collision`

Description: Total number of procedures collided

Sample Query: `sum(ccf_procedure_collision) by (ccf_current_procedure, ccf_current_state, ccf_new_procedure, ccf_current_procedure_action)`

Labels:

- Label: `ccf_current_procedure`

Label Description: Current Procedure Name

Example: PDU Session Release - SMF initiated, PDU 5G to 4G Handover, PDU Session Modify - PCF initiated, PDU UE Sync Procedure, PDU Idle Mode Entry - RAN initiated

- Label: `ccf_current_state`

Label Description: Current Procedure State

Example: String format for procedure stat

- Label: `ccf_new_procedure`

Label Description: New Procedure Name

Example: String format for new procedure

- Label: `ccf_current_procedure_action`

Label Description: Current Procedure Action on Collision

Example: Ignore, Suspend, Resume, Abort, Cleanup, Continue, Ready, INVALID ACTION

CCF Procedure Total Time Statistics Category

`ccf_procedure_seconds`

Description: Total number of seconds taken to complete the procedure

Sample Query: `'ccf_procedure_seconds{ccf_proc_status="Aborted"}'`

Labels:

- Label: `ccf_proc_type`

Label Description: Procedure Name

Example: N40 Charging Data Request Create, N40 Charging Data Request Release SMF Initiated, N40 Session Modify SMF Initiated, N40 Session Notify - Abort, N40 Session Notify - Reauth, N28 Spending Limit Subscribe, N28 Spending Limit Subscribe Update, N28 Spending Limit UnSubscribe, N28 Spending Limit Notify Status, N28 Spending Limit Terminate Status, N28 Next Reval Notify, N40 Next Reval Notify

- Label: `ccf_proc_status`

Label Description: Procedure Status

Example: Queued, Running, Aborted, Suspended, Invalid, Cleanedup, RequireSuspend, RequireCleanup, RequireAbort, ProcStatusComplete, Unknown

CCF Start Procedure Statistics Category

ccf_procedure_start

Description: Total number of procedures started

Sample Query: `'ccf_procedure_start{ccf_proc_type="PDN Connect"}'`

Labels:

- Label: `ccf_proc_type`

Label Description: Procedure Name

Example: String format for procedure stat

CCF Stop Procedure Statistics Category

ccf_procedure_stop

Description: Total number of procedures stopped

Sample Query: `'ccf_procedure_stop{ccf_proc_type="PDU Session Establishment"}'`

Labels:

- Label: `ccf_proc_type`

Label Description: Procedure Name

Example: String format for procedure stat

- Label: `ccf_proc_status`

Label Description: Procedure Status

Example: Queued, Running, Aborted, Suspended, Invalid, Cleanedup, RequireSuspend, RequireCleanup, RequireAbort, ProcStatusComplete

CCF Total Procedure Count Category

ccf_procedure_total

Description: Total number of procedures executed

Sample Query: 'ccf_procedure_total{ccf_proc_status="Running"}'

Labels:

- Label: `ccf_proc_type`

Label Description: Procedure Name

Example: N40 Charging Data Request Create, N40 Charging Data Request Release SMF Initiated, N40 Session Modify SMF Initiated, N40 Session Notify - Abort, N40 Session Notify - Reauth, N28 Spending Limit Subscribe, N28 Spending Limit Subscribe Update, N28 Spending Limit UnSubscribe, N28 Spending Limit Notify Status, N28 Spending Limit Terminate Status, N28 Next Reval Notify, N40 Next Reval Notify

- Label: `ccf_proc_status`

Label Description: Procedure Status

Example: Queued, Running, Aborted, Suspended, Invalid, Cleanedup, RequireSuspend, RequireCleanup, RequireAbort, ProcStatusComplete, Unknown

CCF Total Timedout Procedure Count Category

ccf_procedure_timeout

Description: Total number of procedures executed more than 10sec

Sample Query: 'ccf_procedure_timeout{ccf_proc_status="Running"}'

Labels:

- Label: `ccf_proc_type`

Label Description: Procedure Name

Example: N40 Charging Data Request Create, N40 Charging Data Request Release SMF Initiated, N40 Session Modify SMF Initiated, N40 Session Notify - Abort, N40 Session Notify - Reauth, N28 Spending Limit Subscribe, N28 Spending Limit Subscribe Update, N28 Spending Limit UnSubscribe, N28 Spending Limit Notify Status, N28 Spending Limit Terminate Status, N28 Next Reval Notify, N40 Next Reval Notify

- Label: `ccf_proc_status`

Label Description: Procedure Status

Example: Queued, Running, Aborted, Suspended, Invalid, Cleanedup, RequireSuspend, RequireCleanup, RequireAbort, ProcStatusComplete, Unknown

CCF Total Timedout Procedure Time Category

ccf_procedure_timeout_seconds

Description: Total number of seconds taken by procedures executed more than 10sec

Sample Query: 'ccf_procedure_timeout_seconds{ccf_proc_status="Running"}'

Labels:

- Label: `ccf_proc_type`

Label Description: Procedure Name

Example: N40 Charging Data Request Create, N40 Charging Data Request Release SMF Initiated, N40 Session Modify SMF Initiated, N40 Session Notify - Abort, N40 Session Notify - Reauth, N28 Spending Limit Subscribe, N28 Spending Limit Subscribe Update, N28 Spending Limit UnSubscribe, N28 Spending Limit Notify Status, N28 Spending Limit Terminate Status, N28 Next Reval Notify, N40 Next Reval Notify

- Label: `ccf_proc_status`

Label Description: Procedure Status

Example: Queued, Running, Aborted, Suspended, Invalid, Cleanedup, RequireSuspend, RequireCleanup, RequireAbort, ProcStatusComplete, Unknown

CCF Total Unhandled Event Statistics Category

ccf_procedure_unhndl_event

Description: Total number of unhandled events per procedure type

Sample Query: 'ccf_procedure_unhndl_event{ccf_proc_type="PDU Session Release - SMF initiated"}'

Labels:

- Label: `ccf_proc_type`

Label Description: Procedure Name

Example: String format for procedure stat

- Label: `message_type`

Label Description: Type of Request/Response Message associated with Unhandled Event

Example: String format for event details

- Label: `ccf_current_state`

Label Description: Current Procedure State

Example: String format for procedure state

- Label: `guard_timer`

Label Description: This is a check for Guard Timeout. TRUE if Guard Timer has expired, else FALSE

Example: TRUE, FALSE

CCF Total Unhandled Transaction Statistics Category

ccf_procedure_unhndl_trans

Description: Total number of unhandled transactions per procedure type

Sample Query: 'xxf_procedure_unhndl_trans{message_type="RadiusCoaDisconnectReq"}'

Labels:

- Label: `ccf_proc_type`

Label Description: Procedure Name

Example: PDU Session Release - SMF initiated, PDU 5G to 4G Handover, PDU Session Modify - PCF initiated, PDU UE Sync Procedure, PDU Idle Mode Entry - RAN initiated

- Label: `message_type`

Label Description: Type of Request/Response Message associated with Unhandled Transaction

Example: String format for event details

- Label: `ccf_current_state`

Label Description: Current Procedure State

Example: String format for procedure state

- Label: `guard_timer`

Label Description: This is a check for Guard Timeout. TRUE if Guard Timer has expired, else FALSE

Example: TRUE, FALSE

CCF Usage Report Stats Category

ccf_usage_trigger_stats

Description: The current count for Used unit Container Recieved from SMF

Sample Query: 'ccf_usage_trigger_stats{ccf_proc_type="N40 Session Modify SMF Initiated"}'

Labels:

- Label: `rating_group`

Label Description: Rating Group for which usage is being reported

Example: Any string

- Label: `service_identifier`

Label Description: Service Identifier for which usage is being reported

Example: Any string

- Label: `ccf_proc_type`

Label Description: Which kind of procedure usage is reported to CCF

Example: Some String

- Label: `trigger`

Label Description: Trigger associated with UUC

Example: Triggers defined as per Specs 32.291

SLA Transaction Category

ccf_sla_transaction_stats

Description: Transaction SLA stats

Sample Query: `sum(ccf_sla_transaction_stats) by (ccf_sla_transaction_stats,ccf_proc_type,status, message_type)`

Labels:

- Label: `ccf_proc_type`

Label Description: Procedure Name

Example: N40 Charging Data Request Create, N40 Charging Data Request Release SMF Initiated, N40 Session Modify SMF Initiated, N40 Session Notify - Abort, N40 Session Notify - Reauth, N28 Spending Limit Subscribe, N28 Spending Limit Subscribe Update, N28 Spending Limit UnSubscribe, N28 Spending Limit Notify Status, N28 Spending Limit Terminate Status, N28 Next Reval Notify, N40 Next Reval Notify

- Label: `status`

Label Description: gives status of the procedure

Example: Queued, Running, Aborted, Suspended, Invalid, Cleanedup, RequireSuspend, RequireCleanup, RequireAbort, Unknown

- Label: `message_type`

Label Description: gives the message type received during sla transaction

Example: IntSelfTxnSla

diameter-ep statistics Category

diam_base_msg_seconds_total

Description: Cumulative response time in seconds of diameter base message requests processed by diameter endpoint

Sample Query: `'diam_base_msg_seconds_total{message_name="DPR"}'`

Labels:

- Label: `message_name`

Label Description: name of interface message

Example: DPR

- Label: `origin_host`

Label Description: name of the origin host

Example: 192.168.169.107

- Label: `origin_realm`

Label Description: name of the origin realm

Example: xyz.com

- Label: `disconnect_cause`

Label Description: reason for the disconnection

Example: REBOOTING, BUSY, DO_NOT_WANT_TO_TALK_TO_YOU

- Label: `result_code`

Label Description: `result_code` describes the error that the diameter node encountered in its processing

Example: 2001, 5012

- Label: `gr_instance`

Label Description: GR Instance ID

Example: 1 or 2

diam_base_msg_total

Description: Count of diameter base message requests processed by diameter endpoint

Sample Query: `'diam_base_msg_total{message_name="DPR"}'`

Labels:

- Label: `message_name`

Label Description: name of interface message

Example: DPR

- Label: `origin_host`

Label Description: name of the origin host

Example: 192.168.169.107

- Label: `origin_realm`

Label Description: name of the origin realm

Example: xyz.com

- Label: `disconnect_cause`

Label Description: reason for the disconnection

Example: REBOOTING, BUSY, DO_NOT_WANT_TO_TALK_TO_YOU

- Label: `result_code`

Label Description: result_code describes the error that the diameter node encountered in its processing

Example: 2001, 5012

- Label: gr_instance

Label Description: GR Instance ID

Example: 1 or 2

diameter_decode_message_total

Description: Count of decoding done by diameter endpoint

Sample Query: 'diameter_decode_message_total{interface="gx"}'

Labels:

- Label: interface

Label Description: name of the interface

Example: gx, gy

Labels:

- Label: message_name

Label Description: name of interface message

Example: ccai, ccaw, ccat, rar, asr

- Label: endpoint_name

Label Description: name of endpoint profile used during processing

Example: gxProfl

- Label: dict_name

Label Description: name of the dictionary used

Example: gx_cust

- Label: status

Label Description: status of the request

Example: success, failure, partial

- Label: unknown_avp

Label Description: unknown_avp indicates if any unknown AVPs were found during encoding where 0 indicates not found and 1 indicates found

Example: 0,1

- Label: gr_instance

Label Description: GR Instance ID

Example: 1 or 2

diameter_encode_message_total

Description: Count of encoding done by diameter endpoint

Sample Query: 'diameter_encode_message_total{interface="gx"}'

Labels:

- Label: `interface`

Label Description: name of the interface

Example: `gx`, `gy`

Labels:

- Label: `message_name`

Label Description: name of interface message

Example: `ccri`, `ccru`, `ccrt`, `raa`, `asa`

Labels:

- Label: `endpoint_name`

Label Description: name of endpoint profile used during processing

Example: `gxProfl`

- Label: `dict_name`

Label Description: name of the dictionary used

Example: `gx_cust`

- Label: `status`

Label Description: status of the request

Example: `success`, `failure`, `partial`

- Label: `unknown_avp`

Label Description: `unknown_avp` indicates if any unknown AVPs were found during encoding where 0 indicates not found and 1 indicates found

Example: 0,1

- Label: `gr_instance`

Label Description: GR Instance ID

Example: 1 or 2

diameter_pod_status

Description: Pod status as active/standby

Sample Query: 'diameter_pod_status{vip="10.0.0.1"}'

Labels:

- Label: `vip`

Label Description: any ip

Example: 10.0.0.1

diameter_request_message_total

Description: Count of diameter requests processed by diameter endpoint

Sample Query: 'diameter_request_message_total{interface="gx"}'

Labels:

- Label: `interface`

Label Description: name of the interface

Example: gx, gy

Labels:

- Label: `message_name`

Label Description: name of interface message

Example: ccni, ccru, ccrt, rar, asr

Labels:

- Label: `peer_address`

Label Description: peer_address will be empty for inbound requests, could be empty for outbound requests depending on point of failure

Example: 10.1.2.110:3868

Labels:

- Label: `status`

Label Description: status of the request

Example: attempted, peer_down, err_cfg, err_maxout, timeout_ipc, err_ipc, err_unmarshal

Labels:

- Label: `retry`

Label Description: retry count

Example: 0

- Label: `gr_instance`

Label Description: GR Instance ID

Example: 1 or 2

- Label: `transaction_type`

Label Description: transaction type

Example: origin

- Label: `endpoint_name`

Label Description: name of endpoint profile used during processing

Example: `gxProfl`

- Label: `message_direction`

Label Description: direction of message from Diameter perspective

Example: `inbound`, `outbound`

diameter_response_message_seconds_total

Description: Cumulative response time in seconds of diameter requests processed by diameter endpoint

Sample Query: `'diameter_response_message_seconds_total{interface="gx"}'`

Labels:

- Label: `interface`

Label Description: name of the interface

Example: `gx`, `gy`

Labels:

- Label: `message_name`

Label Description: name of interface message

Example: `ccai`, `ccau`, `ccat`, `raa`, `asa`

Labels:

- Label: `peer_address`

Label Description: `peer_address` will be empty for inbound requests, could be empty for outbound requests depending on point of failure

Example: `10.1.2.110:3868`

Labels:

- Label: `status`

Label Description: status of the request

Example: `success`, `err_cfg`, `err_maxout`, `err_send`, `timeout_res`, `timeout_ipc`, `err_ipc`, `err_unmarshal`, `err_rc`, `err_exp_rc`

Labels:

- Label: `result_code`

Label Description: `result_code` describes the result-code or experimental-result-code that the diameter node encountered during response processing

Example: `1001`, `2001`, `3001`, `4001`, `5001`

Labels:

- Label: `action`

Label Description: action

Example: continue, terminate

Labels:

- Label: `sub_action`

Label Description: sub action

Example: discard-traffic, local-fallback, retry-server-on-event, send-ccrt-on-call-termination, with-term-req, without-term-req

- Label: `gr_instance`

Label Description: GR Instance ID

Example: 1 or 2

- Label: `endpoint_name`

Label Description: name of endpoint profile used during processing

Example: gxProfl

- Label: `message_direction`

Label Description: direction of message from Diameter perspective

Example: inbound, outbound

diameter_response_message_total

Description: Count of diameter responses processed by diameter endpoint

Sample Query: `'diameter_response_message_total{interface="gx"}'`

Labels:

- Label: `interface`

Label Description: name of the interface

Example: gx, gy

Labels:

- Label: `message_name`

Label Description: name of interface message

Example: ccai, ccaw, ccat, raa, asa

Labels:

- Label: `peer_address`

Label Description: `peer_address` will be empty for inbound requests, could be empty for outbound requests depending on point of failure

Example: 10.1.2.110:3868

Labels:

- Label: `status`

Label Description: status of the request

Example: success, err_cfg, err_maxout, err_send, timeout_res, timeout_ipc, err_ipc, err_unmarshal, err_rc, err_exp_rc

Labels:

- Label: `result_code`

Label Description: result_code describes the result-code or experimental-result-code that the diameter node encountered during response processing

Example: 1001, 2001, 3001, 4001, 5001

Labels:

- Label: `action`

Label Description: action

Example: continue, terminate

Labels:

- Label: `sub_action`

Label Description: sub action

Example: discard-traffic, local-fallback, retry-server-on-event, send-ccrt-on-call-termination, with-term-req, without-term-req

Labels:

- Label: `gr_instance`

Label Description: GR Instance ID

Example: 1 or 2

Labels:

- Label: `endpoint_name`

Label Description: name of endpoint profile used during processing

Example: gxProfl

Labels:

- Label: `message_direction`

Label Description: direction of message from Diameter perspective

Example: inbound, outbound

diameter_route_expires_total

Description: Count of all dynamic routes expired

Sample Query: 'diameter_route_expires_total{gr_instance="1"}'

Labels:

- Label: `route`

Label Description: route identified by host, realm and peer

Example: OCS1:OCS.COM:DRA1

Labels:

- Label: `peer_name`

Label Description: peer name used by the route

Example: DRA1

Labels:

- Label: `gr_instance`

Label Description: GR Instance ID

Example: 1 or 2

diameter_route_hits_total

Description: Count of all route hits for messages processed by diameter endpoint

Sample Query: 'diameter_route_hits_total{route_type="S"}'

Labels:

- Label: `route`

Label Description: route identified by host, realm and peer

Example: OCS1:OCS.COM:DRA1

Labels:

- Label: `route_type`

Label Description: type of the route

Example: S or D

Labels:

- Label: `peer_name`

Label Description: peer name used by the route

Example: DRA1

Labels:

- Label: `wild_carded_route`

Label Description: route with wild carded host or realm

Example: *:OCS.COM:DRA1

Labels:

- Label: `gr_instance`

Label Description: GR Instance ID

Example: 1 or 2

diameter_route_misses_total

Description: Count of all route misses for messages processed by diameter endpoint

Sample Query: `'diameter_route_misses_total{route="OCS1:OCS.COM:DRA1"}'`

Labels:

- Label: `route`

Label Description: route identified by host, realm and peer

Example: OCS1:OCS.COM:DRA1

Labels:

- Label: `route_type`

Label Description: type of the route

Example: S or D

Labels:

- Label: `peer_name`

Label Description: peer name used by the route

Example: DRA1

Labels:

- Label: `gr_instance`

Label Description: GR Instance ID

Example: 1 or 2

diameter_route_status

Description: Status of a route

Sample Query: `'diameter_route_status{route="OCS1:OCS.COM:DRA1"}'`

Labels:

- Label: `route`

Label Description: route identified by host, realm and peer

Example: OCS1:OCS.COM:DRA1

Labels:

- Label: `route_type`

Label Description: type of the route

Example: S or D

Labels:

- Label: `peer_name`

Label Description: peer name used by the route

Example: DRA1

Labels:

- Label: `gr_instance`

Label Description: GR Instance ID

Example: 1 or 2

Labels:

- Label: `route_status`

Label Description: status of the route

Example: Pending or Active or Inactive or Failed or Deleted or Expired or Cloned

{{- end}}

diameter_routes_total

Description: Count of all diameter routes added by diameter endpoint

Sample Query: `'diameter_routes_total{gr_instance="1"}'`

Labels:

- Label: `route_type`

Label Description: type of the route

Example: S or D

Labels:

- Label: `peer_name`

Label Description: peer name used by the route

Example: DRA1

Labels:

- Label: `gr_instance`

Label Description: GR Instance ID

Example: 1 or 2

dispatch_error_seconds_total

Description: Cumulative time in seconds spent during dispatching of inbound requests to service that had error or timeout

Sample Query: 'dispatch_error_seconds_total{gr_instance="1"}'

Labels:

- Label: `application`
Label Description: name of the application
Example: diameter

Labels:

- Label: `command_code`
Label Description: command code
Example: RAR

Labels:

- Label: `error_code`
Label Description: error code
Example: 3002

Labels:

- Label: `gr_instance`
Label Description: GR Instance ID
Example: 1 or 2

dispatch_error_total

Description: Count of inbound requests that had error or timeout during dispatch to service

Sample Query: 'dispatch_error_total{gr_instance="1"}'

Labels:

- Label: `application`
Label Description: name of the application
Example: diameter

Labels:

- Label: `command_code`
Label Description: command code
Example: RAR

Labels:

- Label: `error_code`

Label Description: error code

Example: 3002

Labels:

- Label: `gr_instance`

Label Description: GR Instance ID

Example: 1 or 2

policy_engine_message_seconds_total

Description: Cumulative time in seconds spent during processing of message sent to service

Sample Query: `'policy_engine_message_seconds_total{gr_instance="1"}'`

Labels:

- Label: `application`

Label Description: name of the application

Example: diameter

Labels:

- Label: `command_code`

Label Description: command code

Example: RAR

Labels:

- Label: `gr_instance`

Label Description: GR Instance ID

Example: 1 or 2

policy_engine_message_total

Description: Count of messages sent to service for which response is received

Sample Query: `'policy_engine_message_total{gr_instance="1"}'`

Labels:

- Label: `application`

Label Description: name of the application

Example: diameter

Labels:

- Label: `command_code`

Label Description: command code

Example: RAR

Labels:

- Label: `gr_instance`

Label Description: GR Instance ID

Example: 1 or 2

dns-proxy Metrics Reference

DNS Lookup Request Statistics Category

DNS_Lookup_Requests_Statistics

Description: Total dns packets processed

Sample Query:

```
'DNS_Lookup_Requests_Statistics(dnsPacketDir="Rx",dnsProtocol="udp",dnsQueryType="ipv4",dnsResult="Success",dnsSvrIP="172.17.0.2",dnsSvrPort="53",grInstId="1")'
```

Labels:

- Label: `dnsPacketDir`

Label Description: Direction

Example: Tx, Rx

- Label: `dnsProtocol`

Label Description: Protocol

Example: udp, tcp

- Label: `dnsQueryType`

Label Description: DNS Lookup Query type

Example: ipv4, ipv6, ipv4v6

- Label: `dnsResult`

Label Description: Result

Example: Success, Failure, Timeout, Failure_No_Response

- Label: `dnsSvrIP`

Label Description: DNS Server IP Address

Example: Any string

- Label: `dnsSvrPort`

Label Description: DNS Server Port

Example: Any string

- Label: `grInstId`

Label Description: GR Instance Id

Example: 1 or 2

gtpc-ep Metrics Reference

GTPC BGP Routed Count Stats Category

gtpc_app_bgp_routes_count

Description: BGP routes add counter

Sample Query: `'gtpc_app_bgp_routes_count{status="success"}'`

Labels:

- Label: `status`

Label Description: status

Example: success, failed

- Label: `gr_instance_id`

Label Description: GR instance ID

Example: 1, 2

GTPC Roaming Peer Path Mgmt Stats Category

gtpc_roaming_peer_path_mgmt

Description: GTPC Roaming Peer Path Mgmt Stats

Sample Query: `'gtpc_roaming_peer_path_mgmt{service_name="gtpc-ep",status="suppressed"}'`

Labels:

- Label: `gtpc_peer_type`

Label Description: Gtpc Peer type

Example: ROAMER, HOMER, VISITOR

- Label: `interface_type`

Label Description: Gtpc Interface type

Example: S5, S11, S5E, S2B, S8

- Label: `gtpc_msg_type`

Label Description: Gtpc Message type

Example: NumEchoMsg, NumControlMsg

- Label: `status`

Label Description: Status

Example: suppressed

- Label: `gr_instance_id`

Label Description: GR instance ID

Example: 1, 2

gtp-ep Metrics Reference

ASN1 Encoding stats Category

gtp_asn1field_encoding_failures_total

Description: A counter for total number of fields failed to be ASN1 encoded

Sample Query: `'gtp_asn1field_encoding_failures_total{gtp_profile="pf1"}'`

Labels:

- Label: `gtp_profile`

Label Description: Gtp Profile Name

Example: pf1, pf2

- Label: `dictionary`

Label Description: Gtp Dictionary Used

Example: custom6, custom24

- Label: `asn1_field`

Label Description: ASN1 Field

Example: ServedIMSI, ChargingID, ServingNodeAddress, ChargingCharacteristics

- Label: `reason`

Label Description: Reason for failure

Example: Constraint Violation

CDR Batch flush duration stats Category

gtp_batch_flush_duration_histogram_total

Description: Histogram time bins of batch flush time

Sample Query: 'gtp_batch_flush_duration_histogram_total{gtp_profile="pf1"}'

Labels:

- Label: `gtp_profile`
Label Description: Gtp Profile Name
Example: pf1, pf2
- Label: `dictionary`
Label Description: Gtp Dictionary Used
Example: custom6, custom24
- Label: `status`
Label Description: Status of the operation
Example: batch_success, batch_error

CDR Batch flush stats Category

gtp_batch_flush_millis_total

Description: A Histogram for the time CDRs remain in batch before flushed

Sample Query: 'gtp_batch_flush_millis_total{gtp_profile="pf1"}'

Labels:

- Label: `gtp_profile`
Label Description: Gtp Profile Name
Example: pf1, pf2
- Label: `dictionary`
Label Description: Gtp Dictionary Used
Example: custom6, custom24
- Label: `status`
Label Description: Status of the operation
Example: batch_success, batch_error

CDR Batching Stats Category

gtp_batched_cdrs_total

Description: No. of CDRs in a batch for a given profile

Sample Query: 'gtp_batched_cdrs_total{gtp_profile="pf1"}'

Labels:

- Label: `gtp_p_profile`
Label Description: Gtp Profile Name
Example: pf1, pf2
- Label: `dictionary`
Label Description: Gtp Dictionary Used
Example: custom6, custom24
- Label: `status`
Label Description: Status of the operation
Example: batch_success, batch_error

DupReqList buffer gauge Category

`gtp_dup_reqlist_counter`

Description: GTP Dup Req List

Sample Query: `'gtp_dup_reqlist_counter{gtp_p_profile="pf1"}'`

Labels:

- Label: `gtp_p_profile`
Label Description: Gtp Profile Name
Example: pf1, pf2
- Label: `cgf_addr`
Label Description: Cgf Server Address
Example: 1.2.3.4
- Label: `state`
Label Description: Request Process State
Example: empty_cdr_rsp_wait, dup_cdr_rel_rsp_wait, dup_cdr_can_rsp_wait, to_send_empty_rsp_wait

File based CDR Read Category

`gtp_file_record_read`

Description: GTP CDR file based reads

Sample Query: `'gtp_file_record_read{gtp_p_profile="pf1"}'`

Labels:

- Label: `gtp_p_profile`
Label Description: Gtp Profile Name

Example: pf1, pf2

- Label: `status`

Label Description: CDR read operation status

Example: success,failure

- Label: `pod_status`

Label Description: Active/StandBy

Example: active,standby

File based CDR Write Category

gtpg_file_record_write

Description: GTPG CDR file based writes

Sample Query: 'gtpg_file_record_write(gtpg_profile="pf1")'

Labels:

- Label: `gtpg_profile`

Label Description: Gtpg Profile Name

Example: pf1, pf2

- Label: `status`

Label Description: CDR write operation status

Example: success,failure

- Label: `pod_status`

Label Description: Active/StandBy

Example: active,standby

GTPG Archive List gauge Category

gtpg_archive_list_counter

Description: GTPG Archive List

Sample Query: 'gtpg_archive_list_counter(gtpg_profile="pf1")'

Labels:

- Label: `gtpg_profile`

Label Description: Gtpg Profile Name

Example: pf1, pf2

- Label: `pod_status`

Label Description: Active/StandBy

Example: active,standby

GTPP Messages Stats Category

gtpplib_msg_stats

Description: GTPP MSG Stats

Sample Query: 'gtpplib_msg_stats{gtpplib_profile="pf1"}'

Labels:

- Label: gtpplib_profile

Label Description: Gtpplib Profile Name

Example: pf1, pf2

- Label: msg_type

Label Description: GTPP Msg Name

Example: DataRecTransReq, DataRecTransReqPossibleDup, DataRecTransReqCancel, DataRecTransReqRelease, DataRecTransReqEmpty, DataRecTransReqRetried, DataRecTransReqPossibleDuplRetried, DataRecTransReqCancelRetried, DataRecTransReqReleaseRetried, DataRecTransReqEmptyRetried, DataRecTransRsp, DataRecTransPossibleDuplRsp, DataRecTransCancelRsp, DataRecTransReleaseRsp, DataRecTransEmptyRsp, EchoReqSent, EchoReqRcvd, EchoRspSent, EchoRspRcvd, NodeAliveReqSent, NodeAliveReqRcvd, NodeAliveRspSent, NodeAliveRspRcvd, TestEchoReqSent, TestEchoRspRcvd

- Label: status

Label Description: Request/Response Message Handling Status

Example: success,failure

- Label: cause

Label Description: GTPP Messages Response Cause

Example: accepted, mandatory_ie_incorrect, mandatory_ie_missing, invalid_message_format, optional_ie_incorrect, no_resources_available, system_failure, service_not_supported, version_not_supported, not_fulfilled, already_fulfilled, cdr_decode_error, sequence_numbers_incorrect,buffer_full,internal_failure,ipc_err

- Label: cgf_addr

Label Description: Cgf Server Address

Example: 1.2.3.4

- Label: trigger_type

Label Description: Trigger for this Message

Example: normal cdr, pod_switchover, peer_restart, cgf_down

GTPP Replication Msg Stats Category

gtpplib_replication_stats

Description: GTPP Replication Data Msg

Sample Query: 'gtpplib_replication_stats{gtpplib_profile="pf1"}'

Labels:

- Label: gtpplib_profile
Label Description: Gtpplib Profile Name
Example: pf1, pf2
- Label: cgf_addr
Label Description: Cgf Server Address
Example: 1.2.3.4
- Label: item
Label Description: Peer Struct Replicated Item
Example:
SndReqListTx,DupReqListTx,SeqPoolTx,SndReqListRx,DupReqListRx,SeqPoolRx,ArchiveListTx,ArchiveListRx,FileCdrTx,FileCdrRx
- Label: op_type
Label Description: Operation Type
Example: Add,Update,Delete
- Label: status
Label Description: Peer Replication Msg Handling Status
Example: success,failure

Inbound CDR Requests Category

gtpplib_received_cdrs_total

Description: A counter for total number of CDRs received in request

Sample Query: 'gtpplib_received_cdrs_total{gtpplib_profile="pf1"}'

Labels:

- Label: gtpplib_profile
Label Description: Gtpplib Profile Name
Example: pf1, pf2
- Label: dictionary
Label Description: Gtpplib Dictionary Used

Example: custom6, custom24

Processed CDR Requests Category

gtpc_processed_cdrs_total

Description: A counter for total number of CDRs processed in transaction

Sample Query: 'gtpc_processed_cdrs_total{gtpc_profile="pf1"}'

Labels:

- Label: gtpc_profile
Label Description: Gtpc Profile Name
Example: pf1, pf2
- Label: dictionary
Label Description: Gtpc Dictionary Used
Example: custom6, custom24
- Label: status
Label Description: Status of processed CDR request
Example: Success, profile_error, not_leader_pod_error

Read from GTPC Archive List Stats Category

gtpc_archive_list_read

Description: GTPC Archive List Read

Sample Query: 'gtpc_archive_list_read{gtpc_profile="pf1"}'

Labels:

- Label: gtpc_profile
Label Description: Gtpc Profile Name
Example: pf1, pf2
- Label: status
Label Description: Status of CDR read from Archive
Example: success, failure
- Label: sub_status
Label Description: Sub Status of CDR read from Archive
Example: lookup, send_to_cgf, send_to_hdd, purge
- Label: pod_status

Label Description: Active/StandBy

Example: active,standby

SendReqList buffer gauge Category

gtp_send_reqlist_counter

Description: GTPP Send Req List

Sample Query: 'gtp_send_reqlist_counter{gtp_profile="pf1"}'

Labels:

- Label: `gtp_profile`
Label Description: Gtp Profile Name
Example: pf1, pf2
- Label: `cgf_addr`
Label Description: Cgf Server Address
Example: 1.2.3.4
- Label: `state`
Label Description: Request Process State
Example: Normal_CDR_Rsp_Wait,Duplicate_CDR_Rsp_Wait

Write to GTPP Archive List Stats Category

gtp_archive_list_write

Description: GTPP Archive List Write

Sample Query: 'gtp_archive_list_write{gtp_profile="pf1"}'

Labels:

- Label: `gtp_profile`
Label Description: Gtp Profile Name
Example: pf1, pf2
- Label: `status`
Label Description: Status of CDR write to Archive
Example: success, failure
- Label: `sub_status`
Label Description: Sub Status of CDR write to Archive
Example: purge_oldest_cdr

- Label: `pod_status`

Label Description: Active/StandBy

Example: active,standby

nodemgr Metrics Reference

Nodemgr messages Category

nodemgr_msg_stats

Description: Node Manager Resource management message counters

Sample Query: `'nodemgr_msg_stats{nodemgr_id="0", id_req_type="ID_REQ_ALLOC", ip_req_type="IP_REQ_ALLOC", ip_version="IP_TYPE_V4", sent_to_owner="0", service_user="SERVICE_USER_SMF"}'`

Labels:

- Label: `nodemgr_id`

Label Description: Node Manager instance for which statistics are to be checked

Example: 0, 1, 2, 3, 4, 5, 6, 7, 8

- Label: `id_req_type`

Label Description: Type of request recieved at node manager message

Example: ID_REQ_NONE, ID_REQ_ALLOC, ID_REQ_REL, ID_REQ_REALLOC

- Label: `ip_req_type`

Label Description: Type of request recieved at node manager for IP address

Example: IP_REQ_NONE, IP_REQ_ALLOC, IP_REQ_REL, IP_REQ_REALLOC, IP_REQ_STATIC

- Label: `ip_version`

Label Description: IP address type for which request was recieved

Example: IP_TYPE_NONE, IP_TYPE_V4, IP_TYPE_V6, IP_TYPE_V4V6

- Label: `sent_to_owner`

Label Description: Current Node Manager instance for which statistics are to be checked

Example: 0, 1, 2, 3, 4, 5, 6, 7, 8

- Label: `service_user`

Label Description: Node Type which has requested the Node Manager services

Example: SERVICE_USER_NONE, SERVICE_USER_SMF, SERVICE_USER_SGW

- Label: `gr_instance_id`

Label Description: GR instance ID

Example: 1, 2

Nodemgr userplane stats Category

nodemgr_up_stats

Description: Node Manager to userplane (UPF) link status up guage counters

Sample Query: 'nodemgr_up_stats{up_ep_key="192.168.10.2:192.168.20.3", primary_nodemgr_id="0", peer_nodemgr_id="0", interface_type="SXB"}'

Labels:

- Label: `up_ep_key`

Label Description: unique key to identify UPF XXX.XXX.XXX.XXX:YYY.YYY.YYY.YYY where XXX.XXX.XXX.XXX is Ip address of the NF service like SGW / SMF and YYY.YYY.YYY.YYY is the IP address of UPF

Example: 192.168.10.2:192.168.20.3

- Label: `primary_nodemgr_id`

Label Description: Current Node Manager instance Identifier of SGW/SMF service

Example: 0, 1, 2, 3, 4, 5, 6, 7, 8

- Label: `peer_nodemgr_id`

Label Description: Peer Node Manager instance Identifier of UPF service

Example: 0, 1, 2, 3, 4, 5, 6, 7, 8

- Label: `interface_type`

Label Description: Interface type between current node (SMF/SGW) and Peer Node (UPF)

Example: SXA, SXB, SXAB, SXC, N4

- Label: `gr_instance_id`

Label Description: GR instance ID

Example: 1, 2

Nodemgr userplane link status stats Category

nodemgr_upf_link_status

Description: Nodemgr gauge counter to keep track of userplane link status between UPF and SMF/SGW

Sample Query: 'nodemgr_upf_link_status{up_ep_key="192.168.10.2:192.168.20.3", primary_nodemgr_id="0", peer_nodemgr_id="0", interface_type="SXB"}'

Labels:

- Label: `up_ep_key`

Label Description: unique key to identify UPF XXX.XXX.XXX.XXX:YYY.YYY.YYY.YYY where XXX.XXX.XXX.XXX is Ip address of the NF service like SGW / SMF and YYY.YYY.YYY.YYY is the IP address of UPF

Example: 192.168.10.2:192.168.20.3

- Label: `primary_nodemgr_id`

Label Description: Current Node Manager instance Identifier of SGW/SMF service

Example: 0, 1, 2, 3, 4, 5, 6, 7, 8

- Label: `peer_nodemgr_id`

Label Description: Peer Node Manager instance Identifier of UPF service

Example: 0, 1, 2, 3, 4, 5, 6, 7, 8

- Label: `interface_type`

Label Description: Interface type between current node (SMF/SGW) and Peer Node (UPF)

Example: SXA, SXB, SXAB, SXC, N4

- Label: `gr_instance_id`

Label Description: GR instance ID

Example: 1, 2

Nodemgr resource management response statistics Category

nodemgr_resource_mgmt_resp_stats

Description: Node Manager resource management response statistics

Sample Query: 'nodemgr_resource_mgmt_resp_stats{req_type="1", ip_ver_type="1", status="attempted", error=""}'

Labels:

- Label: `req_type`

Label Description: The request for which this response is being sent, Request with no operation = 0, Request with IP allocation = 1, Request with IP release = 2, Request with IP reallocation = 3, Request with Static IP allocation = 4

Example: 0, 1, 2, 3, 4

- Label: `ip_ver_type`

Label Description: Type of IP addresses requested in the message, IP type requested NONE = 0, IP type requested V4 = 1, IP type requested V6 = 2, IP type requested V4V6 = 3

Example: 0, 1, 2, 3

- Label: `status`

Label Description: Status of the request

Example: attempted, success, failed

Example: Unable to get UpfKey for upf

Example: 1, 2

Example: v_1, v_2

Nodemgr gtpc peer status statistics Category

nodemgr_gtpc_peer_status

Description: Node manager gtpc peer status statistics for keeping track of gtpc peers like SGW, PGW or ePDG via keep alive or restart counter tracking

Sample Query: 'nodemgr_gtpc_peer_status{gtpc_peer_ip="192.168.10.2", gtpc_msg_type="gtpc_echo_res_rx", interface_type="S11"}'

Labels:

- Label: `gtpc_peer_ip`

Label Description: IP address of a gtpc peer like SGW, PGW or ePDG

Example: 192.168.10.2

- Label: `gtpc_peer_status`

Label Description: GTPC peer current status as a result of keep alive success/failure or restart counter tracking

Example: `gtpc_peer_path_down`, `gtpc_peer_path_up`, `gtpc_peer_restarted`

- Label: `interface_type`

Label Description: Interfaces on which the gtpc message is recieved or sent PGW, SGW-Egress, SGW-Ingress etc

Example: S11, S5E, S5, S8, S2B

- Label: `restart_time`

Label Description: Gtpc peer restart time

Example: 2022-09-30 14:32:52 +0000 UTC

- Label: `gr_instance_id`

Label Description: GR instance ID

Example: 1, 2

- Label: `gtpc_msg_ver`

Label Description: GTP Message Version

Example: v1, v2

Nodemgr gtp message statistics Category

nodemgr_gtp_msg_stats

Description: Node manager gtp message statistics to update stats for msg triggered by NodeMgr

Sample Query:

'nodemgr_gtp_msg_stats{ca_ip="10.65.45.181", ca_port="2222", cgf_ip="10.78.41.152", cgf_port="3386", gtp_msg_type="gtp_echo_req"}'

Labels:

- Label: `ca_ip`
Label Description: Charging agent ip address
Example: 10.65.45.181
- Label: `ca_port`
Label Description: Charging agent port number
Example: 2222
- Label: `cgf_ip`
Label Description: Cgf ip address
Example: 10.78.41.152
- Label: `cgf_port`
Label Description: Cgf port number
Example: 3386
- Label: `gtpv_msg_type`
Label Description: Msg triggered towards gtpv-ep like echo req/path up/path down/peer restart
Example: `gtpv_echo_req`, `gtpv_peer_path_up`, `gtpv_peer_path_down`, `gtpv_peer_restarted`

Nodemgr gtpv peer status statistics Category

`nodemgr_gtpv_peer_status`

Description: Node manager gtpv peer status statistics for keeping track of cgf nodes via node alive/echo/gtpv control message success/failure or restart counter tracking

Sample Query:

```
'nodemgr_gtpv_peer_status(ca_ip="10.65.45.181",ca_port="2222",cgf_ip="10.78.41.152",cgf_port="3386",gtpv_peer_reason="RESTART",gtpv_peer_status="gtpv_peer_path_up",restart_time="2023-03-29 15:46:27 +0530 IST")'
```

Labels:

- Label: `ca_ip`
Label Description: Charging agent ip address
Example: 10.65.45.181
- Label: `ca_port`
Label Description: Charging agent port number
Example: 2222
- Label: `cgf_ip`
Label Description: Cgf ip address
Example: 10.78.41.152
- Label: `cgf_port`

Label Description: Cgf port number

Example: 3386

- Label: `gtppeer_reason`

Label Description: Cgf update reason (add/update/delete) as a result of node alive/echo/gtp control message success/failure or restart counter tracking

Example: PEER_ADD, PEER_UP, PEER_DELETE, NO_ECHO_RESPONSE, NO_CTRL_MSG_RESPONSE

- Label: `gtppeer_status`

Label Description: Cgf status (up/down/restart) as a result of node alive/echo/gtp control message success/failure or restart counter tracking

Example: `gtppeer_path_down`, `gtppeer_path_up`, `gtppeer_restarted`

- Label: `restart_time`

Label Description: Cgf restart time

Example: 2023-03-29 15:46:27 +0530 IST

Nodemgr GTPP link status Category

nodemgr_gtp_stats

Description: Nodemgr gauge counter to keep track of GTPP peer (CGF) link status between CGF and SMF/SBW

Sample Query: `'nodemgr_gtp_stats{gtppeer_cgf_key="192.168.10.2:9001", gtppeer_ca_key="192.168.10.3:9001"}'`

Labels:

- Label: `gtppeer_cgf_key`

Label Description: unique key to identify CGF `YYY.YYY.YYY.YYY:XXX` where `YYY.YYY.YYY.YYY` is the Ip address of the CGF and `XXX` is the port number

Example: 192.168.10.2:9001

- Label: `gtppeer_ca_key`

Label Description: unique key to identify Charging Agent (CA) `YYY.YYY.YYY.YYY:XXX` where `YYY.YYY.YYY.YYY` is the Ip address of Charging agent configured on the NF service like SGW / SMF and `XXX` is the port number

Example: 192.168.20.3:9001

- Label: `gr_instance_id`

Label Description: GR instance ID

Example: 1, 2

Nodemgr userplane heart beat message stats Category

nodemgr_up_hb_msg_stats

Description: Node Manager userplane heart beat message counters between UPF node and SMF/PGW/SGW node

Sample Query: 'nodemgr_up_hb_msg_stats{up_ep_key="192.168.10.2:192.168.20.3", primary_nodemgr_id="0", current_nodemgr_id="0", up_msg_type="up_heartbeat_req_tx", interface_type="SXB"}'

Labels:

- Label: up_ep_key

Label Description: unique key to identify UPF XXX.XXX.XXX.XXX:YYY.YYY.YYY.YYY where XXX.XXX.XXX.XXX is Ip address of the NF service like SGW / SMF and YYY.YYY.YYY.YYY is the IP address of UPF

Example: 192.168.10.2:192.168.20.3

- Label: primary_nodemgr_id

Label Description: Node Manager instance Identifier of SGW/SMF service which originally established interaction with UPF

Example: 0, 1, 2, 3, 4, 5, 6, 7, 8

- Label: current_nodemgr_id

Label Description: Current Node Manager instance Identifier of SGW/SMF service which is currently established and interacting with UPF

Example: 0, 1, 2, 3, 4, 5, 6, 7, 8

- Label: up_msg_type

Label Description: Message type which is received or sent for heartbeat messaging

Example: up_heartbeat_req_tx, up_heartbeat_req_ret, up_heartbeat_rsp_rx

- Label: interface_type

Label Description: Interface type between current node (SMF/SGW) and Peer Node (UPF)

Example: SXA, SXB, SXAB, SXC, N4

- Label: gr_instance_id

Label Description: GR instance ID

Example: 1, 2

Nodemgr userplane heart beat message failure stats Category

nodemgr_up_hb_msg_fail_stats

Description: Node Manager userplane heart beat message failure counters between UPF node and SMF/PGW/SGW node as unable to send request to UPF

Sample Query: 'nodemgr_up_hb_msg_fail_stats{up_ep_key="192.168.10.2:192.168.20.3", primary_nodemgr_id="0", current_nodemgr_id="0", up_msg_type="up_heartbeat_req_tx", interface_type="SXB"}'

Labels:

- Label: up_ep_key

Label Description: unique key to identify UPF XXX.XXX.XXX.XXX:YYY.YYY.YYY.YYY where XXX.XXX.XXX.XXX is Ip address of the NF service like SGW / SMF and YYY.YYY.YYY.YYY is the IP address of UPF

Example: 192.168.10.2:192.168.20.3

- Label: primary_nodemgr_id

Label Description: Node Manager instance Identifier of SGW/SMF service which originally established interaction with UPF

Example: 0, 1, 2, 3, 4, 5, 6, 7, 8

- Label: current_nodemgr_id

Label Description: Current Node Manager instance Identifier of SGW/SMF service which is currently established and interacting with UPF

Example: 0, 1, 2, 3, 4, 5, 6, 7, 8

- Label: up_msg_type

Label Description: Message type which is received or sent for heartbeat messaging

Example: up_heartbeat_req_tx, up_heartbeat_req_retx, up_heartbeat_rsp_rx

- Label: interface_type

Label Description: Interface type between current node (SMF/SGW) and Peer Node (UPF)

Example: SXA, SXB, SXAB, SXC, N4

- Label: gr_instance_id

Label Description: GR instance ID

Example: 1, 2

Nodemgr userplane heart beat message failure due to retransmission stats Category

nodemgr_up_heartbeat_fail_stats

Description: Node Manager userplane heart beat message failure counters between UPF node and SMF/PGW/SGW node as retransmission requests exhausted to UPF

Sample Query: 'nodemgr_up_heartbeat_fail_stats{up_ep_key="192.168.10.2:192.168.20.3", primary_nodemgr_id="0", current_nodemgr_id="0", up_msg_type="up_heartbeat_req_tx", interface_type="SXB"}'

Labels:

- Label: `up_ep_key`

Label Description: unique key to identify UPF XXX.XXX.XXX.XXX:YYY.YYY.YYY.YYY where XXX.XXX.XXX.XXX is Ip address of the NF service like SGW / SMF and YYY.YYY.YYY.YYY is the IP address of UPF

Example: 192.168.10.2:192.168.20.3

- Label: `interface_type`

Label Description: Interface type between current node (SMF/SGW) and Peer Node (UPF)

Example: SXA, SXB, SXAB, SXC, N4

- Label: `gr_instance_id`

Label Description: GR instance ID

Example: 1, 2

Nodemgr node report message handling from UPF to current node stats Category

nodemgr_node_report_stats

Description: Node Manager handling of node report from UPF about the status of NR's or gNB's having sessions with the UPF

Sample Query: 'nodemgr_node_report_stats{up_ep_key="192.168.10.2:192.168.20.3", node_report_peer_gtpu="192.168.30.4", node_report_no_of_sess="0", status="success", node_report_type="", session_tmr="10", backlog_tmr="1564555678270689300"}'

Labels:

- Label: `up_ep_key`

Label Description: unique key to identify UPF XXX.XXX.XXX.XXX:YYY.YYY.YYY.YYY where XXX.XXX.XXX.XXX is Ip address of the NF service like SGW / SMF and YYY.YYY.YYY.YYY is the IP address of UPF

Example: 192.168.10.2:192.168.20.3

- Label: `node_report_peer_gtpu`

Label Description: Peer GTPU IP address of gNB or NR to which UPF has established the userplane session

Example: 192.168.30.4

- Label: `node_report_no_of_sess`

Label Description: Total number of session established for the Peer GTPU gNB or NR via the UPF

Example: 0

- Label: `status`

Label Description: Node report message handling status by Node manager

Example: attempted, success, failure

- Label: `node_report_type`
Label Description: Type of node report message being handled
Example: `upd_TS_failed`, `duplicate`, `origin`
- Label: `session_tmr`
Label Description: Time duration in minutes during which the node report message has to be handled by the SMF/SGW/PGW node
Example: 0, 10
- Label: `backlog_tmr`
Label Description: Current time stamp in unix epoch value for node report message processing
Example: 1564555678270689300
- Label: `gr_instance_id`
Label Description: GR instance ID
Example: 1, 2

Nodemgr node report message handling timer stats Category

`nodemgr_node_rpt_timer_stats`

Description: Timer to handle Node Manager handling of node report from UPF about the status of NR's or gNB's having sessions with the UPF

Sample Query: `'nodemgr_node_rpt_timer_stats{up_ep_key="192.168.10.2:192.168.20.3", node_report_peer_gtpu="192.168.30.4", node_report_no_of_sess="0", status="success", node_report_type="", backlog_tmr="1564555678270689300"}'`

Labels:

- Label: `up_ep_key`
Label Description: unique key to identify UPF XXX.XXX.XXX.XXX:YYY.YYY.YYY.YYY where XXX.XXX.XXX.XXX is Ip address of the NF service like SGW / SMF and YYY.YYY.YYY.YYY is the IP address of UPF
Example: 192.168.10.2:192.168.20.3
- Label: `node_report_peer_gtpu`
Label Description: Peer GTPU IP address of gNB or NR to which UPF has established the userplane session
Example: 192.168.30.4
- Label: `node_report_no_of_sess`
Label Description: Total number of session established for the Peer GTPU gNB or NR via the UPF
Example: 0
- Label: `status`

Label Description: Node report message handling status by Node manager

Example: attempted, success, failure

- Label: `node_report_type`

Label Description: Type of node report message being handled

Example: `tmr_start_failed`, `dbg_tmr`, `retry_clrBlkSubs`

- Label: `backlog_tmr`

Label Description: Current time stamp in unix epoch value for node report message processing

Example: 1564555678270689300

- Label: `gr_instance_id`

Label Description: GR instance ID

Example: 1, 2

Nodemgr UPF ip address threshol hit stats Category

nodemgr_up_threshold_stats

Description: When particular IP address pool threshold hit for usage of ip addresses of a particular address type, this stats will be recorded

Sample Query: `'nodemgr_up_threshold_stats{up_ep_key="192.168.10.2:192.168.20.3", dnn="sampleDNN", threshold_hit="yes", ip_ver_type="IP_TYPE_V4"}'`

Labels:

- Label: `up_ep_key`

Label Description: unique key to identify UPF XXX.XXX.XXX.XXX:YYY.YYY.YYY.YYY where XXX.XXX.XXX.XXX is Ip address of the NF service like SGW / SMF and YYY.YYY.YYY.YYY is the IP address of UPF

Example: 192.168.10.2:192.168.20.3

- Label: `dnn`

Label Description: DNN of which ip pool reached the configured threshold usgae.

Example: sampleDNN

- Label: `threshold_hit`

Label Description: Indicates if threshold hit is yes or no.

Example: yes

- Label: `threshold_clear`

Label Description: Indicates if threshold hit is cleared or not

Example: yes

- Label: `nodemgr_id`

Example: 1

- Label Description: GR instance ID

Label Description: Type of IP addresses for which threshold is hit or clear

Label Description: Numa ID of the UPF for which threshold is hit or clear

Example: 4

Example: 1, 2

```

"logging_upper_status": "up", "cluster": "t", "datacenter": "t", "instance_id": "t", "interface_type": "S2", "service_name": "logging", "ip_prefix": "20.20.20.6/20.20.20.42", "upper_status": "upper_path_u"}
1'

```

Labels:

- Label: `up_peer_ip`

Label Description: unique key to identify UPF `YYY.YYY.YYY.YYY:XXX.XXX.XXX.XXX` where `XXX.XXX.XXX.XXX` is Ip address of the NF service like SGW / SMF and `YYY.YYY.YYY.YYY` is the IP address of UPF

Example: `20.20.20.66:20.20.20.42`

- Label: `up_peer_status`

Label Description: Node manager UPF Peer status

Example: `up_peer_path_down,up_peer_path_up`

- Label: `interface_type`

Label Description: nterface type between Peer Node (UPF)

Example: `SXA`

- Label: `gr_instance_id`

Label Description: GR instance ID

Example: `1, 2`

Nodemgr resource management batch reconciliation counter Category

`nodemgr_rmgr_batch_reconcile_stats`

Description: Node manager resource management batch reconciliation counter

Sample Query: `'nodemgr_rmgr_batch_reconcile_stats{status="success"}'`

Labels:

- Label: `status`

Label Description: reconciliation status

Example: `success, failed`

SMF Recovery Value stats Category

`smf_recovery_value`

Description: SMF Recovery Value stats

Sample Query: `'smf_recovery_value{smf_ip="192.168.10.2"}'`

Labels:

- Label: `smf_ip`

Label Description: smf ip address

Example: `192.168.10.2`

Nodemgr diagnostics address validation counter Category

nodemgr_diag_ip_verify

Description: Node manager diagnostics address validation counter

Sample Query: 'nodemgr_diag_ip_verify{status="success"}'

Labels:

- Label: status

Label Description: diagnostics address validation status

Example: success, unknown, cdl_ipc_failure, ipv4_alloc_failed, ipv6_alloc_failed, ip_mismatch_ignored, duplicate_record_found

Nodemgr userplane routes update or delete counter Category

nodemgr_up_route_stats

Description: Nodemgr userplane routes update or delete counter

Sample Query:

```
'nodemgr_up_route_stats{op="update",cluster="t1",datacenter="t1",instance="t1",service="t1",integration="t1",status="Success",up_key="192.168.10.2:192.168.20.3",tx_type="NewTx"}'
```

Labels:

- Label: route_operation

Label Description: Kind of route operation

Example: Update, Delete

- Label: status

Label Description: Status of the request

Example: Success, Failed, Dropped

- Label: up_ep_key

Label Description: unique key to identify UPF XXX.XXX.XXX.XXX:YYY.YYY.YYY.YYY where XXX.XXX.XXX.XXX is Ip address of the NF service like SGW / SMF and YYY.YYY.YYY.YYY is the IP address of UPF

Example: 192.168.10.2:192.168.20.3

- Label: tx_type

Label Description: Type of the transaction for the route operation

Example: NewTx, RetTx

oam Metrics Reference

Node level LCI metric Category

node_lci_metric

Description: Total node level LCI metric

Sample Query: `node_lci_metric{}`

Node level OCI metric Category

node_oci_metric

Description: Total node level OCI reduction metric

Sample Query: `node_oci_metric{}`

Node level overload state Category

node_overload_status

Description: Total node level overload state

Sample Query: `node_overload_status{}`

protocol Metrics Reference

PFCP Decoded Messages Category

proto_pfcg_decode_msg_total

Description: Total number of pfcg decode by type,size

Sample Query: `'proto_pfcg_decode_msg_total{message_name="session_modification_res"}'`

Labels:

- Label: `message_name`

Label Description: PFCP Message name

Example: `session_modification_res`, `session_report_req`, `session_deletion_res`, `heartbeat_res`, `heartbeat_req`

- Label: `optimised`

Label Description: PFCP Message decode optimised

Example: `true`, `false`

- Label: `status`

Label Description: PFCP Message status - accepted/denied/discarded

Example: accepted, denied, discarded

- Label: `gr_instance_id`

Label Description: GR instance ID

Example: 1, 2

PFCP Encoded Messages Category

proto_pfcpl_encode_msg_total

Description: Total number of pfcpl encode by type,size

Sample Query: 'proto_pfcpl_encode_msg_total{message_name="session_modification_req"}'

Labels:

- Label: `message_name`

Label Description: PFCP Message name

Example: session_establishment_req, session_modification_req, session_report_req, session_deletion_req, heartbeat_req, heartbeat_res, session_report_res

- Label: `msgbufsize`

Label Description: PFCP Message buffer size

Example: little, jumbo, optimized

- Label: `status`

Label Description: PFCP Message status - accepted/denied/discarded

Example: accepted, denied, discarded

- Label: `gr_instance_id`

Label Description: GR instance ID

Example: 1, 2

radius-ep Metrics Reference

Radius COA and DM packet statistics Category

Radius_CoaDM_Requests_Current

Description: Current outstanding radius COA/DM requests

Sample Query:

```
'Radius_CoaDM_Requests_Current{radSvrIp="1.1.1.1",radMsgCode="CoaReq",grInstId="1"}'
```

Labels:

- Label: `radSvrIp`
Label Description: Radius Server IP address
Example: Any string
- Label: `radMsgCode`
Label Description: Message type
Example: DisconnectRequest, CoARequest
- Label: `grInstId`
Label Description: GR Instance Id
Example: 1 or 2

Radius_CoaDM_Requests_Statistics

Description: Total number of radius COA and DM packets sent and received

Sample Query:

```
'Radius_CoaDM_Requests_Statistics{radSvrIp="1.1.1.1",radMsgCode="CoARequest",grInstId="1"}'
```

Labels:

- Label: `radSvrIp`
Label Description: Radius Server IP address
Example: Any string
- Label: `radMsgCode`
Label Description: Message type
Example: DisconnectRequest, DisconnectACK, DisconnectNAK, CoARequest, CoaDMReq, CoAACK
- Label: `radPacketType`
Label Description: Direction
Example: Tx, Rx
- Label: `radResult`
Label Description: Result
Example: Success, Failure_Invalid_Request
- Label: `grInstId`
Label Description: GR Instance Id
Example: 1 or 2

Radius Server status Category

Radius_Server_Status

Description: Display active/inactive status of radius-server

Sample Query:

```
'Radius_Server_Status{radSvrIp="1.1.1.1",radSvrPort="1812",radSvrPortType="Auth"}'
```

Labels:

- Label: `radSvrIP`
Label Description: Radius Server IP address
Example: Any string
- Label: `radSvrPort`
Label Description: Radius Server Port
Example: Any string
- Label: `radSvrPortType`
Label Description: Type of server
Example: Auth, Acct

Radius packet statistics Category

Radius_requests_current

Description: Current outstanding radius requests

Sample Query:

```
'Radius_requests_current{radSvrIp="1.1.1.1",radSvrPort="1812",radSvrPortType="Auth",grInstId="1"}'
```

Labels:

- Label: `radSvrIp`
Label Description: Radius Server IP address
Example: Any string
- Label: `radSvrPort`
Label Description: Radius Server Port
Example: Any string
- Label: `radSvrPortType`
Label Description: Type of server
Example: Auth, Acct
- Label: `radMsgCode`
Label Description: Message type

Example: SecondaryAuthenReq, RadiusAcctReq, TestAuth, TestAcct

- Label: `radPacketType`

Label Description: Direction

Example: Tx, Rx

- Label: `dnn`

Label Description: DNN of session

Example: Any string

- Label: `procType`

Label Description: Procedure type

Example: Any string

- Label: `ratType`

Label Description: RAT Type

Example: Any string

- Label: `sessType`

Label Description: Session type

Example: Any string

- Label: `grInstId`

Label Description: GR Instance Id

Example: 1 or 2

Radius_requests_statistics

Description: Total number of radius packets sent and received

Sample Query:

```
'Radius_requests_statistics(radSvrIp="1.1.1.1",radSvrPort="1812",radSvrPortType="Auth",grInstId="1")'
```

Labels:

- Label: `radSvrIp`

Label Description: Radius Server IP address

Example: Any string

- Label: `radSvrPort`

Label Description: Radius Server Port

Example: Any string

- Label: `radSvrPortType`

Label Description: Type of server

Example: Auth, Acct

- Label: `radMsgCode`
Label Description: Message type
Example: SecondaryAuthenReq, RadiusAcctReq, TestAuth, TestAcct
- Label: `radPacketType`
Label Description: Direction
Example: Tx, Retry_Tx, Rx
- Label: `radResult`
Label Description: Result
Example: Success, Timeout, Failure_Reject, Failure_NoServer
- Label: `dnn`
Label Description: DNN of session
Example: Any string
- Label: `procType`
Label Description: Procedure type
Example: Any string
- Label: `ratType`
Label Description: RAT Type
Example: Any string
- Label: `sessType`
Label Description: Session type
Example: Any string
- Label: `grInstId`
Label Description: GR Instance Id
Example: 1 or 2

rest-ep Metrics Reference

Discover Messages statistics Category

`nf_discover_messages_total`

Description: Discover Messages statistics

Sample Query: `nf_discover_messages_total{nf_type=\"udm\", host=\"10.105.227.109:8082\", svc_name=\"nudm-sdm\", version=\"v1\", result=\"timeouOrRPCError\"}`

Labels:

- Label: `nf_type`
Label Description: Network Function type
Example: nrf, udm, amf, pcf, chf, ciscocontrol
- Label: `host`
Label Description: End Point address
Example: 10.105.227.109:8082
- Label: `svc_name`
Label Description: Network function service name
Example: nudm-sdm, namf-comm
- Label: `version`
Label Description: Api version info
Example: v1, v2,
- Label: `result`
Label Description: result of discover message
Example: 200, 201, 204, success, timeout_rpc_error, response_parse_failure, empty_response

Discover Messages Time statistics Category

nf_discover_total_time

Description: Discover Messages Total time statistics

Sample Query: `nf_discover_total_time(nf_type=\"udm\", host=\"10.105.227.109:8082\", svc_name=\"nudm-sdm\", version=\"v1\", result=\"timeouOrRPCError\")`

Labels:

- Label: `nf_type`
Label Description: Network Function type
Example: nrf, udm, amf, pcf, chf, ciscocontrol
- Label: `host`
Label Description: End Point address
Example: 10.105.227.109:8082
- Label: `svc_name`
Label Description: Network function service name
Example: nudm-sdm, namf-comm
- Label: `version`
Label Description: Api version info

Example: v1, v2,

- Label: `result`

Label Description: result of discover message

Example: 200, 201, 204, success, timeout_rpc_error, response_parse_failure

FQDN resolution statistics Category

fqdn_dns_msg_total

Description: Number of FQDN attempted/resolved/failed

Sample Query: `fqdn_dns_msg_total{fqdn="host.example.com", nf_type="udm", svc_name="nudm-sdm", status="attempted", req="resolution", error="8314"}`

Labels:

- Label: `fqdn`

Label Description: End Point hostname

Example: host.example.com

- Label: `nf_type`

Label Description: Network Function type

Example: nrf, udm, amf, pcf, chf, ciscocontrol

- Label: `svc_name`

Label Description: Network function service name

Example: nudm-sdm, namf-comm

- Label: `status`

Label Description: resolution status

Example: attempted, success, failure

- Label: `req`

Label Description: whether resolved from dns-server or read from cache

Example: resolution, cache

- Label: `error`

Label Description: result of fqdn

Example: 8311, 8312, 8314,

NF End point selections Category

nf_endpoint_selections_total

Description: NF End Point Selection Statistics

Sample Query: `nf_endpoint_selections_total{nf_type="udm", host="10.105.227.109:8097", svc_name="nudm-sdm", version="v1", req="initial", retransmit="retransmit_1", peer_input="yes", gr_instance_id="1"}`

Labels:

- Label: `nf_type`
Label Description: Network Function type
Example: nrf, udm, amf, pcf, chf, ciscocontrol
- Label: `host`
Label Description: End Point address
Example: 10.105.227.109:8097
- Label: `svc_name`
Label Description: Network function service name
Example: nudm-sdm, namf-comm
- Label: `version`
Label Description: Api version info
Example: v1, v2,
- Label: `req`
Label Description: req type
Example: initial, fallback,
- Label: `retransmit`
Label Description: retransmit count
Example: retransmit_1, retransmit_2,
- Label: `peer_input`
Label Description: peer input
Example: yes, no,
- Label: `gr_instance_id`
Label Description: GRInstanceId
Example: 0, 1

NF failure handling stats Category

nf_failure_handling_stats_total

Description: NF Failure handling stats

Sample Query: `nf_failure_handling_stats_total{nf_type=\"udm\", host=\"10.105.227.109:8097\", svc_name=\"nudm-sdm\", version=\"v1\", message_type=\"UdmUecmRegisterSMF\", req=\"initial\", response=\"202\", status=\"final\", peer_input=\"yes\", failure_source=\"SCP\"}`

Labels:

- Label: `nf_type`
Label Description: Network Function type
Example: nrf, udm, amf, pcf, chf, ciscocontrol
- Label: `host`
Label Description: End Point address
Example: 10.105.227.109:8097
- Label: `svc_name`
Label Description: Network function service name
Example: nudm-sdm, namf-comm, nnrf-disc
- Label: `version`
Label Description: Api version info
Example: v1, v2,
- Label: `message_type`
Label Description: Message Type
Example: UdmUecmRegisterSMF, UdmSdmGetUESMSSubscriptionData, DiscoverNF
- Label: `req`
Label Description: Request type
Example: initial, fallback,
- Label: `response`
Label Description: Response from the server
Example: 200, 201, 204, timeout_rpc_error,
- Label: `status`
Label Description: Status from the server
Example: retry, final, retry-next, blocklist
- Label: `peer_input`
Label Description: peer input

Example: yes, no

- Label: `failure_source`

Label Description: Source Network Function type from where failure originated

Example: SCP, SEPP, UDM, PCF, CHF, AMF

NF management messages statistics Category

`nf_management_stats_total`

Description: NF management messages statistics

Sample Query: `nf_management_stats_total{host=\"10.105.227.109:8082\", svc_name=\"nnrf-nfm\", version=\"v1\", direction=\"outbound\", message_type=\"registration\", result=\"timeouOrRPCError\" }`

Sample Query: `nf_management_stats_total{host=\"10.105.227.109:8082\", svc_name=\"nnrf-nfm\", version=\"v1\", direction=\"inbound\", message_type=\"notification\", result=\"success\", notification_event_type=\"NF_REGISTERED\", condition_event_type=\"NF_ADDED\", gr_instance_id=\"0\" }`

Labels:

- Label: `host`

Label Description: End Point address

Example: 10.105.227.109:8082

- Label: `svc_name`

Label Description: Network function service name

Example: nudm-sdm, namf-comm

- Label: `version`

Label Description: Api version info

Example: v1, v2,

- Label: `direction`

Label Description: Direction indicates about the message going out or coming in

Example: inbound, outbound

- Label: `message_type`

Label Description: Type of Message

Example: registration, heartbeat, subscription, notification

- Label: `notification_event_type`

Label Description: Notification Event Type

Example: NF_REGISTERED, NF_DEREGISTERED, NF_PROFILE_CHANGED

- Label: `condition_event_type`

Label Description: Condition Event Type

Example: NF_ADDED, NF_REMOVED

- Label: `result`

Label Description: result of registration/subscription/notification message

Example: 200, 201, 204, success, timeout_rpc_error, response_parse_failure

- Label: `gr_instance_id`

Label Description: GRInstanceId

Example: 0, 1

NF management message time statistics Category

nf_management_total_time

Description: NF management messages total time taken

Sample Query: `nf_management_total_time{host=\"10.105.227.109:8082\", svc_name=\"nudm-sdm\", version=\"v1\", direction=\"outbound\", message_type=\"registration\", result=\"timeouOrRPCError\" }`

Labels:

- Label: `host`

Label Description: End Point address

Example: 10.105.227.109:8082

- Label: `svc_name`

Label Description: Network function service name

Example: nudm-sdm, namf-comm

- Label: `version`

Label Description: Api version info

Example: v1, v2,

- Label: `direction`

Label Description: Direction indicates about the message going out or coming in

Example: inbound, outbound

- Label: `message_type`

Label Description: Type of Message

Example: registration, heartbeat, subscription, notification

- Label: `result`

Label Description: result of discover message

Example: 200, 201, 204, success, timeout_rpc_error, response_parse_failure, request_parse_failure, invalid_notify_event, invalid_nf_instance_uri, internal_error

NF Send messages statistics Category

nf_req_recieved_messages_total

Description: NF recieved messages to NRF client library

Sample Query: `nf_req_recieved_messages_total{nf_type=\"udm\", svc_name=\"nudm-sdm\", message_type=\"UdmUecmRegisterSMF\"}`

Labels:

- Label: `nf_type`

Label Description: Network Function type

Example: udm, amf, pcf, chf, ciscocontrol

- Label: `svc_name`

Label Description: Network function service name

Example: nudm-sdm, namf-comm

- Label: `message_type`

Label Description: Message Type

Example: UdmUecmRegisterSMF, UdmSdmGetUESMSSubscriptionData

nf_resp_sent_messages_total

Description: NF message responses sent from NRF client library

Sample Query: `nf_resp_sent_messages_total{nf_type=\"udm\", svc_name=\"nudm-sdm\", message_type=\"UdmUecmRegisterSMF\", result=\"SendSuccess\", status_code=\"200\"}`

Labels:

- Label: `nf_type`

Label Description: Network Function type

Example: nrf, udm, amf, pcf, chf, ciscocontrol

- Label: `svc_name`

Label Description: Network function service name

Example: nudm-sdm, namf-comm

- Label: `message_type`

Label Description: Message Type

Example: UdmUecmRegisterSMF, UdmSdmGetUESMSSubscriptionData

- Label: `result`

Label Description: result of discover message

Example: SendSuccess, SendFailure

- Label: `status_code`

Label Description: result of NF send message

Example: 200, 201, 204,

nf_send_message_total_time

Description: NF send message total time taken

Sample Query: `nf_send_message_total_time{nf_type="udm", svc_name="nudm-sdm", message_type="UdmUecmRegisterSMF", result="SendSuccess", status_code="200"}`

Labels:

- Label: `nf_type`

Label Description: Network Function type

Example: nrf, udm, amf, pcf, chf, ciscocontrol

Labels:

- Label: `svc_name`

Label Description: Network function service name

Example: nudm-sdm, namf-comm

- Label: `message_type`

Label Description: Message Type

Example: UdmUecmRegisterSMF, UdmSdmGetUESMSubscriptionData

- Label: `result`

Label Description: result of discover message

Example: SendSuccess, SendFailure

- Label: `status_code`

Label Description: result of NF send message

Example: 200, 201, 204,

NRF Discovery Category

nf_discover_events_total

Description: NF Discover Stats

Sample Query: `nf_discover_events_total{nf_type="pcf", response_type="local"}`

Labels:

- Label: `nf_type`

Label Description: Network Function type

Example: nrf, udm, amf, pcf, chf, ciscocontrol

- Label: `response_type`

Label Description: Discovery response choosen from

Example: local, cache, expired-cache, intervaltree-cache

NRF subscription messages statistics Category

nrf_subscription_send_messages_total

Description: NRF Subscription send messages total

Sample Query: `nrf_subscription_send_messages_total{host=\"10.105.227.109:8082\", message_type=\"subscription\", req=\"initial\", gr_instance_id=\"1\", subscrCond=\"NFSetId\"}`

Labels:

- Label: `host`

Label Description: End Point address

Example: 10.105.227.109:8082

- Label: `message_type`

Label Description: subscription message typwe

Example: unsubscription,subscription,updateSubscription

- Label: `req`

Label Description: req type

Example: resourceUri, initial,retry_2

- Label: `gr_instance_id`

Label Description: GRInstanceId

Example: 0, 1

- Label: `subscrCond`

Label Description: sunscription condition

Example: NFInstanceId, NFSetId

Range based discovery statistics Category

nf_rangebased_discovery_total

Description: Range based discovery operation on IntervalTree cache stats

Sample Query: `nf_rangebased_discovery_total{range_type=\"supi\", nf_type=\"UDM\", operation=\"add\", message_type=\"discovery\", status=\"success\"}`

Labels:

- Label: `range_type`
Label Description: range type used in discovery-filter
Example: `supi`, `gpsi`
- Label: `nf_type`
Label Description: Network Function type
Example: `udm`, `pcf`, `chf`, `ausf`, `udr`
- Label: `operation`
Label Description: operation performed in IntervalTree cache
Example: `add`, `update`, `remove`
- Label: `message_type`
Label Description: which triggered operation on IntervalTree cache
Example: `discovery`, `cache-refresh`, `cache-expiry`, `profile-removal`, `notification`
- Label: `status`
Label Description: status of the operation
Example: `success`, `failure`

REST EP message Exchange Time Category

smf_restep_http_msg_seconds

Description: SMF REST time between request and response messages

Sample Query: `'smf_restep_http_msg_seconds{message_direction="inbound",nf_type="amf"}'`

Labels:

- Label: `nf_type`
Label Description: Network Function type
Example: `nrf`, `udm`, `amf`, `pcf`, `chf`, `ciscocontrol`
- Label: `message_direction`
Label Description: direction of message from SMF perspective
Example: `inbound`, `outbound`
- Label: `api_name`
Label Description: API name
Example: `register_ue`, `deregister_ue`, `subscription_req`, `sdm_subscription_req`, `sdm_data_change_notify`, `nf_registration`, `nf_discovery`, `slice_selection`, `amf_create_sm_context`, `amf_update_sm_context`,

amf_release_sm_context, amf_n1_n2_transfer, amf_n1_n2_transfer_notify_failure, amf_assign_ebi, amf_status_notify, pcf_sm_policy_control_create, chf_charging_data_request, pcf_sm_policy_control_update, pcf_sm_policy_control_delete, pcf_sm_policy_control_update_notify, cisco_control_clear_subscriber, cisco_control_show_subscriber, pcf_sm_policy_control_terminate_notify, chf_abort_notify

- Label: `nf_uri`

Label Description: Network Function URI

Example: actual HTTP URI of the message

- Label: `response_status`

Label Description: HTTP response status code

Example: 200, 201, 204

- Label: `response_cause`

Label Description: HTTP response cause code

Example: cause string as received from peer nf

REST EP messages Category

smf_restep_http_msg_total

Description: SMF REST message counter

Sample Query: 'smf_restep_http_msg_total{message_direction="inbound",nf_type="amf"}'

Labels:

- Label: `nf_type`

Label Description: Network Function type

Example: nrf, udm, amf, pcf, chf, ciscocontrol

- Label: `message_direction`

Label Description: direction of message from SMF perspective

Example: inbound, outbound

- Label: `api_name`

Label Description: API name

Example: register_ue, deregister_ue, subscription_req, sdm_subscription_req, sdm_data_change_notify, nf_registration, nf_discovery, slice_selection, amf_create_sm_context, amf_update_sm_context, amf_release_sm_context, amf_n1_n2_transfer, amf_n1_n2_transfer_notify_failure, amf_assign_ebi, amf_status_notify, pcf_sm_policy_control_create, chf_charging_data_request, pcf_sm_policy_control_update, pcf_sm_policy_control_delete, pcf_sm_policy_control_update_notify, cisco_control_clear_subscriber, cisco_control_show_subscriber, pcf_sm_policy_control_terminate_notify, chf_abort_notify

- Label: `nf_uri`

Label Description: Network Function URI

Example: actual HTTP URI of the message

- Label: `response_status`

Label Description: HTTP response status code

Example: 200, 201, 204

REST EP messages Decode Status Category

smf_restep_http_msg_decode

Description: SMF REST number of decoding failures

Sample Query:

```
'smf_restep_http_msg_decode{nf_type="amf",api_name="register_ue",decoding_status="decoding_failure"}'
```

Labels:

- Label: `nf_type`

Label Description: Network Function type

Example: nrf, udm, amf, pcf, chf, ciscocontrol

- Label: `api_name`

Label Description: API name

Example: register_ue, deregister_ue, subscription_req, sdm_subscription_req, sdm_data_change_notify, nf_registration, nf_discovery, slice_selection, amf_create_sm_context, amf_update_sm_context, amf_release_sm_context, amf_n1_n2_transfer, amf_n1_n2_transfer_notify_failure, amf_assign_ebi, amf_status_notify, pcf_sm_policy_control_create, chf_charging_data_request, pcf_sm_policy_control_update, pcf_sm_policy_control_delete, pcf_sm_policy_control_update_notify, cisco_control_clear_subscriber, cisco_control_show_subscriber, pcf_sm_policy_control_terminate_notify, chf_abort_notify

- Label: `decoding_status`

Label Description: Decoding status

Example: decoding_failure

- Label: `interface_type`

Label Description: Interface Type

Example: N11, N1, N2

- Label: `response_status`

Label Description: HTTP response status code

Example: 200, 201, 204

- Label: `application_error`

Label Description: Application error

smf-service Metrics Reference

SMF Procedure Category

smf_service_stats

Description: SMF call flow procedure counters

Sample Query: 'smf_service_stats{procedure_type="pdu_sess_create"}'

Labels:

- Label: `procedure_type`

Label Description: The procedure type associated with an call flow procedure

Example: pdu_sess_create, ue_req_pdu_sess_mod, smf_req_pdu_sess_mod, pcf_req_pdu_sess_mod, udm_req_pdu_sess_mod, gnb_req_pdu_sess_mod, ue_req_pdu_sess_rel, smf_req_pdu_sess_rel, pcf_req_pdu_sess_rel, amf_req_pdu_sess_rel, udm_req_pdu_sess_rel, gnb_req_pdu_sess_rel, chf_req_pdu_sess_rel, admin_req_pdu_sess_rel, ue_req_active_to_idle, ue_req_idle_to_active, nw_req_service_active, upf_notify_downlink_data, xn_path_switch, pdn_sess_create, pdn_5g_4g_handover, pcf_req_ded_brr_create, pcf_req_ded_brr_delete, pcf_req_ded_brr_mod, n2_handover, xn_handover, n26_4g_to_5g_handover, n26_4g_to_5g_im_mobility, pdu_im, pdn_sess_create, pcf_req_ded_brr_create, pcf_req_ded_brr_delete, pcf_req_ded_brr_mod, pcf_initiated_pdn_detach, smf_initiated_pdn_detach, upf_initiated_pdn_detach, smf_eps_fb, misc_pdu_sess_rel, pcrf_req_ded_brr_mod, pcrf_req_ded_brr_create, pcrf_req_ded_brr_delete, suspend_notification, resume_notification, change_notification, gx_validation_failure_pdn_sess_rel, smf_inter_plmn_ro2ho_n2ho, smf_inter_plmn_ho2ro_n2ho, smf_idft_inter_plmn_ro2ho_n2ho, smf_dft_inter_plmn_ro2ho_n2ho, smf_idft_inter_plmn_ho2ro_n2ho smf_dft_inter_plmn_ho2ro_n2ho

- Label: `status`

Label Description: call flow procedure counter

Example: attempted, success, failures, pcrf_failure

- Label: `pdu_type`

Label Description: pdu connection type

Example: ipv4, ipv6, ipv4v6, unknown

- Label: `dnn`

Label Description: Dnn configured in dnn-policy, also can have virtual_dnn if configured, separated by #

Example: intershat, intershat#cisco.com

- Label: `reason`

Label Description: Reason for failure status. For sucessess and attempted it will be Empty

Example: proc_pdu_not_established, proc_pdu_ctx_not_found, n2ho_ie_validation_failed, n2ho_n4_ho_preparing_failed, n2ho_n4_ho_prepared_failed, n2ho_n4_ho_completed_failed, n2ho_ho_cancelled, n2ho_resource_alloc_unsuccess_transfer, n2ho_invalid_state,

n2ho_preparation_unsuccess_transfer, n2ho_n1n2_transfer_failure, n2ho_dft_intra_amf,
 n2ho_dft_inter_amf, n2ho_idft_intra_amf, n2ho_idft_inter_amf, n2ho_default_flow_failed,
 n2ho_n2_decode_failiure, n2ho_chf_update_failure, n2ho_invalid_response,
 xnho_tobe_switched_flag_not_set, xnho_dl_tunnel_info_not_found, xnho_invalid_accepted_qfi_list,
 xnho_n4_modification_failed, xnho_n1n2_transfer_failure//NotUsedtoberemoved,
 xnho_n2_decode_failiure, xnho_pdu_state_error, n26ho_4g_5g_n1n2_transfer_failure,
 n26ho_4g_5g_invalid_state, n26ho_4g_5g_n4_failed_prepared_state,
 n26ho_4g_5g_resource_alloc_unsuccess_transfer, n26ho_4g_5g_timedout_in_post_exec_state,
 n26ho_4g_5g_n4_failed_completed_state, n26ho_4g_5g_handover_cancelled,
 n26ho_4g_5g_send_n4mod_failed_preparing_state, n26ho_4g_5g_n4mod_rsp_failed_preparing_state,
 n26ho_4g_5g_n4mod_rsp_timeout_preparing_state, n26ho_4g_5g_im_mobility_send_n4mod_failed,
 n26ho_4g_5g_im_mobility_n4mod_rsp_failed, n26ho_4g_5g_im_mobility_n4mod_rsp_timeout,
 n26ho_4g_5g_invalid_eps_pdn_connlist, n26ho_4g_5g_udm_reg_failed, n26ho_4g_5g_dft,
 n26ho_4g_5g_idft, n26ho_5g_4g_dft, n26ho_5g_4g_idft, n26ho_5g_4g_ctrtrive_rec_for_4g_session,
 n26ho_5g_4g_handover_cancel, n26ho_4g_5g_no_eps_5gs_continuity, n26ho_default_flow_failed,
 n26ho_n2_decode_failiure, n26ho_chf_update_failure, n26im_mobility_4g_5g_no_eps_5gs_continuity,
 n26im_mobility_4g_5g_default_eps_bearer_inactive, pduim_n1n2_transfer_failure,
 pduim_n2_setup_response_failure, pduim_n1n2_txfr_failure_notification, pduim_n4_modification_failed,
 pduim_misc_error, pduim_n1n2ack_decode_error, pduim_n1n2ack_unhndl_cause,
 pduim_n1n2ack_unhndl_rsp_code, pduim_n1n2ack_unhndl_prb_cause, pduim_suspended_procedure,
 pduim_amf_ctx_not_found, pduim_internal_error, pduim_upstate_not_in_deactivated_state,
 pduim_pdu_access_type_mismatch, pduim_pdu_gnb_tunnel_not_available,
 pduim_pdu_n4_deactivated_state, pduim_sla_timer_expired, pduim_temp_reject_max_retry, upf_failure,
 pcf_failure, idft_release_failure, access_4g_already, idft_setup_failure, mbr_setup_failure, sgw_failure,
 udm_registration_failure, udm_subscription_fetch_failure, udm_subscribe_notify_failure,
 udm_update_notify_failure, aaa_subscribe_auth_failure, aaa_framed_ip_addr_conflict, pcf_create_failure,
 pcf_update_failure, charging_data_failure, no_rule_matched, invalid_protocol, invalid_dst_mask,
 invalid_src_mask, invalid_5qi, invalid_arp, invalid_other, internal_error, invalid_ebi,
 invalid_framed_ipv6_pfx_length, invalid_acct_sess_id_radius_dm, reason_unknown, invalid_rat_type,
 session_associated_to_online_chf, session_not_in_state, unknown, n4_release_failed,
 gtpu_peer_path_failed, rel_received_for_non_5g_session, qfi_failed_to_setup,
 utn3gppto5gho_n4_failed_completed_state, utn3gppto5gho_n4_failed_prepared_state,
 utn3gppto5gho_resource_alloc_unsuccess_transfer, utn3gppto5gho_invalid_state,
 utn3gppto5gho_policy_update_failure, utn3gppto5gho_charging_update_failure,
 utn3gppto5gho_n1n2_transfer_failure, utn3gppto5gho_pcf_update_failed_post_ho,
 utn3gppto5gho_chf_update_failed_post_ho, utn3gppto5gho_n4_failed_post_ho,
 utn3gppto5gho_del_bearer_failed, utn3gppto5gho_partial_flow_failure,
 utn3gppto5gho_default_flow_failed, utn3gppto5gho_eps_fallback,
 utn3gppto5gho_setup_unsuccess_transfer, utn3gppto5gho_fail_due_n2msg_rsp_not_rcvd,
 utn3gppto5gho_ctxt_create_res_failure, utn3gppto5gho_invalid_ctxt_create_req,
 utn3gpp_epsfallback_failed_during_5g_4g_ho, utn3gpp_epsfallback_failed_guard_timer_expiry,
 nr_to_untrusted_wifi_invalid_sess_state, nr_to_untrusted_wifi_invalid_json,
 nr_to_untrusted_wifi_invalid_paa, nr_to_untrusted_wifi_invalid_msg, nr_to_untrusted_wifi_pcf_failed,
 nr_to_untrusted_wifi_n40_failed, nr_to_untrusted_wifi_n4_failed,
 nr_to_untrusted_wifi_pcf_failed_post_cb, nr_to_untrusted_wifi_n40_failed_post_cb,
 nr_to_untrusted_wifi_n4_failed_post_cb, nr_to_untrusted_wifi_cbr_failed,
 nr_to_untrusted_wifi_ubr_failed, nr_to_untrusted_wifi_cb_res_failed,
 nr_to_untrusted_wifi_n1n2_release_failed, nr_to_untrusted_wifi_n4_failed_post_ho,
 nr_to_untrusted_wifi_pcf_update_failed_post_ho, nr_to_untrusted_wifi_chf_update_failed_post_ho,
 nr_to_untrusted_wifi_sla_timer_expired, nr_to_untrusted_wifi_dbr_failed,
 enb_to_untrusted_wifi_to_enb_ho_reject, enb_to_untrusted_wifi_to_enb_invalid_sess_state,

enb_to_untrusted_wifi_to_enb_invalid_json, enb_to_untrusted_wifi_to_enb_invalid_paa, enb_to_untrusted_wifi_to_enb_invalid_msg, enb_to_untrusted_wifi_to_enb_udm_failed, enb_to_untrusted_wifi_to_enb_pcf_failed, enb_to_untrusted_wifi_to_enb_n40_failed, enb_to_untrusted_wifi_to_enb_n4_failed, enb_to_untrusted_wifi_to_enb_pcf_failed_post_cb, enb_to_untrusted_wifi_to_enb_mbr_failed, enb_to_untrusted_wifi_to_enb_n4_failed_post_mbr, enb_to_untrusted_wifi_to_enb_n40_failed_post_cb, enb_to_untrusted_wifi_to_enb_n4_failed_post_db, enb_to_untrusted_wifi_to_enb_pcf_failed_post_db, enb_to_untrusted_wifi_to_enb_cbr_failed, enb_to_untrusted_wifi_to_enb_dbr_failed, enb_to_untrusted_wifi_to_enb_ubr_failed, dsr_target_rat_rejected, upip_req_denied_in_rat, nr_to_untrusted_wifi_upip_status_req_denied_in_rat, pcrf_create_failure, cbr_fail_upstate_inactive, ubr_fail_upstate_inactive, pdnrel_conditional_ie_missing, pdn_create_over_created_pdn, interplmn_ho_not_configured, dtssa_acscr_not_supported, ho2ro_invalid_state, ro2ho_invalid_state, mbc_retransmit_msg, change_notification_retransmit_msg, pdn_ho_5g_2g_not_allowed, pdn_ho_5g_3g_not_allowed, pdn_ho_wifi_2g_not_allowed, pdn_ho_wifi_3g_not_allowed, pdn_ho_2g_wifi_not_allowed, pdn_ho_3g_wifi_not_allowed, pdn_invalid_pcf_version, pdn_invalid_chf_version, pdn_2g3g_cli_not_enabled, pdn_ho_2g_5g_not_allowed, pdn_ho_3g_5g_not_allowed, pdn_ho_2g_not_allowed_in_upgrade, pdn_ho_3g_not_allowed_in_upgrade, pdn_initial_attach_in_2g3g_4g_to_5g_ho_not_allowed, oper_not_supported_in_rat

- Label: emergency_call

Label Description: Flag indicating if it is an emergency call

Example: true, false

- Label: rat_type

Label Description: RAT Type of the Session

Example: EUTRA, NR, WLAN, UTRA, GERA, rat_type_unknown

- Label: roaming_status

Label Description: Roaming status of the subscriber session

Example: visitor-lbo, visitor-hr, roamer, homer, none

- Label: up_state

Label Description: Userplane connection status of the session

Example: UpState_None, UpState_Establishing, UpState_Activating, UpState_Activated, UpState_Deactivating, UpState_Deactivated, UpState_Modifying, UpState_Deleting, UpState_Deleted

- Label: qos_5qi

Label Description: 5Qi applicable for the QoS flow

Example: 1, 2, 5

- Label: always_on

Label Description: always on status

Example: enable, disable

- Label: dcnr

Label Description: UE DCNR status

Example: enable, disable

- Label: `smf_current_procedure`

Label Description: Current Procedure Name for Message Level Stats

Example: `DedBearerProc`, `eps_fb_ded_brr`, `ue_req_ded_brr_mod`, `udm_req_ded_brr_mod`, `smf_req_ded_brr_del`, `upf_req_ded_brr_del`, `mme_req_ded_brr_del`, `mme_req_ded_brr_mod`, `pcf_req_ded_brr_mod`, `pcf_req_ded_brr_create`, `pcf_req_ded_brr_delete`, `pdn_modify_2g3g`

- Label: `fourg_only_ue`

Label Description: Only 4g capable UE flag

Example: `true`, `false`

- Label: `pra`

Label Description: Presence Reporting Area Information

Example: `enable`, `none`

- Label: `upip_active`

Label Description: UPIP activated for the session or not

Example: `true`, `false`

- Label: `local_policy`

Label Description: Flows or Bearers created based on local policy config

Example: `true`, `false`

SMF 2G/3G Procedure Category

smf_service_stats_2g3g

Description: SMF call flow procedure counters for 2g/3g session

Sample Query: `'smf_service_stats_2g3g{procedure_type="pdn_mbr_2gv1"}'`

Labels:

- Label: `procedure_type`

Label Description: The procedure type associated with an call flow procedure

Example: `pdn_mbr_2gv1`, `pdn_mbr_2gv2`, `pdn_mbr_3gv1`, `pdn_mbr_3gv2`, `pdn_ho_sgsn_2gv1`, `pdn_ho_sgw_2gv2`, `pdn_ho_sgsn_3gv1`, `pdn_ho_sgw_3gv2`, `pdn_ho_2gv1_2gv2`, `pdn_ho_2gv2_2gv1`, `pdn_ho_3gv2_3gv1`, `pdn_ho_3gv2_2gv2`, `pdn_ho_2gv1_4g`, `pdn_ho_2gv2_4g`, `pdn_ho_3gv1_4g`, `pdn_ho_3gv2_4g`, `pdn_ho_4g_2gv1`, `pdn_ho_4g_2gv2`, `pdn_ho_4g_3gv1`, `pdn_ho_4g_3gv2`, `pdn_ho_2gv1_3gv2`, `pdn_ho_2gv1_3gv1`, `pdn_ho_2gv2_3gv1`, `pdn_ho_2gv2_3gv2`, `pdn_ho_3gv1_2gv2`, `pdn_ho_3gv1_2gv1`, `pdn_ho_3gv1_3gv2`, `pdn_ho_3gv2_2gv1`, `pdn_ho_5g_3gv1`, `pdn_ho_5g_3gv2`, `pdn_ho_5g_2gv1`, `pdn_ho_5g_2gv2`, `pdn_ho_wifi_2gv1`, `pdn_ho_wifi_2gv2`, `pdn_ho_wifi_3gv1`, `pdn_ho_wifi_3gv2`, `pdn_ho_2gv1_wifi`, `pdn_ho_2gv2_wifi`, `pdn_ho_3gv1_wifi`, `pdn_ho_3gv2_wifi`, `pdn_ho_2gv1_upgrade`, `pdn_ho_2gv2_upgrade`, `pdn_ho_3gv1_upgrade`, `pdn_ho_3gv2_upgrade`, `pdn_ho_initial_attach_in_2g3g_4g_5g`, `location_changed_3gv1`, `location_changed_3gv2`, `location_changed_2gv1`, `location_changed_2gv2`

- Label: `status`

Label Description: call flow procedure counter

Example: attempted, success, failures

- Label: `reason`

Label Description: Reason for failure status. For success and attempted it will be Empty

Example: `pdn_ho_5g_2g_not_allowed`, `pdn_ho_5g_3g_not_allowed`, `pdn_ho_wifi_2g_not_allowed`, `pdn_ho_wifi_3g_not_allowed`, `pdn_ho_2g_wifi_not_allowed`, `pdn_ho_3g_wifi_not_allowed`, `pdn_invalid_pcf_version`, `pdn_invalid_chf_version`, `pdn_2g3g_cli_not_enabled`, `pdn_ho_2g_5g_not_allowed`, `pdn_ho_3g_5g_not_allowed`, `pdn_ho_2g_not_allowed_in_upgrade`, `pdn_ho_3g_not_allowed_in_upgrade`, `pdn_initial_attach_in_2g3g_4g_to_5g_ho_not_allowed`

- Label: `rat_type`

Label Description: RAT Type of the Session

Example: UTRA, GERA, `rat_type_unknown`

- Label: `dnn`

Label Description: Dnn configured in `dnn-policy`, also can have `virtual_dnn` if configured, separated by #

Example: `intershat`, `intershat#cisco.com`

- Label: `roaming_status`

Label Description: Roaming status of the subscriber session

Example: `visitor-lbo`, `visitor-hr`, `roamer`, `homer`, `none`

- Label: `smf_current_procedure`

Label Description: Current Procedure Name for Message Level Stats

Example: `pdn_modify_2g3g`

SMF PDU Status Category

`smf_service_counters`

Description: The current count of SMF pdu sessions

Sample Query: `'smf_service_counters{pdu_state="all_pdu"}'`

Labels:

- Label: `pdu_state`

Label Description: PDU session status indicated by N3 UPF tunnel status

Example: `all_pdu`, `idle`, `connected`

- Label: `rat_type`

Label Description: RAT Type of the Session

Example: EUTRA, NR, WLAN, UTRA, GERA, `rat_type_unknown`

- Label: `dnn`

Label Description: Dnn configured in dnn-policy, also can have virtual_dnn if configured, separated by #

Example: intershat, intershat#cisco.com

- Label: `roaming_status`

Label Description: Roaming status of the subscriber session

Example: visitor-lbo, visitor-hr, roamer, homer, none

- Label: `ssc_mode`

Label Description: SSC Mode of the session

Example: ssc_mode_1, ssc_mode_2, ssc_mode_3, ssc_mode_unknown

- Label: `flow_type`

Label Description: Indicates whether it's total bearer or dedicated bearer

Example: dedicated_bearer, total_bearer

SMF Protocol message counters Category

smf_proto_udp_msg_total

Description: SMF Protocol message statistics

Sample Query: 'smf_proto_udp_msg_total{message_direction="inbound",nf_type="amf"}'

Labels:

- Label: `message_name`

Label Description: name of N4 interface message

Example: n4_session_establishment_req, n4_session_establishment_res, n4_session_modification_req, n4_session_modification_res, n4_session_report_req, n4_session_report_res, n4_session_deletion_req, n4_session_deletion_res, n4_association_setup_req, n4_association_setup_res, n4_association_update_req, n4_association_update_res, n4_association_release_req, n4_association_release_res, n4_prime_pfd_management_req, n4_prime_pfd_management_res, n4_heartbeat_req, n4_heartbeat_res, n4_node_report_req, n4_node_report_res

- Label: `message_direction`

Label Description: direction of message from SMF perspective

Example: inbound, outbound

- Label: `status`

Label Description: status of message processing

Example: accepted, denied, discarded

SMF IPAM Address Events Total Counter Category

IPAM_address_events_total

Description: Total number of SMF IPAM Address events

Sample Query:

```
'IPAM_address_events_total(dn='dn1',servingArea='area1',nssai='nssai1',pool='p1,eventType='Allocation',allocationType='dynamic',addressType='IPv4',upf='upf1',grInstId='1')
```

Labels:

- Label: `dnn`

Label Description: name of the dnn associated with the request

Example: Any string

- Label: `servingArea`

Label Description: name of the serving area associated with the request

Example: Any string

- Label: `nssai`

Label Description: name of the nssai associated with the request

Example: Any string

- Label: `pool`

Label Description: name of the pool associated with the request

Example: Any string

- Label: `eventType`

Label Description: type of event associated with the request

Example: Allocation/Release

- Label: `allocationType`

Label Description: type of allocation associated with the request

Example: static/dynamic

- Label: `addressType`

Label Description: address type associated with the request

Example: IPv4/IPv6PD

- Label: `upf`

Label Description: upf identifier associated with the request

Example: Any string

- Label: `grInstId`

Label Description: GR Instance ID

Example: 1 or 2

SMF IPAM Chunk Events Total Counter Category

IPAM_chunk_events_total

Description: Total number of SMF IPAM Address Chunk events

Sample Query:

```
'IPAM_chunk_events_total(chr='dm1',servingArea='area1',nssai='slice1',pool='p1,eventType='Allocation',addressType='IPv4',upf='up1',grInstId='1',forRemoteSmf='true')'
```

Labels:

- Label: `dnn`
Label Description: name of the dnn associated with the request
Example: Any string
- Label: `servingArea`
Label Description: name of the serving area associated with the request
Example: Any string
- Label: `nssai`
Label Description: name of the nssai associated with the request
Example: Any string
- Label: `pool`
Label Description: name of the pool associated with the request
Example: Any string
- Label: `eventType`
Label Description: type of event associated with the request
Example: Allocation/Release
- Label: `addressType`
Label Description: address type associated with the request
Example: IPv4/IPv6PD
- Label: `upf`
Label Description: upf identifier associated with the request
Example: Any string
- Label: `grInstId`
Label Description: GR Instance ID
Example: 1 or 2
- Label: `forRemoteSmf`
Label Description: Indicates if chunk is reserved for Remote SMF
Example: true/false

SMF IPAM Address Events Current Counter Category

IPAM_address_allocations_current

Description: Current state of SMF IPAM Address allocations

Sample Query:

```
'IPAM_address_allocations_current(dnn='dnn1',servingArea='area1',nssai='nssai1',pool='pool1',allocationType='dynamic',addressType='IPv4',upf='upf1',grInstId='1')
```

Labels:

- Label: `dnn`

Label Description: name of the dnn associated with the request

Example: Any string

- Label: `servingArea`

Label Description: name of the serving area associated with the request

Example: Any string

- Label: `nssai`

Label Description: name of the nssai associated with the request

Example: Any string

- Label: `pool`

Label Description: name of the pool associated with the request

Example: Any string

- Label: `allocationType`

Label Description: type of allocation associated with the request

Example: static/dynamic

- Label: `addressType`

Label Description: address type associated with the request

Example: IPv4/IPv6PD

- Label: `upf`

Label Description: upf identifier associated with the request

Example: Any string

- Label: `grInstId`

Label Description: GR Instance ID

Example: 1 or 2

SMF IPAM Chunk Events Current Counter Category

IPAM_chunk_allocations_current

Description: Current state of SMF IPAM Address Chunk allocations

Sample Query:

```
'IPAM_chunk_allocations_current(dnn='dnn1',servingArea='areal',nssai='slice1',pool='pl',addressType='IPv4',upf='upl',grInstId='1',forRemoteSmf='true')'
```

Labels:

- Label: `dnn`

Label Description: name of the dnn associated with the request

Example: Any string

- Label: `servingArea`

Label Description: name of the serving Area associated with the request

Example: Any string

- Label: `nssai`

Label Description: name of the nssai associated with the request

Example: Any string

- Label: `pool`

Label Description: name of the pool associated with the request

Example: Any string

- Label: `addressType`

Label Description: address type associated with the request

Example: IPv4/IPv6PD

- Label: `upf`

Label Description: upf identifier associated with the request

Example: Any string

- Label: `grInstId`

Label Description: GR Instance ID

Example: 1 or 2

- Label: `forRemoteSmf`

Label Description: Indicates if chunk is reserved for Remote SMF

Example: true/false

SMF Disconnect stats Category

smf_disconnect_stats

Description: SMF Disconnect stats counters

Sample Query: 'smf_disconnect_stats(reason="disc_pdurel_amf_init_detach")'

Labels:

- Label: `rat_type`

Label Description: RAT Type of the Session

Example: EUTRA, NR, WLAN, `rat_type_unknown`

- Label: `reason`

Label Description: The reason associated with an call disconnect

Example: `disc_pdusetup_create_over_create`, `disc_pdusetup_release_over_create`,
`disc_pdusetup_admin_clear`, `disc_pdusetup_n1_decode_failure`, `disc_pdusetup_n1_content_not_found`,
`disc_pdusetup_sess_abs_timeout`, `disc_pdusetup_sess_idle_timeout`, `disc_pdusetup_sess_cp_idle_timeout`,
`disc_pdusetup_sess_default_flow_only_timeout`, `disc_pdusetup_ssc_mode_not_supported`,
`disc_pdusetup_ssc_mode_denied`, `disc_pdusetup_identity_conflict`, `disc_pdusetup_pdtype_unsupported`,
`disc_pdusetup_pdtype_denied`, `disc_pdusetup_snssai_denied`, `disc_pdusetup_dnn_denied`,
`disc_pdusetup_iwf_denied`, `disc_pdusetup_subscription_denied`, `disc_pdusetup_dnn_not_supported`,
`disc_pdusetup_dnn_not_supported_in_slice`, `disc_pdusetup_network_failure`,
`disc_pdusetup_pdu_sess_does_not_exist`, `disc_init_chg_data_err`, `disc_pdusetup_ip_alloc_failed`,
`disc_pdusetup_static_ip_alloc_failed`, `disc_pdusetup_pdu_fetch_failure`, `disc_pdusetup_udm_reg_failed`,
`disc_pdusetup_udm_sub_fetch_failure`, `disc_pdusetup_udm_sub_fetch_resp_failed`,
`disc_pdusetup_udm_sub_notify_failed`, `disc_pdusetup_upf_setup_cause_not_accepted`,
`disc_pdusetup_secondary_auth_failed`, `disc_pdusetup_secondary_auth_resp_failed`,
`disc_pdusetup_sm_ext_invalid`, `disc_pdusetup_sm_ext_invalid_ie`, `disc_pdusetup_sm_ext_sess_id_err`,
`disc_pdusetup_sm_ext_invalid_json`, `disc_pdusetup_sm_ext_n1_process_failed`,
`disc_pdusetup_sm_ext_man_param_missing`, `disc_pdusetup_pcf_create_exchg_failure`,
`disc_pdusetup_pcf_create_rsp_failure`, `disc_pdusetup_rm_exchg_failure`, `disc_pdusetup_rm_rsp_failure`,
`disc_pdusetup_pcf_update_exchg_failure`, `disc_pdusetup_pcf_update_rsp_failure`,
`disc_chf_data_exchg_failure`, `disc_chf_data_rsp_failure`, `disc_pdusetup_upf_setup_exchg_failure`,
`disc_pdusetup_upf_setup_rsp_failure`, `disc_pdusetup_n1n2_transfer_exchg_failure`,
`disc_pdusetup_n1n2_transfer_rsp_failure`, `disc_pdusetup_n2_setup_failed`, `disc_pdusetup_ue_init_release`,
`disc_pdusetup_amf_assign_ebi_failure`, `disc_pdusetup_upf_modify_exchg_failure`,
`disc_pdusetup_upf_modify_rsp_failure`, `disc_pdusetup_upf_modify_failed`,
`disc_pdusetup_upf_serv_data_nill`, `disc_pdusetup_upf_dl_tunnel_info_not_found`,
`disc_pdusetup_upf_tunnel_id_not_found`, `disc_pdusetup_upf_mod_gnb_tun_params_failed`,
`disc_pdusetup_upf_mod_rsra_tun_params_failed`, `disc_pdusetup_upf_mod_tun_param_tos-failed`,
`disc_pdusetup_smf_mop_offline`, `disc_pdusetup_sm_context_nssai_not_supported`,
`disc_pdusetup_sm_context_network_failure`, `disc_pdusetup_lbo_rejected`,
`disc_pdusetup_home_route_not_supported`, `disc_pdusetup_internal_error`,
`disc_pdusetup_plmn_not_supported`, `disc_pdurel_amf_sends_ue_not_found`, `disc_pdusetup_dnn_missing`,
`disc_pdusetup_udm_dnn_missing`, `disc_pdusetup_resource_mgr_rsp_failed`,
`disc_pdusetup_apply_wps_failed`, `disc_pdurel_ue_init_release`, `disc_pdurel_amf_init_release`,
`disc_pdurel_amf_init_release_404`, `disc_pdurel_amf_init_release_mod_req`,
`disc_pdurel_pcf_reconciliation`, `disc_rel_chf_err`, `disc_pdurel_pcf_init_release`,
`disc_pdurel_udm_init_release`, `disc_pdurel_gnb_init_release`, `disc_pdurel_smf_init_release`,

disc_pdurel_upf_init_association_release, disc_pdurel_radius_init_release,
 disc_pdurel_upf_init_path_failure, disc_pdurel_upf_recovered, disc_pdurel_config_change,
 disc_db_conflict_release, disc_pdurel_pcf_reconciliation, disc_n2ho_n4_modify_failed, disc_n2ho_failure,
 disc_n2ho_guard_timer_expiry, disc_n2ho_idft_timer_expiry, disc_n26_4g_5g_ho_n4_modify_failed,
 disc_n26_4g_5g_im_mobility_n4_modify_failed, disc_pdumodify_context_not_found,
 disc_pdumodify_invalid_pdu_sess_identity, disc_pdurelease_invalid_pdu_sess_identity,
 disc_pduim_context_not_found, disc_n26_4g_5g_ho, disc_n26_5g_4g_ho,
 disc_n26_5g_4g_ho_timer_expired_post_exec, disc_n26_4g_5g_ho_udm_reg_failed,
 disc_n26_5g_4g_ho_mbr_failed, disc_pdusetup_upf_rule_creation_mod_failure,
 disc_non3gpp_utn_5g_ho, disc_5gtonon3gpp_utn_ho, disc_4g_non3gpp_utn_ho,
 disc_non3gpp_utn_4g_ho, disc_enb_wifi_ho_failed, disc_utn3gpp_5g_ho_failed,
 disc_sess_report_srsr_pdu_sess_rel, disc_pdn_ue_init_release, disc_pdn_mme_init_release,
 disc_pdn_chf_reconciliation, disc_pdn_pcf_reconciliation, disc_pdn_pcf_init_release,
 disc_pdn_pcf_fallback, disc_pdn_udm_init_release, disc_pdn_chf_init_release, disc_pdn_upf_init_release,
 disc_admin_init_release, disc_sess_time_exp_release, disc_sess_cp_idle_time_exp_release,
 disc_session_recreate, disc_gtpc_peer_pathfail, disc_gtpc_peer_restart, disc_upf_init_path_failure,
 disc_transaction_timedout, disc_upf_recovered, disc_sgw_ctx_failure, disc_pdn_internal_release,
 disc_reason_unknown,, disc_pdnsetup_iwk_5gs_flag_false, disc_pdnsetup_pduid_init_failed,
 disc_pdnsetup_csr_invalid, disc_pdnsetup_udm_reg_failed, disc_pdnsetup_udm_reg_req_create_failed,
 disc_pdnsetup_udm_rpc_failed, disc_pdnsetup_udm_dnn_missing, disc_pdnsetup_udm_reg_resp_failed,
 disc_pdnsetup_udm_sub_fetch_failed, disc_pdnsetup_udm_sub_fetch_resp_failed,
 disc_pdnsetup_udm_sub_notify_failed, disc_pdnsetup_udm_sub_notify_resp_failed,
 disc_pdnsetup_udm_sgw_u_teid_missing, disc_pdnsetup_secondary_auth_failed,
 disc_pdnsetup_secondary_auth_resp_failed, disc_pdnsetup_secondary_auth_ip_addr_conflict,
 disc_pdnsetup_pcf_create_failed, disc_pdnsetup_pcf_create_resp_failed,
 disc_pdnsetup_pcf_update_req_create_failed, disc_pdnsetup_pcf_update_exchg_failed,
 disc_pdnsetup_pcf_update_resp_failed, disc_pdnsetup_resource_mgr_exchg_failed,
 disc_pdnsetup_resource_mgr_resp_failed, disc_pdnsetup_upf_sess_setup_exchg_failed,
 disc_pdnsetup_upf_sess_setup_resp_failed, disc_pdnsetup_upf_sgw_tunnelid_error,
 disc_pdnsetup_upf_local_fteid_error, disc_pdnsetup_ssc_mode_denied, disc_pdnsetup_pdu_type_denied,
 disc_pdnsetup_pdu_type_not_supported, disc_pdnsetup_ssc_mode_not_supported,
 disc_pdnsetup_subscription_denied, disc_pdnsetup_smf_mop_offline, disc_pdnsetup_plmn_not_supported,
 disc_pdnsetup_non5gcapableue_not_allowed, disc_pdnsetup_default_flow_only_timeout,
 disc_affinity_add_error, disc_pdnsetup_sgwctx_brr_data_invalid, disc_ue_int_n1_5g_sm_status,
 disc_pdu_ctx_not_found, disc_internal_affinity_add_error, upf_sess_report_gter_pdn_sess_rel,
 upf_sess_report_srir_pdn_sess_rel, upf_sess_report_spter_pdn_sess_rel,
 upf_sess_report_srsr_pdn_sess_rel, upf_sess_report_erir_pdn_sess_rel, upf_sess_report_upir_pdn_sess_rel,
 disc_sess_report_srsr_pdn_sess_rel, disc_originatingEntity_request_timed_out,
 disc_new_pdn_type_due_to_single_addr_bearer_only, disc_new_pdn_type_due_to_network_preference,
 disc_pdnsetup_dnn_missing_or_unknown, disc_request_timeout_at_originating_entry,
 disc_pdusetup_integrity_protected_mdr_not_acceptable, disc_pdnsetup_upip_status_req_denied_in_rat,
 disc_pdn_pcrf_init_release, disc_pdnsetup_pcrf_create_resp_failed,
 disc_pdnsetup_charging_create_resp_failed, disc_vsmf_insert_dtssa_acscr_not_configured,
 disc_vsmf_insert_interplmn_ho_not_configured, disc_vsm_insert_hsmf_retrieve_failure,
 disc_ro2ho_n2ho_interplmn_ho_not_configured, disc_ro2ho_n4_modify_failed,
 disc_ho2ro_n4_modify_failed, disc_ho2ro_failure disc_ro2ho_failure, disc_ro2ho_guard_timer_expiry,
 disc_ho2ro_guard_timer_expiry

SMF Session stats Category

smf_session_stats

Description: SMF Session stats counters

Sample Query:

```
'smf_session_stats{rat_type="NR",pdu_type="ipv4",dnn="dnn1",ssc_mode="ssc_mode_1",status="attempted"}'
```

Labels:

- Label: `rat_type`

Label Description: Type of the radio access associated with the request

Example: EUTRA, NR, WLAN, UTRA, GERA, `rat_type_unknown`

- Label: `pdu_type`

Label Description: pdu connection type

Example: `ipv4`, `ipv6`, `ipv4v6`, `unknown`

- Label: `dnn`

Label Description: Dnn configured in `dnn-policy`, also can have `virtual_dnn` if configured, separated by #

Example: `intershat`, `intershat#cisco.com`

- Label: `ssc_mode`

Label Description: Type of ssc mode associated with the request

Example: `ssc_mode_1`, `ssc_mode_2`, `ssc_mode_3`, `ssc_mode_unknown`

- Label: `status`

Label Description: PDU session status indicated at SMF

Example: `attempted`, `success`, `setup`

- Label: `roaming_status`

Label Description: Roaming status of the subscriber session

Example: `visitor-lbo`, `visitor-hr`, `roamer`, `homer`, `none`

- Label: `policy_type`

Label Description: Policy type of the subscriber session

Example: `pcf`, `pcrf`, `none`

SMF Session counters Category

smf_session_counters

Description: SMF current active Session counters

Sample Query:

```
'smf_session_counters{rat_type="NR",pdu_type="ipv4",dnn="dnn1",ssc_mode="ssc_mode_1"}'
```

Labels:

- Label: `rat_type`
Label Description: Type of the radio access associated with the request
Example: EUTRA, NR, WLAN, UTRA, GERA, `rat_type_unknown`
- Label: `pdu_type`
Label Description: pdu connection type
Example: `ipv4`, `ipv6`, `ipv4v6`, `unknown`
- Label: `dnn`
Label Description: Dnn configured in dnn-policy, also can have `virtual_dnn` if configured, separated by #
Example: `intershat`, `intershat#cisco.com`
- Label: `ssc_mode`
Label Description: Type of ssc mode associated with the request
Example: `ssc_mode_1`, `ssc_mode_2`, `ssc_mode_3`, `ssc_mode_unknown`
- Label: `always_on`
Label Description: always on status
Example: `enable`, `disable`
- Label: `dcnr`
Label Description: UE DCNR status
Example: `enable`, `disable`
- Label: `emergency_call`
Label Description: Flag indicating if it is an emergency call
Example: `true`, `false`
- Label: `fourg_only_ue`
Label Description: Only 4g capable UE flag
Example: `true`, `false`
- Label: `unauthenticated_supi`
Label Description: indicates if SUPI is unauthenticated
Example: `true`, `false`
- Label: `pra`
Label Description: Presence Reporting Area Information
Example: `enable`, `none`

- Label: `roaming_status`
Label Description: Roaming status of the subscriber session
Example: visitor-lbo, visitor-hr, roamer, homer, none
- Label: `policy_type`
Label Description: Policy type of the subscriber session
Example: pcf, pcrf, none
- Label: `local_policy`
Label Description: Flows or Bearers created based on local policy config
Example: true, false

SMF User Plane Session counters Category

smf_up_session_counters

Description: SMF current active User Plane Sessions

Sample Query: `'smf_up_session_counters{pdu_type="ipv4",dnn="dnn1",ssc_mode="ssc_mode_1"}'`

Labels:

- Label: `rat_type`
Label Description: Type of the radio access associated with the request
Example: EUTRA, NR, WLAN, UTEA, GERA, rat_type_unknown
- Label: `pdu_type`
Label Description: pdu connection type
Example: ipv4, ipv6, ipv4v6, unknown
- Label: `dnn`
Label Description: name of the dnn associated with the request
Example: Any string
- Label: `ssc_mode`
Label Description: Type of ssc mode associated with the request
Example: ssc_mode_1, ssc_mode_2, ssc_mode_3, ssc_mode_unknown

SMF Timeout stats Category

smf_timeout_stats

Description: SMF Timeout stats

Sample Query: `'smf_timeout_stats{timeout_type="SessionSetupTimeout"}'`

Labels:

- Label: `timeout_type`

Label Description: SMF Timeout type

Example: SessionSetupTimeout, SessionCallflowTimeout, SessionEpsFbTimeout, SessionPolicyRevalTimeout, SessionRsRaAdvTime, SessionModifyTimeout, SessionReleaseTimeout, SessionN2HoTimeout, SessionImTimeout, SessionDedBearerTimeout, SessionPdnSetupTimeout, SessionPdnDisconnectTimeout, SessionPdnModifyTimeout, SessionPduIdftTimeout, SessionPdu5G4GHandover, SessionNrToUnTrustWifiHOTimeout, Session4GWifi4GHOTimeout, SessionWifiTo4GHoMBReqTimeout, SessionRouterSolicitTimeout, SessionUsageReportTimeout, SessionPathSwitchTimeout, SessionN1N2RetryAfter, SessionPDUIMN1N2RetryAfter, SessionN2HoIdftTimeout, SessionN26HoIdftTimeout, SessionAbsoluteTimeout, SessionIwfn26IdftTimeout, SessionDedBrrReEstTimer, SessionDedBrrDelayTimer, Session4G5GN26Timeout, SessionN1N2RetryTimeout, SessionN1N2RetransTimeout, SessionPDUIMResumeTimeout, SessionUrrOutOfOrderWaitTimeout, SessionPduRelCmdRetryTimeout, SessionUnTrustWifiToNrHOTimeout, SessionUbrRetryTimer, SessionDbrRetryTimer, SessionPduUeSyncTimeout, SessionAmfChangeGuardTimeout, SessionPduSetupProcSLA, SessionPduImProcSLA, ProcedureSlaTimeout, SessionN2HOProcSLA, SessionCatchAllTimeout, SessionIdleTimeout, SessionCpIdleTimeout, SessionTempRejectHoTimeout, SessionDefaultFlowOnlyTimeout, SessionErirDelayTimeout

SMF RAN failed stats Category

smf_ran_failed_flows

Description: Stats for the failed QFIs sent in UE Sync

Sample Query: `'smf_ran_failed_flows{procedure_type="pdu_ue_sync_proc}'`

Labels:

- Label: `procedure_type`

Label Description: The procedure type associated with an call flow procedure

Example: `pdu_ue_sync_proc`

- Label: `reason`

Label Description: The reason associated with failure

Example: `qfi_failed_to_setup`

SMF N1 Message stats Category

smf_n1_message_stats

Description: Stats for N1 Messages

Sample Query: `'smf_n1_message_stats{procedure_type="pcf_req_pdu_sess_mod}'`

Labels:

- Label: `procedure_type`

Label Description: The procedure type associated with an call flow procedure

Example: pdu_sess_create, ue_req_pdu_sess_mod, smf_req_pdu_sess_mod, pcf_req_pdu_sess_mod, udm_req_pdu_sess_mod, gnb_req_pdu_sess_mod, ue_req_pdu_sess_rel, smf_req_pdu_sess_rel, pcf_req_pdu_sess_rel, amf_req_pdu_sess_rel, udm_req_pdu_sess_rel, gnb_req_pdu_sess_rel, chf_req_pdu_sess_rel, admin_req_pdu_sess_rel, ue_req_active_to_idle, ue_req_idle_to_active, nw_req_service_active, upf_notify_downlink_data, xn_path_switch, pdn_sess_create, pdn_5g_4g_handover, pcf_req_ded_brr_create, pcf_req_ded_brr_delete, pcf_req_ded_brr_mod, n2_handover, xn_handover, n26_4g_to_5g_handover, n26_4g_to_5g_im_mobility, pdu_im, pdn_sess_create, pcf_req_ded_brr_create, pcf_req_ded_brr_delete, pcf_req_ded_brr_mod, pcf_initiated_pdn_detach, smf_initiated_pdn_detach, upf_initiated_pdn_detach, smf_eps_fb

- Label: `direction`

Label Description: Direction of N1 message

Example: outbound, inbound

- Label: `message_type`

Label Description: The N1 message type

Example: pdu_session_establishment_reject, pdu_session_release_request, pdu_session_modification_command_reject, pdu_session_modification_reject, pdu_session_release_reject, 5g_sm_status_msg_release, 5g_sm_status_msg_no_action, 5g_sm_status_msg_invalid_pti

- Label: `n1_cause`

Label Description: N1 cause associated with the message

Example: OPERATOR_DETERMINED_BARRING, INSUFFICIENT_RESOURCES, MISSING_OR_UNKNOWN_DNN, UNKNOWN_PDU_SESSION_TYPE, USER_AUTHENTICATION_OR_AUTHORIZATION_FAILED, REQUEST_REJECTED_UNSPECIFIED, SERVICE_OPTION_NOT_SUPPORTED, REQUESTED_SERVICE_OPTION_NOT_SUBSCRIBED, SERVICE_OPTION_TEMPORARILY_OUT_OF_ORDER, PTI_ALREADY_IN_USE, REGULAR_DEACTIVATION, NETWORK_FAILURE, REACTIVATION_REQUESTED, SEMANTIC_ERROR_IN_THE_TFT_OPERATION, SYNTACTICAL_ERROR_IN_THE_TFT_OPERATION, INVALID_PDU_SESSION_IDENTITY, SEMANTIC_ERRORS_IN_PACKET_FILTER, SYNTACTICAL_ERROR_IN_PACKET_FILTER, OUT_OF_LADN_SERVICE_AREA, PTI_MISMATCH, PDU_SESSION_TYPE_IPV4_ONLY_ALLOWED, PDU_SESSION_TYPE_IPV6_ONLY_ALLOWED, PDU_SESSION_DOES_NOT_EXIST, INSUFFICIENT_RESOURCES_FOR_SPECIFIC_SLICE_AND_DNN, NOT_SUPPORTED_SSC_MODE, INSUFFICIENT_RESOURCES_FOR_SPECIFIC_SLICE, MISSING_OR_UNKNOWN_DNN_IN_A_SLICE, INVALID_PTI_VALUE, MAXIMUM_DATA_RATE_PER_UE_FOR_USER_PLANE_INTEGRITY_PROTECTION_IS_TOO_LOW, SEMANTIC_ERROR_IN_THE_QOS_OPERATION, SYNTACTICAL_ERROR_IN_THE_QOS_OPERATION, INVALID_MAPPED_EPS_BEARER_IDENTITY, SEMANTICALLY_INCORRECT_MESSAGE, INVALID_MANDATORY_INFORMATION, MESSAGE_TYPE_NON_EXISTENT_OR_NOT_IMPLEMENTED, MESSAGE_TYPE_NOT_COMPATIBLE_WITH_THE_PROTOCOL_STATE, INFORMATION_ELEMENT_NON_EXISTENT_OR_NOT_IMPLEMENTED,

CONDITIONAL_IE_ERROR, MESSAGE_NOT_COMPATIBLE_WITH_THE_PROTOCOL_STATE,
 PROTOCOL_ERROR_UNSPECIFIED

SMF N2 Message stats Category

smf_n2_message_stats

Description: Stats for N2 Messages

Sample Query: 'smf_n2_message_stats{procedure_type="pcf_req_pdu_sess_mod"}'

Labels:

- Label: `procedure_type`

Label Description: The procedure type associated with an call flow procedure

Example: pdu_sess_create, ue_req_pdu_sess_mod, smf_req_pdu_sess_mod, pcf_req_pdu_sess_mod, udm_req_pdu_sess_mod, gnb_req_pdu_sess_mod, ue_req_pdu_sess_rel, smf_req_pdu_sess_rel, pcf_req_pdu_sess_rel, amf_req_pdu_sess_rel, udm_req_pdu_sess_rel, gnb_req_pdu_sess_rel, chf_req_pdu_sess_rel, admin_req_pdu_sess_rel, ue_req_active_to_idle, ue_req_idle_to_active, nw_req_service_active, upf_notify_downlink_data, xn_path_switch, pdn_sess_create, pdn_5g_4g_handover, pcf_req_ded_brr_create, pcf_req_ded_brr_delete, pcf_req_ded_brr_mod, n2_handover, xn_handover, n26_4g_to_5g_handover, n26_4g_to_5g_im_mobility, pdu_im, pdn_sess_create, pcf_req_ded_brr_create, pcf_req_ded_brr_delete, pcf_req_ded_brr_mod, pcf_initiated_pdn_detach, smf_initiated_pdn_detach, upf_initiated_pdn_detach, smf_eps_fb

- Label: `direction`

Label Description: Direction of N2 message

Example: outbound, inbound

- Label: `n2_Ngap_ie_type`

Label Description: The N2 Ngap IE type

Example: N2_PDU_SESSION_RESOURCE_RELEASE_COMMAND_TRANSFER, N2_PDU_SESSION_PATH_SWITCH_REQUEST_TRANSFER, N2_INVALID_OR_UNSUPPORTED_NGAP_IE_TYPE, N2_PDU_SESSION_PATH_SWITCH_REQUEST_SETUP_FAILED_TRANSFER, N2_PDU_SESSION_RESOURCE_SETUP_UNSUCCESS_TRANSFER, N2_PDU_SESSION_RESOURCE_NOTIFY_RELEASED_TRANSFER, N2_PDU_SESSION_RESOURCE_MODIFY_UNSUCCESS_TRANSFER, N2_PDU_SESSION_HANDOVER_REQUEST_ACK_TRANSFER, N2_PDU_SESSION_HANDOVER_RESOURCE_ALLOC_UNSUCCESS_TRANSFER, N2_INVALID_OR_UNSUPPORTED_NGAP_TYPE, N2_PDU_SESSION_RESOURCE_SETUP_RESPONSE_TRANSFER

- Label: `n2_cause_group`

Label Description: The N2 Cause Group

Example: NgapCauseGroupEnum_RadioNetworkCause, NgapCauseGroupEnum_TransportLayerCause, NgapCauseGroupEnum_NASCause, NgapCauseGroupEnum_ProtocolCause, NgapCauseGroupEnum_MiscCause, NgapCauseGroupEnum_NgapCauseGroupDummy

- Label: `n2_cause`

Label Description: N2 cause associated with the message

Example: `NgapCauseEnum_RadioNetwork_DummyEnum`, `NgapCauseEnum_RadioNetwork_Unspecified`,
`NgapCauseEnum_RadioNetwork_TXnRELOCoverall_expiry`,
`NgapCauseEnum_RadioNetwork_Successful_handover`,
`NgapCauseEnum_RadioNetwork_Release_due_to_NG_RAN_generated_reason`,
`NgapCauseEnum_RadioNetwork_Release_due_to_5GC_generated_reason`,
`NgapCauseEnum_RadioNetwork_Handover_cancelled`,
`NgapCauseEnum_RadioNetwork_Partial_handover`,
`NgapCauseEnum_RadioNetwork_Handover_failure_in_target_5GC_NG_RAN_node_or_target_system`,
`NgapCauseEnum_RadioNetwork_Handover_target_not_allowed`,
`NgapCauseEnum_RadioNetwork_TNGRELOCoverall_expiry`,
`NgapCauseEnum_RadioNetwork_TNGRELOCprep_expiry`,
`NgapCauseEnum_RadioNetwork_Cell_not_available`,
`NgapCauseEnum_RadioNetwork_Unknown_target_ID`,
`NgapCauseEnum_RadioNetwork_No_radio_resources_available_in_target_cell`,
`NgapCauseEnum_RadioNetwork_Unknown_local_UE_NGAP_ID`,
`NgapCauseEnum_RadioNetwork_Inconsistent_remote_UE_NGAP_ID`,
`NgapCauseEnum_RadioNetwork_Handover_desirable_for_radio_reasons`,
`NgapCauseEnum_RadioNetwork_Time_critical_handover`,
`NgapCauseEnum_RadioNetwork_Resource_optimisation_handover`,
`NgapCauseEnum_RadioNetwork_Reduce_load_in_serving_cell`,
`NgapCauseEnum_RadioNetwork_User_inactivity`,
`NgapCauseEnum_RadioNetwork_Radio_connection_with_UE_lost`,
`NgapCauseEnum_RadioNetwork_Radio_resources_not_available`,
`NgapCauseEnum_RadioNetwork_Invalid_QoS_combination`,
`NgapCauseEnum_RadioNetwork_Failure_in_the_radio_interface_procedure`,
`NgapCauseEnum_RadioNetwork_Interaction_with_other_procedure`,
`NgapCauseEnum_RadioNetwork_Unknown_PDU_Session_ID`,
`NgapCauseEnum_RadioNetwork_Unknown_QoS_Flow_ID`,
`NgapCauseEnum_RadioNetwork_Multiple_PDU_Session_ID_Instances`,
`NgapCauseEnum_RadioNetwork_Multiple_QoS_Flow_ID_Instances`,
`NgapCauseEnum_RadioNetwork_Encryption_and_or_integrity_protection_algorithms_not_supported`,
`NgapCauseEnum_RadioNetwork_NG_intra_system_handover_triggered`,
`NgapCauseEnum_RadioNetwork_NG_inter_system_handover_triggered`,
`NgapCauseEnum_RadioNetwork_Xn_handover_triggered`,
`NgapCauseEnum_RadioNetwork_Not_supported_5QI_value`,
`NgapCauseEnum_RadioNetwork_UE_context_transfer`,
`NgapCauseEnum_RadioNetwork_IMS_voice_EPS_fallback_or_RAT_fallback_triggered`,
`NgapCauseEnum_RadioNetwork_UP_integrity_protection_not_possible`,
`NgapCauseEnum_RadioNetwork_UP_confidentiality_protection_not_possible`,
`NgapCauseEnum_RadioNetwork_Slice_not_supported`,
`NgapCauseEnum_RadioNetwork_UE_in_RRC_INACTIVE_state_not_reachable`,
`NgapCauseEnum_RadioNetwork_Redirection`,
`NgapCauseEnum_RadioNetwork_Resources_not_available_for_the_slice`,
`NgapCauseEnum_RadioNetwork_UE_maximum_integrity_protected_data_rate_reason`,
`NgapCauseEnum_RadioNetwork_Release_due_to_CN_detected_mobility`,
`NgapCauseEnum_RadioNetwork_N26_Interface_Not_Available`,
`NgapCauseEnum_RadioNetwork_Release_Due_To_Pre_Emption`,
`NgapCauseEnum_Transport_resource_unavailable`, `NgapCauseEnum_Transport_Unspecified`,

NgapCauseEnum_Nas_Normal_release, NgapCauseEnum_Nas_Authentication_failure, NgapCauseEnum_Nas_Deregister, NgapCauseEnum_Nas_Nas_Unspecified, NgapCauseEnum_Protocol_Transfer_syntax_error, NgapCauseEnum_Protocol_Abstract_syntax_error_reject, NgapCauseEnum_Protocol_Abstract_syntax_error_ignore_and_notify, NgapCauseEnum_Protocol_Message_not_compatible_with_receiver_state, NgapCauseEnum_Protocol_Semantic_error, NgapCauseEnum_Protocol_Abstract_syntax_error_falsely_constructed_message, NgapCauseEnum_Protocol_Proto_Unspecified, NgapCauseEnum_Misc_Control_processing_overload, NgapCauseEnum_Misc_Not_enough_user_plane_processing_resources, NgapCauseEnum_Misc_Hardware_failure, NgapCauseEnum_Misc_O_M_intervention, NgapCauseEnum_Misc_Unknown_PLMN, NgapCauseEnum_Misc_Unspecified, NgapCauseEnum_UP_integrity_protection_not_possible, NgapCauseEnum_Encryption_and_or_integrity_protection_algorithms_not_supported

- Label: `n2_fail_reason`

Label Description: N2 failure reason

Example: None, N2 Decode Failed, Invalid N2 Container, upfServData is Nil, DL TunnelInfo is Not Found, UPF Tunnel ID lookup Failed, UPF MOD GNB Tunnel Params Failed, UPF MOD RSRA Tunnel Params Failed, UPF MOD Apply WPS Failed, MOD Tunnel LI Params Failed, Qos Mod Info Failed, Missing N2 SM Info, PDU Context Not Found, Default QFI (1) present in failed QosFlowList, RSRA Tunnel Recreation Failed For HO, Update QER Rule Map Failed, Rollback N2 Failed, Invalid Cause N2 SM Info, Mandatory IE incorrect in N2 SM Info, Xn HO Tobe Switch Flag Is Not Set in SmContextUpdateData, Invalid QFI List in PathSwitchRequest, QoS Flow Accepted List not found in XnHO, at least one Qfi to be accepted, PDU Session is Not Established, Missing T-gNB DL UP TunnelInfo, Missing S-gNB DL UP TunnelInfo, Default QFI is present in the Failed QFI List, N4 Session Modification failed, SLA Timeout

SMF Service Resource Management Stats Category

smf_service_resource_mgmt_stats

Description: SMF Service Resource Management Stats

Sample Query:

```
'smf_service_resource_mgmt_stats{ip_req_type="ip-alloc",pdu_type="ipv4",dnn="dnn1"}'
```

Labels:

- Label: `ip_req_type`

Label Description: Type of IP request

Example: ip-alloc, ip-dealloc, ip-static, ip-static-subscription, ip-static-radius

- Label: `procedure_type`

Label Description: The procedure type associated with an call flow procedure

Example: pdu_sess_create, ue_req_pdu_sess_mod, smf_req_pdu_sess_mod, pcf_req_pdu_sess_mod, udm_req_pdu_sess_mod, gnb_req_pdu_sess_mod, ue_req_pdu_sess_rel, smf_req_pdu_sess_rel, pcf_req_pdu_sess_rel, amf_req_pdu_sess_rel, udm_req_pdu_sess_rel, gnb_req_pdu_sess_rel, chf_req_pdu_sess_rel, admin_req_pdu_sess_rel, ue_req_active_to_idle, ue_req_idle_to_active,

nw_req_service_active, upf_notify_downlink_data,
 xn_path_switch, pdn_sess_create, pdn_5g_4g_handover, pcf_req_ded_brr_create, pcf_req_ded_brr_delete,
 pcf_req_ded_brr_mod, n2_handover, xn_handover, n26_4g_to_5g_handover, n26_4g_to_5g_im_mobility,
 pdu_im, pdn_sess_create, pcf_req_ded_brr_create, pcf_req_ded_brr_delete, pcf_req_ded_brr_mod,
 pcf_initiated_pdn_detach, smf_initiated_pdn_detach, upf_initiated_pdn_detach, smf_eps_fb, Cleanuplocal

- Label: `status`

Label Description: status of resource management request

Example: attempted, success, failures

- Label: `pdu_type`

Label Description: pdu connection type

Example: ipv4, ipv6, ipv4v6, unknown

- Label: `dnn`

Label Description: name of the dnn associated with the request

Example: Any string

- Label: `emergency_call`

Label Description: Flag indicating if it is an emergency call

Example: true, false

- Label: `rat_type`

Label Description: Type of the radio access associated with the request

Example: EUTRA, NR, WLAN, rat_type_unknown

SMF Node Manager stats Category

smf_service_node_mgr_stats

Description: Stats for SMF Node Manager

Sample Query: 'smf_service_node_mgr_stats{ip_req_type="ip-alloc"}'

Labels:

- Label: `upf_ep_key`

Label Description: UPF Endpoint Key

Example: IP String Value

- Label: `first_nodemgr_inst`

Label Description: First Nodemgr instance ID

Example: unsigned integer

- Label: `second_nodemgr_inst`

Label Description: Second Nodemgr instance ID

Example: unsigned integer

- Label: `error`

Label Description: Error in case of Node Mgr failure

Example: None, Both associated nodemgr instances are down, Second nodeMgr down and First NodeMgr responded with SmfRspFailure, Second nodeMgr down and First NodeMgr failed with IpcError, First NodeMgr responded with SmfRspFailure, First NodeMgr failed with IpcError, Second NodeMgr failed with IpcError, Second NodeMgr responded with SmfRspFailure

- Label: `retransmit`

Label Description: Is retransmit message

Example: true, false

- Label: `ip_req_type`

Label Description: Type of IP request

Example: ip-alloc, ip-dealloc, ip-static, ip-static-subscription, ip-static-radius, id-only-alloc, id-only-dealloc, id-only-realloc

- Label: `pdu_type`

Label Description: pdu connection type

Example: ipv4, ipv6, ipv4v6, unknown

- Label: `unit_id`

Label Description: Numa Unit ID

Example: unsigned integer

SMF EBI stats Category

smf_ebi_stats

Description: Stats for the EBI Assignment

Sample Query: `'smf_ebi_stats{status="success"}'`

Labels:

- Label: `procedure_type`

Label Description: The procedure type associated with an call flow procedure

Example: pdusetup_ebi_assignment

- Label: `status`

Label Description: status of EBI Assignment

Example: attempted, success, failures

UPF selection stats Category

upf_selection_stats

Description: Stats for the UPF Selection

Sample Query: 'upf_selection_stats{upf_selection_type="preferred"}'

Labels:

- Label: `upf_selection_type`
Label Description: Type of UPF Selection
Example: preferred
- Label: `upf_fqdn`
Label Description: FQDN of the UPF selected
Example: string
- Label: `status`
Label Description: Status the UPF selected
Example: attempted, failed
- Label: `reason`
Label Description: Reason for status of the UPF selected
Example: upf_not_associated, upf_profile_not_found, upf_not_active
- Label: `dnn`
Label Description: name of the dnn associated with the request
Example: Any string
- Label: `rat_type`
Label Description: Type of the radio access associated with the request
Example: EUTRA, NR, WLAN, rat_type_unknown
- Label: `pdu_session_type`
Label Description: PDU Session type
Example: ip-alloc, ip-dealloc, ip-static
- Label: `pdu_subscription_type`
Label Description: PDU Subscription type
Example: ip-alloc, ip-dealloc, ip-static
- Label: `snssai`
Label Description: SNSSAI of the session having sd and sst
Example: sd:<string> sst:<uint>

Radius Message stats Category

smf_radius_message_stats

Description: Stats for Radius interface messages

Sample Query: 'smf_radius_message_stats{message_type="radius_access_request"}'

Labels:

- Label: `direction`

Label Description: Direction indicates about the message going out or coming in

Example: inbound, outbound

- Label: `message_type`

Label Description: Radius Message Type

Example: radius_access_request, radius_access_accept

- Label: `radius_avp_type`

Label Description: Radius AVP Type

Example: radius_avp_pap_username, radius_avp_pap_user_password, radius_avp_chap_challenge, radius_avp_chap_response, radius_avp_mschap_challenge, radius_avp_mschap_response, radius_avp_idle_timeout, radius_avp_session_timeout

- Label: `rat_type`

Label Description: Type of the radio access associated with the request

Example: EUTRA, NR, WLAN, rat_type_unknown

SMF RSRA stats Category

smf_service_rsra_stats

Description: Stats for SMF Service RSRA

Sample Query: 'smf_service_rsra_stats{rat_type="NR"}'

Labels:

- Label: `procedure_type`

Label Description: The RSRA procedure type

Example: router_advt_solicit_request, router_advt_unsolicit_request, router_solicit_request

- Label: `status`

Label Description: status of RSRA

Example: failed, sent, retransmit, received

- Label: `rat_type`

Label Description: Type of the radio access associated with the request

Example: EUTRA, NR, WLAN, rat_type_unknown

- Label: `upf_ep_key`

Label Description: UPF Endpoint Key

Example: IP String Value

- Label: `reason`

Label Description: reason for the failed status

Example: userplane_error, ho_in_progress, ipc_failed, userplane_error, encode_failed, decode_failed

GTPC Message stats Category

smf_gtpc_msg_stats

Description: Stats for GTPC interface messages

Sample Query: 'smf_gtpc_msg_stats{message_type="create_bearer_request"}'

Labels:

- Label: `message_type`

Label Description: GTPC Message Type

Example: delete_bearer_request, create_bearer_request, delete_bearer_request_async, suspend_notification, resume_notification, change_notification

- Label: `status`

Label Description: GTPC message status

Example: attempted, success, failures

- Label: `reason`

Label Description: The reason associated with failure

Example: ipc_failed, sgw_failure, EGTP_CAUSE_LOCAL_DETACH, EGTP_CAUSE_RAT_CHANGED_FROM_3GPP_TO_NON_3GPP, EGTP_CAUSE_COMPLETE_DETACH, EGTP_CAUSE_ISR_DEACTIVATION, EGTP_CAUSE_ERROR_IND_RCVD_RNC_ENODE, EGTP_CAUSE_IMSI_DETACH_ONLY, EGTP_CAUSE_REACTIVATION_REQUESTED, EGTP_CAUSE_PDN_RECONNECTION_TO_THIS_APN_DISALLOWED, EGTP_CAUSE_ACCESS_CHANGED_FROM_NON_3GPP_TO_3GPP, EGTP_CAUSE_PDN_CONN_INACTIVITY_TIMER_EXPIRED, EGTP_CAUSE_PGW_NOT_RESPONDING, EGTP_CAUSE_NETWORK_FAILURE, EGTP_CAUSE_QOS_PARAMETER_MISMATCH, EGTP_CAUSE_REQ_ACCEPTED, EGTP_CAUSE_REQ_ACCEPTED_PARTIALLY, EGTP_CAUSE_NEW_PDN_TYPE_NETWORK_PREFERENCE, EGTP_CAUSE_NEW_PDN_TYPE_SINGLE_ADDR_BEARER_ONLY, EGTP_CAUSE_CONTEXT_NOT_FOUND, EGTP_CAUSE_INVALID_MESSAGE_FORMAT, EGTP_CAUSE_VERSION_NOT_SUPPORTED_BY_NEXT_PEER, EGTP_CAUSE_INVALID_LENGTH, EGTP_CAUSE_SERVICE_NOT_SUPPORTED, EGTP_CAUSE_MANDATORY_IE_INCORRECT, EGTP_CAUSE_MANDATORY_IE_MISSING,

EGTP_CAUSE_SYSTEM_FAILURE, EGTP_CAUSE_NO_RESOURCES_AVAILABLE,
 EGTP_CAUSE_SEMANTIC_ERROR_IN_TFT_OPERATION,
 EGTP_CAUSE_SYNTACTIC_ERROR_IN_TFT_OPERATION,
 EGTP_CAUSE_SEMANTIC_ERROR_IN_PKT_FILTERS,
 EGTP_CAUSE_SYNTACTIC_ERROR_IN_PKT_FILTERS,
 EGTP_CAUSE_MISSING_OR_UNKNOWN_APN, EGTP_CAUSE_UNEXPECTED_REPEATED_IE,
 EGTP_CAUSE_GRE_KEY_NOT_FOUND, EGTP_CAUSE_REALLOCATION_FAILURE,
 EGTP_CAUSE_DENIED_IN_RAT, EGTP_CAUSE_PREFERRED_PDN_TYPE_UNSUPPORTED,
 EGTP_CAUSE_ALL_DYNAMIC_ADDR_OCCUPIED,
 EGTP_CAUSE_UE_CTX_WO_TFT_ALREADY_ACTIVATED,
 EGTP_CAUSE_PROTOCOL_TYPE_NOT_SUPPORTED, EGTP_CAUSE_UE_NOT_RESPONDING,
 EGTP_CAUSE_UE_REFUSES, EGTP_CAUSE_SERVICE_DENIED,
 EGTP_CAUSE_UNABLE_TO_PAGE_UE, EGTP_CAUSE_NO_MEMORY_AVAILABLE,
 EGTP_CAUSE_USER_AUTHENTICATION_FAILED,
 EGTP_CAUSE_APN_DENIED_NO_SUBSCRIPTION, EGTP_CAUSE_REQUEST_REJECTED,
 EGTP_CAUSE_PTMSI_SIGNATURE_MISMATCH, EGTP_CAUSE_IMSI_IMEI_NOT_KNOWN,
 EGTP_CAUSE_SEMANTIC_ERROR_IN_TAD_OPERATION,
 EGTP_CAUSE_SYNTACTIC_ERROR_IN_TAD_OPERATION,
 EGTP_CAUSE_RESERVED_MESSAGE_VALUE_RECEIVED,
 EGTP_CAUSE_PEER_NOT_RESPONDING,
 EGTP_CAUSE_COLLISION_WITH_NETWORK_INIT_REQUEST,
 EGTP_CAUSE_UNABLE_TO_PAGE_UE_DUE_TO_SUSPENSION,
 EGTP_CAUSE_CONDITIONAL_IE_MISSING, EGTP_CAUSE_INCOMPATIBLE_APN_REST_TYPE,
 EGTP_CAUSE_INVALID_LENGTH_WITH_PIGGYBACK_MSG,
 EGTP_CAUSE_DATA_FORWARDING_NOT_SUPPORTED,
 EGTP_CAUSE_INVALID_REPLY_FROM_REMOTE_PEER,
 EGTP_CAUSE_FALLBACK_TO_GTPV1, EGTP_CAUSE_INVALID_PEER,
 EGTP_CAUSE_TEMP_REJECTED_DUE_TO_HANOVER_IN_PROGRESS,
 EGTP_CAUSE_REQ_REJECTED_FOR_PMPV6_REASON, EGTP_CAUSE_APN_CONGESTION,
 EGTP_CAUSE_BEARER_HANDLING_NOT_SUPPORTED,
 EGTP_CAUSE_UE_ALREADY_REATTACHED,
 EGTP_CAUSE_MULTI_PDN_CONNECTION_FOR_APN_NOT_ALLOWED,
 EGTP_CAUSE_MME_SGSN_REFUSES_DUE_TO_VPLMN_POLICY,
 EGTP_CAUSE_GTPC_ENTITY_CONGESTION,
 EGTP_CAUSE_TARGET_ACCESS_RESTRICTED_FOR_THE_SUBSCRIBER,
 EGTP_CAUSE_UE_TEMP_NOT_REACHABLE_DUE_TO_POWER_SAVING,
 EGTP_CAUSE_RELOC_FAILURE_DUE_TO_NAS_MSG_REDIRECTION,
 EGTP_CAUSE_MISSING_TIMESTAMP_OPTION,
 EGTP_CAUSE_MULTIPLE_HNP_NOT_ALLOWED, EGTP_CAUSE_SN_MALFORMED_MSG,
 EGTP_CAUSE_INT_TIMEOUT, cbr_fail_upstate_inactive, ubr_fail_upstate_inactive,
 mbc_retransmit_msg, change_notification_retransmit_msg, pdn_ho_2g_not_allowed_in_upgrade,
 pdn_ho_3g_not_allowed_in_upgrade, pdn_invalid_pcf_version, pdn_invalid_chf_version,
 pdn_2g3g_cli_not_enabled, pdn_ho_wifi_2g_not_allowed, pdn_ho_wifi_3g_not_allowed,
 pdn_ho_2g_wifi_not_allowed, pdn_ho_3g_wifi_not_allowed, pdn_ho_5g_2g_not_allowed,
 pdn_ho_5g_3g_not_allowed, pdn_initial_attach_in_2g3g_4g_to_5g_ho_not_allowed

- Label: qos_5qi

Label Description: 5Qi applicable for the QoS flow

Example: 1, 2, 5

- Label: rat_type

Label Description: Type of the radio access associated with the request

Example: EUTRA, NR, WLAN, UTRA, GERA, rat_type_unknown

- Label: `smf_current_procedure`

Label Description: Current Procedure Name for Message Level Stats

Example: nr_to_untrusted_wifi_handover, eps_fb_ded_brr, PdnDisconnectProcedure, enb_to_untrusted_wifi_handover, pcf_req_ded_brr_create, pcf_req_ded_brr_delete, pcf_req_ded_brr_mod, smf_initiated_pdn_detach, untrusted_wifi_to_enb_handover, upf_sess_report_srir_sess_rel, utn3gpp_to_5g_handover, pdn_modify_2g3g

Radius Authentication Message Stats Category

radius_authentication_message_stats

Description: Stats for Radius Authentication messages

Sample Query:

```
'radius_authentication_message_stats{radius_auth_algorithm="radius_auth_algorithm_pap"}'
```

Labels:

- Label: `dnn`

Label Description: name of the dnn associated with the request

Example: Any string

- Label: `radius_auth_algorithm`

Label Description: Radius Authentication Algorithm used

Example: radius_auth_algorithm_pap, radius_auth_algorithm_chap, radius_auth_algorithm_mschap, radius_auth_algorithm_default

- Label: `status`

Label Description: Radius Auth message status

Example: attempted, success, encode_failed, decode_failed, failed

- Label: `reason`

Label Description: The reason associated with failure

Example: timeout, parse_error, invalid_code, invalid_pco, invalid_apco, invalid_epco, write_error

- Label: `rat_type`

Label Description: Type of the radio access associated with the request

Example: EUTRA, NR, WLAN, rat_type_unknown

SMF Secondary RAT Usage Report Stats Category

smf_secondary_rat_usage_report_stats

Description: Stats for SMF Secondary RAT Usage Report

Sample Query: 'smf_secondary_rat_usage_report_stats{rat_type="NR"}'

Labels:

- Label: `status`

Label Description: Status of Sec RAT Usage Report

Example: ReceivedFromSgw

- Label: `reason`

Label Description: The reason associated with status

Example: success

- Label: `rat_type`

Label Description: Type of the radio access associated with the request

Example: NR

- Label: `ebi`

Label Description: ebi number as string

Example: unsigned int as string or NA

- Label: `qfi`

Label Description: qfi number as string

Example: unsigned int as string or NA

SMF Service Node Report Stats Category

smf_service_node_report_stats

Description: Stats for SMF Service Node Report

Sample Query: 'smf_service_node_report_stats{procedure_type="upf_node_report_pdu_sess_rel"}'

Labels:

- Label: `procedure_type`

Label Description: The SMF procedure type

Example: upf_node_report_pdu_sess_rel, upf_node_report_pdn_sess_rel

- Label: `status`

Label Description: Status of SMF Service Node Report

Example: attempted, failures, success

- Label: pdu_type
Label Description: pdu connection type
Example: ipv4, ipv6, ipv4v6, unknown
- Label: rat_type
Label Description: Type of the radio access associated with the request
Example: EUTRA, NR, WLAN, rat_type_unknown
- Label: up_state
Label Description: Userplane connection status of the session
Example: UpState_None, UpState_Establishing, UpState_Activating, UpState_Activated, UpState_Deactivating, UpState_Deactivated, UpState_Modifying, UpState_Deleting, UpState_Deleted
- Label: peer_gtpu_ep_key
Label Description: GTP Peer
Example: IP String
- Label: upf_endpoint
Label Description: UPF Endpoint
Example: IP String Value

UDM Message Failure Action Stats Category

smf_udm_msg_fail_action

Description: Stats for UDM Message Failure Action

Sample Query: 'smf_udm_msg_fail_action{udm_msg="UdmRegistration"}'

Labels:

- Label: udm_msg
Label Description: Type of UDM Message
Example: UdmRegistration, UdmDeregistration, UdmSmSubscription, UdmSubscribeToNotify, UdmUnSubscribeToNotify
- Label: udm_failure_action
Label Description: Action taken on UDM Message failure
Example: ignore, continue, terminate
- Label: udm_end_point
Label Description: UDM Endpoint
Example: IP String

SMF Charging Descriptor Drop Stats Category

smf_chrg_desc_drop_stats

Description: The current count of charging descriptors dropped due to validation error on Rule Id

Sample Query: 'smf_chrg_desc_drop_stats{rating_group="10"}'

Labels:

- Label: `rating_group`
Label Description: Rating Group for which charging descriptors is dropped
Example: Any string
- Label: `service_identifier`
Label Description: Service Identifier for which charging descriptors is dropped
Example: Any string
- Label: `action`
Label Description: Action with respect to Rule Id
Example: add, mod, del
- Label: `configured`
Label Description: Configured signifies if Rule Id is configured or is dynamic
Example: true, false
- Label: `reason`
Label Description: Reason for the charging descriptor drop
Example: Error string value

SMF Charging Descriptor Delete Stats Category

smf_chrg_desc_del_stats

Description: The current count of charging descriptors deleted because of all associate Rule Ids are deleted

Sample Query: 'smf_chrg_desc_del_stats{rating_group="10"}'

Labels:

- Label: `charging_id`
Label Description: Charging Descriptor Identifier
Example: Any string
- Label: `rating_group`
Label Description: Rating Group for which charging descriptors is dropped
Example: Any string

- Label: `configured`

Label Description: Configured signifies if a Rule Id is configured or is dynamic

Example: true, false

- Label: `reason`

Label Description: Reason for the charging descriptor delete

Example: Error string value

SMF Charging PFCP usage Report Stats Category

smf_pfcip_usage_report_stats

Description: The current count of PFCP usage reports towards CHF

Sample Query: `'smf_pfcip_usage_report_stats{usage_report_type="async"}'`

Labels:

- Label: `usage_report_type`

Label Description: Synchronous usage report or Asynchronous usage report

Example: async, sync

- Label: `status`

Label Description: Usage report status

Example: recieved, dropped, ignored, processed

- Label: `procedure_type`

Label Description: The procedure type associated with an call flow procedure

Example: pdu_sess_create, ue_req_pdu_sess_mod, smf_req_pdu_sess_mod, pcf_req_pdu_sess_mod, udm_req_pdu_sess_mod, gnb_req_pdu_sess_mod, ue_req_pdu_sess_rel, smf_req_pdu_sess_rel, pcf_req_pdu_sess_rel, amf_req_pdu_sess_rel, udm_req_pdu_sess_rel, gnb_req_pdu_sess_rel, chf_req_pdu_sess_rel, admin_req_pdu_sess_rel, ue_req_active_to_idle, ue_req_idle_to_active, nw_req_service_active, upf_notify_downlink_data, xn_path_switch, pdn_sess_create, pdn_5g_4g_handover, pcf_req_ded_brr_create, pcf_req_ded_brr_delete, pcf_req_ded_brr_mod, n2_handover, xn_handover, n26_4g_to_5g_handover, n26_4g_to_5g_im_mobility, pdu_im, pdn_sess_create, pcf_req_ded_brr_create, pcf_req_ded_brr_delete, pcf_req_ded_brr_mod, pcf_initiated_pdn_detach, smf_initiated_pdn_detach, upf_initiated_pdn_detach

- Label: `usage_report_discard_reason`

Label Description: Reason for usage report rejection

Example: uuc_encl_cond_not_met, charg_parm_not_found, start_of_traffic_rcvd, ignore_rule_base_urr, no_valid_trgr_present, ignore_immd_trgr, urr_not_present, no_term_and_drop_traffic, onlinertp_false_or_drop_traffic, mandatory_ie_incorrect, session_ctxt_not_found, radius_accounting, radius_accounting_not_enabled, urr_or_radius_accounting_missing

SMF ADC URR Statistics Category

smf_pfcpc_adc_report_stats

Description: The current count of PFCPC adc reports towards PCF

Sample Query: 'smf_pfcpc_adc_report_stats{adc_report_type="async"}'

Labels:

- Label: `adc_report_type`

Label Description: Synchronus adc report or Asynchronous adc report

Example: `async`, `sync`

- Label: `status`

Label Description: ADC report status

Example: `dropped`, `processed`

SMF Charging Usage Report Stats Category

chf_usage_report_stats

Description: The current count for usage reports towards CHF

Sample Query: 'chf_usage_report_stats{charging_method="offline"}'

Labels:

- Label: `rating_group`

Label Description: Rating Group for which usage is being reported

Example: Any string

- Label: `service_identifier`

Label Description: Service Identifier for which usage is being reported

Example: Any string

- Label: `charging_method`

Label Description: Metering method for the PDU Session

Example: `online`, `offline`, `online_offline`

- Label: `charging_trigger_type`

Label Description: Trigger for usage report

Example: `QUOTA_THRESHOLD`, `QHT`, `FINAL`, `QUOTA_EXHAUSTED`, `VALIDITY_TIME`, `OTHER_QUOTA_TYPE`, `FORCED_REAUTHORISATION`, `UNIT_COUNT_INACTIVITY_TIMER`, `ABNORMAL_RELEASE`, `QOS_CHANGE`, `VOLUME_LIMIT`, `TIME_LIMIT`, `EVENT_LIMIT`, `PLMN_CHANGE`, `USER_LOCATION_CHANGE`, `RAT_CHANGE`, `UE_TIMEZONE_CHANGE`, `TARIFF_TIME_CHANGE`, `MAX_NUMBER_OF_CHANGES_IN_CHARGING_CONDITIONS`, `MANAGEMENT_INTERVENTION`,

CHANGE_OF_UE_PRESENCE_IN_PRESENCE_REPORTING_AREA,
CHANGE_OF_3GPP_PS_DATA_OFF_STATUS, SERVING_NODE_CHANGE, REMOVAL_OF_UPF,
ADDITION_OF_UPF, START_OF_SERVICE_DATA_FLOW, AMBR_CHANGE

- Label: `procedure_type`

Label Description: The procedure type associated with an call flow procedure

Example: pdu_sess_create, ue_req_pdu_sess_mod, smf_req_pdu_sess_mod, pcf_req_pdu_sess_mod, udm_req_pdu_sess_mod, gnb_req_pdu_sess_mod, ue_req_pdu_sess_rel, smf_req_pdu_sess_rel, pcf_req_pdu_sess_rel, amf_req_pdu_sess_rel, udm_req_pdu_sess_rel, gnb_req_pdu_sess_rel, chf_req_pdu_sess_rel, admin_req_pdu_sess_rel, ue_req_active_to_idle, ue_req_idle_to_active, nw_req_service_active, upf_notify_downlink_data, xn_path_switch, pdn_sess_create, pdn_5g_4g_handover, pcf_req_ded_brr_create, pcf_req_ded_brr_delete, pcf_req_ded_brr_mod, n2_handover, xn_handover, n26_4g_to_5g_handover, n26_4g_to_5g_im_mobility, pdu_im, pdn_sess_create, pcf_req_ded_brr_create, pcf_req_ded_brr_delete, pcf_req_ded_brr_mod, pcf_initiated_pdn_detach, smf_initiated_pdn_detach, upf_initiated_pdn_detach

SMF Charging Zero Usage Report Stats Category

`chf_zero_usage_report_stats`

Description: The current count for usage reports dropped due to zero usage

Sample Query: `'chf_zero_usage_report_stats{measurement_type="volume"}'`

Labels:

- Label: `measurement_type`

Label Description: Measurement type

Example: volume, duration, duration-volume

- Label: `charging_trigger_type`

Label Description: Trigger for usage report

Example: QUOTA_THRESHOLD, QHT, FINAL, QUOTA_EXHAUSTED, VALIDITY_TIME, OTHER_QUOTA_TYPE, FORCED_REAUTHORISATION, UNIT_COUNT_INACTIVITY_TIMER, ABNORMAL_RELEASE, QOS_CHANGE, VOLUME_LIMIT, TIME_LIMIT, EVENT_LIMIT, PLMN_CHANGE, USER_LOCATION_CHANGE, RAT_CHANGE, UE_TIMEZONE_CHANGE, TARIFF_TIME_CHANGE, MAX_NUMBER_OF_CHANGES_IN_CHARGING_CONDITIONS, MANAGEMENT_INTERVENTION, CHANGE_OF_UE_PRESENCE_IN_PRESENCE_REPORTING_AREA, CHANGE_OF_3GPP_PS_DATA_OFF_STATUS, SERVING_NODE_CHANGE, REMOVAL_OF_UPF, ADDITION_OF_UPF, START_OF_SERVICE_DATA_FLOW, AMBR_CHANGE

Dropped Charging Data Requests Statistics Category

`cdr_dropped_stats`

Description: The current count for charging data requests dropped due to zero usage

Sample Query: 'cdr_dropped_stats{procedure_type="pdu_sess_create"}'

Labels:

- Label: `procedure_type`

Label Description: The procedure type associated with an call flow procedure

Example: pdu_sess_create, ue_req_pdu_sess_mod, smf_req_pdu_sess_mod, pcf_req_pdu_sess_mod, udm_req_pdu_sess_mod, gnb_req_pdu_sess_mod, ue_req_pdu_sess_rel, smf_req_pdu_sess_rel, pcf_req_pdu_sess_rel, amf_req_pdu_sess_rel, udm_req_pdu_sess_rel, gnb_req_pdu_sess_rel, chf_req_pdu_sess_rel, admin_req_pdu_sess_rel, ue_req_active_to_idle, ue_req_idle_to_active, nw_req_service_active, upf_notify_downlink_data, xn_path_switch, pdn_sess_create, pdn_5g_4g_handover, pcf_req_ded_brr_create, pcf_req_ded_brr_delete, pcf_req_ded_brr_mod, n2_handover, xn_handover, n26_4g_to_5g_handover, n26_4g_to_5g_im_mobility, pdu_im, pdn_sess_create, pcf_req_ded_brr_create, pcf_req_ded_brr_delete, pcf_req_ded_brr_mod, pcf_initiated_pdn_detach, smf_initiated_pdn_detach, upf_initiated_pdn_detach

SMF Charging Quota Event Stats Category

`chf_quota_event_stats`

Description: The current count for quota event received from CHF

Sample Query: 'chf_quota_event_stats{quota_type="initial"}'

Labels:

- Label: `rating_group`

Label Description: Rating group for which quota is received from CHF

Example: Any string

- Label: `quota_type`

Label Description: Quota type as received from CHF

Example: initial, update, initial_final, update_final, fail

- Label: `quota_method`

Label Description: Quota method received from CHF

Example: time, volume, time_volume

- Label: `quota_status`

Label Description: Result for the quota received from CHF

Example: SUCCESS, END_USER_SERVICE_DENIED, QUOTA_MANAGEMENT_NOT_APPLICABLE, QUOTA_LIMIT_REACHED, END_USER_SERVICE_REJECTED, RATING_FAILED

- Label: `quota_fail_action`

Label Description: Action on quota failure

Example: No Action , Disable charging, Drop Traffic, Offline Converted

- Label: `service_identifier`

Label Description: Service Identifier for CHF quota event

Example: Any string

SMF Charging OOO Usage Report Stats Category

smf_ooo_usage_report

Description: The current count for OOO usage report

Sample Query: `'smf_ooo_usage_report{procedure_type="pdu_sess_create"}'`

Labels:

- Label: `procedure_type`

Label Description: The procedure type associated with an call flow procedure

Example: `pdu_sess_create, ue_req_pdu_sess_mod, smf_req_pdu_sess_mod, pcf_req_pdu_sess_mod, udm_req_pdu_sess_mod, gnb_req_pdu_sess_mod, ue_req_pdu_sess_rel, smf_req_pdu_sess_rel, pcf_req_pdu_sess_rel, amf_req_pdu_sess_rel, udm_req_pdu_sess_rel, gnb_req_pdu_sess_rel, chf_req_pdu_sess_rel, admin_req_pdu_sess_rel, ue_req_active_to_idle, ue_req_idle_to_active, nw_req_service_active, upf_notify_downlink_data, xn_path_switch, pdn_sess_create, pdn_5g_4g_handover, pcf_req_ded_brr_create, pcf_req_ded_brr_delete, pcf_req_ded_brr_mod, n2_handover, xn_handover, n26_4g_to_5g_handover, n26_4g_to_5g_im_mobility, pdu_im, pdn_sess_create, pcf_req_ded_brr_create, pcf_req_ded_brr_delete, pcf_req_ded_brr_mod, pcf_initiated_pdn_detach, smf_initiated_pdn_detach, upf_initiated_pdn_detach`

- Label: `dnn`

Label Description: DNN for which the flow is created

Example: `cisco.com`

- Label: `status`

Label Description: Status of OOO usage report processing

Example: `attempted, success, timeout`

SMF Charging Failure Handling Stats Category

chf_failure_handling_stats

Description: Statistics for application error received from CHF

Sample Query: `'chf_failure_handling_stats{appl_err_code="HTTP_STATUS_CODE_403_FORBIDDEN"}'`

Labels:

- Label: `http2_err_code`

Label Description: HTTP2 error code received from CHF

Example: `HTTP_STATUS_CODE_403_FORBIDDEN`

- Label: `appl_err_code`

Label Description: Application error code received from CHF

Example: `END_USER_REQUEST_REJECTED`, `QUOTA_LIMIT_REACHED`, `CHARGING_FAILED`, `USER_UNKNOWN`, `END_USER_REQUEST_DENIED`, `QUOTA_LIMIT_REACHED`, `CHARGING_NOT_APPLICABLE`

- Label: `fh_action`

Label Description: Action taken on failure from CHF

Example: Terminate, Drop Traffic, Disable Charging

- Label: `fh_exchg_type`

Label Description: CHF Exchange in which failure occurred

Example: update, initial

- Label: `disposition`

Label Description: SMF action on failure

Example: disable-charging, drop-traffic, terminate, convert-offline, allocate-max-quota

- Label: `procedure_type`

Label Description: The procedure type associated with an call flow procedure

Example: `pdu_sess_create`, `ue_req_pdu_sess_mod`, `smf_req_pdu_sess_mod`, `pcf_req_pdu_sess_mod`, `udm_req_pdu_sess_mod`, `gnb_req_pdu_sess_mod`, `ue_req_pdu_sess_rel`, `smf_req_pdu_sess_rel`, `pcf_req_pdu_sess_rel`, `amf_req_pdu_sess_rel`, `udm_req_pdu_sess_rel`, `gnb_req_pdu_sess_rel`, `chf_req_pdu_sess_rel`, `admin_req_pdu_sess_rel`, `ue_req_active_to_idle`, `ue_req_idle_to_active`, `nw_req_service_active`, `upf_notify_downlink_data`, `xn_path_switch`, `pdn_sess_create`, `pdn_5g_4g_handover`, `pcf_req_ded_brr_create`, `pcf_req_ded_brr_delete`, `pcf_req_ded_brr_mod`, `n2_handover`, `xn_handover`, `n26_4g_to_5g_handover`, `n26_4g_to_5g_im_mobility`, `pdu_im`, `pdn_sess_create`, `pcf_req_ded_brr_create`, `pcf_req_ded_brr_delete`, `pcf_req_ded_brr_mod`, `pcf_initiated_pdn_detach`, `smf_initiated_pdn_detach`, `upf_initiated_pdn_detach`

SMF Charging Message Stats Category

`chf_message_stats`

Description: Charging Message Statistics

Sample Query: `'chf_message_stats{procedure_type="charging_initial"}'`

Labels:

- Label: `procedure_type`

Label Description: Charging message type

Example: `charging_initial`, `charging_update`, `charging_terminate`

- Label: `dnn`

Label Description: DNN for which the flow is created

Example: cisco.com

- Label: `status`

Label Description: Status of OOO usage report processing

Example: attempted, success, timeout

- Label: `rat_type`

Label Description: RAT type on which the flow is created

Example: EUTRA, NR, WLAN, VIRTUAL, `rat_type_unknown`

- Label: `chf_type`

Label Description: Type of CHF with which message is exchanged

Example: online, offline

- Label: `smf_current_procedure`

Label Description: The procedure type associated with an call flow procedure

Example: `pdu_sess_create`, `ue_req_pdu_sess_mod`, `smf_req_pdu_sess_mod`, `pcf_req_pdu_sess_mod`, `udm_req_pdu_sess_mod`, `gnb_req_pdu_sess_mod`, `ue_req_pdu_sess_rel`, `smf_req_pdu_sess_rel`, `pcf_req_pdu_sess_rel`, `amf_req_pdu_sess_rel`, `udm_req_pdu_sess_rel`, `gnb_req_pdu_sess_rel`, `chf_req_pdu_sess_rel`, `admin_req_pdu_sess_rel`, `ue_req_active_to_idle`, `ue_req_idle_to_active`, `nw_req_service_active`, `upf_notify_downlink_data`, `xn_path_switch`, `pdn_sess_create`, `pdn_5g_4g_handover`, `pcf_req_ded_brr_create`, `pcf_req_ded_brr_delete`, `pcf_req_ded_brr_mod`, `n2_handover`, `xn_handover`, `n26_4g_to_5g_handover`, `n26_4g_to_5g_im_mobility`, `pdu_im`, `pdn_sess_create`, `pcf_req_ded_brr_create`, `pcf_req_ded_brr_delete`, `pcf_req_ded_brr_mod`, `pcf_initiated_pdn_detach`, `smf_initiated_pdn_detach`, `upf_initiated_pdn_detach`

- Label: `interface_type`

Label Description: Type of Interface communicate with PGW

Example: N40, Gy

SMF Charging Radius Accounting Message Stats Category

radius_accounting_message_stats

Description: SMF Radius accounting message stats

Sample Query: `'radius_accounting_message_stats{procedure_type="radius_initial"}'`

Labels:

- Label: `procedure_type`

Label Description: Charging Radius message type

Example: `radius_initial`, `radius_update`, `radius_terminate`

- Label: `dnn`

Label Description: DNN for which the flow is created

Example: cisco.com

- Label: `status`
Label Description: Status of Radius charging message processing
Example: attempted, success, failures
- Label: `reason`
Label Description: Reason for Radius message failure
Example: error, reject, timeout, invalid_arg
- Label: `rat_type`
Label Description: RAT type on which the flow is created
Example: EUTRA, NR, WLAN, VIRTUAL, rat_type_unknown

SMF Charging Session Limit Dynamic Stats Category

chf_sess_limit_dynamic_stats

Description: SMF Charging Session Limit stats

Sample Query:

```
'chf_sess_limit_dynamic_stats{chf_sess_limit_dyn_reason="chf_sess_limit_dyn_del_all_trig_disabled"}'
```

Labels:

- Label: `chf_sess_limit_dyn_reason`
Label Description: Reason for Charging session limit stats
Example: chf_sess_limit_dyn_del_all_trig_disabled, chf_sess_limit_dyn_del_vol_time_nil, chf_sess_limit_dyn_add_in_cdru

CHF Notification Statistics Category

smf_chf_notification_stats

Description: SMF Charging CHF Notification stats

Sample Query: 'smf_chf_notification_stats{notification_type="reauthorization"}'

Labels:

- Label: `notification_type`
Label Description: Type of notification request
Example: reauthorization, abort_charging
- Label: `dnn`
Label Description: DNN for which the flow is created
Example: cisco.com
- Label: `status`

Label Description: Status of notify message processing

Example: attempted, success, failures

- Label: `rat_type`

Label Description: RAT type on which the flow is created

Example: EUTRA, NR, WLAN, VIRTUAL, `rat_type_unknown`

- Label: `reason`

Label Description: Reason for notify message failure

Example: `pdu_session_not_established`, `charging_failed`, `offline_converted`

NRF Discovery Category

`nf_discover_events_total`

Description: NF Discover Stats

Sample Query: `'nf_discover_events_total{nf_type="pcf", response_type="local"}'`

Labels:

- Label: `nf_type`

Label Description: Network Function type

Example: `nrf`, `udm`, `amf`, `pcf`, `chf`, `ciscocontrol`

- Label: `response_type`

Label Description: Discovery response chosen from

Example: `local`, `cache`, `expired-cache`

NF End point selections Category

`nf_endpoint_selections_total`

Description: NF End Point Selection Statistics

Sample Query: `'nf_endpoint_selections_total{nf_type="amf", host="http://10.105.227.109:8082/nnrf-nfm/v1", req="initial"}'`

Labels:

- Label: `nf_type`

Label Description: Network Function type

Example: `nrf`, `udm`, `amf`, `pcf`, `chf`, `ciscocontrol`

- Label: `host`

Label Description: End Point address

Example: `http://10.105.227.109:8082/nnrf-nfm/v1`

- Label: `req`
Label Description: req type
Example: initial, fallback,

NF failure handling stats Category

`nf_failure_handling_stats_total`

Description: NF Failure handling stats

Sample Query: `'nf_failure_handling_stats_total{nf_type="amf", host="http://10.105.227.109:8082/nnrf-nfm/v1", req="initial", response="202", status="final"}'`

Labels:

- Label: `nf_type`
Label Description: Network Function type
Example: nrf, udm, amf, pcf, chf, ciscocontrol
- Label: `host`
Label Description: End Point address
Example: `http://10.105.227.109:8082/nnrf-nfm/v1`
- Label: `req`
Label Description: Request type
Example: initial, fallback,
- Label: `response`
Label Description: Response from the server
Example: 200, 201, 204, `timeout_rpc_error`,
- Label: `status`
Label Description: Status from the server
Example: retry, final

Discover Messages statistics Category

`nf_discover_messages_total`

Description: Discover Messages statistics

Sample Query: `'nf_discover_messages_total{nf_type="amf", host="http://10.105.227.109:8082/nnrf-nfm/v1", result="timeouOrRPCError"}'`

Labels:

- Label: `nf_type`

Label Description: Network Function type

Example: nrf, udm, amf, pcf, chf, ciscocontrol

- Label: `host`

Label Description: End Point address

Example: `http://10.105.227.109:8082/nnrf-nfm/v1`

- Label: `result`

Label Description: result of discover message

Example: 200, 201, 204, success, timeout_rpc_error, response_parse_failure

Discover Messages Time statistics Category

nf_discover_total_time

Description: Discover Messages Total time statistics

Sample Query: `'nf_discover_total_time{nf_type="amf", host="http://10.105.227.109:8082/nnrf-nfm/v1", result="timeouOrRPCError"}'`

Labels:

- Label: `nf_type`

Label Description: Network Function type

Example: nrf, udm, amf, pcf, chf, ciscocontrol

- Label: `host`

Label Description: End Point address

Example: `http://10.105.227.109:8082/nnrf-nfm/v1`

- Label: `result`

Label Description: result of discover message

Example: 200, 201, 204, success, timeout_rpc_error, response_parse_failure

NF management messages statistics Category

nf_management_stats_total

Description: NF management messages statistics

Sample Query: `'nf_management_stats_total{host="http://10.105.227.109:8082/nnrf-nfm/v1", direction="outbound", message_type="registration", result="timeouOrRPCError" }'`

Labels:

- Label: `host`

Label Description: End Point address

Example: `http://10.105.227.109:8082/nrf-nfm/v1`

- Label: `direction`

Label Description: Direction indicates about the message going out or coming in

Example: inbound, outbound

- Label: `message_type`

Label Description: Type of Message

Example: registration, heartbeat, subscription, notification

- Label: `result`

Label Description: result of discover message

Example: 200, 201, 204, success, timeout_rpc_error, response_parse_failure

NF management message time statistics Category

`nf_management_total_time`

Description: NF management messages total time taken

Sample Query: `'nf_management_total_time{host="http://10.105.227.109:8082/nrf-nfm/v1", direction="outbound", message_type="registration", result="timeouOrRPCError" }'`

Labels:

- Label: `host`

Label Description: End Point address

Example: `http://10.105.227.109:8082/nrf-nfm/v1`

- Label: `direction`

Label Description: Direction indicates about the message going out or coming in

Example: inbound, outbound

- Label: `message_type`

Label Description: Type of Message

Example: registration, heartbeat, subscription, notification

- Label: `result`

Label Description: result of discover message

Example: 200, 201, 204, success, timeout_rpc_error, response_parse_failure, request_parse_failure, invalid_notify_event, invalid_nf_instance_uri, internal_error

Policy control dynamic pcc rule statistics Category

policy_dynamic_pcc_rules_total

Description: PCC Rule total statistics for dynamic rules pushed from PCF

Sample Query: 'sum (policy_dynamic_pcc_rules_total(rule_id="Rule-1")) by(qos_5qi, arp) '

Labels:

- Label: rule_id
Label Description: Rule Id for the received dynamic pcc rule
Example: PccRule-1
- Label: operation
Label Description: Operation performed on the dynamic pcc rule
Example: install, modify, remove
- Label: event
Label Description: Event associated with the operation performed on the pcc rule
Example: attempted, success, failure, abort
- Label: qos_5qi
Label Description: 5Qi applied on the dynamic pcc rule
Example: 1, 2, 5
- Label: arp
Label Description: Priority level of ARP applied on the dynamic pcc rule
Example: 10, 20
- Label: tc_event
Label Description: Traffic Control event applied on the dynamic pcc rule
Example: enabled_ul, enabled_dl, enabled, disabled, removed
- Label: charging_type
Label Description: Charging type applied on the dynamic pcc rule
Example: online, offline, online-offline
- Label: charging_method
Label Description: Charging method applied on the dynamic pcc rule
Example: volume, time, vol_time
- Label: details
Label Description: Details on the operation applied on the dynamic pcc rule
Example: success, failed, validation_failed
- Label: smf_current_procedure

Label Description: Current procedure associated with the operation performed on the pcc rule

Example: pdn_sess_create, pdu_sess_create, pcf_req_pdu_sess_mod, pcf_req_ded_brr_mod, enb_to_untrusted_wifi_handover, untrusted_wifi_to_enb_handover, nr_to_untrusted_wifi_handover, utn3gpp_to_5g_handover, xn_handover, n26_4g_to_5g_handover, pdn_5g_4g_handover, n26_4g_to_5g_im_mobility

- Label: pccrule_change_type

Label Description: pcc rule parameter change type

Example: NA, binding_param_change, no_binding_param_change

- Label: interface_type

Label Description: Type of Interface communicate with PGW

Example: pcf, pcrf

- Label: is_adc

Label Description: Type of rule is ADC or Non-ADC

Example: true, false

- Label: mute

Label Description: Mute is enabled or disabled for ADC rule

Example: true, false

- Label: rule_fail_reason

Label Description: PCC Rule Fail Reason

Example: Rulebase is inactive, Rulebase is not configured, Predefined rule is inactive, Predefined rule is not configured, Pcc Rule recvd w/o RefQos, Pcc Rule recvd with invalid RefQos, Delete Pcc Rule recvd with policy create, Pcc Rule Does not exist, Pcc Rule recvd with reserved precedence, Pcc Rule name and id mismatch, Pcc Rule id is invalid, Pcc Rule recvd with invalid flow direction, Pcc Rule recvd without expected RefQos, Pcc Rule recvd Max filters(16) overflow, Max supported filters reached, Pcc Rule recvd with mismatch RefQoS, Pcc Rule recvd with unexpeted qos desc, Skipped due to Charging Description validation, Pcc Rule recvd with missing charging descriptor, Pcc Rule recvd with invalid charging desc, Qos Desc unexpected content, Pcc Rule recvd with multiple RefQos, Pcc Rule recvd without Flow Information, Pcc Rule recvd with RefQos having invalid, binding params, Sess Rule recvd w/o sess rule id, Sess Rule recvd w/o uplink AMBR, Sess Rule recvd w/o downlink AMBR, Sess Rule recvd with non standard 5QI, Sess Rule Auth def Qos recvd w/o ARP, Sess Rule and Auth def Qos mismatch, Sess Rule Auth def Qos recvd from non default flow, Sess Rule Auth def Qos QCI present in other Qos Desc, Sess Rule name and id mismatch, ARP recvd with invalid params, Flow desc recvd with invalid format(Invalid ipaddr class), Expected format: permit <direction> <protocol> from <Srouce IP> <Srouce Port> to <Dest IP> <Dest Port>, Flow desc recvd with action not supported, Flow desc recvd with direction not supported, Flow desc recvd with protocol not supported, Flow desc recvd with protocol missing, Flow desc recvd with remote IP or mask invalid, Flow desc recvd with source IP or mask invalid, Flow desc invert modifier not allowed, Flow desc assigned not supported for remote IP, Qos Desc Qos ID mismatch, Qos Desc recvd with Non Std 5QI, Qos Desc recvd with Non invalid bitrate, Qos Desc MBR value should be more than GBR value, Qos Desc recvd with invalid QoSID, Qos Desc recvd w/o ARP, Received exisiting Qos Desc with different binding parameters, Policy Trig lastreq data unavailable, Charging Desc not referred by any PCC Rule Or referred by invalid PCC Rule, Received Charging Id different from charging desc map key, Charging Desc not referred by any PCC Rule Or referred by invalid PCC Rule, Received Charging Id not referred by any PCC Rule, Existing Charging

Desc unsupported modify, Invalid Input, Missing Charging ID information from Charging Descriptor, Missing RatingGroup information for Charging Id, Neither Online nor Offline charging method is enabled for charging descriptor Missing Service ID information for Charging Desc, Missing Service ID information for Charging Desc, URR ID not found for rating group, URR ID not found for rating group and service ID, Received Charging Desc conflicts with another charging descriptor, Charging Desc skipped due to Pcc Rule, Conflicting with dynamic charging descriptor, Duplicate report function data invalid, IsMatching function data invalid, Conflicting RG service ID, PCC Rule Dropped due to charging association, Last Rule data not available, PCC Rule Invalid due to Ref TC Data, TC ID - Name mismatch, Missing Redirect Server address, Invalid Address Type, Session Rule recvd with Invalid 5QI, Qos Desc recvd with Invalid 5QI, Pcc Rule recvd with RefQos having invalid Flow for Non-Std QCI, Received Qos Desc with different Flow parameters between same flow for Non-Std QCI, Received existing Qos Desc with different Flow parameters for Non-Std QCI, Received Std-QCI Non-GBR Flow with GBR value, Received Std-QCI GBR Flow without GBR value, Predefine Pcc Rule recvd without AppID but its configs as ADC Rule, Predefine Pcc Rule recvd with AppID but its configs as Non-ADC Rule, Application Id change is not supported for Predefine Pcc Rule, PCC Rule rcvd with missing rule name, PCC Rule rcvd with invalid Flow Description, PCC Rule rcvd with Invalid ToS Traffic Class, PCC Rule rcvd with Invalid SecurityParameterIndex, PCC Rule rcvd with Invalid Flow Label, PCC Rule rcvd with missing precedence, PCC Rule rcvd with missing QoS Information, PCC Rule rcvd with missing QCI in QoS Information, PCC Rule rcvd with invalid or unsupported QCI in QoS Information, PCC Rule rcvd with missing ARP priority level in QoS Information, PCC Rule rcvd with invalid ARP priority level, PCC Rule rcvd with invalid reporting level, PCC Rule rcvd with invalid flow status, Def Bearer Qos received with missing QCI, Def Bearer Qos received with invalid or unsupported QCI, Def Bearer Qos received with invalid ARP priority level, Invalid BCM received, Failure due Result Code AVP, Failure due to Experimental Result Code AVP, Invalid or Missing Supported Feature AVP, Usage Monitoring data instance is not defined, Invalid Usage Monitoring data referenced in Sess or PCC rule, Pcc Rule recvd with invalid refUmData, Sess Rule recvd with invalid refUmData, Gx Session release cause received, ADC Rule rcvd with both AppID and Flow Info, ADC Rule rcvd with AppID not present in config, ADC Rule rcvd with TDF App ID Modification, ADC Rule rcvd without Mute Notification, ADC Rule rcvd with invalid Mute Notification, Non-ADC Rule rcvd with TDF App ID Modification

Policy control pre-defined pcc rule statistics Category

policy_predefined_pcc_rules_total

Description: PCC Rule total statistics for pre-defined rules activated by PCF

Sample Query: 'sum (policy_predefined_pcc_rules_total{rule_id="Rule-1"}) by(event, operation)'

Labels:

- Label: `rulebase`

Label Description: Rulebase to which this pre-defined rule belongs

Example: Rulebase-1

- Label: `operation`

Label Description: Operation performed on the pre-defined pcc rule

Example: install, modify, remove

- Label: `event`

Label Description: Event associated with the operation performed on the pre-defined rule

Example: attempted, success, failure

- Label: qos_5qi

Label Description: 5Qi applied on the pre-defined pcc rule

Example: 1, 2, 5

- Label: arp

Label Description: Priority level of ARP applied on the pre-defined pcc rule

Example: 10, 20

- Label: charging_type

Label Description: Charging type applied on the pre-defined pcc rule

Example: online, offline, online-offline

- Label: charging_method

Label Description: Charging method applied on the pre-defined pcc rule

Example: volume, time, vol_time

- Label: smf_current_procedure

Label Description: Current procedure associated with the operation performed on the pcc rule

Example: pdn_sess_create, pdu_sess_create, smf_initiated_pdn_detach, disc_pdurel_smf_init_release, pcf_req_pdu_sess_mod, pcf_req_ded_brr_mod, enb_to_untrusted_wifi_handover, untrusted_wifi_to_enb_handover, nr_to_untrusted_wifi_handover, utn3gpp_to_5g_handover, xn_handover, n26_4g_to_5g_handover, pdn_5g_4g_handover, n26_4g_to_5g_im_mobility

- Label: interface_type

Label Description: Type of Interface communicate with PGW

Example: pcf, pcrf

- Label: rule_fail_reason

Label Description: PCC Rule Fail Reason

Example: Rulebase is inactive, Rulebase is not configured, Predefined rule is inactive, Predefined rule is not configured, Pcc Rule recvd w/o RefQos, Pcc Rule recvd with invalid RefQos, Delete Pcc Rule recvd with policy create, Pcc Rule Does not exist, Pcc Rule recvd with reserved precedence, Pcc Rule name and id mismatch, Pcc Rule id is invalid, Pcc Rule recvd with invalid flow direction, Pcc Rule recvd without expected RefQos, Pcc Rule recvd Max filters(16) overflow, Max supported filters reached, Pcc Rule recvd with mismatch RefQoS, Pcc Rule recvd with unexpeted qos desc, Skipped due to Charging Description validation, Pcc Rule recvd with missing charging descriptor, Pcc Rule recvd with invalid charging desc, Qos Desc unexpected content, Pcc Rule recvd with multiple RefQos, Pcc Rule recvd without Flow Information, Pcc Rule recvd with RefQos having invalid, binding params, Sess Rule recvd w/o sess rule id, Sess Rule recvd w/o uplink AMBR, Sess Rule recvd w/o downlink AMBR, Sess Rule recvd with non standard 5QI, Sess Rule Auth def Qos recvd w/o ARP, Sess Rule and Auth def Qos mismatch, Sess Rule Auth def Qos recvd from non default flow, Sess Rule Auth def Qos QCI present in other Qos Desc, Sess Rule name and id mismatch, ARP recvd with invalid params, Flow desc recvd with invalid format(Invalid ipaddr class), Expected format: permit <direction> <protocol> from <Srouce IP> <Srouce Port> to <Dest IP> <Dest Port>, Flow desc recvd with action not supported, Flow desc recvd with direction not supported, Flow desc recvd with protocol not supported, Flow desc recvd with

protocol missing, Flow desc recvd with remote IP or mask invalid, Flow desc recvd with source IP or mask invalid, Flow desc invert modifier not allowed, Flow desc assigned not supported for remote IP, Qos Desc Qos ID mismatch, Qos Desc recvd with Non Std 5QI, Qos Desc recvd with Non invalid bitrate, Qos Desc MBR value should be more than GBR value, Qos Desc recvd with invalid QoSID, Qos Desc recvd w/o ARP, Received existing Qos Desc with different binding parameters, Policy Trig lastreq data unavailable, Charging Desc not referred by any PCC Rule Or referred by invalid PCC Rule, Received Charging Id different from charging desc map key, Charging Desc not referred by any PCC Rule Or referred by invalid PCC Rule, Received Charging Id not referred by any PCC Rule, Existing Charging Desc unsupported modify, Invalid Input, Missing Charging ID information from Charging Descriptor, Missing RatingGroup information for Charging Id, Neither Online nor Offline charging method is enabled for charging descriptor Missing Service ID information for Charging Desc, Missing Service ID information for Charging Desc, URR ID not found for rating group, URR ID not found for rating group and service ID, Received Charging Desc conflicts with another charging descriptor, Charging Desc skipped due to Pcc Rule, Conflicting with dynamic charging descriptor, Duplicate report function data invalid, IsMatching function data invalid, Conflicting RG service ID, PCC Rule Dropped due to charging association, Last Rule data not available, PCC Rule Invalid due to Ref TC Data, TC ID - Name mismatch, Missing Redirect Server address, Invalid Address Type, Session Rule recvd with Invalid 5QI, Qos Desc recvd with Invalid 5QI, Pcc Rule recvd with RefQos having invalid Flow for Non-Std QCI, Received Qos Desc with different Flow parameters between same flow for Non-Std QCI, Received existing Qos Desc with different Flow parameters for Non-Std QCI, Received Std-QCI Non-GBR Flow with GBR value, Received Std-QCI GBR Flow without GBR value, Predefine Pcc Rule recvd without AppID but its configs as ADC Rule, Predefine Pcc Rule recvd with AppID but its configs as Non-ADC Rule, Application Id change is not supported for Predefine Pcc Rule, PCC Rule rcvd with missing rule name, PCC Rule rcvd with invalid Flow Description, PCC Rule rcvd with Invalid ToS Traffic Class, PCC Rule rcvd with Invalid SecurityParameterIndex, PCC Rule rcvd with Invalid Flow Label, PCC Rule rcvd with missing precedence, PCC Rule rcvd with missing QoS Information, PCC Rule rcvd with missing QCI in QoS Information, PCC Rule rcvd with invalid or unsupported QCI in QoS Information, PCC Rule rcvd with missing ARP priority level in QoS Information, PCC Rule rcvd with invalid ARP priority level, PCC Rule rcvd with invalid reporting level, PCC Rule rcvd with invalid flow status, Def Bearer Qos received with missing QCI, Def Bearer Qos received with invalid or unsupported QCI, Def Bearer Qos received with invalid ARP priority level, Invalid BCM received, Failure due Result Code AVP, Failure due to Experimental Result Code AVP, Invalid or Missing Supported Feature AVP, Usage Monitoring data instance is not defined, Invalid Usage Monitoring data referenced in Sess or PCC rule, Pcc Rule recvd with invalid refUmData, Sess Rule recvd with invalid refUmData, Gx Session release cause received

Policy control static pcc rule statistics Category

policy_static_pcc_rules_total

Description: PCC Rule total statistics for static rules activated via rulebase

Sample Query: 'sum (policy_static_pcc_rules_total{rulebase="Rulebase-1"})'

Labels:

- Label: rulebase

Label Description: Rulebase to which the static rules belong

Example: Rulebase-1

- Label: operation

Label Description: Operation performed on the rulebase

Example: install, remove

- Label: `event`

Label Description: Event associated with the operation performed on the rulebase

Example: attempted, success, failure

- Label: `smf_current_procedure`

Label Description: Current procedure associated with the operation performed on the pcc rule

Example: `pdn_sess_create`, `pdu_sess_create`, `smf_initiated_pdn_detach`, `disc_pdurel_smf_init_release`, `pcf_req_pdu_sess_mod`, `pcf_req_ded_brr_mod`, `enb_to_untrusted_wifi_handover`, `untrusted_wifi_to_enb_handover`, `nr_to_untrusted_wifi_handover`, `utn3gpp_to_5g_handover`, `xn_handover`, `n26_4g_to_5g_handover`, `pdn_5g_4g_handover`, `n26_4g_to_5g_im_mobility`

- Label: `interface_type`

Label Description: Type of Interface communicate with PGW

Example: `pcf`, `pcrf`

- Label: `rule_fail_reason`

Label Description: PCC Rule Fail Reason

Example: Rulebase is inactive, Rulebase is not configured, Predefined rule is inactive, Predefined rule is not configured, Pcc Rule recvd w/o RefQos, Pcc Rule recvd with invalid RefQos, Delete Pcc Rule recvd with policy create, Pcc Rule Does not exist, Pcc Rule recvd with reserved precedence, Pcc Rule name and id mismatch, Pcc Rule id is invalid, Pcc Rule recvd with invalid flow direction, Pcc Rule recvd without expected RefQos, Pcc Rule recvd Max filters(16) overflow, Max supported filters reached, Pcc Rule recvd with mismatch RefQoS, Pcc Rule recvd with unexpeted qos desc, Skipped due to Charging Description validation, Pcc Rule recvd with missing charging descriptor, Pcc Rule recvd with invalid charging desc, Qos Desc unexpected content, Pcc Rule recvd with multiple RefQos, Pcc Rule recvd without Flow Information, Pcc Rule recvd with RefQos having invalid, binding params, Sess Rule recvd w/o sess rule id, Sess Rule recvd w/o uplink AMBR, Sess Rule recvd w/o downlink AMBR, Sess Rule recvd with non standard 5QI, Sess Rule Auth def Qos recvd w/o ARP, Sess Rule and Auth def Qos mismatch, Sess Rule Auth def Qos recvd from non default flow, Sess Rule Auth def Qos QCI present in other Qos Desc, Sess Rule name and id mismatch, ARP recvd with invalid params, Flow desc recvd with invalid format(Invalid ipaddr class), Expected format: permit <direction> <protocol> from <Srouce IP> <Srouce Port> to <Dest IP> <Dest Port>, Flow desc recvd with action not supported, Flow desc recvd with direction not supported, Flow desc recvd with protocol not supported, Flow desc recvd with protocol missing, Flow desc recvd with remote IP or mask invalid, Flow desc recvd with source IP or mask invalid, Flow desc invert modifier not allowed, Flow desc assigned not supported for remote IP, Qos Desc Qos ID mismatch, Qos Desc recvd with Non Std 5QI, Qos Desc recvd with Non invalid bitrate, Qos Desc MBR value should be more than GBR value, Qos Desc recvd with invalid QoSID, Qos Desc recvd w/o ARP, Received exisiting Qos Desc with different binding parameters, Policy Trig lastreq data unavailable, Charging Desc not referred by any PCC Rule Or referred by invalid PCC Rule, Received Charging Id different from charging desc map key, Charging Desc not referred by any PCC Rule Or referred by invalid PCC Rule, Received Charging Id not referred by any PCC Rule, Existing Charging Desc unsupported modify, Invalid Input, Missing Charging ID information from Charging Descriptor, Missing RatingGroup information for Charging Id, Neither Online nor Offline charging method is enabled for charging descriptor Missing Service ID inforamtion for Charging Desc, Missing Service ID inforamtion for Charging Desc, URR ID not found for rating group, URR ID not found for rating group and service

ID, Received Charging Desc conflicts with another charging descriptor, Charging Desc skipped due to Pcc Rule, Conflicting with dynamic charging descriptor, Duplicate report function data invalid, IsMatching function data invalid, Conflicting RG service ID, PCC Rule Dropped due to charging association, Last Rule data not available, PCC Rule Invalid due to Ref TC Data, TC ID - Name mismatch, Missing Redirect Server address, Invalid Address Type, Session Rule recvd with Invalid 5QI, Qos Desc recvd with Invalid 5QI, Pcc Rule recvd with RefQos having invalid Flow for Non-Std QCI, Received Qos Desc with different Flow parameters between same flow for Non-Std QCI, Received existing Qos Desc with different Flow parameters for Non-Std QCI, Received Std-QCI Non-GBR Flow with GBR value, Received Std-QCI GBR Flow without GBR value, Predefine Pcc Rule recvd without AppID but its configs as ADC Rule, Predefine Pcc Rule recvd with AppID but its configs as Non-ADC Rule, Application Id change is not supported for Predefine Pcc Rule, PCC Rule rcvd with missing rule name, PCC Rule rcvd with invalid Flow Description, PCC Rule rcvd with Invalid ToS Traffic Class, PCC Rule rcvd with Invalid SecurityParameterIndex, PCC Rule rcvd with Invalid Flow Label, PCC Rule rcvd with missing precedence, PCC Rule rcvd with missing QoS Information, PCC Rule rcvd with missing QCI in QoS Information, PCC Rule rcvd with invalid or unsupported QCI in QoS Information, PCC Rule rcvd with missing ARP priority level in QoS Information, PCC Rule rcvd with invalid ARP priority level, PCC Rule rcvd with invalid reporting level, PCC Rule rcvd with invalid flow status, Def Bearer Qos received with missing QCI, Def Bearer Qos received with invalid or unsupported QCI, Def Bearer Qos received with invalid ARP priority level, Invalid BCM received, Failure due Result Code AVP, Failure due to Experimental Result Code AVP, Invalid or Missing Supported Feature AVP, Usage Monitoring data instance is not defined, Invalid Usage Monitoring data referenced in Sess or PCC rule, Pcc Rule recvd with invalid refUmData, Sess Rule recvd with invalid refUmData, Gx Session release cause received

Policy control session rule statistics Category

policy_session_rules_total

Description: Session total statistics for session rules applied

Sample Query: 'sum (policy_session_rules_total{rule_id="SessRule-1"})'

Labels:

- Label: `rule_id`

Label Description: Rule Id for the received session rule from PCF

Example: SessRule-1

- Label: `operation`

Label Description: Operation performed on the session rule

Example: install, modify, remove

- Label: `event`

Label Description: Event associated with the operation performed on the rulebase

Example: attempted, success, failure

- Label: `smf_current_procedure`

Label Description: Current procedure associated with the operation performed on the pcc rule

Example: pdn_sess_create, pdu_sess_create, smf_initiated_pdn_detach, disc_pdu_rel_smf_init_release, pcf_req_pdu_sess_mod, pcf_req_ded_brr_mod, enb_to_untrusted_wifi_handover,

untrusted_wifi_to_enb_handover, nr_to_untrusted_wifi_handover, utn3gpp_to_5g_handover, xn_handover, n26_4g_to_5g_handover, pdn_5g_4g_handover, n26_4g_to_5g_im_mobility

- Label: interface_type

Label Description: Type of Interface communicate with PGW

Example: pcf, pcrf

Policy control PCF update statistics Category

policy_pcf_updates_total

Description: Statistics for triggers sent to PCF in SmPolicyUpdate Request to PCF

Sample Query: 'sum (policy_pcf_updates_total{trigger="rat_change"})'

Labels:

- Label: trigger

Label Description: Trigger sent in the policy update request sent to PCF

Example: ue_ip_change, plmn_change, res_mod_req, access_type_change, ue_ip_change, credit_mon_sess_fail, def_qos_change, sess_ambr_change, no_credit, serving_area_change, revalidation_timeout, resoure_release, resource_alloc, rat_change

- Label: smf_current_procedure

Label Description: Current procedure associated with the operation performed on the pcc rule

Example: pdn_sess_create, pdu_sess_create, smf_initiated_pdn_detach, disc_pdurel_smf_init_release, pcf_req_pdu_sess_mod, pcf_req_ded_brr_mod, enb_to_untrusted_wifi_handover, untrusted_wifi_to_enb_handover, nr_to_untrusted_wifi_handover, utn3gpp_to_5g_handover, xn_handover, n26_4g_to_5g_handover, pdn_5g_4g_handover, n26_4g_to_5g_im_mobility

- Label: interface_type

Label Description: Type of Interface communicate with PGW

Example: pcf, pcrf

Policy control total flow statistics Category

policy_pdu_flows_total

Description: QoS flow total statistics

Sample Query: 'sum (policy_pdu_flows_total{flow_type="gbr"}) by (qos_5qi, arp)'

Labels:

- Label: operation

Label Description: Operation performed on the QoS flow

Example: install, modify, remove

- Label: `event`
Label Description: Event associated with the operation performed on QoS flow
Example: attempted, success, failure, abort
- Label: `rat_type`
Label Description: RAT type on which the flow is created
Example: nr, WLAN, EUTRA
- Label: `ssc_mode`
Label Description: SSC mode for the session which created the QoS flow
Example: one, two, three
- Label: `pdn_type`
Label Description: PDN type of the session which created the QoS flow
Example: v4, v6, v4v6
- Label: `dnn`
Label Description: DNN for which the flow is created
Example: cisco.com
- Label: `flow_type`
Label Description: Flow type for the QoS flow
Example: gbr, non_gbr
- Label: `init_or_ho`
Label Description: Flow operation phase
Example: initial, ho
- Label: `qos_5qi`
Label Description: 5Qi applicable for the QoS flow
Example: 1, 2, 5
- Label: `arp`
Label Description: Priority level of ARP applicable for the QoS flow
Example: 10, 20
- Label: `interface_type`
Label Description: Type of Interface communicate with PGW
Example: pcf, pcrf
- Label: `mapped_flow`
Label Description: flow has mapped 5Qi or not
Example: true , false

- Label: `policy_type`
Label Description: policy type for the subscriber session
Example: `pcrf,pcf,optimized,local_policy`

Policy control current flow Category

policy_pdu_flows_current

Description: QoS flow current counts

Sample Query: `'sum (policy_pdu_flows_current{flow_type="gbr"}) by (qos_5qi, arp) '`

Labels:

- Label: `rat_type`
Label Description: RAT type on which the flow is created
Example: `nr, WLAN, EUTRA`
- Label: `ssc_mode`
Label Description: SSC mode for the session which created the QoS flow
Example: `one, two, three`
- Label: `pdn_type`
Label Description: PDN type of the session which created the QoS flow
Example: `v4, v6, v4v6`
- Label: `dnn`
Label Description: DNN for which the flow is created
Example: `cisco.com`
- Label: `flow_type`
Label Description: Flow type for the QoS flow
Example: `gbr, non_gbr`
- Label: `qos_5qi`
Label Description: 5Qi applicable for the QoS flow
Example: `1, 2, 5`
- Label: `arp`
Label Description: Priority level of ARP applicable for the QoS flow
Example: `10, 20`
- Label: `smf_current_procedure`
Label Description: Current procedure associated with the operation performed on the pcc rule

Example: pdn_sess_create, pdu_sess_create, pcf_req_pdu_sess_mod, pcf_req_ded_brr_mod, enb_to_untrusted_wifi_handover, untrusted_wifi_to_enb_handover, nr_to_untrusted_wifi_handover, utn3gpp_to_5g_handover, xn_handover, n26_4g_to_5g_handover, pdn_5g_4g_handover, n26_4g_to_5g_im_mobility

- Label: `interface_type`

Label Description: Type of Interface communicate with PGW

Example: pcf, pcrf

- Label: `mapped_flow`

Label Description: flow has mapped 5Qi or not

Example: true , false

- Label: `policy_type`

Label Description: policy type for the subscriber session

Example: pcrf,pcrf,optimized,local_policy

Policy control rule report statistics Category

pcf_rule_report_stats

Description: Statistics for Rule Report sent to PCF

Sample Query: 'sum (pcf_rule_report_stats{pcf_rule_report_fail_code="INCOR_FLOW_INFO"})'

Labels:

- Label: `pcf_rule_report_fail_code`

Label Description: Failure code sent in RuleReport

Example: INCOR_FLOW_INFO

- Label: `interface_type`

Label Description: Type of Interface communicate with PGW

Example: pcf, pcrf

Policy control NRF fail action statistics Category

policy_msg_nrf_fail_action

Description: NRF fail action stats for policy messages

Sample Query: 'sum (policy_msg_nrf_fail_action{policy_control_msg="SmPolicyCreate"})'

Labels:

- Label: `policy_control_msg`

Label Description: Type of policy control message

Example: SmPolicyCreate, SmPolicyUpdate, SmPolicyDelete

- Label: `policy_nrf_action`

Label Description: NRF failure action

Example: ignore, continue, terminate

- Label: `pcf_end_point`

Label Description: PCF IP Address

Example: 10.84.17.11

- Label: `interface_type`

Label Description: Type of Interface communicate with PGW

Example: pcf, pcrf

Policy control active PCF statistics Category

session_policy_type_total

Description: Stats for PCF active Sessions

Sample Query: 'sum (session_policy_type_total{policy_type="local"})'

Labels:

- Label: `policy_type`

Label Description: Policy type

Example: local, pcf

- Label: `pcf_address`

Label Description: PCF IP Address

Example: 10.84.17.11

- Label: `access_type`

Label Description: Access type

Example: Ipv4PduSession, Ipv6PduSession, Ipv4V6PduSession

- Label: `interface_type`

Label Description: Type of Interface communicate with PGW

Example: pcf, pcrf

Policy control message statistics Category

policy_msg_processing_status

Description: Policy message handling Stats

Sample Query: 'sum

```
(policy_msg_processing_status(policy_notification_msg="SmPolicyUpdateNotify"))'
```

Labels:

- Label: `policy_notification_msg`
 Label Description: Policy message type
 Example: SmPolicyUpdateNotify, SmPolicyTerminate, SmPolicyCreate, SmPolicyUpdate, SmPolicyDelete
- Label: `msg_status`
 Label Description: Policy processing message status
 Example: accepted, rejected, skipped, attempted, failed, exp_attempted, exp_accepted, exp_rejected, exp_failed
- Label: `pcf_end_point`
 Label Description: PCF IP Address
 Example: 10.84.17.11
- Label: `rat_type`
 Label Description: RAT type of the flow
 Example: nr, WLAN, EUTRA
- Label: `result`
 Label Description: result of policy message processing
 Example: cfg_issue, max_outstanding, send_failure, timeout, proc_timeout, rc_with_err, ex_rc_with_err, none
- Label: `policy_fh_action`
 Label Description: Policy CHF action
 Example: continue, terminate, none
- Label: `policy_fh_subaction`
 Label Description: Policy CHF subaction
 Example: discard_traffic, local_fallback, retryserver_on_event, sendccrt_call_term, with_term_req, without_term_req, none
- Label: `interface_type`
 Label Description: Type of Interface communicate with PGW
 Example: pcf, pcrf
- Label: `sess_rel_cause`
 Label Description: Session release cause received from policy server in policy response or policy request
 Example: unspecified, ue_subscription, insuff_server_res, ip_can_sess_term, ue_ip_addr_rel
- Label: `termination_cause`
 Label Description: Termination cause sent in terminate request towards policy server

Example: logout, service_not_provided, bad_answer, administrative, link_broken, auth_expired, user_moved, session_timeout

PDU UE Sync Procedure Category

pdu_ue_sync_proc

Description: PDU UE Sync Procedure counter

Sample Query: 'pdu_ue_sync_proc{status="attempted"}'

Labels:

- Label: `status`

Label Description: call flow procedure status counter

Example: attempted, success, failures, suspend, resume, abort

SMF ALWAYS ON PDU SESSION Category

smf_always_on_session_stats

Description: Always On Pdu Session Statistics

Sample Query: 'smf_always_on_session_stats{status="pdusetup_req_alwayson_requested"}'

Labels:

- Label: `status`

Label Description: always on status statistics

Example: pdusetup_req_alwayson_requested, pdusetup_acc_alwayson_allowed, pdusetup_acc_alwayson_not_allowed, pdumod_req_alwayson_requested, pdumod_cmd_alwayson_allowed, pdumod_cmd_alwayson_not_allowed, pdumod_cmd_nw_init_alwayson_allowed, pdu_utwifit_to_nr_alwayson_requested, pdu_utwifit_to_nr_alwayson_allowed, pdu_utwifit_to_nr_alwayson_not_allowed

- Label: `rat_type`

Label Description: Type of the radio access associated with the request

Example: EUTRA, NR, WLAN, VIRTUAL, rat_type_unknown

- Label: `pdu_type`

Label Description: pdu connection type

Example: ipv4, ipv6, ipv4v6, unknown

- Label: `dnn`

Label Description: name of the dnn associated with the request

Example: Any string

- Label: `ssc_mode`

Label Description: Type of ssc mode associated with the request

Example: ssc_mode_1, ssc_mode_2, ssc_mode_3, ssc_mode_unknown

UDP Request Total Message Stats Category

smf_service_udp_req_msg_total

Description: Stats for Total UDP Request Messages

Sample Query: 'smf_service_udp_req_msg_total{status="attempted"}'

Labels:

- Label: `message_type`

Label Description: Type of UDP Message

Example: N4SessionEstablishmentReq

- Label: `upf_endpoint`

Label Description: UPF Endpoint

Example: IP String Value

- Label: `status`

Label Description: Status of UDP Message

Example: attempted, success, failures

- Label: `trans_type`

Label Description: Transmission type of UDP Message

Example: trans_type_origin, trans_type_reselected

- Label: `cause_code`

Label Description: Causecode of UDP Message

Example: Reserved, Request_Accepted, Request_Rejected_Unspecified, Session_Ctx_Not_Found, Mandatory_IE_Missing, Cond_IE_Missing, Invalid_Length, Mandatory_IE_Incorrect, Invalid_FW_Policy, Invalid_FTEID_Alloc_Opt, No_Established_PFCP_Assc, Rule_Creation_Mod_Failure, PFCP_Entity_In_Congestion, No_Resource_Available, Service_Not_Supported, System_failure, No_Response, Duplicate_Userplane_Id, OutOfRange_Userplane_Id

SLA Transaction Category

smf_sla_transaction_stats

Description: Transaction SLA stats

Sample Query: 'sum(smf_sla_transaction_stats) by (smf_sla_transaction_stats,smf_proc_type,status, message_type)'

Labels:

- Label: `smf_proc_type`

Label Description: Procedure Name

Example: PDU Session Release - SMF initiated, PDU 5G to 4G Handover, PDU Session Modify - PCF initiated, PDU UE Sync Procedure, PDU Idle Mode Entry - RAN initiated, PDN Session Modify - PCRF initiated

- Label: `status`

Label Description: gives status of the procedure

Example: Queued, Running, Aborted, Suspended, Invalid, Cleanedup, RequireSuspend, RequireCleanup, RequireAbort, Unknown

- Label: `message_type`

Label Description: gives the message type received during sla transaction

Example: IntSelfTxnSla

SMF DB Marshal Category

smf_db_marshal_stats

Description: SMF DB marshal stats

Sample Query: `'sum(smf_db_marshal_stats) by (module)'`

Labels:

- Label: `module`

Label Description: module type counter

Example: policy, charging, upserv, access, generic

SMF Procedure Total Time Statistics Category

smf_procedure_seconds

Description: Total number of seconds taken to complete the procedure

Sample Query: `'smf_procedure_seconds{smf_proc_status="Aborted"}'`

Labels:

- Label: `smf_proc_type`

Label Description: Procedure Name

Example: PDU Session Release - SMF initiated, PDU 5G to 4G Handover, PDU Session Modify - PCF initiated, PDU UE Sync Procedure, PDU Idle Mode Entry - RAN initiated, PDN Session Modify - PCRF initiated

- Label: `smf_proc_status`

Label Description: Procedure Status

Example: Queued, Running, Aborted, Suspended, Invalid, Cleanup, RequireSuspend, RequireCleanup, RequireAbort, ProcStatusComplete, Unknown

SMF Total Procedure Count Category

smf_procedure_total

Description: Total number of procedures executed

Sample Query: 'smf_procedure_total{smf_proc_status="Running"}'

Labels:

- Label: smf_proc_type

Label Description: Procedure Name

Example: PDU Session Release - SMF initiated, PDU 5G to 4G Handover, PDU Session Modify - PCF initiated, PDU UE Sync Procedure, PDU Idle Mode Entry - RAN initiated, PDN Session Modify - PCRF initiated

- Label: smf_proc_status

Label Description: Procedure Status

Example: Queued, Running, Aborted, Suspended, Invalid, Cleanup, RequireSuspend, RequireCleanup, RequireAbort, ProcStatusComplete, Unknown

SMF Total Timeout Procedure Count Category

smf_procedure_timeout

Description: Total number of procedures executed more than 10sec

Sample Query: 'smf_procedure_timeout{smf_proc_status="Running"}'

Labels:

- Label: smf_proc_type

Label Description: Procedure Name

Example: PDU Session Release - SMF initiated, PDU 5G to 4G Handover, PDU Session Modify - PCF initiated, PDU UE Sync Procedure, PDU Idle Mode Entry - RAN initiated, PDN Session Modify - PCRF initiated

- Label: smf_proc_status

Label Description: Procedure Status

Example: Queued, Running, Aborted, Suspended, Invalid, Cleanup, RequireSuspend, RequireCleanup, RequireAbort, ProcStatusComplete, Unknown

SMF Total Timedout Procedure Time Category

smf_procedure_timeout_seconds

Description: Total number of seconds taken by procedures executed more than 10sec

Sample Query: 'smf_procedure_timeout_seconds{smf_proc_status="Running"}'

Labels:

- Label: smf_proc_type

Label Description: Procedure Name

Example: PDU Session Release - SMF initiated, PDU 5G to 4G Handover, PDU Session Modify - PCF initiated, PDU UE Sync Procedure, PDU Idle Mode Entry - RAN initiated, PDN Session Modify - PCRF initiated

- Label: smf_proc_status

Label Description: Procedure Status

Example: Queued, Running, Aborted, Suspended, Invalid, Cleanup, RequireSuspend, RequireCleanup, RequireAbort, ProcStatusComplete, Unknown

SMF Procedure Collision Category

smf_procedure_collision

Description: Total number of procedures collided

Sample Query: 'sum(smf_procedure_collision) by (smf_current_procedure, smf_current_state, smf_new_procedure, smf_current_procedure_action)'

Labels:

- Label: smf_current_procedure

Label Description: Current Procedure Name

Example: PDU Session Release - SMF initiated, PDU 5G to 4G Handover, PDU Session Modify - PCF initiated, PDU UE Sync Procedure, PDU Idle Mode Entry - RAN initiated, PDN Session Modify - PCRF initiated

- Label: smf_current_state

Label Description: Current Procedure State

Example: DEDICATED BEARER: Await N7 Policy Update, PDN5G4GHO: Await UPF Modify Response, 4G RELEASE: Idle, MODIFY: Await N2 Update, RELEASE: Await PCF Delete, SETUP: Post UPF Modify

- Label: smf_new_procedure

Label Description: New Procedure Name

Example: PDU Session Release - SMF initiated, PDU 5G to 4G Handover, PDU Session Modify - PCF initiated, PDU UE Sync Procedure, PDU Idle Mode Entry - RAN initiated, PDN Session Modify - PCRF initiated

- Label: `smf_current_procedure_action`

Label Description: Current Procedure Action on Collision

Example: Ignore, Suspend, Resume, Abort, Cleanup, Continue, Ready, INVALID ACTION

SMF Start Procedure Statistics Category

smf_procedure_start

Description: Total number of procedures started

Sample Query: `'smf_procedure_start{smf_proc_type="PDN Connect"}'`

Labels:

- Label: `smf_proc_type`

Label Description: Procedure Name

Example: PDU Session Release - SMF initiated, PDU 5G to 4G Handover, PDU Session Modify - PCF initiated, PDU UE Sync Procedure, PDU Idle Mode Entry - RAN initiated, PDN Session Modify - PCRF initiated

SMF Stop Procedure Statistics Category

smf_procedure_stop

Description: Total number of procedures stopped

Sample Query: `'smf_procedure_stop{smf_proc_type="PDU Session Establishment"}'`

Labels:

- Label: `smf_proc_type`

Label Description: Procedure Name

Example: PDU Session Release - SMF initiated, PDU 5G to 4G Handover, PDU Session Modify - PCF initiated, PDU UE Sync Procedure, PDU Idle Mode Entry - RAN initiated, PDN Session Modify - PCRF initiated

- Label: `smf_proc_status`

Label Description: Procedure Status

Example: Queued, Running, Aborted, Suspended, Invalid, Cleanedup, RequireSuspend, RequireCleanup, RequireAbort, ProcStatusComplete

SMF Total Unhandled Event Statistics Category

smf_procedure_unhndl_event

Description: Total number of unhandled events per procedure type

Sample Query: 'smf_procedure_unhndl_event{smf_proc_type="PDU Session Release - SMF initiated"}'

Labels:

- Label: smf_proc_type

Label Description: Procedure Name

Example: PDU Session Release - SMF initiated, PDU 5G to 4G Handover, PDU Session Modify - PCF initiated, PDU UE Sync Procedure, PDU Idle Mode Entry - RAN initiated, PDN Session Modify - PCRF initiated

- Label: message_type

Label Description: Type of Request/Response Message associated with Unhandled Event

Example: N11SmContextUpdateSuccess, N11EbiAssignmentReq, N4HeartBeatFailure, S5CreateSessRsp, NLiSubscriberQueryReq, RadiusCoaDisconnectReq, N7SmPolicyUpdateSuccess

- Label: smf_current_state

Label Description: Current Procedure State

Example: DEDICATED BEARER: Await N7 Policy Update, PDN5G4GHO: Await UPF Modify Response, 4G RELEASE: Idle, MODIFY: Await N2 Update, RELEASE: Await PCF Delete, SETUP: Post UPF Modify

- Label: guard_timer

Label Description: This is a check for Guard Timeout. TRUE if Guard Timer has expired, else FALSE

Example: TRUE, FALSE

SMF Total Unhandled Transaction Statistics Category

smf_procedure_unhndl_trans

Description: Total number of unhandled transactions per procedure type

Sample Query: 'smf_procedure_unhndl_trans{message_type="RadiusCoaDisconnectReq"}'

Labels:

- Label: smf_proc_type

Label Description: Procedure Name

Example: PDU Session Release - SMF initiated, PDU 5G to 4G Handover, PDU Session Modify - PCF initiated, PDU UE Sync Procedure, PDU Idle Mode Entry - RAN initiated, PDN Session Modify - PCRF initiated

- Label: message_type

Label Description: Type of Request/Response Message associated with Unhandled Transaction

Example: N11SmContextUpdateSuccess, N11EbiAssignmentReq, N4HeartBeatFailure, S5CreateSessRsp, NLiSubscriberQueryReq, RadiusCoaDisconnectReq, N7SmPolicyUpdateSuccess

- Label: smf_current_state

Label Description: Current Procedure State

Example: DEDICATED BEARER: Await N7 Policy Update, PDN5G4GHO: Await UPF Modify Response, 4G RELEASE: Idle, MODIFY: Await N2 Update, RELEASE: Await PCF Delete, SETUP: Post UPF Modify

- Label: `guard_timer`

Label Description: This is a check for Guard Timeout. TRUE if Guard Timer has expired, else FALSE

Example: TRUE, FALSE

SMF Data Consistency Check Category

smf_datacheck_stats

Description: Total number of sessions checked for consistency

Sample Query: `'smf_datacheck_stats{rat_type="NR", status="failed"}'`

Labels:

- Label: `procedure_type`

Label Description: Procedure Name

Example: PDU Session Release - SMF initiated, PDU 5G to 4G Handover, PDU Session Modify - PCF initiated, PDU UE Sync Procedure, PDU Idle Mode Entry - RAN initiated, PDN Session Modify - PCRF initiated

- Label: `rat_type`

Label Description: Type of the radio access associated

Example: EUTRA, NR, WLAN, VIRTUAL, `rat_type_unknown`

- Label: `pdu_type`

Label Description: Type of PDU session

Example: ipv4, ipv6, ipv4v6, unknown

- Label: `status`

Label Description: Procedure status after data consistency check

Example: success, failed

- Label: `reason`

Label Description: Failure reason of data inconsistency

Example: `invalid_n4_data_in_txn_start`, `invalid_n4_data_in_txn_end`, `invalid_n7_data_in_txn_start`, `invalid_n7_data_in_txn_end`, `invalid_n40_data_in_txn_start`, `invalid_n40_data_in_txn_end`

SMF PCSCF Server Stats Category

smf_pcscf_server_stats

Description: Stats for SMF PCSCF Server

Sample Query: 'smf_pcscf_server_stats{PrimaryIPv4="1.2.3.4"}'

Labels:

- Label: PrimaryIPv4
Label Description: Primary PCSCF IPV4 address
Example: 1.2.3.4
- Label: SecondaryIPv4
Label Description: Secondary PCSCF IPV4 address
Example: 1.2.3.4
- Label: TertiaryIPv4
Label Description: Tertiary PCSCF IPV4 address
Example: 1.2.3.4
- Label: PrimaryIPv6
Label Description: Primary PCSCF IPV6 address
Example: IPv6 IP
- Label: SecondaryIPv6
Label Description: Secondary PCSCF IPV6 address
Example: IPv6 IP
- Label: TertiaryIPv6
Label Description: Tertiary PCSCF IPV6 address
Example: IPv6 IP
- Label: ResolvedFrom
Label Description: Info used to resolve PCSCF Address
Example: DNS, LocalConfig

Incoming Message Throttling Statistics Category

smf_inc_msg_throttling_stats

Description: Stats of throttled incoming messages

Sample Query: 'smf_inc_msg_throttling_stats{message_type="S5S8CreateSessReq"}'

Labels:

- Label: interface
Label Description: Interface Type
Example: S5, S8, S2B
- Label: message_type

Label Description: Message type corresponding to given interface

Example: S5S8CreateSessReq, S5S8DeleteSessReq, S5S8ModifyBearerReq, S5S8ModifyBearerCmd, S5S8BearerResourceCmd, S5S8DeleteBearerCmd

- Label: Cause

Label Description: Cause of Message Throttling

Example: EGTP_CAUSE_GTPC_ENTITY_CONGESTION

Gy Online charging reporting reason statistics Category

ocs_reporting_reason_stats

Description: Statistics for reporting reason to OCS

Sample Query: 'sum (ocs_reporting_reason_stats{Reporting_Reason="THRESHOLD"}) '

Labels:

- Label: rating_group

Label Description: Rating Group for which usage is being reported

Example: Any string

- Label: service_identifier

Label Description: Service Identifier for which usage is being reported

Example: Any string

- Label: Reporting_Reason

Label Description: Type of 3GPP reporting reason from OCS

Example: THRESHOLD, QHT, FINAL, QUOTA_EXHAUSTED, VALIDITY_TIME, OTHER_QUOTA_TYPE, RATING_CONDITION_CHANGE, FORCED_REAUTHORISATION, POOL_EXHAUSTED

Gy Online charging destination host change statistics Category

ocs_dest_host_change_stats

Description: Statistics for charging destination host change

Sample Query: 'sum (ocs_dest_host_change_stats) '

Labels:

Charging final unit indication statistics Category

chf_recieved_fui_stats

Description: Statistics for final unit indication with final unit action

Sample Query: 'sum (chf_recieved_fui_stats{interface_type="Gy"}) '

Labels:

- Label: `chf_type`
Label Description: Type of CHF with which message is exchanged
Example: online, offline
- Label: `interface_type`
Label Description: Type of Interface communicate with PGW
Example: N40, Gy
- Label: `fua_type`
Label Description: Type of final unit action
Example: FinalUnitActionType_TERMINATE, FinalUnitActionType_REDIRECT, FinalUnitActionType_RESTRICT_ACCESS

Gz Offline CDR message statistics Category

ofcs_cdr_message_stats

Description: Statistics for CDR message with record closure reason to OFCS

Sample Query: 'sum (ofcs_cdr_message_stats{record_closure_reason="normalRelease"}) '

Labels:

- Label: `gtpb_profile`
Label Description: gtpb profile name used for bearer
Example: Any string
- Label: `RuleBase`
Label Description: RuleBase name used for bearer
Example: Any string
- Label: `record_closure_reason`
Label Description: CDR closure reason
Example: normalRelease, abnormalRelease, cAMELInitCallRelease, volumeLimit, timeLimit, servingNodeChange, maxChangeCond, managementIntervention, intraSGSNIntersystemChange, rATChange, mSTimeZoneChange, sGSNPLMNIDChange
- Label: `dnn`
Label Description: DNN for which the flow is created
Example: cisco.com
- Label: `TriggerType`
Label Description: Trigger reason

Example: GZ_SECONDARY_RAT_USAGE_LIMIT_REACHED

Gz Offline SDF Containers statistics Category

ofcs_sdf_container_stats

Description: Statistics for SDF Container with service condition change to OFCS

Sample Query: 'sum (ofcs_sdf_container_stats{service_condition_change="PdpContextRelease"}) '

Labels:

- Label: `service_condition_change`

Label Description: Service condition Change for SDF container

Example: QoSChange, SgsnChange, SgsnPlmnIdChange, TariffTimeSwitch, PdpContextRelease, RatChange, ServiceIdleOut, ConfigurationChange, ServiceStop, DccaTimeThresholdReached, DccaVolumeThresholdReached, DccaServiceSpecificUnitThresholdReached, DccaTimeExhausted, DccaVolumeExhausted, DccaValidityTimeout, DccaReauthorisationRequest, DccaContinueOngoingSession, DccaRetryAndTerminateOngoingSession, DccaTerminateOngoingSession, CgiSaiChange, RaiChange, DccaServiceSpecificUnitExhausted, RecordClosure, TimeLimit, VolumeLimit, ServiceSpecificUnitLimit, EnvelopeClosure, EcgiChange, TaiChange, UserLocationChange

- Label: `dnn`

Label Description: DNN for which the flow is created

Example: cisco.com

Gz Offline CDR drop statistics Category

ofcs_cdr_drop_stats

Description: Statistics for CDR drop with trigger reason

Sample Query: 'sum (ofcs_cdr_drop_stats{TriggerType="final-cdr"}) '

Labels:

- Label: `procedure_type`

Label Description: The procedure name associated with a call flow procedure

Example: Any string

- Label: `TriggerType`

Label Description: Trigger reason

Example: final-cdr, external-trigger-cdr, internal-trigger-cdr

- Label: `dnn`

Label Description: DNN for which the flow is created

Example: cisco.com

Policy destination host change statistics Category

policy_pcrf_dest_host_change

Description: Statistics for Policy destination host change

Sample Query: 'sum (policy_pcrf_dest_host_change{gr_instance_id="1"}) '

Labels:

- Label: `gr_instance_id`
Label Description: GR instance ID
Example: Any string
- Label: `interface_type`
Label Description: Type of Interface communicate with PGW
Example: pcf, pcrf

UDP RPC message statistics Category

udp_rpc_msg_stats

Description: Statistics for UDP RPC

Sample Query: 'sum (udp_rpc_msg_stats{gr_instance_id="1"}) '

Labels:

- Label: `msgtype`
Label Description: message Type
Example: MessageNone, PfcPProxyMsg, UdpProxyMsg, UnknownMsg
- Label: `direction`
Label Description: Direction of UDP RPC message
Example: inbound, outbound
- Label: `status`
Label Description: status of message processing
Example: success, failures
- Label: `transport_type`
Label Description: Transport type of message
Example: original, asyncmessage, retransmitted,
- Label: `gr_instance_id`
Label Description: GR instance ID
Example: Any string

- Label: `interface_type`

Label Description: Type of Interface communicate with PGW

Example: `pcf`, `pcrf`

Policy control ADC pcc rule statistics Category

`policy_adc_total`

Description: PCC Rule total statistics for ADC

Sample Query: `'sum (policy_adc_total{app_id="abc"})'`

Labels:

- Label: `app_id`

Label Description: ADC Application ID for pcc rule

Example: Any string

- Label: `mute`

Label Description: Mute for ADC rule

Example: `true`, `false`

- Label: `operation`

Label Description: Operation performed on the ADC pcc rule

Example: `install`, `modify`, `remove`

- Label: `event`

Label Description: Event associated with the operation performed on the ADC pcc rule

Example: `attempted`, `success`, `failure`, `abort`

- Label: `gr_instance_id`

Label Description: GR instance ID

Example: Any string

- Label: `interface_type`

Label Description: Type of Interface communicate with PGW

Example: `pcf`, `pcrf`

SMF Service gtpc cache statistics Category

`smf_service_gtpc_cache_stats`

Description: SMF Service gtpc cache counters

Sample Query: `'smf_service_gtpc_cache_stats{gr_instance_id="1"}'`

Labels:

- Label: `smf_proc_type`

Label Description: The procedure type associated with an call flow procedure

Example: `eps_fb_ded_brr`, `ue_req_ded_brr_mod`, `udm_req_ded_brr_mod`, `smf_req_ded_brr_del`, `mme_req_ded_brr_del`, `mme_req_ded_brr_mod`, `mme_req_ded_brr_del`, `pcrf_req_ded_brr_create`, `pcf_req_ded_brr_create`, `pcrf_req_ded_brr_delete`, `pcf_req_ded_brr_delete`, `pcrf_req_ded_brr_mod`, `pcf_req_ded_brr_mod`, `ProcessNoStateMBR`, `suspend_acknowledgement`

- Label: `message_type`

Label Description: GTPC Message Type

Example: `CreateBearerReq`, `UpdateBearerReq`, `DeleteBearerReq`, `ModifyBearerResp`, `DeleteSessionResp`, `ModifyBearerResp`, `CreateSessionResp`, `SuspendAck`,

- Label: `gtpc_cache_operation`

Label Description: GTPC cache operation

Example: `add`, `delete`

- Label: `gr_instance_id`

Label Description: GR instance ID

Example: Any string

udp-proxy Metrics Reference

UDP-Proxy BGP Routes Count Category

upd_proxy_bgp_routes_count

Description: UDP Proxy BGP routes added count

Sample Query: `'upd_proxy_bgp_routes_count{service_name="udp-proxy", status="success"}'`

Labels:

- Label: `status`

Label Description: Status of message while sending or receiving

Example: `success`, `failed`

UDP-Proxy messages Category

udp_proxy_msg_total

Description: UDP Proxy message counters being recieved or sent

Sample Query: 'udp_proxy_msg_total{message_name="radius_request", message_direction="inbound", status="success"}'

Labels:

- Label: `message_name`

Label Description: UDP messages coming via udp-proxy service

Example: radius_request, radius_response, heartbeat_request, heartbeat_response

- Label: `message_direction`

Label Description: Message being sent or being received

Example: inbound, outbound

- Label: `status`

Label Description: Status of message while sending or receiving

Example: success, failed