



Sample UPF Configuration

- [Sample Configuration, on page 1](#)

Sample Configuration

The following is only a sample configuration file provided solely for your reference. You must create and modify your own configuration file according to the specific needs of your deployment.

```
----- snip -----
  active-charging service acs
    bandwidth-policy BWP
      flow limit-for-bandwidth id 1 group-id 2
      flow limit-for-bandwidth id 2 group-id 3
      flow limit-for-bandwidth id 100 group-id 100
      group-id 2 direction uplink peak-data-rate 256000 peak-burst-size 1000 violate-action
discard
      group-id 2 direction downlink peak-data-rate 200000 peak-burst-size 1000 violate-action
discard
      group-id 3 direction downlink peak-data-rate 256000 peak-burst-size 1000 violate-action
discard
      group-id 4 direction uplink peak-data-rate 300000 peak-burst-size 1200 violate-action
lower-ip-precedence
      group-id 100 direction downlink peak-data-rate-kbps 4294967295 peak-burst-size
4294967295 violate-action discard

  ruledef L3_SERVER
    ip server-ip-address = 2.2.2.2/32
    tcp either-port = 80
  #exit
  ruledef L4_PORT
    tcp either-port = 80
    udp either-port = 80
    multi-line-or all-lines
  #exit
  ruledef L7_HTTP
    http host contains 2.2.2.2
    multi-line-or all-lines
  #exit
  ruledef http-pkts
    http any-match = TRUE
  #exit
  ruledef http-port
    tcp either-port = 80
    rule-application routing
  #exit
```

```

ruledef ip-any-rule
  ip any-match = TRUE
#exit
urr-list urrs
  rating-group 10 urr-id 5
#exit
charging-action starent
  content-id 10
  billing-action egcdr
#exit
rulebase default
#exit
credit-control group default
  pending-traffic-treatment noquota buffer
  pending-traffic-treatment quota-exhausted pass
  usage-reporting quotas-to-report based-on-grant

rulebase starent
  billing-records egcdr
  dynamic-rule order first-if-tied
  action priority 5 ruledef http-pkts charging-action standard
  action priority 10 ruledef L7_HTTP charging-action starent
  action priority 20 ruledef L4_PORT charging-action starent
  action priority 100 ruledef L3_SERVER charging-action starent
  action priority 10000 ruledef ip-any-rule charging-action starent
  route priority 1 ruledef http-port analyzer http
  egcdr threshold interval 1000
  bandwidth default-policy BWP
#exit
traffic-optimization-policy default
#exit
#exit
context ingress
  interface N3_interface
    ip address 1.1.2.1 1.1.2.2
    ipv6 address abc0:0:0:cb::1/64 secondary
  #exit
  interface N3_interface_LOGICAL loopback
    ip address 1.1.2.1 1.1.2.2
  #exit
  interface N3_interface_LOGICAL2 loopback
    ip address 1.1.2.1 1.1.2.2
  #exit
  interface N4U_interface
    ip address 1.1.2.1 1.1.2.2
    ipv6 address abc0:0:0:cd::1/64 secondary
    ipv6 address abc0:0:0:ca::1/64 secondary
  #exit
  interface N4U_interface_LOGICAL loopback
    ip address 1.1.2.1 1.1.2.2
  #exit
  interface N4_interface
    ip address 1.1.2.1 1.1.2.2
    ipv6 address abc0:0:0:cc::1/64 secondary
  #exit
  interface N4_interface_LOGICAL loopback
    ip address 1.1.2.1 1.1.2.2
  #exit
  subscriber default
  exit
  aaa group default
  #exit
  gtpv group default
  #exit

```

```

gtpu-service N3-GNB1
  bind ipv4-address 1.1.1.1
exit
gtpu-service N3-GNB2
  bind ipv4-address 1.1.2.1
exit
gtpu-service control_gtpu
  bind ipv4-address 1.1.2.1
exit
sx-service N4
  instance-type userplane
  bind ipv4-address 1.1.2.1
  sx-protocol heartbeat interval 3600
  sx-protocol heartbeat max-retransmissions 1
  sx-protocol association reattempt-timeout 30
exit
user-plane-service user-plane-service
  associate gtpu-service N3-GNB1 pf-ingress
  associate gtpu-service control_gtpu cp-tunnel
  associate sx-service N4
  associate fast-path service
  associate control-plane-group default
  load-control capacity 900
exit
user-plane-service user-plane-service1
exit
ip route 1.1.2.1 1.1.2.2 1.1.2.3 N4_interface
ip route 1.1.2.1 1.1.2.2 1.1.2.3 N4_interface
ip route 1.1.2.1 1.1.2.2 1.1.2.3 N3_interface
ip route 1.1.2.1 1.1.2.2 1.1.2.3 N3_interface
ip route 1.1.2.1 1.1.2.2 1.1.2.3 N4_interface
ip route 1.1.2.1 1.1.2.2 1.1.2.3 N3_interface
ip route 1.1.2.1 1.1.2.2 1.1.2.3 N4_interface
ip route 1.1.2.1 1.1.2.2 1.1.2.3 N3_interface
#exit
context egress
  interface N6_interface
    ip address 1.1.2.1 1.1.2.2
    ipv6 address abc0:0:0:cf::1/64 secondary
  #exit
  subscriber default
  exit
  apn starent.com
    pdp-type ipv4 ipv6
    selection-mode subscribed sent-by-ms chosen-by-sgsn
    gtp group default accounting-context egress
    ip context-name egress
    active-charging rulebase starent
  exit
  aaa group default
  #exit
  gtp group default
    gtp attribute local-record-sequence-number
    gtp dictionary custom24
    gtp egcdr service-data-flow threshold interval 60
    gtp egcdr service-data-flow threshold volume downlink 13000
    gtp egcdr service-data-flow threshold volume uplink 17000
    gtp egcdr service-data-flow threshold volume total 22222
  #exit
  ipv6 route 2:2:2:2::/64 next-hop abc0::ab:1c:2ff:def9:1ad interface N6_interface
  ip route 1.1.2.1 1.1.2.2 1.1.2.3 N6_interface
  ip route 1.1.2.1 1.1.2.2 1.1.2.3 N6_interface
  ipv6 route 2:2:2:2::/64 next-hop abc0::ab:1c:2ff:def9:1ab interface N6_interface
  ip route 1.1.2.1 1.1.2.2 1.1.2.3 N6_interface

```

```
#exit
control-plane-group default
  sx-association initiated-by-cp
  peer-node-id ipv4-address 1.1.1.1 interface n4
#exit
user-plane-group default
#exit
port ethernet 1/11
  no shutdown
  vlan 203
    no shutdown
    bind interface N4U_interface ingress
  #exit
  vlan 204
    no shutdown
    bind interface N4_interface ingress
  #exit
  vlan 205
    no shutdown
    bind interface N3_interface ingress
  #exit
  vlan 206
    no shutdown
  #exit
  vlan 207
    no shutdown
    bind interface N6_interface egress
  #exit
#exit
end
```