

Contenido

[Pregunta](#)

[Respuesta](#)

[Discusiones relacionadas de la comunidad del soporte de Cisco](#)

Pregunta

Cómo determinar la tarifa de la falla actual para una alarma en cualquier momento después del activador inicial. ¿La tasa de fallas inicial puede ser más obvio encontrar, pero una encontraría las horas actuales de la tarifa del fall posiblemente más adelante?

Respuesta

Mientras que el SNMP trap inicial, el registro y la alarma siguen la tasa de fallas inicial de un umbral monitoreado, puede no ser obvio cómo conseguir la tarifa actual del fall. En la parte inferior del “umbral de la demostración”, los comandos informa el estatus de todas las alarmas en lo que respecta a la tarifa actual del fall en el intervalo de sondeo más reciente.

```
[local]PDSN> show thresholdFriday June 12 04:39:32 UTC 2015Outstanding alarms:      Threshold
Name:      aaa-acct-failure-rate      Alarm Source:      System Last Measured: 77% Raise Time:
2015-Jun-11+22:15:05[local]PDSN> show threshFriday June 12 05:34:04 UTC 2015Outstanding alarms:
Threshold Name:      aaa-acct-failure-rateAlarm Source: System Last Measured: 65%      Raise
Time:      2015-Jun-11+22:15:05[local]PDSN> show threshFriday June 12 06:06:07 UTC
2015Outstanding alarms:      Threshold Name:      aaa-acct-failure-rate      Alarm Source:
SystemLast Measured: 61%      Raise Time:      2015-Jun-11+22:15:05[local]PDSN> show alarm
outstanding verboseFriday June 12 04:41:28 UTC 2015Severity Object      Timestamp
Alarm ID-----
Details-----
Chassis      Thursday June 11 22:15:05 U      5770524519230406656 <28:aaa-acct-failure-
rate> has reached or exceeded the configured threshold <25%>, the measured value is <32%>. It is
detected at <System>.2015-Jun-11+22:15:05.418 [alarmctrl 65201 info] [8/0/5185 <evlogd:0>
alarmctrl.c:192] [software internal system critical-info syslog] Alarm condition: id
5015057a08690000 (Minor): <28:aaa-acct-failure-rate> has reached or exceeded the configured
threshold <25%>, the measured value is <32%>. It is detected at <System>.Thu Jun 11 22:15:05
2015 Internal trap notification 222 (ThreshAAAacctFailRate) threshold 25% measured value 32%
```

Claros del problema:

```
2015-Jun-12+07:15:05.210 [alarmctrl 65200 info] [8/0/5185 <evlogd:0> alarmctrl.c:285] [software
internal system critical-info syslog] Alarm cleared: id 5015057a08690000: <28:aaa-acct-failure-
rate> has reached or exceeded the configured threshold <25%>, the measured value is <32%>. It is
detected at <System>.Fri Jun 12 07:15:05 2015 Internal trap notification 223
(ThreshClearAAAacctFailRate) threshold 20%measured value 0%[local]PDSN> show threshold Friday
June 12 13:45:26 UTC 2015...No outstanding alarm
```