

# Émettez dans l'affichage de données de NetFlow PI3.0- pour les différents sites

## Contenu

[Introduction](#)

[Informations générales](#)

[Procédure](#)

## Introduction

Ce document décrit comment surmonter la question des données de NetFlow qui ne sont pas affichées pour le site individuel mais pour les périphériques non affectés.

## Informations générales

Si des règles ne sont pas déclarées correctement à l'**association de services > de visibilité et de contrôle > de point final d'application** puis vous faites face à cette question.

Après la déclaration de la même chose nous pouvons voir le trafic classifié dans le site correspondant.

Pour des données de NetFlow non affichées pour des sites.

[http://www.cisco.com/c/en/us/td/docs/net\\_mgmt/prime/infrastructure/3-0/administrator/guide/PIAdminBook/metrics.html](http://www.cisco.com/c/en/us/td/docs/net_mgmt/prime/infrastructure/3-0/administrator/guide/PIAdminBook/metrics.html)

## Procédure

Suivez la procédure suivant les indications de l'image :

**Step 1** Create a site structure for your organization and assign your principal routers to the appropriate sites:

- a. Choose **Maps > Site Maps**.
- b. Add one or more campuses, buildings, and floors (for details, see "Working With Maps").

**Step 2** Associate your sites with authorized data sources:

- a. Choose **Services > Application Visibility & Control > Data Deduplication**.
- b. Click **Enable Data Deduplication**, then click **Apply**. You can then assign authoritative sources for ART, Traffic Analysis and Voice/Video data (see "Enabling Data Deduplication").

**Step 3** Associate your sites with endpoint subnets:

- a. Choose **Services > Application Visibility & Control > Endpoint Association**.
- b. Associate subnets with your sites (see "Associating Endpoints With Sites").

If you fail to do this, by default the data collected for these endpoints will have their sites set to "Unassigned".

**Step 4** Configure your compatible routers for Cisco Medianet Performance Monitor (see "Configuring Mediatrace on Routers and Switches").

**Step 5** Configure your routers for Mediatrace and WSMA (see "Using Mediatrace").

---