

Utiliser la fonction switchDeviceType de BroadWorks

Table des matières

[Introduction](#)

[Conditions préalables](#)

[Exigences](#)

[Composants utilisés](#)

[Informations générales](#)

[Options d'utilisation](#)

[BWCLI](#)

[Commande OCI-P](#)

[Schéma XML](#)

[Exemple de TP](#)

[Exemple BWCLI](#)

[Exemple de journal](#)

[Informations connexes](#)

Introduction

Ce document décrit l'utilisation de la fonctionnalité switchDeviceType de BroadWorks.

Conditions préalables

Exigences

Aucune exigence spécifique n'est associée à ce document.

Composants utilisés

Ce document n'est pas limité à des versions de matériel et de logiciel spécifiques.

The information in this document was created from the devices in a specific lab environment. All of the devices used in this document started with a cleared (default) configuration. Si votre réseau est en ligne, assurez-vous de bien comprendre l'incidence possible des commandes.

Informations générales

À partir de BroadWorks, version 23.0 et ultérieure, un mécanisme a été introduit pour passer d'un type de profil de périphérique à un autre.

Options d'utilisation

Les `switchDeviceType` peut être exécutée à partir de l'interface BWCLI ou de la commande `oci-p, SystemDeviceManagementSwitchDeviceTypeDeviceRequest`.

BWCLI

```
AS_CLI/System/Device/IpDeviceMgmt> help switchDeviceType
```

This command is used to switch device profiles from one device type to another.

Parameters description:

`attribute` : The name of the attribute that scopes the command.

`system` : This parameter specifies the switch command is issued at the system level.

`fromDeviceType` : This parameter specifies the original device type.

`toDeviceType` : This parameter specifies the destination device type.

`serviceProvider` : This parameter specifies the switch command is issued at the service provider level.

`svcProviderId` : This parameter specifies the ID of the service provider.

`group` : This parameter specifies the switch command is issued at the group level.

`groupId` : This parameter specifies the valid group within the service provider.

`systemDeviceProfile` : This parameter specifies the switch command is issued for a single device profile at the system level.

`deviceName` : This parameter specifies the name of the device profile.

`svcProvDeviceProfile`: This parameter specifies the switch command is issued for a single device profile at the service provider level.

`groupDeviceProfile` : This parameter specifies the switch command is issued for a single device profile at the group level.

```
=====
switchDeviceType
<attribute>, Choice = {system, serviceProvider, group, systemDeviceProfile,
svcProvDeviceProfile, groupDeviceProfile}
system:
<fromDeviceType>, String {1 to 40 characters}
<toDeviceType>, String {1 to 40 characters}
serviceProvider:
<svcProviderId>, String {1 to 30 characters}
<fromDeviceType>, String {1 to 40 characters}
<toDeviceType>, String {1 to 40 characters}
group:
<svcProviderId>, String {1 to 30 characters}
<groupId>, String {1 to 30 characters}
<fromDeviceType>, String {1 to 40 characters}
<toDeviceType>, String {1 to 40 characters}
systemDeviceProfile:
<deviceName>, String {1 to 40 characters}
<toDeviceType>, String {1 to 40 characters}
svcProvDeviceProfile:
<svcProviderId>, String {1 to 30 characters}
<deviceName>, String {1 to 40 characters}
<toDeviceType>, String {1 to 40 characters}
groupDeviceProfile:
<svcProviderId>, String {1 to 30 characters}
<groupId>, String {1 to 30 characters}
<deviceName>, String {1 to 40 characters}
<toDeviceType>, String {1 to 40 characters}
```

Commande OCI-P

```
<?xml version="1.0" encoding="ISO-8859-1"?>
<BroadsoftDocument protocol="OCI" xmlns="C" xmlns:xsi="http://www.w3.org/2001/XMLSchema-
```

```

instance">
<sessionId xmlns="">SESSIONID</sessionId>
<command xsi:type="SystemDeviceManagementSwitchDeviceTypeDeviceRequest" xmlns="">
<svcProviderId>YOUR ENT/SP</svcProviderId>
<groupId>YOUR GROUP</groupId>
<deviceName>ORIGINAL DEVICE TYPE</deviceName>
<toDeviceType>NEW DEVICE TYPE</toDeviceType>
</command>
</BroadsoftDocument>

```

Schéma XML

```

<xs:complexType name="SystemDeviceManagementSwitchDeviceTypeDeviceRequest">
<xs:annotation>
<xs:appinfo>
<bwAppInfo bwtag="_1843b06e76464254bf146a91622df7b4"/>
<asDataModeSupported>true</asDataModeSupported>
<amplifyDataModeSupported>true</amplifyDataModeSupported>
<xsDataModeSupported>true</xsDataModeSupported>
</xs:appinfo>
<xs:documentation>
Switch the device type for a specified device.
To switch a system level device profile, serviceProviderId and groupId should not be present.
To switch a service provider level device profile, only serviceProviderId should be specified.
To switch a group level device profile, serviceProviderId and groupId should specified.
The response is either a SuccessResponse or an ErrorResponse.
</xs:documentation>
</xs:annotation>
<xs:complexContent>
<xs:extension base="core:OCIRequest">
<xs:sequence>
<xs:choice minOccurs="0">
<xs:element name="serviceProviderId" type="ServiceProviderId"/>
<xs:sequence>
<xs:element name="svcProviderId" type="ServiceProviderId"/>
<xs:element name="groupId" type="GroupId"/>
</xs:sequence>
</xs:choice>
<xs:element name="deviceName" type="AccessDeviceName"/>
<xs:element name="toDeviceType" type="AccessDeviceType"/>
</xs:sequence>
</xs:extension>
</xs:complexContent>
</xs:complexType>

```

Exemple de TP

Exemple BWCLI

Dans cet exemple, vous pouvez basculer un groupDeviceProfile du type de périphérique Poly_VX_D230 vers le type de périphérique Cisco-CP-78xx-88xx-68xx-3PCC.

- Ajoutez un profil de périphérique de groupe Poly_VX_D230_Switch et attribuez le périphérique Poly_VX_D230 :

```

AS_CLI/System/Device/IpDeviceMgmt> add pws_ent pws_grp Poly_VVX_D230_Switch Poly_VVX_D230
macAddress 678678678678

```

- Effectuez le basculement du profil Poly_VX_D230_Switch vers Cisco-CP-78xx-88xx-68xx-

3PCC :

```
AS_CLI/System/Device/IpDeviceMgmt> switchDeviceType groupDeviceProfile pws_ent pws_grp
Poly_VVX_D230_Switch Cisco-CP-78xx-88xx-68xx-3PCC
...Done
[Request for switch is being processed; Rebuild triggered for device type: Cisco-CP-78xx-88xx-
68xx-3PCC,
please refer to DMEventQueues for completion status.]
```

Exemple de journal

Ceci est un exemple de journal pour ce type de requête vu depuis le PSLog.

```
2022.05.26 09:34:57:686 EDT | Info | OCI-P | BCCT Worker #0
```

```
Received the following request from: 127.0.0.1:56212
<?xml version="1.0" encoding="ISO-8859-1"?>
<BroadsoftDocument protocol="OCI" xmlns="C" xmlns:xsi="http://www.w3.org/2001/XMLSchema-
instance">
<sessionId xmlns="">16535720065220.14787900206648874</sessionId>
<command xsi:type="SystemDeviceManagementSwitchDeviceTypeDeviceRequest" xmlns="">
<svcProviderId>pws_ent</svcProviderId>
<groupId>pws_grp</groupId>
<deviceName>Poly_VVX_D230_Switch</deviceName>
<toDeviceType>Cisco-CP-78xx-88xx-68xx-3PCC</toDeviceType>
</command>
</BroadsoftDocument>
```

```
2022.05.26 09:34:57:711 EDT | FieldDebug | Generic | BCCT Worker #0
```

```
OCI Transaction
com.broadsoft.oci.transactions.system.SystemDeviceManagementSwitchDeviceTypeDeviceTransaction
write5193 executed.
User: Default Administrator (admin) Authorization Level: System
Start Time: 2022.05.26 09:34:57:687 EDT
End Time: 2022.05.26 09:34:57:711 EDT
Duration: 24 ms
```

```
2022.05.26 09:34:57:711 EDT | Info | OCI-P | BCCT Worker #0 | admin
```

```
TO 127.0.0.1:56212
<?xml version="1.0" encoding="ISO-8859-1"?>
<BroadsoftDocument protocol="OCI" xmlns="C" xmlns:xsi="http://www.w3.org/2001/XMLSchema-
instance">
<sessionId xmlns="">16535720065220.14787900206648874</sessionId>
<command echo="" xsi:type="c:SuccessResponse" xmlns:c="C" xmlns=""/>
</BroadsoftDocument>
```

Informations connexes

- [Amélioration Personnalisation Type Profil Périphérique-AS-FD](#)
- [Assistance technique et téléchargeements Cisco](#)

À propos de cette traduction

Cisco a traduit ce document en traduction automatisée vérifiée par une personne dans le cadre d'un service mondial permettant à nos utilisateurs d'obtenir le contenu d'assistance dans leur propre langue.

Il convient cependant de noter que même la meilleure traduction automatisée ne sera pas aussi précise que celle fournie par un traducteur professionnel.