

Dépannez l'équipement représenté de NonCisco sur PCA 11

Contenu

[Introduction](#)

[Conditions préalables](#)

[Conditions requises](#)

[Composants utilisés](#)

[Problème](#)

[Solution](#)

[Problème](#)

[Solution](#)

Introduction

Ce document décrit comment réparer les questions principales de l'assurance de Collaboration d'inventaire (PCA) tout en ajoutant Cisco Unified Communications Manager (CUCM) et le gestionnaire principal de permis (PLM). L'inventaire affiche le périphérique en tant que non Cisco tandis que c'est une application CUCM ou un PLM.

Contribué par Michal Myszor et Andrea Cingolani, ingénieurs TAC Cisco.

Conditions préalables

Conditions requises

Aucune spécification déterminée n'est requise pour ce document.

[Composants utilisés](#)

Ce document s'applique à :

- Mode de fournisseur de services gérés PCA 11.X (FSG)
- Exécution hébergée de médiation de Collaboration (HCM-F) 10.6.X
- Cisco Unified Communications Manager (CUCM) 11.5.X
- PLM autonome 11.5.X

Les informations contenues dans ce document ont été créées à partir des périphériques d'un environnement de laboratoire spécifique. Tous les périphériques utilisés dans ce document ont démarré avec une configuration effacée (par défaut). Si votre réseau est opérationnel, assurez-vous que vous comprenez l'effet potentiel de toute commande.

Problème


Le périphérique CUCM est affiché en tant que non Cisco sur l'inventaire paginé ou dans l'affichage périphériques quand le PCA ne peut pas déterminer le type de périphérique basé sur des requêtes SNMP.

Expositions d'inventaire PCA :

cucm-alfa.alfa.com NonCisco RTAC ciscoUCVir... 10.48.55.29 10.48.55.29

Même est présenté sur la vue du périphérique 360 :

Device 360° View



CUCM-ALFA

10.48.55.29 / 00:50:56:9e:01:9e

NONCISCO

Not Configured / NAT Disabled
94 days, 8 hours, 52 minutes

[View Details](#)

Private IP Address **10.48.55.29**
Model **ciscoUCVirtualMachine**
Customer **RTAC**

Expositions de log d'AccessLevelDiscovery :

```
12-Sep-2017|15:25:43.003|DEBUG|AccessLevelDiscovery|pool-4-thread-4|work() : Starting Access
Level Discovery for device 10.48.55.29
12-Sep-2017|15:25:43.003|DEBUG|AccessLevelDiscovery|pool-4-thread-
4|com.cisco.nm.emms.inv.AbstractDiscoveryStage|updateStatusReason|41| Later Error Index for
device 10.48.55.29 is 1022 Old Message
12-Sep-2017|15:25:43.003|DEBUG|AccessLevelDiscovery|pool-4-thread-
4|com.cisco.nm.emms.inv.AbstractDiscoveryStage|updateStatusReason|94| Error Index for device
10.48.55.29 is 1022 New Message Discovery in progress.
12-Sep-2017|15:25:43.003|DEBUG|AccessLevelDiscovery|pool-4-thread-4|probeAccessLevel() : Started
for device 10.48.55.29
12-Sep-2017|15:25:43.003|DEBUG|AccessLevelDiscovery|pool-4-thread-4|probeAccessLevel() :
Matching credentials for 10.48.55.29
12-Sep-2017|15:25:43.003|ERROR|AccessLevelDiscovery|pool-4-thread-
4|com.cisco.nm.emms.inv.access.core.DeviceAccessLevelDiscovery$MyWorkItem|getFinalDeviceCredenti
alsList|709| Ignoring the DEFAULT profile as the snmp community string is not provided.
12-Sep-2017|15:25:43.005|DEBUG|AccessLevelDiscovery|pool-4-thread-
4|com.cisco.nm.emms.inv.access.core.DeviceAccessLevelDiscovery$MyWorkItem|getFinalDeviceCredenti
alsList|760| probeAccessLevel() : CmDevice Credentials List size : 0
12-Sep-2017|15:25:43.006|DEBUG|AccessLevelDiscovery|pool-4-thread-
4|com.cisco.nm.emms.inv.access.core.DeviceAccessLevelDiscovery$MyWorkItem|probeAccessLevel|231|
Before classificationOfDeviceType, device credential id is 6429244
12-Sep-2017|15:25:43.007|DEBUG|AccessLevelDiscovery|pool-4-thread-4|probeAccessLevel() :
isDeviceTypeReDiscoveryEnabled flag has set to true or mode is MSP - 10.48.55.29 device type
is re-initilize to Unknown.
12-Sep-2017|15:25:43.007|DEBUG|AccessLevelDiscovery|pool-4-thread-4|probeAccessLevel() : *****
CmDevice Type Classification - STARTS [ 10.48.55.29 ]*****
12-Sep-2017|15:25:43.007|DEBUG|AccessLevelDiscovery|pool-4-thread-4|probeAccessLevel() :
DeviceType is null/Other/Unknown for device 10.48.55.29
12-Sep-2017|15:25:43.007|DEBUG|AccessLevelDiscovery|pool-4-thread-4|probeAccessLevel() : Running
device type classification for device 10.48.55.29
12-Sep-2017|15:25:43.007|DEBUG|AccessLevelDiscovery|pool-4-thread-
```

```
4|com.cisco.nm.emms.inv.access.core.DeviceTypeGeneratorManager|getDeviceType|167|
getDeviceType() : For device 10.48.55.29 - Find the device Type
12-Sep-2017|15:25:43.007|DEBUG|AccessLevelDiscovery|pool-4-thread-
4|com.cisco.nm.emms.inv.access.core.DeviceTypeGeneratorManager|getDeviceType|169|
getDeviceType() : For device 10.48.55.29; DC PROFILE NAME : 10.48.55.29
12-Sep-2017|15:25:43.007|INFO |AccessLevelDiscovery|pool-4-thread-
4|com.cisco.nm.emms.inv.access.core.DeviceTypeGeneratorManager|getDeviceType|217| DC Id: 6429244
12-Sep-2017|15:25:43.008|INFO |AccessLevelDiscovery|pool-4-thread-
4|com.cisco.nm.emms.access.DeviceUtil|getSysOID|759| DeviceUtil.getSysOID:Before invoking PAL
for SysOID10.48.55.29
12-Sep-2017|15:25:43.077|INFO |AccessLevelDiscovery|pool-4-thread-
4|com.cisco.nm.emms.access.DeviceUtil|getSysOID|766| DeviceUtil.getSysOID:After involking PAL:
sysOID =1.3.6.1.4.1.9.1.1348 Ip Address 10.48.55.29
12-Sep-2017|15:25:43.107|DEBUG|AccessLevelDiscovery|pool-4-thread-
4|com.cisco.nm.emms.inv.access.core.DeviceTypeGeneratorManager|getDeviceType|240|
getDeviceType(): SysOID and SysDescr are fetched from device 10.48.55.29
12-Sep-2017|15:25:43.107|DEBUG|AccessLevelDiscovery|pool-4-thread-
4|com.cisco.nm.emms.inv.access.core.DeviceTypeGeneratorManager|getDeviceType|241|
getDeviceType(): SysOID : 1.3.6.1.4.1.9.1.1348
12-Sep-2017|15:25:43.107|DEBUG|AccessLevelDiscovery|pool-4-thread-
4|com.cisco.nm.emms.inv.access.core.DeviceTypeGeneratorManager|getDeviceType|242|
getDeviceType(): SysDescr : Linux release:2.6.32-431.20.3.el6.x86_64 machine:x86_64
12-Sep-2017|15:25:43.108|DEBUG|AccessLevelDiscovery|pool-4-thread-
4|com.cisco.nm.emms.inv.access.core.DeviceTypeGeneratorManager|getDeviceType|268| Device type of
profile is null
12-Sep-2017|15:25:43.108|INFO |AccessLevelDiscovery|pool-4-thread-
4|com.cisco.nm.emms.inv.access.core.impl.DeviceSwitchType|getDeviceType|17| Checking is Switch
Type check for 10.48.55.29
12-Sep-2017|15:25:43.108|INFO |AccessLevelDiscovery|pool-4-thread-
4|com.cisco.nm.emms.inv.access.core.impl.DeviceRouterType|getDeviceType|17| Checking is Router
Type for 10.48.55.29
(...)
12-Sep-2017|15:25:44.548|DEBUG|AccessLevelDiscovery|pool-4-thread-
4|com.cisco.nm.emms.inv.access.core.impl.DeviceUC500SeriesType|getDeviceType|19|
DeviceUC500SeriesType:getDeviceType
12-Sep-2017|15:25:44.548|DEBUG|AccessLevelDiscovery|pool-4-thread-
4|com.cisco.nm.emms.inv.access.core.impl.DeviceUC500SeriesType|getDeviceType|26| DeviceGroup-
Call Control : DeviceName - Cisco CallManager
12-Sep-2017|15:25:44.637|ERROR|AccessLevelDiscovery|pool-4-thread-
4|com.cisco.nm.emms.inv.access.core.impl.DeviceESXType|checkifESX|65| Exception in
checkIfESXnull
12-Sep-2017|15:25:44.692|DEBUG|AccessLevelDiscovery|pool-4-thread-
4|com.cisco.nm.emms.inv.access.core.impl.DeviceCIMType|checkIfCIM|61| checkIfCIM ()
12-Sep-2017|15:25:45.390|INFO |AccessLevelDiscovery|pool-4-thread-
4|com.cisco.nm.emms.inv.access.core.impl.DeviceSOFTSWITCHType|getDeviceType|42| From
DeviceSOFTSWITCHType
12-Sep-2017|15:25:45.390|DEBUG|AccessLevelDiscovery|pool-4-thread-
4|com.cisco.nm.emms.inv.access.core.impl.DeviceSOFTSWITCHType|checkIfSoftSwitch|60|
checkIfSoftSwitch ()
12-Sep-2017|15:25:46.070|DEBUG|AccessLevelDiscovery|pool-4-thread-
4|com.cisco.nm.emms.inv.access.core.impl.DeviceSOFTSWITCHType|getDeviceType|51| Device
10.48.55.29 is not a SOFTSWITCH
12-Sep-2017|15:25:46.070|DEBUG|AccessLevelDiscovery|pool-4-thread-
4|com.cisco.nm.emms.inv.access.core.impl.DeviceNonCiscoType|getDeviceType|32|
DeviceNonCiscoType: device Type is Non Cisco
12-Sep-2017|15:25:46.139|DEBUG|AccessLevelDiscovery|pool-4-thread-
4|com.cisco.nm.emms.inv.access.core.DeviceTypeGeneratorManager|getDeviceType|175|
probeAccessLevel() : Found DeviceType NONCISCO for device 10.48.55.29
12-Sep-2017|15:25:46.139|DEBUG|AccessLevelDiscovery|pool-4-thread-
4|com.cisco.nm.emms.inv.access.core.DeviceAccessLevelDiscovery$MyWorkItem|classificationOfDevice
Type|339| probeAccessLevel() : ***** CmDevice Type Classification - ENDS *****
12-Sep-2017|15:25:46.140|DEBUG|AccessLevelDiscovery|pool-4-thread-
4|com.cisco.nm.emms.inv.access.core.DeviceAccessLevelDiscovery$MyWorkItem|probeAccessLevel|244|
After classificationOfDeviceType, device credential id is 6429244
```

```
12-Sep-2017|15:25:46.140|DEBUG|AccessLevelDiscovery|pool-4-thread-4|com.cisco.nm.emms.inv.access.core.DeviceAccessLevelDiscovery$MyWorkItem|probeAccessLevel|251|
After resetting to original id, device credential id is 6429244
12-Sep-2017|15:25:46.140|DEBUG|AccessLevelDiscovery|pool-4-thread-4|probeAccessLevel() : DC
10.48.55.29 with type null NOT matched CmDevice 10.48.55.29 with type NONCISCO
```

Solution

Vérifiez si le service SNMP fonctionne sur l'application UC.

Note: Cisco CUCM a deux services SNMP.

```
12-Sep-2017|15:25:43.003|DEBUG|AccessLevelDiscovery|pool-4-thread-4|work() : Starting Access
Level Discovery for device 10.48.55.29
12-Sep-2017|15:25:43.003|DEBUG|AccessLevelDiscovery|pool-4-thread-4|com.cisco.nm.emms.inv.AbstractDiscoveryStage|updateStatusReason|41| Later Error Index for
device 10.48.55.29 is 1022 Old Message
12-Sep-2017|15:25:43.003|DEBUG|AccessLevelDiscovery|pool-4-thread-4|com.cisco.nm.emms.inv.AbstractDiscoveryStage|updateStatusReason|94| Error Index for device
10.48.55.29 is 1022 New Message Discovery in progress.
12-Sep-2017|15:25:43.003|DEBUG|AccessLevelDiscovery|pool-4-thread-4|probeAccessLevel() : Started
for device 10.48.55.29
12-Sep-2017|15:25:43.003|DEBUG|AccessLevelDiscovery|pool-4-thread-4|probeAccessLevel() :
Matching credentials for 10.48.55.29
12-Sep-2017|15:25:43.003|ERROR|AccessLevelDiscovery|pool-4-thread-4|com.cisco.nm.emms.inv.access.core.DeviceAccessLevelDiscovery$MyWorkItem|getFinalDeviceCredenti
alsList|709| Ignoring the DEFAULT profile as the snmp community string is not provided.
12-Sep-2017|15:25:43.005|DEBUG|AccessLevelDiscovery|pool-4-thread-4|com.cisco.nm.emms.inv.access.core.DeviceAccessLevelDiscovery$MyWorkItem|getFinalDeviceCredenti
alsList|760| probeAccessLevel() : CmDevice Credentials List size : 0
12-Sep-2017|15:25:43.006|DEBUG|AccessLevelDiscovery|pool-4-thread-4|com.cisco.nm.emms.inv.access.core.DeviceAccessLevelDiscovery$MyWorkItem|probeAccessLevel|231|
Before classificationOfDeviceType, device credential id is 6429244
12-Sep-2017|15:25:43.007|DEBUG|AccessLevelDiscovery|pool-4-thread-4|probeAccessLevel() :
isDeviceTypeReDiscoveryEnabled flag has set to true or mode is MSP - 10.48.55.29 device type
is re-initilize to Unknown.
12-Sep-2017|15:25:43.007|DEBUG|AccessLevelDiscovery|pool-4-thread-4|probeAccessLevel() : *****
CmDevice Type Classification - STARTS [ 10.48.55.29 ]*****
12-Sep-2017|15:25:43.007|DEBUG|AccessLevelDiscovery|pool-4-thread-4|probeAccessLevel() :
DeviceType is null/Other/Unknown for device 10.48.55.29
12-Sep-2017|15:25:43.007|DEBUG|AccessLevelDiscovery|pool-4-thread-4|probeAccessLevel() : Running
device type classification for device 10.48.55.29
12-Sep-2017|15:25:43.007|DEBUG|AccessLevelDiscovery|pool-4-thread-4|com.cisco.nm.emms.inv.access.core.DeviceTypeGeneratorManager|getDeviceType|167|
getDeviceType() : For device 10.48.55.29 - Find the device Type
12-Sep-2017|15:25:43.007|DEBUG|AccessLevelDiscovery|pool-4-thread-4|com.cisco.nm.emms.inv.access.core.DeviceTypeGeneratorManager|getDeviceType|169|
getDeviceType() : For device 10.48.55.29; DC PROFILE NAME : 10.48.55.29
12-Sep-2017|15:25:43.007|INFO |AccessLevelDiscovery|pool-4-thread-4|com.cisco.nm.emms.inv.access.core.DeviceTypeGeneratorManager|getDeviceType|217| DC Id: 6429244
12-Sep-2017|15:25:43.008|INFO |AccessLevelDiscovery|pool-4-thread-4|com.cisco.nm.emms.access.DeviceUtil|getSysOID|759| DeviceUtil.getSysOID:Before invoking PAL
for SysOID10.48.55.29
12-Sep-2017|15:25:43.077|INFO |AccessLevelDiscovery|pool-4-thread-4|com.cisco.nm.emms.access.DeviceUtil|getSysOID|766| DeviceUtil.getSysOID:After involking PAL:
sysOID =1.3.6.1.4.1.9.1.1348 Ip Address 10.48.55.29
12-Sep-2017|15:25:43.107|DEBUG|AccessLevelDiscovery|pool-4-thread-
```

```

4|com.cisco.nm.emms.inv.access.core.DeviceTypeGeneratorManager|getDeviceType|240|
getDeviceType(): SysOID and SysDescr are fetched from device 10.48.55.29
12-Sep-2017|15:25:43.107|DEBUG|AccessLevelDiscovery|pool-4-thread-
4|com.cisco.nm.emms.inv.access.core.DeviceTypeGeneratorManager|getDeviceType|241|
getDeviceType(): SysOID : 1.3.6.1.4.1.9.1.1348
12-Sep-2017|15:25:43.107|DEBUG|AccessLevelDiscovery|pool-4-thread-
4|com.cisco.nm.emms.inv.access.core.DeviceTypeGeneratorManager|getDeviceType|242|
getDeviceType(): SysDescr : Linux release:2.6.32-431.20.3.el6.x86_64 machine:x86_64
12-Sep-2017|15:25:43.108|DEBUG|AccessLevelDiscovery|pool-4-thread-
4|com.cisco.nm.emms.inv.access.core.DeviceTypeGeneratorManager|getDeviceType|268| Device type of
profile is null
12-Sep-2017|15:25:43.108|INFO |AccessLevelDiscovery|pool-4-thread-
4|com.cisco.nm.emms.inv.access.core.impl.DeviceSwitchType|getDeviceType|17| Checking is Switch
Type check for 10.48.55.29
12-Sep-2017|15:25:43.108|INFO |AccessLevelDiscovery|pool-4-thread-
4|com.cisco.nm.emms.inv.access.core.impl.DeviceRouterType|getDeviceType|17| Checking is Router
Type for 10.48.55.29
(...)
12-Sep-2017|15:25:44.548|DEBUG|AccessLevelDiscovery|pool-4-thread-
4|com.cisco.nm.emms.inv.access.core.impl.DeviceUC500SeriesType|getDeviceType|19|
DeviceUC500SeriesType:getDeviceType
12-Sep-2017|15:25:44.548|DEBUG|AccessLevelDiscovery|pool-4-thread-
4|com.cisco.nm.emms.inv.access.core.impl.DeviceUC500SeriesType|getDeviceType|26| DeviceGroup-
Call Control : DeviceName - Cisco CallManager
12-Sep-2017|15:25:44.637|ERROR|AccessLevelDiscovery|pool-4-thread-
4|com.cisco.nm.emms.inv.access.core.impl.DeviceESXType|checkifESX|65| Exception in
checkIfESXnull
12-Sep-2017|15:25:44.692|DEBUG|AccessLevelDiscovery|pool-4-thread-
4|com.cisco.nm.emms.inv.access.core.impl.DeviceCIMType|checkIfCIM|61| checkIfCIM ()
12-Sep-2017|15:25:45.390|INFO |AccessLevelDiscovery|pool-4-thread-
4|com.cisco.nm.emms.inv.access.core.impl.DeviceSOFTSWITCHType|getDeviceType|42| From
DeviceSOFTSWITCHType
12-Sep-2017|15:25:45.390|DEBUG|AccessLevelDiscovery|pool-4-thread-
4|com.cisco.nm.emms.inv.access.core.impl.DeviceSOFTSWITCHType|checkIfSoftSwitch|60|
checkIfSoftSwitch ()
12-Sep-2017|15:25:46.070|DEBUG|AccessLevelDiscovery|pool-4-thread-
4|com.cisco.nm.emms.inv.access.core.impl.DeviceSOFTSWITCHType|getDeviceType|51| Device
10.48.55.29 is not a SOFTSWITCH
12-Sep-2017|15:25:46.070|DEBUG|AccessLevelDiscovery|pool-4-thread-
4|com.cisco.nm.emms.inv.access.core.impl.DeviceNonCiscoType|getDeviceType|32|
DeviceNonCiscoType: device Type is Non Cisco
12-Sep-2017|15:25:46.139|DEBUG|AccessLevelDiscovery|pool-4-thread-
4|com.cisco.nm.emms.inv.access.core.DeviceTypeGeneratorManager|getDeviceType|175|
probeAccessLevel() : Found DeviceType NONCISCO for device 10.48.55.29
12-Sep-2017|15:25:46.139|DEBUG|AccessLevelDiscovery|pool-4-thread-
4|com.cisco.nm.emms.inv.access.core.DeviceAccessLevelDiscovery$MyWorkItem|classificationOfDevice
Type|339| probeAccessLevel() : ***** CmDevice Type Classification - ENDS *****
12-Sep-2017|15:25:46.140|DEBUG|AccessLevelDiscovery|pool-4-thread-
4|com.cisco.nm.emms.inv.access.core.DeviceAccessLevelDiscovery$MyWorkItem|probeAccessLevel|244|
After classificationOfDeviceType, device credential id is 6429244
12-Sep-2017|15:25:46.140|DEBUG|AccessLevelDiscovery|pool-4-thread-
4|com.cisco.nm.emms.inv.access.core.DeviceAccessLevelDiscovery$MyWorkItem|probeAccessLevel|251|
After resetting to original id, device credential id is 6429244
12-Sep-2017|15:25:46.140|DEBUG|AccessLevelDiscovery|pool-4-thread-4|probeAccessLevel() : DC
10.48.55.29 with type null NOT matched CmDevice 10.48.55.29 with type NONCISCO

```

Le service SNMP de Cisco CallManager est responsable de répondre à des requêtes SNMP MIB de particularité de Cisco

Le service SNMP vers le bas est déjà réparé dans PCA 11.6, et le service SNMP étant en baisse est suggéré :

12-Sep-2017|15:25:43.003|DEBUG|AccessLevelDiscovery|pool-4-thread-4|work() : Starting Access Level Discovery for device 10.48.55.29
12-Sep-2017|15:25:43.003|DEBUG|AccessLevelDiscovery|pool-4-thread-4|com.cisco.nm.emms.inv.AbstractDiscoveryStage|updateStatusReason|41| Later Error Index for device 10.48.55.29 is 1022 Old Message
12-Sep-2017|15:25:43.003|DEBUG|AccessLevelDiscovery|pool-4-thread-4|com.cisco.nm.emms.inv.AbstractDiscoveryStage|updateStatusReason|94| Error Index for device 10.48.55.29 is 1022 New Message Discovery in progress.
12-Sep-2017|15:25:43.003|DEBUG|AccessLevelDiscovery|pool-4-thread-4|probeAccessLevel() : Started for device 10.48.55.29
12-Sep-2017|15:25:43.003|DEBUG|AccessLevelDiscovery|pool-4-thread-4|probeAccessLevel() : Matching credentials for 10.48.55.29
12-Sep-2017|15:25:43.003|ERROR|AccessLevelDiscovery|pool-4-thread-4|com.cisco.nm.emms.inv.access.core.DeviceAccessLevelDiscovery\$MyWorkItem|getFinalDeviceCredentialsList|709| Ignoring the DEFAULT profile as the snmp community string is not provided.
12-Sep-2017|15:25:43.005|DEBUG|AccessLevelDiscovery|pool-4-thread-4|com.cisco.nm.emms.inv.access.core.DeviceAccessLevelDiscovery\$MyWorkItem|getFinalDeviceCredentialsList|760| probeAccessLevel() : CmDevice Credentials List size : 0
12-Sep-2017|15:25:43.006|DEBUG|AccessLevelDiscovery|pool-4-thread-4|com.cisco.nm.emms.inv.access.core.DeviceAccessLevelDiscovery\$MyWorkItem|probeAccessLevel|231| Before classificationOfDeviceType, device credential id is 6429244
12-Sep-2017|15:25:43.007|DEBUG|AccessLevelDiscovery|pool-4-thread-4|probeAccessLevel() : isDeviceTypeReDiscoveryEnabled flag has set to true or mode is MSP - 10.48.55.29 device type is re-initilize to Unknown.
12-Sep-2017|15:25:43.007|DEBUG|AccessLevelDiscovery|pool-4-thread-4|probeAccessLevel() : *****
CmDevice Type Classification - STARTS [10.48.55.29]*****
12-Sep-2017|15:25:43.007|DEBUG|AccessLevelDiscovery|pool-4-thread-4|probeAccessLevel() : DeviceType is null/Other/Unknown for device 10.48.55.29
12-Sep-2017|15:25:43.007|DEBUG|AccessLevelDiscovery|pool-4-thread-4|probeAccessLevel() : Running device type classification for device 10.48.55.29
12-Sep-2017|15:25:43.007|DEBUG|AccessLevelDiscovery|pool-4-thread-4|com.cisco.nm.emms.inv.access.core.DeviceTypeGeneratorManager|getDeviceType|167| getDeviceType() : For device 10.48.55.29 - Find the device Type
12-Sep-2017|15:25:43.007|DEBUG|AccessLevelDiscovery|pool-4-thread-4|com.cisco.nm.emms.inv.access.core.DeviceTypeGeneratorManager|getDeviceType|169| getDeviceType() : For device 10.48.55.29; DC PROFILE NAME : 10.48.55.29
12-Sep-2017|15:25:43.007|INFO |AccessLevelDiscovery|pool-4-thread-4|com.cisco.nm.emms.inv.access.core.DeviceTypeGeneratorManager|getDeviceType|217| DC Id: 6429244
12-Sep-2017|15:25:43.008|INFO |AccessLevelDiscovery|pool-4-thread-4|com.cisco.nm.emms.access.DeviceUtil|getSysOID|759| DeviceUtil.getSysOID:Before invoking PAL for SysOID10.48.55.29
12-Sep-2017|15:25:43.077|INFO |AccessLevelDiscovery|pool-4-thread-4|com.cisco.nm.emms.access.DeviceUtil|getSysOID|766| DeviceUtil.getSysOID:After involking PAL: sysOID =1.3.6.1.4.1.9.1.1348 Ip Address 10.48.55.29
12-Sep-2017|15:25:43.107|DEBUG|AccessLevelDiscovery|pool-4-thread-4|com.cisco.nm.emms.inv.access.core.DeviceTypeGeneratorManager|getDeviceType|240| getDeviceType(): SysOID and SysDescr are fetched from device 10.48.55.29
12-Sep-2017|15:25:43.107|DEBUG|AccessLevelDiscovery|pool-4-thread-4|com.cisco.nm.emms.inv.access.core.DeviceTypeGeneratorManager|getDeviceType|241| getDeviceType(): SysOID : 1.3.6.1.4.1.9.1.1348
12-Sep-2017|15:25:43.107|DEBUG|AccessLevelDiscovery|pool-4-thread-4|com.cisco.nm.emms.inv.access.core.DeviceTypeGeneratorManager|getDeviceType|242| getDeviceType(): SysDescr : Linux release:2.6.32-431.20.3.el6.x86_64 machine:x86_64
12-Sep-2017|15:25:43.108|DEBUG|AccessLevelDiscovery|pool-4-thread-4|com.cisco.nm.emms.inv.access.core.DeviceTypeGeneratorManager|getDeviceType|268| Device type of profile is null
12-Sep-2017|15:25:43.108|INFO |AccessLevelDiscovery|pool-4-thread-4|com.cisco.nm.emms.inv.access.core.impl.DeviceSwitchType|getDeviceType|17| Checking is Switch Type check for 10.48.55.29
12-Sep-2017|15:25:43.108|INFO |AccessLevelDiscovery|pool-4-thread-4|com.cisco.nm.emms.inv.access.core.impl.DeviceRouterType|getDeviceType|17| Checking is Router Type for 10.48.55.29
(...)
12-Sep-2017|15:25:44.548|DEBUG|AccessLevelDiscovery|pool-4-thread-

```

4|com.cisco.nm.emms.inv.access.core.impl.DeviceUC500SeriesType|getDeviceType|19|
DeviceUC500SeriesType:getDeviceType
12-Sep-2017|15:25:44.548|DEBUG|AccessLevelDiscovery|pool-4-thread-
4|com.cisco.nm.emms.inv.access.core.impl.DeviceUC500SeriesType|getDeviceType|26| DeviceGroup-
Call Control : DeviceName - Cisco CallManager
12-Sep-2017|15:25:44.637|ERROR|AccessLevelDiscovery|pool-4-thread-
4|com.cisco.nm.emms.inv.access.core.impl.DeviceESXType|checkifESX|65| Exception in
checkifESXnull
12-Sep-2017|15:25:44.692|DEBUG|AccessLevelDiscovery|pool-4-thread-
4|com.cisco.nm.emms.inv.access.core.impl.DeviceCIMType|checkIfCIM|61| checkIfCIM ()
12-Sep-2017|15:25:45.390|INFO |AccessLevelDiscovery|pool-4-thread-
4|com.cisco.nm.emms.inv.access.core.impl.DeviceSOFTSWITCHType|getDeviceType|42| From
DeviceSOFTSWITCHType
12-Sep-2017|15:25:45.390|DEBUG|AccessLevelDiscovery|pool-4-thread-
4|com.cisco.nm.emms.inv.access.core.impl.DeviceSOFTSWITCHType|checkIfSoftSwitch|60|
checkIfSoftSwitch ()
12-Sep-2017|15:25:46.070|DEBUG|AccessLevelDiscovery|pool-4-thread-
4|com.cisco.nm.emms.inv.access.core.impl.DeviceSOFTSWITCHType|getDeviceType|51| Device
10.48.55.29 is not a SOFTSWITCH
12-Sep-2017|15:25:46.070|DEBUG|AccessLevelDiscovery|pool-4-thread-
4|com.cisco.nm.emms.inv.access.core.impl.DeviceNonCiscoType|getDeviceType|32|
DeviceNonCiscoType: device Type is Non Cisco
12-Sep-2017|15:25:46.139|DEBUG|AccessLevelDiscovery|pool-4-thread-
4|com.cisco.nm.emms.inv.access.core.DeviceTypeGeneratorManager|getDeviceType|175|
probeAccessLevel() : Found DeviceType NONCISCO for device 10.48.55.29
12-Sep-2017|15:25:46.139|DEBUG|AccessLevelDiscovery|pool-4-thread-
4|com.cisco.nm.emms.inv.access.core.DeviceAccessLevelDiscovery$MyWorkItem|classificationOfDevice
Type|339| probeAccessLevel() : ***** CmDevice Type Classification - ENDS *****
12-Sep-2017|15:25:46.140|DEBUG|AccessLevelDiscovery|pool-4-thread-
4|com.cisco.nm.emms.inv.access.core.DeviceAccessLevelDiscovery$MyWorkItem|probeAccessLevel|244|
After classificationOfDeviceType, device credential id is 6429244
12-Sep-2017|15:25:46.140|DEBUG|AccessLevelDiscovery|pool-4-thread-
4|com.cisco.nm.emms.inv.access.core.DeviceAccessLevelDiscovery$MyWorkItem|probeAccessLevel|251|
After resetting to original id, device credential id is 6429244
12-Sep-2017|15:25:46.140|DEBUG|AccessLevelDiscovery|pool-4-thread-4|probeAccessLevel() : DC
10.48.55.29 with type null NOT matched CmDevice 10.48.55.29 with type NONCISCO

```

Problème

Le périphérique PLM est affiché en tant que non Cisco sur l'inventaire paginent.

Solution

1. Sélectionnez le **serveur PLM** dans la page d'inventaire et interrompez le périphérique.
2. Supprimez le périphérique de l'inventaire PCA.
3. Supprimez n'importe quelle chaîne de la communauté ajoutée dans le PLM par l'intermédiaire de l'interface de ligne de commande (CLI) :

effacement de communauté-chaîne du config 1/2c SNMP d'utilis

4. Ajoutez le périphérique de retour dans le PCA avec l'utilisation de la plate-forme du système d'exploitation credential (SYSTÈME D'EXPLOITATION PLM CLI) dans le gisement de créance de périphérique des HTTPS PCA suivant les indications de l'image.

Add Device



*IP Address

Note: For multiple IP Addresses, use a unique delimiter: comma, pipe or blank space.
Example: 10.39.65.1|10.33.68.99

▶ General SNMP Options

▼ CLI

CLI Login Username

CLI Login Password

Re-enter CLI Login Password

CLI Enable Password

Re-enter CLI Enable Password

▼ HTTP(s)

HTTP(s) Username

HTTP(s) Password

Re-enter HTTP(s) Password

*Note: Please enter the domain name along with username for IICCF devices (ex

Discover

Close