

# C シリーズ サーバ再起動のトラブルシューティング

## 目次

[概要](#)

[前提条件](#)

[使用するコンポーネント](#)

[背景説明](#)

[想定リブート](#)

[想定外のリブート](#)

[キーポイント](#)

[分析用のログバンドルの収集](#)

[リポートおよびシャットダウン状態ごとに想定される出力](#)

[OS - ESXi、RHEL、Windows からのリポート](#)

[OBFL ログ](#)

[RHEL - /var/log/messages](#)

[Windows - イベント ログ](#)

[OS - ESXi、RHEL、Windows からのシャットダウン](#)

[OBFL ログ :](#)

[ESXi - /var/log/hostd.log](#)

[RHEL - /var/log/messages](#)

[Windows - イベント ログ](#)

[CIMC からの電源投入](#)

[OBFL ログ :](#)

[CIMC からの電源再投入](#)

[OBFL ログ](#)

[CIMC からの電源切断](#)

[OBFL ログ](#)

[PSU 障害からの電力損失](#)

[OBFL ログ](#)

[前面電源オフ ボタン](#)

[OBFL ログ](#)

[前面電源オン ボタン](#)

[OBFL ログ](#)

[関連情報](#)

## 概要

このドキュメントでは、リブートまたはシャットダウンがハードウェアで開始されたか、またはオペレーティングシステム (OS) から開始されたかを確認する方法を説明します。

サーバがリブートしたりシャットダウンする理由を判断する際に注目すべきログがいくつかあります。Cisco Integrated Management Controller (CIMC) のテクニカルサポートを検索する場合

、var/log/messages または オンボード障害ロギング ( OBFL ) ログを参照してください。

このドキュメントで示されている出力例は、var/log/messages または OBFL に加えて ESXi、RHEL、Windows の OS ログから引用したものです。

## 前提条件

このドキュメントに関しては個別の要件はありません。

## 使用するコンポーネント

このドキュメントの情報は、次のソフトウェアとハードウェアのバージョンに基づくものです。

- Cisco Unified Computing System ( UCS ) C200-M1 ファームウェアバージョン 1.4(3w)
- Cisco UCS C210-M2 ファームウェアバージョン 1.4(3w)
- Cisco UCS C220-M3 ファームウェアバージョン 2.0(3d)
- Cisco UCS C220-M4 ファームウェアバージョン 2.0(3f)
- ESXi 5.0 U2
- RHEL 6.6
- Windows 2008 R2

本書の情報は、特定のラボ環境にあるデバイスに基づいて作成されたものです。このドキュメントで使用するすべてのデバイスは、初期 ( デフォルト ) 設定の状態から起動しています。稼働中のネットワークで作業を行う場合、コマンドの影響について十分に理解したうえで作業してください。

## 背景説明

リブートには想定内のものと想定外のものがあります。想定されたリブートでも、すべての利害関係者がそれを想定しているとは限りません。全員が把握した上でこの操作ができるように、リブートまたはシャットダウン タスクの変更制御プロセスを実施することが重要です。

## 想定リブート

これは、人、プロセス、またはスクリプトによって意図的に開始されたリブートまたはシャットダウン イベントです。このイベントには複数のきっかけがあります。これらのログ スニペットはどのリブート シナリオが発生したかを特定するのに役立ち、誰が、または何がこの操作を行ったかを追跡することができます。

- CIMC GUI を通じて
- OS から
- サーバの前面にある前面パネル ボタンを押したとき

## 想定外のリブート

これは計画も想定もされていないリブートですが、操作を開始した人またはプロセスはこのリブートを想定可能です。また、データセンターの PSU 障害や停電などのハードウェア障害も考えられます。これらのイベントには複数のきっかけがあります。

前面パネルのボタンが押されたことが判明したら、リポート時にデータセンターへ誰が物理的にアクセスしたかを追跡できます。電源の問題である場合、そのときに電源障害が発生していたかどうかをデータセンター チームに確認してもらいます。

- CIMC GUI を通じて
- OS から
- サーバの前面にある前面パネル ボタンを押したとき
- PSU 障害や電源コードの不良などのハードウェア障害から
- データセンターの配電ユニット ( PDU ) の障害
- データセンターの無停電電源装置 ( UPS ) の障害、停電、電圧低下

## キー ポイント

- CIMC 始められたリポート、シャットダウンおよび電源 ons はログで「do\_power」キーワードが常に含まれています。
- 前面パネル ボタンは新しいファームウェアのバージョンを実行するとき含まれています "passthrough\_pin2\_isr" が押します。また、これに関連する OS レベルのイベントはない可能性が高いです。
- OS が開始したリポートとシャットダウンでは、関連する OS レベルのイベントがあります。「do\_power」が記録されない場合、その代わりに「高電圧モード」が記録される可能性があることに注意してください。

## 分析用のログ バンドルの収集

関連するログを調べる前に、まずログ バンドルを生成する必要があります。このドキュメントの出力例と比較するときの参照用に、次のリソースを使用して必要なログを作成してください。

### C シリーズ CIMC テクニカル サポート

[テクニカル サポート ファイルを収集するためのビジュアル ガイド \( B および C シリーズ \)](#)

#### ESXi

[VMware ナレッジベース](#)

#### RHEL

[What is a sosreport and how to create one in Red Hat Enterprise Linux 4.6 and later?](#)

#### Windows

[Archive a Windows Event Log](#)

## リポートおよびシャットダウン状態ごとに想定される出力

### OS - ESXi、RHEL、Windows からのリポート

#### OBFL ログ

```
5:2017 Mar 2 09:46:44:BMC:kernel:-:<5>[lpc_reset_isr_handler]:79:LPC Reset ISR -> ResetState: 1
5:2017 Mar 2 09:46:44:BMC:kernel:-:<5>[readPostData]:525:BIOS_POST_CMPLT Asserted --> BIOS has
completed
5:2017 Mar 2 09:46:44:BMC:kernel:-:<5>[lpc_reset_isr_handler]:79:LPC Reset ISR -> ResetState: 0
5:2017 Mar 2 09:46:44:BMC:kernel:-:<5>[lpc_reset_handler_Port80_Capture_setup]:566:
BIOS_POST_CMPLT De-asserted --> BIOS is running
5:2017 Mar 2 09:46:44:BMC:kernel:-:<5>[block_transfer_fetch_host_request_for_app]:1860:
block_transfer_fetch_host_request_for_app: BT_OPEN_FOR_READ: HostDescriptor = 4740 : Filename =
BiosTech_7.txt
5:2017 Mar 2 09:46:44:BMC:BIOSReader:1304: BIOSReader.c:242:File Open : BiosTech_7.txt
5:2017 Mar 2 09:46:44:BMC:kernel:-:<5>[block_transfer_fetch_host_request_for_app]:1944:
block_transfer_fetch_host_request_for_app : BT_FILE_CLOSE : HostBTDescr = 4740 : FName =
BiosTech_7.txt
5:2017 Mar 2 09:46:44:BMC:BIOSReader:1304: BIOSReader.c:748:File Close :
/var/nuova/BIOS/BiosTech_7.txt
5:2017 Mar 2 09:46:44:BMC:lv_dimm:1625: lv_dimm.c:129:[lpc_reset_seen]
LPC Reset Count is Different [0x77:0x78] Asserted LPC Reset Seen
5:2017 Mar 2 09:46:44:BMC:lv_dimm:1625: common.c:940:Disabling Sensor scan for sensor 0x83.
5:2017 Mar 2 09:46:44:BMC:lv_dimm:1625: common.c:940:Disabling Sensor scan for sensor 0x84.
5:2017 Mar 2 09:46:44:BMC:lv_dimm:1625: common.c:940:Disabling Sensor scan for sensor 0x85.
5:2017 Mar 2 09:46:44:BMC:lv_dimm:1625: common.c:940:Disabling Sensor scan for sensor 0x86.
5:2017 Mar 2 09:46:44:BMC:lv_dimm:1625: common.c:940:Disabling Sensor scan for sensor 0x89.
5:2017 Mar 2 09:46:44:BMC:lv_dimm:1625: common.c:940:Disabling Sensor scan for sensor 0x8a.
5:2017 Mar 2 09:46:44:BMC:lv_dimm:1625: common.c:940:Disabling Sensor scan for sensor 0x91.
5:2017 Mar 2 09:46:44:BMC:lv_dimm:1625: common.c:940:Disabling Sensor scan for sensor 0x92.
5:2017 Mar 2 09:46:44:BMC:lv_dimm:1625: lv_dimm.c:200:[transition_function]
Starting Transition to [High Voltage Mode] from [Unknown Mode]
5:2017 Mar 2 09:46:44:BMC:lv_dimm:1625: common.c:940:Disabling Sensor scan for sensor 0x83.
5:2017 Mar 2 09:46:44:BMC:lv_dimm:1625: common.c:940:Disabling Sensor scan for sensor 0x84.
5:2017 Mar 2 09:46:44:BMC:lv_dimm:1625: common.c:940:Disabling Sensor scan for sensor 0x85.
5:2017 Mar 2 09:46:44:BMC:lv_dimm:1625: common.c:940:Disabling Sensor scan for sensor 0x86.
5:2017 Mar 2 09:46:44:BMC:lv_dimm:1625: common.c:940:Disabling Sensor scan for sensor 0x89.
5:2017 Mar 2 09:46:44:BMC:lv_dimm:1625: common.c:940:Disabling Sensor scan for sensor 0x8a.
5:2017 Mar 2 09:46:44:BMC:lv_dimm:1625: common.c:940:Disabling Sensor scan for sensor 0x91.
5:2017 Mar 2 09:46:44:BMC:lv_dimm:1625: common.c:940:Disabling Sensor scan for sensor 0x92.
5:2017 Mar 2 09:46:44:BMC:lv_dimm:1625: lv_dimm.c:220:[transition_function]
Transition to [High Voltage Mode] Success
...
5:2017 Mar 2 09:47:01:BMC:BIOSReader:1304: BIOSReader.c:748:File Close :
/var/nuova/BIOS/DimmTempOffset
5:2017 Mar 2 09:47:06:BMC:kernel:-:<5>[lpc_reset_isr_handler]:79:LPC Reset ISR -> ResetState: 1
5:2017 Mar 2 09:47:06:BMC:kernel:-:<5>drivers/bmc/usb/usbl.1/se_pilot2_udc_usb1_1.c:2290:
USB FS: VDD Power WAKEUP- Power Good = OFF
5:2017 Mar 2 09:47:06:BMC:BIOSReader:1304: BIOSReader.c:748:File Close :
/var/nuova/BIOS/BiosTech.txt
5:2017 Mar 2 09:47:06:BMC:kernel:-:<5>[se_pilot2_wakeup_interrupt]:2561:USB HS: VDD Power = OFF
5:2017 Mar 2 09:47:06:BMC:kernel:-:<5>[block_transfer_fetch_host_request_for_app]:1944:
block_transfer_fetch_host_request_for_app : BT_FILE_CLOSE : HostBTDescr = 4756 : FName =
BiosTech.txt
5:2017 Mar 2 09:47:06:BMC:IPMI:1497: Rack_FanCtrl.c:1183:fscUpdateActualFanPolicyFile:
Applied Policy: N/A, Configuration Status: PENDING - Host powered off
5:2017 Mar 2 09:47:06:BMC:IPMI:1466: Pilot2SrvPower.c:466:Blade Power Changed To: [ OFF ]
5:2017 Mar 2 09:47:06:BMC:selparser:1547: selparser.c:710:
# 7E 03 00 00 01 02 00 00 6A 30 B8 58 20 00 04 25 05 00 00 00 08 00 FF FF # 37e | 03/02/2017
09:47:06
| CIMC | Entity presence MAIN_POWER_PRS #0x05 | Device Absent | Asserted
...
5:2017 Mar 2 09:47:12:BMC:kernel:-:<5>[se_pilot2_wakeup_interrupt]:2561:USB HS: VDD Power = ON
5:2017 Mar 2 09:47:12:BMC:kernel:-:<5>[se_pilot2_udc_usb_connect]:2685:Failed USB2.0 register
test
5:2017 Mar 2 09:47:12:BMC:kernel:-:last message repeated 2 times
5:2017 Mar 2 09:47:12:BMC:kernel:-:<5>[lpc_reset_isr_handler]:79:LPC Reset ISR -> ResetState: 0
```

```
5:2017 Mar  2 09:47:12:BMC:kernel:-:<5>[lpc_reset_handler_Port80_Capture_setup]:566:
BIOS_POST_CMPLT De-asserted --> BIOS is running
5:2017 Mar  2 09:47:12:BMC:kernel:-:<5>[block_transfer_fetch_host_request_for_app]:1860:
block_transfer_fetch_host_request_for_app: BT_OPEN_FOR_READ: HostDescriptor = 4778 : Filename =
BiosTech_7.txt
5:2017 Mar  2 09:47:12:BMC:BIOSReader:1304: BIOSReader.c:242:File Open : BiosTech_7.txt
5:2017 Mar  2 09:47:12:BMC:kernel:-:<5>[block_transfer_fetch_host_request_for_app]:1944:
block_transfer_fetch_host_request_for_app : BT_FILE_CLOSE : HostBTDescr = 4778 : FName =
BiosTech_7.txt
5:2017 Mar  2 09:47:12:BMC:BIOSReader:1304: BIOSReader.c:748:File Close :
/var/nuova/BIOS/BiosTech_7.txt
5:2017 Mar  2 09:47:12:BMC:selparser:1547: selparser.c:710:
# 7F 03 00 00 01 02 00 00 6F 30 B8 58 20 00 04 25 05 00 00 00 08 01 FF FF # 37f
| 03/02/2017 09:47:11 | CIMC | Entity presence MAIN_POWER_PRS #0x05 | Device Present | Asserted
5:2017 Mar  2 09:47:12:BMC:IPMI:1495: Pilot2SrvPower.c:466:Blade Power Changed To: [ ON ]
OS がこのイベントを開始した理由についての詳細は、ESXi ログを確認します。
```

- /var/log/vmksuSummary.log
- /var/log/vmkernel.log
- /var/log/hostd.log
- /var/log/shell.log

[VMware KB](#)

## RHEL - /var/log/messages

```
May 12 12:55:00 localhost rtkit-daemon[10450]: Demoting known real-time threads.
May 12 12:55:00 localhost rtkit-daemon[10450]: Successfully demoted thread
10987 of process 10987 (/usr/bin/pulseaudio).
May 12 12:55:00 localhost console-kit-daemon[10311]: WARNING: no sender#012
May 12 12:55:00 localhost rtkit-daemon[10450]: Demoted 1 threads.
May 12 12:55:00 localhost rpcbind: rpcbind terminating on signal.
Restart with "rpcbind -w" May 12 12:55:00 localhost init:
Disconnected from system bus
May 12 12:55:00 localhost auditd[3587]: The audit daemon is exiting.
May 12 12:55:00 localhost kernel: type=1305 audit(1431453300.949:33):
audit_pid=0 old=3587 auid=4294967295 ses=4294967295 subj=system_u:
system_r:auditd_t:s0 res=1
May 12 12:55:01 localhost kernel: type=1305 audit(1431453301.053:34):
audit_enabled=0 old=1 auid=4294967295 ses=4294967295 subj=system_u:
system_r:auditctl_t:s0 res=1
May 12 12:55:01 localhost kernel: Kernel logging (proc) stopped.
May 12 12:55:01 localhost rsyslogd: [origin software="rsyslogd" swVersion="5.8.10"
x-pid="3617" x-info="http://www.rsyslog.com"] exiting on signal 15.
May 12 12:58:27 localhost kernel: imklog 5.8.10, log source = /proc/kmsg started.
May 12 12:58:27 localhost rsyslogd: [origin software="rsyslogd" swVersion="5.8.10"
x-pid="3631" x-info="http://www.rsyslog.com"] start
May 12 12:58:27 localhost kernel: Initializing cgroup subsys cpuset
May 12 12:58:27 localhost kernel: Initializing cgroup subsys cpu
May 12 12:58:27 localhost kernel: Linux version 2.6.32-504.el6.x86_64
(mockbuild@x86-023.build.eng.bos.redhat.com) (gcc version 4.4.7 20120313
(Red Hat 4.4.7-11) (GCC) ) #1 SMP Tue Sep 16 01:56:35 EDT 2014
May 12 12:58:27 localhost kernel: Command line:
ro root=/dev/mapper/VolGroup-lv_root rd_NO_LUKS LANG=en_US.UTF-8
rd_NO_MD rd_LVM_LV=VolGroup/lv_swap SYSFONT=latarcyrheb-sun16 crashkernel=auto
rd_LVM_LV=VolGroup/lv_root KEYBOARDTYPE=pc KEYTABLE=us rd_NO_DM rhgb quiet
```

RHEL のリブートに関するトラブルシューティングの方法については、「[Red Hat KB article](#)」を参照してください。

## Windows - イベント ログ

### Event 1074

The process **Explorer.EXE** has initiated the restart of computer WIN-5JPBKNMMRNF on behalf of user WIN-5JPBKNMMRNF\Administrator for the following reason: Other (Planned)

Reason Code: 0x85000000

Shutdown Type: restart

Comment: C-Series Test

### Event 1074

The process **C:\Windows\system32\winlogon.exe (WIN-5JPBKNMMRNF)** has initiated the restart of computer WIN-5JPBKNMMRNF on behalf of user WIN-5JPBKNMMRNF\Administrator for the following reason: No title for this reason could be found

Reason Code: 0x500ff

Shutdown Type: restart Comment:

### Event 109

The kernel power manager has initiated a shutdown transition.

### Event 13

The operating system is shutting down at system time ?2015?-?05?-?18T08:26:32.778837300Z.

### Event 12

The operating system started at system time ?2015?-?05?-?18T08:28:28.610798500Z.

Windows イベント ログの詳細については、「[TechNet article](#)」を参照してください。

## OS - ESXi、RHEL、Windows からのシャットダウン

### OBFL ログ :

```
5:2015 May 12 18:03:37:BMC:IPMI:1563: Bridge.c:1478:audit from:kcs
Fn:0x6 Cmd:0x6 Data&colon; 0x85 0x83
5:2015 May 12 18:03:37:BMC:IPMI:1563: Bridge.c:1484:audit Resp:0x0
5:2015 May 12 18:03:38:BMC:kernel:-:<5>[lpc_reset_isr_handler]:79:LPC
Reset ISR -> ResetState: 1
5:2015 May 12 18:03:38:BMC:kernel:-:<5>[readPostData]:519:BIOS_POST_
CMPLT Asserted --> BIOS has completed
5:2015 May 12 18:03:38:BMC:kernel:-:<5>drivers/bmc/usb/usb1.1/se_pilot2_udc_
usb1_1.c:2288:USB FS:
VDD Power WAKEUP- Power Good = OFF
5:2015 May 12 18:03:38:BMC:kernel:-:<5>[se_pilot2_wakeup_interrupt]
:2561:USB HS: VDD Power = OFF
5:2015 May 12 18:03:38:BMC:IPMI:1563: Pilot3SrvPower.c:484:Blade Power Changed To: [ OFF ]
5:2015 May 12 18:03:38:BMC:video_trigger:-: video_trigger.c:262:
Sending event_ipmi_power_state_change (OFF) ..
5:2015May 12 18:03:39:BMC:selparser:1602: selparser.c:678:
# 11 04 00 00 01 02 00 00 7A 40 52 55 2C 60 04 DC 1A 00 00 00 F4 03 00 00
# 411 | 05/12/2015 18:03:38 | Unknown #0x602c | Unknown #0x1a |
5:2015 May 12 18:03:39:BMC:selparser:1602: selparser.c:678:
# 12 04 00 00 01 02 00 00 7A 40 52 55 20 00 04 25 A9 00 00 00 08 00 FF FF # 412 |
05/12/2015 18:03:38 | CIMC | Entity presence MAIN_POWER_PRS #0xa9 | Device Absent | Asserted
```

### ESXi - /var/log/hostd.log

```
2015-05-15T00:46:01.809Z [28B69B90 info 'TaskManager'] Task Created :
  haTask--vim.host.AutoStartManager.autoPowerOff-245137084
2015-05-15T00:46:01.810Z [28AE7B90 info 'TaskManager'] Task Completed :
haTask--vim.host.AutoStartManager.autoPowerOff-245137084 Status success
2015-05-15T00:46:01.814Z [28AE7B90 verbose 'Default']
CloseSession called for session id=526869fe-3f96-f54a-4bb6-41250fa3242b
2015-05-15T00:46:01.814Z [28AE7B90 info 'ha-eventmgr'] Event 107 : User dcui logged out
2015-05-15T00:46:01.822Z [28AA6B90 verbose 'Proxysvc Req00060'] New proxy client SSL
(TCP(local=127.0.0.1:0, peer=127.0.0.1:58274))
2015-05-15T00:46:01.822Z [28AA6B90 warning 'Proxysvc Req00060'] Error reading from
client while waiting for header: N7Vmacore15SystemExceptionE(Connection reset by peer)
2015-05-15T00:46:02.077Z [29441B90 verbose 'Proxysvc Req00061'] New proxy client
SSL(TCP(local=127.0.0.1:443, peer=127.0.0.1:58877))
2015-05-15T00:46:02.088Z [28AE7B90 verbose 'Ticket 52 27 9e 4d f0 16 ac aa-13 f8
86 f9 f1 a3 61 8b'] Ticket issued for dcui
2015-05-15T00:46:02.090Z [2930AB90 verbose 'Ticket 52 27 9e 4d f0 16 ac aa-13 f8
86 f9 f1 a3 61 8b'] Ticket used
Accepted password for user dcui from 127.0.0.1
2015-05-15T00:46:02.090Z [2930AB90 info 'Vimsvc'] [Auth]: User dcui
2015-05-15T00:46:02.091Z [2930AB90 info 'ha-eventmgr'] Event 108 :
User dcui@127.0.0.1 logged in
2015-05-15T00:46:02.093Z [29366B90 info 'InternalServiceInstance'] Shutting down service
2015-05-15T00:46:22.104Z [FFAB2AD0 error 'Default'] SSLStreamImpl::
BIORead (291a1000) timed out
Section for VMware ESX, pid=2882, version=5.0.0, build=build-914586, option=Release
```

## RHEL - /var/log/messages

```
May 12 13:03:24 localhost init: tty (/dev/tty2) main process
(10152) killed by TERM signal
May 12 13:03:24 localhost init: tty (/dev/tty3) main process
(10154) killed by TERM signal
May 12 13:03:24 localhost init: tty (/dev/tty4) main process
(10156) killed by TERM signal
May 12 13:03:24 localhost init: tty (/dev/tty5) main process
(10158) killed by TERM signal
May 12 13:03:24 localhost init: tty (/dev/tty6) main process
(10162) killed by TERM signal
May 12 13:03:25 localhost abrttd: Got signal 15, exiting
May 12 13:03:29 localhost acpid: exiting
May 12 13:03:30 localhost NetworkManager[9732]: <info>
  caught signal 15, shutting down normally.
May 12 13:03:30 localhost NetworkManager[9732]: <info> (eth0): cleaning up...
May 12 13:03:30 localhost NetworkManager[9732]: <info> (eth0): taking down device.
May 12 13:03:30 localhost NetworkManager[9732]: <info> (eth1): cleaning up...
May 12 13:03:30 localhost NetworkManager[9732]: <info> (eth1): taking down device.
May 12 13:03:30 localhost NetworkManager[9732]: <info> (eth4): cleaning up...
May 12 13:03:30 localhost NetworkManager[9732]: <info> (eth4): taking down device.
May 12 13:03:30 localhost NetworkManager[9732]: <info> (eth5): cleaning up...
May 12 13:03:30 localhost NetworkManager[9732]: <info> (eth5): taking down device.
May 12 13:03:30 localhost NetworkManager[9732]: <info> (eth6): cleaning up...
May 12 13:03:30 localhost NetworkManager[9732]: <info> (eth6): taking down device.
May 12 13:03:30 localhost NetworkManager[9732]: <info> (eth7): cleaning up...
May 12 13:03:30 localhost NetworkManager[9732]: <info> (eth7): taking down device.
May 12 13:03:30 localhost NetworkManager[9732]: <info> (eth2): cleaning up...
May 12 13:03:30 localhost NetworkManager[9732]: <info> (eth2): taking down device.
May 12 13:03:30 localhost NetworkManager[9732]: <info> (eth3): cleaning up...
May 12 13:03:30 localhost NetworkManager[9732]: <info> (eth3): taking down device.
May 12 13:03:30 localhost NetworkManager[9732]: <info> exiting (success)
May 12 13:03:31 localhost rpcbind: rpcbind terminating on signal.
Restart with "rpcbind -w"
```

```
May 12 13:03:31 localhost rtkit-daemon[10367]: Demoting known real-time threads.
May 12 13:03:31 localhost rtkit-daemon[10367]: Successfully demoted thread 1
0365 of process 10365 (/usr/bin/pulseaudio).
May 12 13:03:31 localhost rtkit-daemon[10367]: Demoted 1 threads.
May 12 13:03:31 localhost console-kit-daemon[10228]: WARNING: no sender#012
May 12 13:03:31 localhost init: Disconnected from system bus
May 12 13:03:31 localhost auditd[3601]: The audit daemon is exiting.
May 12 13:03:31 localhost kernel: type=1305 audit(1431453811.355:22):
audit_pid=0 old=3601 auid=4294967295 ses=4294967295 subj=system_u
:system_r:auditd_t:s0 res=1
May 12 13:03:31 localhost kernel: type=1305 audit(1431453811.459:23):
audit_enabled=0 old=1 auid=4294967295 ses=4294967295 subj=system_u
:system_r:auditctl_t:s0 res=1
May 12 13:03:31 localhost kernel: Kernel logging (proc) stopped.
May 12 13:03:31 localhost rsyslogd: [origin software="rsyslogd"
swVersion="5.8.10" x-pid="3631" x-info="http://www.rsyslog.com"] exiting on signal 15.
```

## Windows - イベント ログ

### Event 1074

The process C:\Windows\system32\winlogon.exe (WIN-5JPBKNNMRRNF)  
has initiated the power off of computer WIN-5JPBKNNMRRNF on behalf  
of user WIN-5JPBKNNMRRNF\Administrator  
for the following reason: No title for this reason could be found  
Reason Code: 0x500ff  
Shutdown Type: power off  
Comment

### Event 1074

The process Explorer.EXE has initiated the shutdown of computer  
WIN-5JPBKNNMRRNF on behalf of  
user WIN-5JPBKNNMRRNF\Administrator for the following reason: Other (Planned)  
Reason Code: 0x85000000  
Shutdown Type: shutdown  
Comment: Shut down Test

### Event 109

The kernel power manager has initiated a shutdown transition.

### Event 13

The operating system is shutting down at system time ?2015?-?05?-?18T08:38:13.237425300Z.

## CIMC からの電源投入

### OBFL ログ :

```
5:2015 May 12 18:08:31:BMC:kernel:--<5>[__do_power_on]:340:__do_power_on
5:2015 May 12 18:08:31:BMC:IPMI:1563: Bridge.c:1478:audit from:kcs Fn:0x0 Cmd:0x2
Data&colon; 0x1
5:2015 May 12 18:08:31:BMC:kernel:--<5>[__do_power_on]:345:Power Driver:
Power On Logic Pulse for 250ms @ 25164275955:2015 May 12 18:08:31:BMC:IPMI:
1563: Bridge.c:1484:audit Resp:0x0
5:2015 May 12 18:08:31:BMC:AUDIT:20723: Server power state modify (op:power-on)
5:2015 May 12 18:08:31:BMC:kernel:--<5>drivers/bmc/usb/usb1.1/
se_pilot2_udc_usb1_1.c:2288:USB FS: VDD Power WAKEUP- Power Good = ON
5:2015 May 12 18:08:31:BMC:kernel:--<5>[se_pilot2_wakeup_interrupt]
:2561:USB HS: VDD Power = ON
5:2015 May 12 18:08:31:BMC:kernel:--<5>[se_pilot2_udc_usb_connect]:
```



```
2685:Failed USB2.0 register test
5:2015 May 12 18:08:31:BMC:IPMI:1565: Pilot3SrvPower.c:481: ->
Power State On: LPC RESET is NOT IN RESET; powerOnLPCOff[2]
5:2015 May 12 18:08:31:BMC:kernel:--<5>[se_pilot2_udc_usb_connect]
:2685:Failed USB2.0 register test
5:2015 May 12 18:08:31:BMC:IPMI:1565: Pilot3SrvPower.c:484:Blade
Power Changed To: [ ON ]
5:2015 May 12 18:08:31:BMC:kernel:--<5>[lpc_reset_isr_handler]
:79:LPC Reset ISR -> ResetState: 0
5:2015 May 12 18:08:31:BMC:kernel:--<5>[lpc_reset_handler_Port80_Capture_setup]
:560:BIOS_POST_CMPLT De-asserted --> BIOS is running
5:2015 May 12 18:08:31:BMC:IPMI:1566: Pilot3SrvPower.c:191:Pilot2SrvPowerOn
5:2015 May 12 18:08:31:BMC:kernel:--<5>[__do_power_on]:375:
Power Driver: Power On Logic Done @ 2516427846
5:2015 May 12 18:08:31:BMC:BIOSReader:1247: BIOSReader.c:242:File Open : BiosTech_7.txt
5:2015 May 12 18:08:31:BMC:BIOSReader:1247: BIOSReader.c:748:File Close
: /var/nuova/BIOS/BiosTech_7.txt
5:2015 May 12 18:08:31:BMC:kernel:--<5>[block_transfer_fetch_host_request_for_app]
:1860:block_transfer_fetch_host_request_for_app: BT_OPEN_FOR_READ:
HostDescriptor = 1406 : Filename = BiosTech_7.txt
5:2015 May 12 18:08:31:BMC:kernel:--<5>[block_transfer_fetch_host_request_for_app]
:1944:block_transfer_fetch_host_request_for_app : BT_FILE_CLOSE :
HostBTDescr = 1406 : FName = BiosTech_7.txt
5:2015 May 12 18:08:32:BMC:kernel:--<5>[block_transfer_fetch_host_request_for_app]
:1860:block_transfer_fetch_host_request_for_app: BT_OPEN_FOR_READ:
HostDescriptor = 1408 : Filename = BiosTech_6.txt
5:2015 May 12 18:08:32:BMC:BIOSReader:1247: BIOSReader.c:242:File Open : BiosTech_6.txt
5:2015 May 12 18:08:32:BMC:BIOSReader:1247: BIOSReader.c:748:File Close
: /var/nuova/BIOS/BiosTech_6.txt
5:2015 May 12 18:08:32:BMC:kernel:--<5>[block_transfer_fetch_host_request_for_app]
:1944:block_transfer_fetch_host_request_for_app : BT_FILE_CLOSE :
HostBTDescr = 1408 : FName = BiosTech_6.txt
5:2015 May 12 18:08:32:BMC:video_trigger:--: video_trigger.c:262:Sending
event_ipmi_power_state_change (ON) ..
5:2015 May 12 18:08:32:BMC:video_trigger:--: video_trigger.c:137:Sending
event_server_boot_start..
5:2015 May 12 18:08:32:BMC:video_trigger:--: video_trigger.c:148:
Will be able to send event_server_crash..
5:2015 May 12 18:08:32:BMC:selparser:1602: selparser.c:678:
# 13 04 00 00 01 02 00 00 A0 41 52 55 2C 60 04 DC 1A 00 00 00 74 07 00 00
# 413 | 05/12/2015 18:08:32 | Unknown
#0x602c | Unknown #0x1a |
5:2015 May 12 18:08:32:BMC:selparser:1602: selparser.c:678:
# 14 04 00 00 01 02 00 00 A0 41 52 55 20 00 04 25 00 00 00 00 08 00 FF FF
# 414 | 05/12/2015 18:08:32 | CIMC | Entity presence BIOS_POST_CMPLT
#0x00 | Device Absent | Asserted
5:2015 May 12 18:08:32:BMC:kernel:--<5>[block_transfer_fetch_host_request_for_app]
:1860:block_transfer_fetch_host_request_for_app: BT_OPEN_FOR_READ:
HostDescriptor = 1410 : Filename = BiosTech_5.txt
5:2015 May 12 18:08:32:BMC:kernel:--<5>[block_transfer_fetch_host_request_for_app]
:1944:block_transfer_fetch_host_request_for_app : BT_FILE_CLOSE :
HostBTDescr = 1410 : FName = BiosTech_5.txt
5:2015 May 12 18:08:32:BMC:BIOSReader:1247: BIOSReader.c:242:File Open : BiosTech_5.txt
```

## CIMC からの電源再投入

### OBFL ログ

```
5:2015 May 12 19:18:45:BMC:kernel:--<5>[do_cycle]:560:do_cycle
5:2015 May 12 19:18:45:BMC:IPMI:1563: Bridge.c:1478:audit from:kcs Fn:0x0
Cmd:0x2 Data&colon; 0x2
5:2015 May 12 19:18:45:BMC:kernel:--<5>[__do_power_off]:298:__do_power_off
```

5:2015 May 12 19:18:45:BMC:IPMI:1563: Bridge.c:1484:audit Resp:0x0  
5:2015 May 12 19:18:45:BMC:kernel:--<5>[**\_\_do\_power\_off**]:300:Power Driver:  
**Power Off Logic @ 2520641182**  
5:2015 May 12 19:18:45:BMC:IPMI:1566: **Pilot3SrvPower.c:539:**  
**Pilot2SrvPowerCycle**  
5:2015 May 12 19:18:45:BMC:AUDIT:20723: **Server power state modify**  
**(op:power-cycle)**  
5:2015 May 12 19:18:49:BMC:kernel:--<5>[**lpc\_reset\_isr\_handler**]:  
**79:LPC Reset ISR -> ResetState: 1**  
5:2015 May 12 19:18:49:BMC:kernel:--<5>[readPostData]:519:  
BIOS\_POST\_CMPLT Asserted --> BIOS has completed  
5:2015 May 12 19:18:49:BMC:kernel:--<5>drivers/bmc/usb/  
usb1.1/se\_pilot2\_udc\_usb1\_1.c:2288:USB FS: VDD Power WAKEUP- Power Good = OFF  
5:2015 May 12 19:18:49:BMC:kernel:--<5>[se\_pilot2\_wakeup\_interrupt]  
:2561:USB HS: VDD Power = OFF  
5:2015 May 12 19:18:49:BMC:video\_trigger:-- video\_trigger.c:262:  
Sending event\_ipmi\_power\_state\_change (OFF) ..  
5:2015 May 12 19:18:49:BMC:IPMI:1532: **Pilot3SrvPower.c:484:**  
**Blade Power Changed To: [ OFF ]**  
5:2015 May 12 19:18:49:BMC:selparser:1602: selparser.c:678:  
# 1A 04 00 00 01 02 00 00 19 52 52 55 20 00 04 25 A9 00 00 00 08 00 FF FF  
# 41a | 05/12/2015 19:18:49 | CIMC | Entity presence MAIN\_POWER\_PRS #0xa9  
| Device Absent | Asserted  
5:2015 May 12 19:18:55:BMC:selparser:1602: selparser.c:678:  
# 1B 04 00 00 01 02 00 00 1E 52 52 55 2C 60 04 DC 1A 00 00 00 74 03 00 00  
# 41b | 05/12/2015 19:18:54 | Unknown #0x602c | Unknown #0x1a |  
5:2015 May 12 19:18:55:BMC:selparser:1602: selparser.c:678:  
# 1C 04 00 00 01 02 00 00 1E 52 52 55 2C 60 04 16 16 00 00 00 0A 00 00 00  
# 41c | 05/12/2015 19:18:54 | Unknown  
#0x602c | Microcontroller/Coprocessor  
#0x16 | Transition to Running | Asserted  
5:2015 May 12 19:19:05:BMC:kernel:--<5>[**\_\_do\_power\_on**]:340:**\_\_do\_power\_on**  
5:2015 May 12 19:19:05:BMC:kernel:--<5>[**\_\_do\_power\_on**]:345:  
**Power Driver: Power On Logic Pulse**for 250ms @ 2520661694  
5:2015 May 12 19:19:05:BMC:kernel:--<5>drivers/bmc/usb/usb1.1/  
se\_pilot2\_udc\_usb1\_1.c:2288:USB FS: VDD Power WAKEUP- Power Good = ON  
5:2015 May 12 19:19:05:BMC:kernel:--<5>[se\_pilot2\_wakeup\_interrupt]  
:2561:USB HS: VDD Power = ON  
5:2015 May 12 19:19:05:BMC:kernel:--<5>[se\_pilot2\_udc\_usb\_connect]:  
2685:Failed USB2.0 register test  
5:2015 May 12 19:19:05:BMC:kernel:--<5>[se\_pilot2\_udc\_usb\_connect]:  
2685:Failed USB2.0 register test  
5:2015 May 12 19:19:05:BMC:kernel:--<5>[**lpc\_reset\_isr\_handler**]  
**:79:LPC Reset ISR -> ResetState: 0**  
5:2015 May 12 19:19:05:BMC:kernel:--<5>[lpc\_reset\_handler\_Port80\_Capture\_setup]  
:560:BIOS\_POST\_CMPLT De-asserted --> BIOS is running  
5:2015 May 12 19:19:05:BMC:IPMI:1566: **Pilot3SrvPower.c:542:Pilot2SrvPowerCycle**  
5:2015 May 12 19:19:05:BMC:kernel:--<5>[**\_\_do\_power\_on**]  
**:375:Power Driver: Power On Logic Done @ 2520661945**  
5:2015 May 12 19:19:05:BMC:IPMI:1566: **Pilot3SrvPower.c:481:**  
**-> Power State On: LPC RESET is NOT IN RESET; powerOnLPCOff[2]**  
5:2015 May 12 19:19:05:BMC:IPMI:1566: **Pilot3SrvPower.c:484:**  
**Blade Power Changed To: [ ON ]**  
5:2015 May 12 19:19:06:BMC:BIOSReader:1247: BIOSReader.c:242:  
File Open : BiosTech\_7.txt  
5:2015 May 12 19:19:06:BMC:BIOSReader:1247: BIOSReader.c:748:  
File Close : /var/nuova/BIOS/BiosTech\_7.txt  
5:2015 May 12 19:19:06:BMC:kernel:--<5>[block\_transfer\_fetch\_host\_  
request\_for\_app]:1860:block\_transfer\_fetch\_host\_request\_for\_app:  
BT\_OPEN\_FOR\_READ: HostDescriptor = 1466 : Filename = BiosTech\_7.txt  
5:2015 May 12 19:19:06:BMC:kernel:--<5>[block\_transfer\_fetch\_host\_  
request\_for\_app]:1944:block\_transfer\_fetch\_host\_request\_for\_app :  
BT\_FILE\_CLOSE : HostBTDescr = 1466 : FName = BiosTech\_7.txt  
5:2015 May 12 19:19:06:BMC:selparser:1602: selparser.c:678:

```
# 1D 04 00 00 01 02 00 00 29 52 52 55 2C 60 04 DC 1A 00 00 00 74 07 00 00
# 41d | 05/12/2015 19:19:05 | Unknown #0x602c | Unknown #0x1a |
5:2015 May 12 19:19:06:BMC:video_trigger--: video_trigger.c:262:
Sending event_ipmi_power_state_change (ON) ..
5:2015 May 12 19:19:06:BMC:video_trigger--: video_trigger.c:137:
Sending event_server_boot_start ..
5:2015 May 12 19:19:06:BMC:video_trigger--: video_trigger.c:148:
Will be able to send event_server_crash ..
5:2015 May 12 19:19:06:BMC:kernel--:<5>[block_transfer_fetch_host_
request_for_app]:1860:block_transfer_fetch_host_request_for_app:
BT_OPEN_FOR_READ: HostDescriptor = 1468 : Filename = BiosTech_6.txt
```

## CIMC からの電源切断

### OBFL ログ

```
5:2015 May 12 20:18:25:BMC:kernel--:<5>[__do_power_off]:298:__do_power_off
5:2015 May 12 20:18:25:BMC:IPMI:1563: Bridge.c:1478:audit from:kcs Fn:0x0
Cmd:0x2 Data&colon; 0x0
5:2015 May 12 20:18:25:BMC:kernel--:<5>[__do_power_off]:300:Power Driver:
Power Off Logic@ 2524221543
5:2015 May 12 20:18:25:BMC:IPMI:1563: Bridge.c:1484:audit Resp:0x0
5:2015 May 12 20:18:25:BMC:AUDIT:20723: Server power state modify (op:power-off)
5:2015 May 12 20:18:30:BMC:kernel--:<5>[lpc_reset_isr_handler]:
79:LPC Reset ISR -> ResetState: 1
5:2015 May 12 20:18:30:BMC:kernel--:<5>[readPostData]:519:BIOS_POST_CMPLT
Asserted --> BIOS has completed
5:2015 May 12 20:18:30:BMC:kernel--:<5>drivers/bmc/usb/usb1.1/se_pilot2_udc_
usb1_1.c:2288:USB FS: VDD Power WAKEUP- Power Good = OFF
5:2015 May 12 20:18:30:BMC:IPMI:1567: Pilot3SrvPower.c:484:Blade Power Changed To: [ OFF ]
5:2015 May 12 20:18:30:BMC:kernel--:<5>[se_pilot2_wakeup_interrupt]:
2561:USB HS: VDD Power = OFF
5:2015 May 12 20:18:30:BMC:selparser:1602: selparser.c:678:
# 24 04 00 00 01 02 00 00 16 60 52 55 20 00 04 25 A9 00 00 00 08 00 FF FF
# 424 | 05/12/2015 20:18:30 | CIMC | Entity presence MAIN_POWER_PRS
#0xa9 | Device Absent | Asserted
5:2015 May 12 20:18:30:BMC:video_trigger--: video_trigger.c:262:
Sending event_ipmi_power_state_change (OFF) ..
5:2015 May 12 20:18:31:BMC:vkcs_mux:1582: vkcs_mux.c:76:[REQ] 00 01
5:2015 May 12 20:18:36:BMC:IPMI:1566: Pilot3SrvPower.c:348:Pilot2SrvPowerOff
5:2015 May 12 20:18:37:BMC:kernel--:<5>[__do_power_off]:298:__do_power_off
5:2015 May 12 20:18:37:BMC:blade-power:11311: host-power.c:53:POWER Off
5:2015 May 12 20:18:38:BMC:run-update:11313: ../..
/src/runupdate.c:511:Run-update Process Starting.
5:2015 May 12 20:18:38:BMC:run-update:11313: ../..
/src/runupdate.c:44:Setting FP Button Lock: current state 0
5:2015 May 12 20:18:38:BMC:kernel--:<5>[lock_front_panel_buttons]
:1373:Front Panel Power Button is now permanently locked.
5:2015 May 12 20:18:38:BMC:kernel--:<5>[lock_front_panel_buttons]
:1378:Front Panel Reset Button is now permanently locked.
```

## PSU 障害からの電力損失

### OBFL ログ

```
5:2015 May 15 14:29:12:BMC:kernel--:<5>[lpc_reset_isr_handler]:
79:LPC Reset ISR -> ResetState: 1
5:2015 May 15 14:29:12:BMC:kernel--:<5>[readPostData]:519:
BIOS_POST_CMPLT Asserted --> BIOS has completed
5:2015 May 15 14:29:12:BMC:kernel--:<5>drivers/bmc/usb/usb1.1/
```

```
se_pilot2_udc_usb1_1.c:2288:USB FS: VDD Power WAKEUP- Power Good = OFF
5:2015 May 15 14:29:12:BMC:kernel:--<5>[se_pilot2_wakeup_interrupt]
:2561:USB HS: VDD Power = OFF
5:2015 May 15 14:29:12:BMC:IPMI:1532: Pilot3SrvPower.c:484:
Blade Power Changed To: [ OFF ]
5:2015 May 15 14:29:12:BMC:video_trigger--: video_trigger.c:262:
Sending event_ipmi_power_state_change (OFF) ..
5:2015 May 15 14:29:13:BMC:selparser:1602: selparser.c:678:
# 33 04 00 00 01 02 00 00 B8 02 56 55 20 00 04 08 27 00 00 00 03 00 FF FF
# 433 | 05/15/2015 14:29:12 | CIMC | Power supply PSU1_AC_OK
#0x27 | State Deasserted | Asserted
5:2015 May 15 14:29:13:BMC:selparser:1602: selparser.c:678:
# 34 04 00 00 01 02 00 00 B8 02 56 55 20 00 04 08 42 00 00 00 04 01 FF FF
# 434 | 05/15/2015 14:29:12 | CIMC | Power supply PMBUS_ALERT #0x42
| Predictive Failure asserted | Asserted
5:2015 May 15 14:29:13:BMC:selparser:1602: selparser.c:678:
# 35 04 00 00 01 02 00 00 B8 02 56 55 20 00 04 25 A9 00 00 00 08 00 FF FF
# 435 | 05/15/2015 14:29:12 | CIMC | Entity presence MAIN_POWER_PRS
#0xa9 | Device Absent | Asserted
5:1970 Jan 1 00:02:48:BMC:kernel:--<5>Linux version 2.6.35.10
(buildsa@savbu-swbmc-vb1) (gcc version 3.4.5)
#2 Tue Nov 18 07:09:13 PST 2014 Unversioned directory
4:1970 Jan 1 00:02:48:BMC:kernel:--<4>CPU: ARM926EJ-S [41069265]
revision 5 (ARMv5TEJ), cr=00053177
4:1970 Jan 1 00:02:48:BMC:kernel:--<4>CPU: VIVT data cache, VIVT instruction cache
4:1970 Jan 1 00:02:48:BMC:kernel:--<4>Machine: ServerEngines PILOT3 Hornet Board
4:1970 Jan 1 00:02:48:BMC:kernel:--<4>Memory policy: ECC disabled, Data cache writeback
```

## 前面電源オフ ボタン

## OBFL ログ

```
5:2015 May 15 14:50:19:BMC:kernel:--<5>[passthrough_pin2_isr]:158:x86
Host Power Button Press
5:2015 May 15 14:50:19:BMC:kernel:--<5>drivers/bmc/usb/usb1.1/se_pilot2_udc_
usb1_1.c:2288:USB FS: VDD Power WAKEUP- Power Good = ON
5:2015 May 15 14:50:19:BMC:kernel:--<5>[se_pilot2_wakeup_interrupt]:2561:
USB HS: VDD Power = ON
5:2015 May 15 14:50:31:BMC:IPMI:1561: Bridge.c:1478:audit from:kcs Fn:0x6
Cmd:0x6 Data&colon; 0x85 0x83
5:2015 May 15 14:50:31:BMC:IPMI:1561: Bridge.c:1484:audit Resp:0x0
5:2015 May 15 14:50:35:BMC:kernel:--<5>[lpc_reset_isr_handler]
:79:LPC Reset ISR -> ResetState: 1
5:2015 May 15 14:50:35:BMC:kernel:--<5>[readPostData]:519:BIOS_POST_CMPLT
Asserted --> BIOS has completed
5:2015 May 15 14:50:35:BMC:video_trigger--: video_trigger.c:262:
Sending event_ipmi_power_state_change (OFF) ..
5:2015 May 15 14:50:35:BMC:kernel:--<5>drivers/bmc/usb/usb1.1/se_pilot2_udc_
usb1_1.c:2288:USB FS: VDD Power WAKEUP- Power Good = OFF
5:2015 May 15 14:50:35:BMC:kernel:--<5>[se_pilot2_wakeup_interrupt]:
2561:USB HS: VDD Power = OFF
5:2015 May 15 14:50:35:BMC:IPMI:1531: Pilot3SrvPower.c:484:
Blade Power Changed To: [ OFF ]
5:2015 May 15 14:50:35:BMC:selparser:1602: selparser.c:678:
# A2 04 00 00 01 02 00 00 BB 07 56 55 2C 60 04 DC 1A 00 00 00 F4 03 00 00
# 4a2 | 05/15/2015 14:50:35 | Unknown #0x602c | Unknown #0x1a |
5:2015 May 15 14:50:35:BMC:selparser:1602: selparser.c:678:
# A3 04 00 00 01 02 00 00 BB 07 56 55 20 00 04 25 A9 00 00 00 08 00 FF FF
# 4a3 | 05/15/2015 14:50:35 | CIMC | Entity presence MAIN_POWER_PRS
#0xa9 | Device Absent | Asserted
```

## 前面電源オン ボタン

## OBFL ログ

```
5:2015 May 15 14:51:18:BMC:kernel:-:<5>[passthrough_pin2_isr]
:158:x86 Host Power Button Press
5:2015 May 15 14:51:18:BMC:kernel:-:<5>drivers/bmc/usb/usbl1.1/se_pilot2
_udc_usbl1.c:2288:USB FS: VDD Power WAKEUP- Power Good = OFF
5:2015 May 15 14:51:18:BMC:kernel:-:<5>[se_pilot2_wakeup_interrupt]:
2561:USB HS: VDD Power = OFF
5:2015 May 15 14:51:19:BMC:kernel:-:<5>drivers/bmc/usb/usbl1.1/se_pilot2_
udc_usbl1.c:2288:USB FS: VDD Power WAKEUP- Power Good = ON
5:2015 May 15 14:51:19:BMC:kernel:-:<5>[se_pilot2_wakeup_interrupt]
:2561:USB HS: VDD Power = ON
5:2015 May 15 14:51:19:BMC:kernel:-:<5>[se_pilot2_udc_usb_connect]:
2685:Failed USB2.0 register test
5:2015 May 15 14:51:19:BMC:kernel:-:<5>[se_pilot2_udc_usb_connect]:
2685:Failed USB2.0 register test
5:2015 May 15 14:51:19:BMC:kernel:-:<5>[lpc_reset_isr_handler]:
79:LPC Reset ISR -> ResetState: 0
5:2015 May 15 14:51:19:BMC:kernel:-:<5>[lpc_reset_handler_Port80_Capture_setup]
:560:BIOS_POST_CMPLT De-asserted --> BIOS is running
5:2015 May 15 14:51:19:BMC:IPMI:1561: Pilot3SrvPower.c:481: ->
Power State On: LPC RESET is NOT IN RESET; powerOnLPCoff[0]
5:2015 May 15 14:51:19:BMC:IPMI:1561: Pilot3SrvPower.c:484:
Blade Power Changed To: [ ON ]
5:2015 May 15 14:51:19:BMC:BIOSReader:1247: BIOSReader.c:242:File Open : BiosTech_7.txt
5:2015 May 15 14:51:19:BMC:BIOSReader:1247: BIOSReader.c:242:File Open : BiosTech_6.txt
5:2015 May 15 14:51:19:BMC:kernel:-:<5>[block_transfer_fetch_host_request_for_app]
:1860:block_transfer_fetch_host_request_for_app: BT_OPEN_FOR_READ:
HostDescriptor = 118 : Filename = BiosTech_7.txt
5:2015 May 15 14:51:19:BMC:BIOSReader:1247: BIOSReader.c:242:File Open : BiosTech_5.txt
5:2015 May 15 14:51:19:BMC:kernel:-:<5>[block_transfer_fetch_host_request_for_app]
:1860:block_transfer_fetch_host_request_for_app: BT_OPEN_FOR_READ:
HostDescriptor = 119 : Filename = BiosTech_6.txt
5:2015 May 15 14:51:19:BMC:BIOSReader:1247: BIOSReader.c:242:File Open : BiosTech_4.txt
5:2015 May 15 14:51:19:BMC:BIOSReader:1247: BIOSReader.c:748:
File Close : /var/nuova/BIOS/BiosTech_4.txt
5:2015 May 15 14:51:19:BMC:kernel:-:<5>[block_transfer_fetch_host_request_for_app]
:1860:block_transfer_fetch_host_request_for_app: BT_OPEN_FOR_READ:
HostDescriptor = 120 : Filename = BiosTech_5.txt
5:2015 May 15 14:51:19:BMC:kernel:-:<5>[block_transfer_fetch_host_request_for_app]
:1860:block_transfer_fetch_host_request_for_app: BT_OPEN_FOR_READ:
HostDescriptor = 121 : Filename = BiosTech_4.txt
5:2015 May 15 14:51:19:BMC:kernel:-:<5>[block_transfer_fetch_host_request_for_app]
:1944:block_transfer_fetch_host_request_for_app : BT_FILE_CLOSE :
HostBTDescr = 121 : FName = BiosTech_4.txt
5:2015 May 15 14:51:19:BMC:video_trigger:-: video_trigger.c:262:
Sending event_ipmi_power_state_change (ON) ..
5:2015 May 15 14:51:19:BMC:video_trigger:-: video_trigger.c:137:
Sending event_server_boot_start ..
5:2015 May 15 14:51:19:BMC:video_trigger:-: video_trigger.c:148
:Will be able to send event_server_crash ..
5:2015 May 15 14:51:19:BMC:kernel:-:<5>[block_transfer_fetch_host_request_for_app]
:1860:block_transfer_fetch_host_request_for_app: BT_OPEN_FOR_READ:
HostDescriptor = 123 : Filename = BiosTech_3.txt
5:2015 May 15 14:51:19:BMC:BIOSReader:1247: BIOSReader.c:242:File Open : BiosTech_3.txt
5:2015 May 15 14:51:19:BMC:kernel:-:<5>[block_transfer_fetch_host_request_for_app]
:1944:block_transfer_fetch_host_request_for_app : BT_FILE_CLOSE :
HostBTDescr = 123 : FName = BiosTech_3.txt
5:2015 May 15 14:51:19:BMC:BIOSReader:1247: BIOSReader.c:748:
File Close : /var/nuova/BIOS/BiosTech_3.txt
```

## 関連情報

- [Cシリーズはトラブルシューティングをリポートします](#)
- [テクニカル サポートとドキュメント - Cisco Systems](#)