

# Nutanix (CCHC + N) を使用 した Cisco コンピューティン グハイパーコンバージド X シ リーズ M8 の発注ガイド

## はじめに

### Nutanix ソリューションを使用した Cisco コンピューティング ハイパーコンバージド X シリーズ M8 サーバー

Nutanix を使用した Cisco コンピューティング ハイパーコンバージドは、Cisco クラス最高のコンピューティング (X シリーズ モダルシステム) 、データセンター ネットワーキング、および SaaS インフラストラクチャ管理プラットフォーム (Cisco Intersight) と、市場をリードする Nutanix のハイパーコンバージドストレージ ソフトウェアである Nutanix Cloud Platform を統合したハイパーコンバージドインフラストラクチャソリューションです。Nutanix を使用した Cisco Compute Hyperconverged ファミリびアプライアンスは、さまざまな構成で Nutanix クラスタ経由でノードとして展開可能な事前構成された X シリーズ サーバーをお届けします。各サーバー アプライアンスには、X シリーズ サーバ フームウェア、ハイパーバイザ (Nutanix AHV) 、およびハイパーコンバージドストレージ ソフトウェア (Nutanix AOS) の 3 つのソフトウェアレイヤが含まれています。

### Nutanix クラスタを使用した Cisco コンピューティング ハイパーコンバージド M8 サーバー

Cisco コンピューティング ハイパーコンバージド X シリーズ モジュラ システムは、データセンターを簡素化し、最新のアプリケーションの予測不可能なニーズに対応すると同時に、従来のスケールアウトやエンタープライズワークロードにも対応します。維持するサーバ タイプの数が減り、運用の効率性と俊敏性が向上し、複雑さが軽減されます。Cisco UCS X シリーズには Cisco Intersight™ クラウド運用プラットフォームが搭載されているため、思考の矛先を管理からビジネス成果へと変えることができます。使用するハイブリッドクラウドインフラストラクチャは、クラウドからワークロードに合わせて組み合わせて成形し、継続的に最適化できます。

## 目的、対象者、範囲

### 目的

このマニュアルでは、CCW 見積書の作成から Nutanix を使用した Cisco Compute Hyperconverged の発注に関する情報を提供します。

### 対象範囲


この発注ガイドでは、以下に関する情報について説明します。

- Nutanix を使用した Cisco コンピューティング ハイパーコンバージド X シリーズ M8 サーバーの注文構造
- Cisco コンピューティング ハイパーコンバージド X シリーズ M8 サーバーの製品 ID のカタログ
- Nutanix ハードウェア、ソフトウェアライセンス、およびプロフェッショナル サービスのオプションの注文
- その他の技術情報へのリンク

### 対象読者

Cisco セールス チームとパートナー。

# Nutanix を使用した Cisco コンピューティング ハイパーコンバージド X シリーズ M8 サーバーの注文構造



## 製品 ID (PID) カタログ

注： 部品番号の完全なリストについては、[Cisco Compute Hyperconverged with Nutanix-HCIX210c M8 All-NVMe Node](#)、[Cisco Compute Hyperconverged with Nutanix-HCIXNX215c M8 All-NVMe Node](#)、[Cisco Compute Hyperconverged 9508 Chassis](#)、および[Cisco Compute Hyperconverged X440p PCIe Node](#) の仕様シートを参照してください。

注： ハードウェアの発注により、IMM ソフトウェアのサポートに合わせて、ベアメタルの Cisco コンピューティング ハイパーコンバージド X シリーズ サーバー (HCI SKU) が出荷されます (以下を参照)。

表 1. 主要ラインのバンドル (MLB) の PID

製品 ID (PID)	説明
HCIX-M8-NTNX-MLB	Nutanix MLB を使用した Cisco コンピューティング ハイパーコンバージド X シリーズ M8

製品 ID (PID)	説明
	このメジャー ラインバンドル (MLB) は、Cisco コンピューティング ハイパーコンバージド サーバーと、Intersight および Nutanix ソフトウェア PID で構成されます。

表 2. 表 3Cisco コンピューティング ハイパーコンバージド シャーシ メジャー ライン PID

製品 ID (PID)	説明
HCIXNX-9508-U	Cisco Compute Hyperconverged 9508 シャーシの構成

表 3. Cisco Compute Hyperconverged サーバー ノード メジャー ライン PID

製品 ID (PID)	説明
HCIXNX210C-M8SN-U (All NVMe)	210c M8 All NVMe Hyperconverged Node CPU、メモリ、ストレージなし
HCIXNX215C-M8SN-U (All NVMe)	215c M8 All NVMe Hyperconverged Node CPU、メモリ、ストレージなし

表 4. Cisco コンピューティング ハイパーコンバージド PCIe ノードのメジャー ライン PID

製品 ID (PID)	説明
HCIX-440P-U	HCI X シリーズ第 4 世代の PCIe ノード

表 5. ファブリック インターコネクト メジャー ライン PID

製品 ID (PID)	説明
HCIX-FI-6536	Cisco Compute Hyperconverged ファブリック インターコネクト 6536
HCIX-FI-64108	Cisco Compute Hyperconverged ファブリック インターコネクト 64108
HCIX-FI-6454	Cisco Compute Hyperconverged ファブリック インターコネクト 6454

表 6. Cisco Intersight メジャー ライン PID

製品 ID (PID)	説明
DC-MGT-SAAS	Cisco Intersight SaaS
CNDL-DESELECT-D	条件付き選択解除

## ステップバイステップの発注プロセス

このセクションでは、Nutanix を使用した Cisco Compute Hyperconverged M8 Server に固有のパッケージと PID に関して詳細に記載します。また、Nutanix 製品を使用した Compute Hyperconverged M8 Server が含まれるその他の購入プログラムやサブスクリプション パッケージに関する参照情報も提供します。

ステップ 1. Web ブラウザを起動し、[Cisco Commerce 見積もり作成ページ](#)に移動します。

ステップ 2. Cisco のログイン画面で、使用する Cisco.com のユーザー ID とパスワードを入力します。

**ステップ 3.** [見積 (Estimates) ] ページで、SKU、PID、製品の説明、または製品ファミリー (HCIX-M8-MLB など) を入力して、この見積の基本設定を行い、注文する HCI 製品を検索します。

注：

- 製品の設定に進む前に、Nutanix Sizer Tool ( <https://sizer.nutanix.com/#/home> ) を参照してください。

## ハードウェア コンポーネントの構成


**ステップ 4.**

The screenshot shows the CCW interface with a search result for the product 'HCIX-M8-NTNX-MLB'. The search bar at the top contains 'HCIX-M8-NTNX-MLB'. Below the search bar, there are various configuration options and a table of search results. The table has columns for Estimated Lead Time (Days), Unit List Price (USD), Qty, Unit Net Price (USD), Discounts (%), and Extended Net Price (USD). One row is selected, showing 'Not Applicable' for Estimated Lead Time, '0.00' for Unit List Price, '1' for Qty, '0.00' for Unit Net Price, '0.00' for Discounts, and '0.00' for Extended Net Price. A red box labeled 'a' highlights the search bar, and another red box labeled 'b' highlights the 'Select Options' button at the bottom of the table row.

Hardware, Software and Services	Estimated Lead Time (Days)	Unit List Price (USD)	Qty	Unit Net Price (USD)	Discounts (%)	Extended Net Price (USD)
1.0 HCIX-M8-NTNX-MLB   Invalid as of 21-Jul-2025 01:42:03 PDT Cisco Compute Hyperconverged X-Series M8 with Nutanix MLB	Not Applicable	0.00	1	0.00	0.00	0.00

- CCW で MLB PID を検索して、[追加 (Add) ] をクリックします。
- Configurator を入力するため、[オプションの選択 (Select Options) ] をクリックします。

**ステップ 5.**



- MLB の下で「PLUS」をクリックすることで、HCIXNX-9508-U ATO を検索します。
- さらに構成が必要なため、HCIXNX-9508-U ATO ステータスが無効であることを通知します。
- Configurator を入力するために、[オプションの編集 (Edit Option) ] をクリックします。

## ステップ 6.

**HCI X 9500 Chassis**

Product Configuration  
HCIXNX-9508-U part of HCIX-M8-NTNX-MLB

Estimated Lead Time  
21 days

**HCIXNX-9508-U**

Price List  
Global Price

Total (USD)  
10,783.64

**Server Node**

**IFM/FIM**

**Power Supply**

**Configuration Summary** [View Full Summary](#)

**Country/Region Specification** [View Details](#)

Select Country/Region (Not Required)

Category	Qty	Extended List Price (USD)
<b>Compute Node</b> <span style="color: red;">⚠</span>		
Fabric Interconnect Module		
Intelligent Fabric Module		
X-Fabric Module		
Accessory		
Power Supply		
HCIX-PSU-2800AC	2	2,252.68
Power Cable		
X-Series Chassis SW		
<b>Total</b>		10,783.64
<b>Estimated Lead Time</b>		21 days

Reset Configuration [Cancel](#) [Done](#)

**Option Search** [Multiple Options Search](#)

**HCIXNX-9508-U > Compute Node**

**Compute Node**

SKU	Estimated Lead Time	Unit List Price (USD)
HCIXNX210C-M8SN <span style="color: green;">P&amp;H</span>	21 days	7,612.70
HCIXNX215C-M8SN <span style="color: green;">P&amp;H</span>	21 days	8,542.50

Show Incompatible SKUs

- 左側のカテゴリ ウィンドウから【コンピューティング ノード（Compute Node）】、【ファブリック インターコネクト モジュール（Fabric Interconnect Module）】、または【インテリジェント ファブリック モジュール、電源モジュール、電源ケーブル（Power Supply and Power Cables）】を選択して、**HCIXNX-9508-U** を設定します。
- 警告メッセージに従って、「シャーシ」の下で最小の必要な選択を構成します。

## ステップ 7.

**HCI X 9500 Chassis**

Product Configuration  
HCIXNX-9508-U part of HCIX-M8-NTNX-MLB

Estimated Lead Time  
21 days

Price List  
Global

Total (USD)  
18,396.34

**Configuration Summary**

**Country/Region Specification**

**Compute Node**

Category	Qty	Extended List Price (USD)
HCIXNX210C-M8SN	1	7,612.70
HCIX-X10C-PTE3	1	0.00
HCIX-AOSAHV-73SWK9	1	0.00
HCIX-TPM-002D	1	0.00
HCIX-C-SW-LATEST	1	0.00
UCS-DDR5-BLK	32	0.00
UCSX-M8I-HS-F	1	0.00
UCSC-E3ST-F	9	0.00
UCSX-M2I-HWRD-FPS	1	0.00
<b>Total</b>		<b>18,396.34</b>
<b>Estimated Lead Time</b>		<b>21 days</b>

**Reset Configuration**   **Cancel**   **Done**

**Option Search**   **Multiple Options Search**

**Compute Node**

SKU	Custom Name	Qty:	Unit List Price (USD)
<input checked="" type="checkbox"/> HCIXNX210C-M8SN (1)	Add Custom Name	1	7,612.70
<input type="checkbox"/> HCIXNX215C-M8SN (1)			8,542.50

**Show Incompatible SKUs**

**a** 1: A selection from either Fabric Interconnect Module or Intelligent Fabric Module is required. Please adjust the selections. (CE200069)  
 2: The quantity of Power Cable must be equal to the quantity of Power Supply selected. Please adjust the quantity. (CE200050)  
 3: Use Power Calculator to determine the correct power supply. The Power Calculator can be found at <http://ucspowercalc.cisco.com>. (CE200696)  
 4: It is recommended that the user purchase Debug Cable: HCIX-C-DEBUGCBL. (CE202155)

**b**

a. HCIXNX210C-M8SN および/または HCIXNX215C-M8SN は選択が必須で、さらに設定可能です。

b. 警告メッセージに従って、「サーバー」の下で最小の必要な構成を行います。

#### ステップ 8.

**HCI X 9500 Chassis**

Product Configuration  
HCIXNX-9508-U part of HCIX-M8-NTNX-MLB

Estimated Lead Time  
21 days

Price List  
Global

Total (USD)  
26,009.04

**Configuration Summary**

**Country/Region Specification**

**Compute Node**

Category	Qty	Extended List Price (USD)
UCSC-E3ST-F	9	0.00
UCSX-M2I-HWRD-FPS	1	0.00
HCIXNX210C-M8SN (2)	1	7,612.70
HCIX-X10C-PTE3	1	0.00
HCIX-AOSAHV-73SWK9	1	0.00
HCIX-TPM-002D	1	0.00
HCIX-C-SW-LATEST	1	0.00
UCS-DDR5-BLK	32	0.00
UCSX-M8I-HS-F	1	0.00
UCSC-E3ST-F	9	0.00
<b>Total</b>		<b>26,009.04</b>
<b>Estimated Lead Time</b>		<b>21 days</b>

**Reset Configuration**   **Cancel**   **Done**

**Option Search**   **Multiple Options Search**

**Compute Node**

SKU	Custom Name	Qty:	Unit List Price (USD)
<input checked="" type="checkbox"/> HCIXNX210C-M8SN (1)	Add Custom Name	1	7,612.70
<input checked="" type="checkbox"/> HCIXNX210C-M8SN (2)	Add Custom Name	1	7,612.70
<input type="checkbox"/> HCIXNX215C-M8SN (1)			8,542.50

**Show Incompatible SKUs**

**a** 1: A selection from either Fabric Interconnect Module or Intelligent Fabric Module is required. Please adjust the selections. (CE200069)  
 2: The quantity of Power Cable must be equal to the quantity of Power Supply selected. Please adjust the quantity. (CE200050)  
 3: Please note that with GRID (N+N) Power Redundancy, minimum of 4 QTY of Power Supply is required. (CE202322)  
 4: Use Power Calculator to determine the correct power supply. The Power Calculator can be found at <http://ucspowercalc.cisco.com>. (CE200696)

**b**

**c**

- サーバー : HCIXNX210C-M8SN は、ボックス内の数量を変更することで複数の数量で選択することも、【新規追加】ボタンをクリックして同じシャーシ内で異なる設定を行うこともできます。
- この例では、各 1 個ずつサーバーを選択して 2 インスタンスがあります。
- 左側のサーバー PID をクリックして、特定のインスタンスを構成します。

#### ステップ 9.

**HCIXNX-9508-U**

**Server Node**

**IFM/FIM**

**Power Supply**

**HCIXNX210C-M8SN (1)**

**HCIX-CPU-i6781P**

**Total (USD) 26,009.04**

**Estimated Lead Time 21 days**

**Reset Configuration**

**Copy Class**

**Select target classes for copy**

**HCIXNX210C-M8SN (2)**

**Yes** **No**

- 1 つのサーバー インスタンスの構成が別のインスタンスにコピーできます。ここに示すように右端の [コピー] ボタンをクリックします。
- 特定のインスタンスを選択し、[はい]をクリックします。

#### ステップ 10.

**HCI X 9500 Chassis**

Product Configuration			Estimated Lead Time	Total (USD)
HCIXNX-9508-U part of HCI-X-M8-NTNX-MLB	21 days	175,744.38		

**Configuration Summary** [View Full Summary](#)

**Country/Region Specification** [Select Country/Region \(Not Required\)](#)

Category	Qty	Extended List Price (USD)
Compute Node		
HCIXNX210C-MBSN	1	7,612.70
HCIX-CPU-I6730P	2	27,381.42
HCIX-MRX64G2RE5	16	73,678.56
HCIX-X10C-PTE3	1	0.00
HCIX-ML-V5D200GV2	1	1,959.75
HCIX-NVE13T8K1V	3	20,078.55
HCIX-M2-480G	2	1,675.70
HCIX-AOSAHV-73SWK9	1	0.00
<b>Total</b>		<b>175,744.38</b>
<b>Estimated Lead Time</b>		<b>21 days</b>

[Reset Configuration](#) [Cancel](#) [Done](#)

**Option Search** [Multiple Options Search](#)

HCIXNX-9508-U > Compute Node > Compute Node > HCIXNX210C-MBSN

80 - 86 Core Processors | 36 - 64 Core Processors | 24 - 32 Core Processors | 8 - 16 Core Processors | 210CM8 Memory 6400 | Rear MEZZ - MLOM/PCI | GPU PCIe Node | ESS Capacity Drives | 210CM8 Boot Drives | 210CM8 Security

This is an AI Capable product. May need AI Intent capture as part of purchase.

SKU	Qty	Estimated Lead Time	Unit List Price (USD)
HCIX-CPU-I6767P (AI-C)	Qty	21 days	32,288.44
Intel i6767P 2.2GHz/350W 64C/xxMB DDR5 6400MT/s			
HCIX-CPU-I6761P (AI-C)	Qty	21 days	24,095.78
Intel i6761P 2GHz/350W 64C/xxMB DDR5 6400MT/s			
HCIX-CPU-I6760P	Qty	21 days	29,544.79
Intel i6760P 2GHz/330W 64C/xxMB DDR5 6400MT/s			
HCIX-CPU-I6747P	Qty	21 days	24,944.60
Intel i6747P 2.5GHz/350W 48C/xxMB DDR5 6400MT/s			
HCIX-CPU-I6741P	Qty	21 days	15,831.97
Intel i6741P 2.4GHz/300W 48C/xxMB DDR5 6400MT/s			
HCIX-CPU-I6740P	Qty	21 days	17,781.57
Intel i6740P 1.9GHz/270W 48C/xxMB DDR5 6400MT/s			
HCIX-CPU-I6736P	Qty	21 days	14,265.87
Intel i6736P 2.0GHz/205W 36C/144MB DDR5 6400MT/s			

- a. AI 対応 PID を選択した場合、ユーザーは AI インテント オプション クラスから選択する必要があります。

## ステップ 11.

**HCI X 9500 Chassis**

Product Configuration			Estimated Lead Time	Total (USD)
HCIXNX-9508-U part of HCI-X-M8-NTNX-MLB	21 days	175,744.38		

**Configuration Summary** [View Full Summary](#)

**Country/Region Specification** [Select Country/Region \(Not Required\)](#)

Category	Qty	Extended List Price (USD)
AI Intent		
Compute Node		
HCIXNX210C-MBSN	1	7,612.70
HCIX-CPU-I6730P	2	27,381.42
HCIX-MRX64G2RE5	16	73,678.56
HCIX-X10C-PTE3	1	0.00
HCIX-ML-V5D200GV2	1	1,959.75
HCIX-NVE13T8K1V	3	20,078.55
HCIX-M2-480G	2	1,675.70
HCIX-AOSAHV-73SWK9	1	0.00
<b>Total</b>		<b>175,744.38</b>
<b>Estimated Lead Time</b>		<b>21 days</b>

[Reset Configuration](#) [Cancel](#) [Done](#)

**Option Search** [Multiple Options Search](#)

HCIXNX-9508-U > AI Intent

AI Intent [SKU](#)

SKU	Qty	Estimated Lead Time	Unit List Price (USD)
COMPUTE-AI	1	21 days	0.00
Compute Artificial Intelligence Use Case			
COMPUTE-OTHER	1	21 days	0.00
Compute Other Use Case			

[Show Incompatible SKUs](#)

- a. 適切な選択を行うことで、サーバーでAI機能を使用することを意図しているかどうかをシスコに伝えることができます。

## ステップ 12.

**HCIX X 9500 Chassis**

**HCIXNX210C-M8SN**

Estimated Lead Time: 21 days

Total (USD): 26,009.04

**Configuration Summary**

**Country/Region Specification**

**Category**

Category	Qty	Extended List Price (USD)
Compute Node		
HCIXNX210C-M8SN (1) <span style="color: yellow;">!</span>	1	7,612.70
HCIX-X10C-PTE3	1	0.00
HCIX-AOSAHV-73SWK9	1	0.00
HCIX-TPM-002D	1	0.00
HCIX-C-SW-LATEST	1	0.00
UCS-DDR5-BLK	32	0.00
UCSX-M8i-HS-F	1	0.00
UCSC-E351T-F	9	0.00
UCSX-M2i-HWRD-FPS	1	0.00
<b>Total</b>		<b>26,009.04</b>
<b>Estimated Lead Time</b>		<b>21 days</b>

**Reset Configuration**   **Cancel**   **Done** C

**Warning Messages:**

- 1: Compute Node quantity 1 allows Processor minimum of 1 and maximum of 2. Please correct the quantity of Processor. (CE100011)
- 2: A selection of either HCIX-ML-V5D200G/V2 or HCIX-ML-V5Q50G from Rear MEZZ - MLOM/PCI is required. Please adjust the selections. (CE200096)
- 3: Please note that Intersight Managed Mode(IMM) is the default deployment mode supported with HCI M8 modular servers. UCS Managed Mode (UMM) is not supported. (CE202322)
- 4: A selection from either Fabric Interconnect Module or Intelligent Fabric Module is required. Please adjust the selections. (CE200069)

- HCIXNX210C-M8SN を設定するには、右側のウィンドウにプロセッサ、メモリ、ドライブ、その他の周辺機器と PID が一覧表示されます。
- 警告メッセージに従って、最低限必要なオプション PID を構成します。
- 完了したら [完了 (Done) ] をクリックします。

## ステップ 13.

**HCIX-440P**

**Riser**

**GPU**

**Product Configuration:** HCIXNX-9508-U part of HCIX-M8-NTNX-MLB

**Estimated Lead Time:** 49 days

**Price List:** Global Price List in US Dollars (USD)

**Total (USD):** 154,099.52

**Configuration Summary:**

**Country/Region Specification:** Select Country/Region (Not Required)

**Category:** Qty Extended List Price (USD)

Compute Node		
HCIXNX210C-M8SN (1) <span style="color: red;">⚠</span>	1	7,612.70
HCIX-CPU-iB730P	2	27,381.42
HCIX-MRX64G2RE5	16	73,678.56
HCIX-X10C-PTE3 <span style="color: green;">✓</span>	1	0.00
HCIX-V5D200GV2	1	1,959.75
HCIX-440P <span style="color: red;">⚠</span> <span style="color: red;">b</span>	1	3,316.50
HCIX-NVE13T8K1V	3	20,078.55
HCIX-M2-480G	2	1,675.70
HCIX-AOSAHV-73SWK9 <span style="color: green;">✓</span>	1	0.00
<b>Total:</b>		<b>154,099.52</b>
<b>Estimated Lead Time:</b>		<b>49 days</b>

**SKU:** HCIX-440P a HCl X-Series Gen4 PCIe node

**Qty:** 1 **Estimated Lead Time:** 49 days **Unit List Price (USD):** 3,316.50

**Clear Selection | Show Incompatible SKUs**

**Reset Configuration** Cancel Done

a. コンピューティングノード：HCIXNX210C-M8SN で GPU PCIe ノード HCIX-440P を構成します。

b. 左側のウィンドウでさらに設定するには、[HCIX-440P] をクリックします。

#### ステップ 14.

**HCIX-440P**

**Riser**

**GPU**

**Product Configuration:** HCIXNX-9508-U part of HCIX-M8-NTNX-MLB

**Estimated Lead Time:** 49 days

**Price List:** Global Price List in US Dollars (USD)

**Total (USD):** 154,099.52

**Configuration Summary:**

**Country/Region Specification:** Select Country/Region (Not Required)

**Category:** Qty Extended List Price (USD)

HCIX-440P <span style="color: red;">⚠</span>	1	3,316.50
HCIX-NVE13T8K1V	3	20,078.55
HCIX-M2-480G	2	1,675.70
HCIX-AOSAHV-73SWK9 <span style="color: green;">✓</span>	1	0.00
HCIX-TPM-002D <span style="color: green;">✓</span>	1	0.00
HCIX-C-SW-LATEST <span style="color: green;">✓</span>	1	0.00
UCS-DDR5-BLK <span style="color: green;">✓</span>	16	0.00
UCSX-M8I-HS-F <span style="color: green;">✓</span>	1	0.00
UCSX-M8I-HS-R <span style="color: green;">✓</span>	1	0.00
<b>Total:</b>		<b>154,099.52</b>
<b>Estimated Lead Time:</b>		<b>49 days</b>

**SKU:** HCIX-RIS-A-440P a Riser A for 1x dual slot GPU per riser, 440P PCIe node

**SKU:** HCIX-RIS-B-440P a Riser B for 2x single slot GPUs per riser, 440P PCIe node

**Qty:** 1 **Estimated Lead Time:** 21 days **Unit List Price (USD):** 596.37

**Qty:** 1 **Estimated Lead Time:** 21 days **Unit List Price (USD):** 706.72

**Show Incompatible SKUs**

**Reset Configuration** Cancel Done

- a. 右側のウィンドウで [ライザー、GPU、および NVIDIA ライセンス(Riser, GPU, and NVIDIA License)] を選択して、GPU PCIe ノード (HCIX-440P) を構成します。

注： HCIX-440P では、シャーシ: HCIXNX-9508-U の下の X-Fabric モジュール HCIX-F-9416 の選択が必要です。

### ステップ 15.

HCI X 9500 Chassis																				
HCIXNX-9508-U	Server Node	IFM/FIM	Power Supply																	
Bundle Configuration HCIX-M8-NTNX-MLB	Estimated Lead Time 21 days	Price List Global Price List (USD)																		
Set service preferences for this configuration ▾																				
1: CISCO INTERSIGHT requires a minimum of 1 component(s). Please add additional quantities as necessary. (CE100010) 2: The category CISCO INTERSIGHT is required. (CE100103) 3: Please refer to the Nutanix Sizer Tool: <a href="https://sizer.nutanix.com/#/home">https://sizer.nutanix.com/#/home</a> before you proceed to do the Product Configuration. (CE202322) 4: Please note that if Nutanix Mission Critical Software Support is purchased, it is recommended that Customer upgrade to CX Success Track Level 1 or Level 2 or Solution Support to ensure consistent SLA response time between Hardware and Software. Refer to <a href="https://www.cisco.com/cidm/en_us/about/doing_business/legal/service_descriptions/docs/cisco-success-tracks.pdf">https://www.cisco.com/cidm/en_us/about/doing_business/legal/service_descriptions/docs/cisco-success-tracks.pdf</a> for more information. (CE202322) 5: It is recommended that the user purchase Nutanix Software SKU: NTX-SW or NTX-SW-1Y. (CE202155)																				
<b>Available Components</b> <table border="1"> <thead> <tr> <th>Product</th> <th>Unit List Price (USD)</th> <th>Adjusted List Price (USD)</th> <th>Extended List Price (USD)</th> </tr> </thead> <tbody> <tr> <td>HCIXNX-9508-U <span style="color: green;">Valid</span></td> <td>8,530.6</td> <td>62,974.10</td> <td>177,375.38</td> </tr> <tr> <td>Cisco Compute Hyperconverged 9508 Nutanix Chassis Configured</td> <td></td> <td></td> <td></td> </tr> <tr> <td><b>Estimated Lead Time:</b> 21 days (Min 0, Max 99999)</td> <td></td> <td></td> <td></td> </tr> </tbody> </table>					Product	Unit List Price (USD)	Adjusted List Price (USD)	Extended List Price (USD)	HCIXNX-9508-U <span style="color: green;">Valid</span>	8,530.6	62,974.10	177,375.38	Cisco Compute Hyperconverged 9508 Nutanix Chassis Configured				<b>Estimated Lead Time:</b> 21 days (Min 0, Max 99999)			
Product	Unit List Price (USD)	Adjusted List Price (USD)	Extended List Price (USD)																	
HCIXNX-9508-U <span style="color: green;">Valid</span>	8,530.6	62,974.10	177,375.38																	
Cisco Compute Hyperconverged 9508 Nutanix Chassis Configured																				
<b>Estimated Lead Time:</b> 21 days (Min 0, Max 99999)																				
+ HCI X 9508 CHASSIS + HCIXNX-9508-U <span style="color: green;">Valid</span> <span style="color: red;">a</span> <span style="color: red;">b</span> Cisco Compute Hyperconverged 9508 Nutanix Chassis Configured <a href="#">Add Custom Name</a>   <a href="#">Edit Options</a>   <a href="#">Edit Services/Subscriptions</a>   <a href="#">Copy</a>   <a href="#">Remove Line</a> Add a HCI X 9508 CHASSIS from the left panel																				
+ HCI X MODULAR SERVER > 0 Selected (Min 0, Max 99999) Add a HCI X MODULAR SERVER from the left panel																				
+ FABRIC INTERCONNECT > 0 Selected (Min 0, Max 99999) Add a FABRIC INTERCONNECT from the left panel																				
+ NUTANIX SOFTWARE > 0 Selected (Min 0, Max 2) Add a NUTANIX SOFTWARE from the left panel																				
+ NUTANIX PROF SERVICE > 0 Selected (Min 0, Max 1) Add a NUTANIX PROF SERVICE from the left panel																				
+ CISCO INTERSIGHT > 0 Selected (Min 1, Max 1) Add a CISCO INTERSIGHT from the left panel																				

- ステータスには現在、[有効 (Valid) ] として表示されています。
- 同じ構成の倍数の数量を増やします。
- 「PLUS」をクリックして、異なるオプション/数量の同じ製品を追加するか、異なる製品を選択します。

### ステップ 16.

**HCIXNX-9508-U**

**Services/Subscriptions**

Bundle Configuration	Estimated Lead Time	Price List	Total
HCIX-MB-NTNX-MLB	21 days	Global Price List (USD)	177,375.38

**Available Components**

Product	Unit List Price (USD)	Adjusted List Price (USD)	Qty	Extended List Price (USD)
HCIXNX-9508-U	8,530.96	62,974.10	1	177,375.38

**Services/Subscriptions**

- HCIXNX-9508-U Valid Cisco Compute Hyperconverged 9508 Nutanix Chassis Configured
- HCI X MODULAR SERVER > 0 Selected (Min 0, Max 999999)
- FABRIC INTERCONNECT > 0 Selected (Min 0, Max 999999)
- NUTANIX SOFTWARE > 0 Selected (Min 0, Max 2)
- NUTANIX PROF SERVICE > 0 Selected (Min 0, Max 1)
- CISCO INTERSIGHT > 0 Selected (Min 1, Max 1)

- a. [サービス/サブスクリプションの編集 (Edit Services/Subscriptions)] をクリックして、ハードウェアサポートの期間を編集します。

注： ハードウェア サポートの期間は、ソフトウェア サブスクリプション期間と一致させることをお勧めします。

## ステップ 17.

**HCI X 9500 Chassis**

HCIXNX-9508-U → Services/Subscriptions

Service Subscription	Price List	Service Total (USD)
HCIXNX-9508-U	Global Price List in US Dollars (USD)	4,893.00

You may receive additional discounts because you selected two or more years of service. To review your discounts you can go to the Order or Quoting discount pages. (C0124)

**Service Options**

Choose Service Level from **SUCCESS TRACKS ENHAN...** ▾  
L1NCO

Note: Cisco may still install another compatible service if required. Compatible services are the services that come with primary service and are based on products.

**Time Duration**  Duration  
 Delay service start to  
 Co-Term service to

**Duration**  a

**Apply** b

**Service SKU**      **Product SKU**      **Unit List Price (USD)**      **Qty**      **Total List Price (USD)**

SUCCESS TRACKS ENHANCED (2 items) L1NCO (ENH 8X7XNCADOS) SUMMARY	Duration 36 Months	1,335.00	1	1,335.00
CON-L1NCO-HCIXNX8U CX LEVEL 1 8X7XNCADOS Cisco Compute Hyperconverged...	HCIXNX-9508-U Cisco Compute Hyperconverged 9508 Nutanix Chassis ...	3,558.00	1	3,558.00
CON-L1NCO-HCIMM8N CX LEVEL 1 8X7XNCADOS 210cM8 All NVMe Hyperconverged...	HCIXNX210C-M8BN 210cM8 All NVMe Hyperconverged Nutanix Node w/o C...			

**Remove All Services**    **Remove All Additional Services**

**Configuration Summary** All prices shown in USD  
Services

**Done** b

- [期間 (Term Duration)] を入力します。
- [適用 (Apply)] をクリックし、[完了 (Done)] をクリックします。

注： Nutanix ミッションクリティカルソフトウェアサポートを購入した場合は、ハードウェアとソフトウェアの間で一貫した SLA 応答時間を確保するために、CX Success Track レベル 1 またはレベル 2 またはソリューションサポートにアップグレードすることをお勧めします。詳細については、

[https://www.cisco.com/c/dam/en\\_us/about/doing\\_business/legal/service\\_descriptions/docs/cisco-success-tracks.pdf](https://www.cisco.com/c/dam/en_us/about/doing_business/legal/service_descriptions/docs/cisco-success-tracks.pdf) を参照してください。

## ステップ 18.

**HCI X Modular Server**

**HCIXNX210C-M8SN-U**

CPU  
Memory  
Drives

**Available Components**

	Unit List Price (USD)
HCIX 9508 CHASSIS	7,811
HCIX MODULAR SERVER	8,542.50
HCIXNX210C-M8SN-U	3,316.50

**HCIX 9508 CHASSIS > 1 Selected (Min 0, Max 9999999)**

Product	Unit List Price (USD)	Adjusted List Price (USD)	Qty	Extended List Price (USD)
HCIXNX-9508-U Valid	66,236.10	66,236.10	1	180,637.38

Add a HCI X 9508 CHASSIS from the left panel

**HCIX MODULAR SERVER > 1 Selected (Min 0, Max 999999)**

Product	Unit List Price (USD)	Adjusted List Price (USD)	Qty	Extended List Price (USD)
HCIXNX210C-M8SN-U Invalid	10,246.18	10,246.18	1	10,246.18

Add a HCI X MODULAR SERVER from the left panel

**FABRIC INTERCONNECT > 0 Selected (Min 0, Max 999999)**

**NUTANIX SOFTWARE > 0 Selected (Min 0, Max 2)**

**NUTANIX PROF SERVICE > 0 Selected (Min 0, Max 1)**

- MLB の下で「PLUS」をクリックすることで、HCIXNX210C-M8SN-U および/または HCIXNX215C-M8SN-U ATO を選択します。
- さらに構成が必要なため、HCIXNX210C-M8SN-U ATO ステータスが「無効」であることに注意してください。
- Configurator を入力するために、[オプションの編集 (Edit Option) ] をクリックします。

ステップ 19.

**HCI X Modular Server**

**HCIXNX210C-M8SN-U**

Product Configuration: HCIXNX210C-M8SN-U part of HCIX-M8-NTNX-MLB

Estimated Lead Time: 21 days

Price List: Global Price

Total (USD): 133,834.16

**Configuration Summary**

Category	Qty	Extended List Price (USD)
<b>Processor</b>	2	27,381.42
<b>Memory 6400</b>	16	73,678.56
<b>Front MEZZ - Controller</b>	1	1,395.22
<b>Rear MEZZ - MLOM/PCI</b>	1	1,959.75
<b>E3S Capacity Drives</b>	1	1,959.75
<b>Total</b>		133,834.16
<b>Estimated Lead Time</b>		21 days

**Processor**

80 - 88 Core | 36 - 64 Core | 24 - 32 Core | 8 - 16 Core

This is an AI Capable product. May need AI Intent capture as part of purchase.

SKU	Qty	Estimated Lead Time	Unit List Price (USD)
HCIX-CPU-i6730P	2	21 days	32,288.44
HCIX-CPU-i6767P	1	21 days	24,095.78
HCIX-CPU-i6761P	1	21 days	29,544.79
HCIX-CPU-i6760P	1	21 days	24,944.60
HCIX-CPU-i6747P	1	21 days	15,831.97
HCIX-CPU-i6741P	1	21 days	17,781.57
HCIX-CPU-i6740P	1	21 days	14,265.87
HCIX-CPU-i6736P	1	21 days	0.00

**Reset Configuration**      **Cancel**      **Done**

- a. AI 対応 PID を選択した場合、ユーザーは AI インテント オプション クラスから選択する必要があります。

## ステップ 20.

**HCI X Modular Server**

**HCIXNX210C-M8SN-U**

Product Configuration: HCIXNX210C-M8SN-U part of HCIX-M8-NTNX-MLB

Estimated Lead Time: 21 days

Price List: Global Price

Total (USD): 141,325.84

**Configuration Summary**

Category	Qty	Extended List Price (USD)
<b>AI Intent</b>	2	34,873.10
<b>Processor</b>	2	34,873.10
<b>Memory 6400</b>	16	73,678.56
<b>Front MEZZ - Controller</b>	1	1,395.22
<b>Rear MEZZ - MLOM/PCI</b>	1	1,959.75
<b>Total</b>		141,325.84
<b>Estimated Lead Time</b>		21 days

**AI Intent**

SKU	Qty	Estimated Lead Time	Unit List Price (USD)
COMPUTE-AI	1	21 days	0.00
COMPUTE-OTHER	1	21 days	0.00

**Show Incompatible SKUs**

**Reset Configuration**      **Cancel**      **Done**

- a. 適切な選択を行うことで、サーバーでAI機能を使用することを意図しているかどうかをシスコに伝えることができます。

## ステップ 21.

**HCI X Modular Server**

**HCIXNX210C-M8SN-U**

Product Configuration  
HCIXNX210C-M8SN-U part of HCIX-M8-NODE-01-R

Estimated Lead Time  
21 days

Total (USD)  
9,060.18

**C**

1: A selection of either HCIX-ML-V5D200GV2 or HCIX-ML-V5Q50G from Rear MEZZ - MLOM/PCI is required. Please adjust the selections. (CE202322)  
2: Please note that Intersight Managed Mode(IMM) is the default deployment mode supported with HCI M8 modular servers. UCS Managed Mode (UMM) is not supported. (CE202322)  
3: HCIX-C-SW-LATEST is defaulted under X-Series Node SW. (CE100033)  
4: HCIX-AOSAHV-73SWK9 is defaulted under Hypervisor OS. (CE100033)

**Configuration Summary**

Category	Qty	Extended List Price (USD)
Processor	1	1,395.22
Memory 6400		
Front MEZZ - Controller	1	1,395.22
HCIX-X10C-PTE3	1	1,395.22
Rear MEZZ - MLOM/PCI		
E38 Capacity Drives		
Boot Drives		
Security	1	52.26
<b>Total</b>		<b>9,060.18</b>
Estimated Lead Time		21 days

**View Full Summary**

**Option Search** | **Multiple Options Search**

**HCIXNX210C-M8SN-U > Processor**

80 - 86 Core | 36 - 64 Core | 24 - 32 Core | 8 - 16 Core

SKU	Qty	Estimated Lead Time	Unit List Price (USD)
HCIX-CPU-I6787P	1	21 days	34,456.93
HCIX-CPU-I6781P	1	21 days	31,762.62

Show Incompatible SKUs

**a** **b** **c** **d**

- 左側のカテゴリ ウィンドウから周辺機器を選択して、HCIXNX210C-M8SN-U を構成します。
- PID は右側のウィンドウにリストされます。CPUなどの一部の PID は、タイプまたはシリーズに応じてグループ化されます。右側の SKU ウィンドウの上にあるグループ化されたオプションから選択します。
- 警告メッセージに従って、最低限必要なオプション PID を構成します。
- 完了したら [完了 (Done) ] をクリックします。

## ステップ 22.

**HCI X Modular Server**

Bundle Configuration: HCIX-M8-NTNX-MLB ⓘ

Estimated Lead Time: 21 days

Price List: Global Price List (USD)

Total: 315,657.54

Set service preferences for this configuration ⓘ

**HCIXNX210C-M8SN-U**

1: CISCO INTERSIGHT requires a minimum of 1 component(s). Please add additional quantities as necessary. (CE100010)  
 2: The category CISCO INTERSIGHT is required. (CE100103)  
 3: Please refer to the Nutanix Sizer Tool: <https://sizer.nutanix.com/#/home> before you proceed to do the Product Configuration. (CE202322)  
 4: Please note that if Nutanix Mission Critical Software Support is purchased, it is recommended that Customer upgrade to CX Success Track Level 1 or Level 2 or Solution Support to ensure consistent SLA response time between Hardware and Software. Refer to [https://www.cisco.com/c/dam/en\\_us/about/doing\\_business/legal/service\\_descriptions/docs/cisco-success-tracks.pdf](https://www.cisco.com/c/dam/en_us/about/doing_business/legal/service_descriptions/docs/cisco-success-tracks.pdf) for more information. (CE202322)  
 5: It is recommended that the user purchase Nutanix Software SKU: NTX-SW or NTX-SW-1Y. (CE202155)

**Available Components**

	Unit List Price (USD)
HCIX X 9508 CHASSIS	7,612.70
HCIX X MODULAR SERVER	8,542.50
HCIXNX210C-M8SN-U	3,316.50
HCIX-440P-U	3,316.50
FABRIC INTERCONNECT	1,350.00
NUTANIX SOFTWARE	1,350.00
NUTANIX PROF SERVICE	1,350.00
CISCO INTERSIGHT	1,350.00

**HCIX X 9508 CHASSIS > 1 Selected (Min 0, Max 999999)**

Product	Unit List Price (USD)	Adjusted List Price (USD)	Qty	Extended List Price (USD)
HCIXNX-9508-U Valid ⓘ	66,236.10		1	180,637.38

Add Custom Name | Edit Options | Edit Services/Subscriptions | Copy | Remove Line

Add a HCI X 9508 CHASSIS from the left panel

**HCIX X MODULAR SERVER > 1 Selected (Min 0, Max 999999)**

Product	Unit List Price (USD)	Adjusted List Price (USD)	Qty	Extended List Price (USD)
HCIXNX210C-M8SN-U Valid ⓘ	38,032.25		1	135,020.16

Add Custom Name | Edit Options | Edit Services/Subscriptions | Copy | Remove Line

Add a HCI X MODULAR SERVER from the left panel

**FABRIC INTERCONNECT > 0 Selected (Min 0, Max 999999)**

Add a FABRIC INTERCONNECT from the left panel

**NUTANIX SOFTWARE > 0 Selected (Min 0, Max 2)**

Add a NUTANIX SOFTWARE from the left panel

**NUTANIX PROF SERVICE > 0 Selected (Min 0, Max 1)**

Add a NUTANIX PROF SERVICE from the left panel

- ステータスには現在、[有効 (Valid) ] として表示されています。
- 同じ構成の倍数の数量を増やします。
- 「PLUS」をクリックして、異なるオプション/数量の同じ製品を追加するか、異なる製品を選択します。

### ステップ 23.

**HCI X Modular Server**

Bundle Configuration: HCIX-M8-NTNX-MLB ⓘ

Estimated Lead Time: 21 days

Price List: Global Price List (USD)

Total: 315,657.54

Set service preferences for this configuration ⓘ

**HCIXNX210C-M8SN-U**

1: CISCO INTERSIGHT requires a minimum of 1 component(s). Please add additional quantities as necessary. (CE100010)  
 2: The category CISCO INTERSIGHT is required. (CE100103)  
 3: Please refer to the Nutanix Sizer Tool: <https://sizer.nutanix.com/#/home> before you proceed to do the Product Configuration. (CE202322)  
 4: Please note that if Nutanix Mission Critical Software Support is purchased, it is recommended that Customer upgrade to CX Success Track Level 1 or Level 2 or Solution Support to ensure consistent SLA response time between Hardware and Software. Refer to [https://www.cisco.com/c/dam/en\\_us/about/doing\\_business/legal/service\\_descriptions/docs/cisco-success-tracks.pdf](https://www.cisco.com/c/dam/en_us/about/doing_business/legal/service_descriptions/docs/cisco-success-tracks.pdf) for more information. (CE202322)  
 5: It is recommended that the user purchase Nutanix Software SKU: NTX-SW or NTX-SW-1Y. (CE202155)

**Available Components**

	Unit List Price (USD)
HCIX X 9508 CHASSIS	7,612.70
HCIX X MODULAR SERVER	8,542.50
HCIXNX210C-M8SN-U	3,316.50
HCIX-440P-U	3,316.50
FABRIC INTERCONNECT	1,350.00
NUTANIX SOFTWARE	1,350.00
NUTANIX PROF SERVICE	1,350.00
CISCO INTERSIGHT	1,350.00

**HCIX X 9508 CHASSIS > 1 Selected (Min 0, Max 999999)**

Product	Unit List Price (USD)	Adjusted List Price (USD)	Qty	Extended List Price (USD)
HCIXNX-9508-U Valid ⓘ	66,236.10		1	180,637.38

Add Custom Name | Edit Options | Edit Services/Subscriptions | Copy | Remove Line

Add a HCI X 9508 CHASSIS from the left panel

**HCIX X MODULAR SERVER > 1 Selected (Min 0, Max 999999)**

Product	Unit List Price (USD)	Adjusted List Price (USD)	Qty	Extended List Price (USD)
HCIXNX210C-M8SN-U Valid ⓘ	38,032.25		1	135,020.16

Add Custom Name | Edit Options | Edit Services/Subscriptions | Copy | Remove Line

Add a HCI X MODULAR SERVER from the left panel

**FABRIC INTERCONNECT > 0 Selected (Min 0, Max 999999)**

Add a FABRIC INTERCONNECT from the left panel

**NUTANIX SOFTWARE > 0 Selected (Min 0, Max 2)**

Add a NUTANIX SOFTWARE from the left panel

**NUTANIX PROF SERVICE > 0 Selected (Min 0, Max 1)**

Add a NUTANIX PROF SERVICE from the left panel

- a. [サービス/サブスクリプションの編集 (Edit Services/Subscriptions)] をクリックして、ハードウェアサポートの期間を編集します。

注： ハードウェア サポートの期間は、ソフトウェア サブスクリプション期間と一致させることをお勧めします。

#### ステップ 24.

**HCI X Modular Server**

**HCIXNX210C-M8SN-U**

**Services/Subscriptions**

Service Subscription HCIXNX210C-M8SN-U	Price List Global Price List in US Dollars (USD)	Service Total (USD) 3,558.00	Subscription Total (USD) 0.00																				
You may receive additional discounts because you selected two or more years of service. To review your discounts you can go to the Order or Quoting discount pages. (C0124)																							
<input checked="" type="radio"/> Service <input type="radio"/> Non Servicable Products																							
<b>The duration that you entered has been successfully applied to all the services. (C0329)</b>																							
<b>Service Options</b>																							
Choose Service Level from <b>SUCCESS TRACKS ENHANCED</b> L1NCO		<b>Time Duration</b> <input checked="" type="radio"/> Duration <input type="radio"/> Delay service start to <input type="radio"/> Co-Term service to	<b>Duration</b> 36																				
<small>Note: Cisco may still install another compatible service if required. Compatible services are the services that come with primary service and are based on products.</small>		<small>Reset</small> <b>Apply</b>																					
<table border="1"> <thead> <tr> <th>Service SKU</th> <th>Product SKU</th> <th>Unit List Price (USD)</th> <th>Qty</th> <th>Total List Price (USD)</th> </tr> </thead> <tbody> <tr> <td>SUCCESS TRACKS ENHANCED (1 ITEM) SERVICE PROGRAM L1NCO (ENH 8X7XNCOS) SUMMARY</td> <td>HCIXNX210C-M8SN-U 210cM8 All NVMe Hyperconverged Nutanix Node w/o C...</td> <td>3,558.00</td> <td>1</td> <td>3,558.00</td> </tr> <tr> <td colspan="2"> <small>Change Service   Remove Service</small> </td> <td colspan="2"></td> <td></td> </tr> <tr> <td colspan="2"> <small>Remove All Services   Remove All Additional Services</small> </td> <td colspan="2"></td> <td></td> </tr> </tbody> </table>				Service SKU	Product SKU	Unit List Price (USD)	Qty	Total List Price (USD)	SUCCESS TRACKS ENHANCED (1 ITEM) SERVICE PROGRAM L1NCO (ENH 8X7XNCOS) SUMMARY	HCIXNX210C-M8SN-U 210cM8 All NVMe Hyperconverged Nutanix Node w/o C...	3,558.00	1	3,558.00	<small>Change Service   Remove Service</small>					<small>Remove All Services   Remove All Additional Services</small>				
Service SKU	Product SKU	Unit List Price (USD)	Qty	Total List Price (USD)																			
SUCCESS TRACKS ENHANCED (1 ITEM) SERVICE PROGRAM L1NCO (ENH 8X7XNCOS) SUMMARY	HCIXNX210C-M8SN-U 210cM8 All NVMe Hyperconverged Nutanix Node w/o C...	3,558.00	1	3,558.00																			
<small>Change Service   Remove Service</small>																							
<small>Remove All Services   Remove All Additional Services</small>																							
<small>Configuration Summary</small> All prices shown in USD Services 3,558.00				<small>Cancel</small> <b>Done</b>																			

- a. [期間 (Term Duration)] を入力します。
- b. [適用 (Apply)] をクリックし、[完了 (Done)] をクリックします。

注： Nutanix ミッションクリティカルソフトウェアサポートを購入した場合は、ハードウェアとソフトウェアの間で一貫した SLA 応答時間を確保するために、CX Success Track レベル 1 またはレベル 2 またはソリューションサポートにアップグレードすることをお勧めします。詳細については、

[https://www.cisco.com/c/dam/en\\_us/about/doing\\_business/legal/service\\_descriptions/docs/cisco-success-tracks.pdf](https://www.cisco.com/c/dam/en_us/about/doing_business/legal/service_descriptions/docs/cisco-success-tracks.pdf) を参照してください。

#### ステップ 25.

**HCI X Modular Server**

Bundle Configuration: HCIX-M8-NTNX-MLB  
Estimated Lead Time: 21 days  
Global Price List (USD): Total 318,029.54

**Available Components**

Product	Unit List Price (USD)	Adjusted List Price (USD)	Qty	Extended List Price (USD)
HCIX-9508 CHASSIS	7,612.70	66,236.10	1	180,637.38
HCIX MODULAR SERVER	8,542.50	40,404.25	1	137,392.16
HCIXN210C-M8SN-U	3,316.50			
FABRIC INTERCONNECT				
NUTANIX SOFTWARE				
NUTANIX PROF SERVICE				
CISCO INTERSIGHT				

**HCI X 9508 CHASSIS > 1 Selected (Min 0, Max 999999)**

**HCI X MODULAR SERVER > 1 Selected (Min 0, Max 99999)**

**FABRIC INTERCONNECT > 0 Selected (Min 0, Max 99999)**

**NUTANIX SOFTWARE > 0 Selected (Min 0, Max 2)**

**NUTANIX PROF SERVICE > 0 Selected (Min 0, Max 1)**

- a. GPU PCIe ノード : HCIX-440P-U はオプションの選択であり、ユーザーは「PLUS」をクリックして選択できます。

## ステップ 26.

**Fabric Interconnect**

Bundle Configuration: HCIX-M8-NTNX-MLB  
Estimated Lead Time: 21 days  
Global Price List (USD): Total 318,029.54

**Available Components**

Product	Unit List Price (USD)	Adjusted List Price (USD)	Qty	Extended List Price (USD)
HCIX-9508 CHASSIS	22,110.00	66,236.10	1	180,637.38
HCIX MODULAR SERVER	41,938.65	40,404.25	1	137,392.16
FABRIC INTERCONNECT	29,034.45			
HCIX-FI-6536				
HCIX-FI-64108				
HCIX-FI-6454				
NUTANIX SOFTWARE				
NUTANIX PROF SERVICE				
CISCO INTERSIGHT				

**HCIX X 9508 CHASSIS > 1 Selected (Min 0, Max 999999)**

**HCIX MODULAR SERVER > 1 Selected (Min 0, Max 99999)**

**FABRIC INTERCONNECT > 0 Selected (Min 0, Max 99999)**

**NUTANIX SOFTWARE > 0 Selected (Min 0, Max 2)**

**NUTANIX PROF SERVICE > 0 Selected (Min 0, Max 1)**

- a. ファブリック インターコネクトはオプションの選択で、ユーザーは「PLUS」をクリックして選択できます。

## ソフトウェア サブスクリプションの構成

ステップ 27.

The screenshot shows the Nutanix Software configuration interface. At the top, there's a green header bar with the title 'NUTANIX SOFTWARE'. Below it, there are four main sections:

- Available Components**: A list of components with their unit list prices in USD. It includes:
  - HCI X 9508 CHASSIS: 0.00
  - HCI X MODULAR SERVER: 0.00
  - FABRIC INTERCONNECT: 0.00
  - NUTANIX SOFTWARE: 0.00
- HCI X**: A section for selecting HCI components. It shows 'NTX-SW' and 'NTX-SW-1Y' selected. A red arrow labeled 'a' points to the 'NTX-SW' entry. A blue arrow points from the 'NTX-SW' entry to the 'NCI' component below.
 

Product	Unit List Price (USD)	Adjusted List Price (USD)	Qty	Extended List Price (USD)
NTX-SW	66,236.10		1	180,637.38
- FABRIC INTERCONNECT**: A section for selecting fabric interconnects. It shows 'NTX-SW-1Y' selected. A red arrow points to the 'NTX-SW-1Y' entry.
 

Product	Unit List Price (USD)	Adjusted List Price (USD)	Qty	Extended List Price (USD)
NTX-SW-1Y			1	
- NUTANIX SOFTWARE**: A section for selecting Nutanix software. It shows 'NTX-SW' selected. A red arrow labeled 'b' points to the 'NTX-SW' entry.
 

Product	Unit List Price (USD)	Adjusted List Price (USD)	Qty	Extended List Price (USD)
NTX-SW	38,032.25		1	135,020.16

Below these sections, there are several buttons and links for managing the configuration, such as 'Add Custom Name', 'Edit Options', 'Edit Services/Subscriptions', 'Copy', and 'Remove Line'.

- a. NTX-SW または NTX-SW-1Y は必須の選択です。 「PLUS」 をクリックして選択してください

- b. [オプションの編集 (Edit Options) ] をクリックして、製品を構成します。

注： サブスクリプション期間は、NTX-SW の場合は 36 ~ 60 カ月、NTX-SW-1Y の場合は 12 カ月です。

## Nutanix Software Product Scope offering in Cisco

Nutanix Cloud Infrastructure (NCI)	NCI is a complete software stack to unify your hybrid cloud infrastructure including compute, storage and network, hypervisors, and containers, in public or enterprise clouds.
Nutanix Cloud Infrastructure Data (NCI-D)	Delivers rich data and storage services but does not include Nutanix compute and networking capabilities. No support for AHV.
Nutanix Cloud Infrastructure Edge (NCI-E)	Provides a Distributed Infrastructure Platform for small Edge Deployments.
End User Computing (EUC)	On-Prem VDI and Desktop as a Service (DaaS) use cases.
Nutanix Cloud Manager (NCM)	NCM offers intelligent operations, self service and orchestration, visibility and governance of spend, security and teams.
Nutanix Cloud Manager Edge (NCM-E)	Provides NCM Capability for Edge Deployments
Nutanix Cloud Manager End User Computing (NCM-U)	Provides NCM Capability in VDI Use Cases
Nutanix Cloud Platform (NCP)	Bundle for NCI and NCM
Nutanix Unified Storage (NUS)	Software-defined data services platform that consolidates the management and protection of siloed block, file, and object storage into a single, unified platform.
Nutanix Enterprise AI (NAI)	Nutanix Enterprise AI provides an easy way to deploy your choice of LLMs from leading LLM providers and create and manage secure APIs.
Nutanix Data Lens (NDL)	SaaS-based cyberstorage solution offering ransomware resilience and global data visibility for unstructured data on Nutanix Unified Storage (NUS).
Nutanix Kubernetes Platform (NKP)	Simplifies platform engineering by reducing operational complexity and establishes consistency across any environment.

## NUTANIX CLOUD INFRASTRUCTURE (NCI)

NT-NCI-PRO-PR

### License Tiers:

- STR (Starter)
- PRO (Professional)
- ULT (Ultimate)

### Support Tiers:

- PR (Production)
- MC (Mission Critical)
- AP (ASP Production)
- AM (ASP Mission Critical)
- FP (US Federal Production)
- FM (US Federal Mission Critical)

### Available Feature Add-Ons:

- Security  
SKU: NT-A-NCI-SEC-PR
- Advanced Replication  
SKU: NT-A-NCI-ADR-PR

**Feature Add-on license can only be added to NCI PRO tier licenses**

## NUTANIX CLOUD INFRASTRUCTURE DATA (NCI-D)

NT-NCI-D-PRO-PR

### License Tiers:

- STR (Starter)
- PRO (Professional)
- ULT (Ultimate)

### Support Tiers:

- PR (Production)
- MC (Mission Critical)
- AP (ASP Production)
- AM (ASP Mission Critical)
- FP (US Federal Production)
- FM (US Federal Mission Critical)

### Available Feature Add-Ons:

- Security  
SKU: NT-A-NCI-D-SEC-PR
- Advanced Replication  
SKU: NT-A-NCI-D-ADR-PR

**Feature Add-on license can only be added to NCI PRO tier licenses**

## NUTANIX CLOUD INFRASTRUCTURE EDGE (NCI-E)

NT-NCI-E-PRO-PR

### License Tiers:

- STR (Starter)
- PRO (Professional)
- ULT (Ultimate)

### Support Tiers:

- PR (Production)
- MC (Mission Critical)
- AP (ASP Production)
- AM (ASP Mission Critical)
- FP (US Federal Production)
- FM (US Federal Mission Critical)

- **1 TiB of NUS Pro per NCI-Edge cluster is included at no cost with NCI-Edge.**
- **NCI-Edge licenses must run on a dedicated licensed cluster with no core-based licensing. Mixing of NCI-Edge licenses with other types of NCI licensing within a cluster is not supported.**
- **NCI-Edge is limited to a maximum of 25 VMs in a cluster, with each VM being limited to a maximum of 96GB of memory.**

**Metric - VMs**

# END USER COMPUTING (EUC)

NT-EUC-PRO-PR

## License Tier:

- STR (Starter)
- PRO (Professional)
- ULT (Ultimate)

## Support Tier:

- PR (Production)
- MC (Mission Critical)
- AP (ASP Production)
- AM (ASP Mission Critical)
- FP (US Federal Production)
- FM (US Federal Mission Critical)

- All users on EUC cluster must be licensed
- There are no add-ons on top of Pro license for EUC. If add-ons required, use EUC Ultimate.

## Note:

- Meter = Users

# NUTANIX CLOUD MANAGER (NCM)

NT-NCM-PRO-PR

## License Tiers:

- STR (Starter)
- PRO (Professional)
- ULT (Ultimate)

## Support Tiers:

- PR (Production)
- MC (Mission Critical)
- AP (ASP Production)
- AM (ASP Mission Critical)
- FP (US Federal Production)
- FM (US Federal Mission Critical)

## Available Feature Add-Ons:

- Self-Service & Orchestration  
SKU: NT-NCM-SS-PR
- Security Central  
SKU: NT-NCM-SC-PR
- Cost Governance  
SKU: NT-NCM-CM-PR

These add-ons give access to respective feature sets for the public cloud

## Note:

- Meter = VM (Virtual Machine)
- Subscription is created on My Nitrogen portal for each product

## NUTANIX CLOUD MANAGER EDGE (NME)

NT-NME-PRO-PR

### License Tiers:

- STR (Starter)
- PRO (Professional)
- ULT (Ultimate)

### Support Tiers:

- PR (Production)
- MC (Mission Critical)
- AP (ASP Production)
- AM (ASP Mission Critical)
- FP (US Federal Production)
- FM (US Federal Mission Critical)

- **NCM EDGE License are metered per VM and to be used only for NCI-EDGE clusters.**
- **To apply such Licenses, customers need minimum PC 2024.2**
- **Edge Cluster maximums are:**
  - **25 VMs per cluster**
  - **Memory maximum is 96GB (per VM)**
  - **Maximum no. of nodes not to exceed 5**

Metric - VMs

## NUTANIX CLOUD MANAGER EUC (NCM-U)

NT-NCM-U-PRO-PR

### License Tiers:

- STR (Starter)
- PRO (Professional)
- ULT (Ultimate)

### Support Tiers:

- PR (Production)
- MC (Mission Critical)
- AP (ASP Production)
- AM (ASP Mission Critical)
- FP (US Federal Production)
- FM (US Federal Mission Critical)

- **NCM EUC License are metered per user and to be used only for NCI-EUC clusters.**
- **To apply such Licenses, customers need minimum PC 2024.2**

Metric - User

# NCP (NUTANIX Cloud Platform) Bundle

NT-NCP-PRO-PR

## License Tier:

- STR (Starter)
- PRO (Professional)
- ULT (Ultimate)

## Support Tier:

- PR (Production)
- MC (Mission Critical)
- AP (ASP Production)
- AM (ASP Mission Critical)
- FP (US Federal Production)
- FM (US Federal Mission Critical)

Product Tier	Offering Combination
NCP ULT	NCI ULT + NCM ULT
NCP PRO	NCI ULT + NCM PRO
NCP STR	NCI PRO + NCM PRO

## NCP Quoting and Licensing rules

### Quoting Rules

- NCP has three bundled offerings, and each bundle has fixed NCI and NCM license tiers.
- Meter is 'Core'. Same for both NCI and NCM constituent products.
- Quantity, Term, Discount offered to be selected at the top-level 'parent' SKU, and all the 'children' components inherit.
- Both the NCI and NCM components display their Quantity.
- Top-level SKU should display Unit List Price, Discount, Total List Price, Quantity and Total Net Price

### Licensing Rules

- The constituent NCI and NCM licenses are applied individually.
- NCI add-ons can be quoted if required for the NCI license in the bundle.
- NCM add-ons can be quoted for the NCM license in the bundle.

# NUTANIX UNIFIED STORAGE (NUS) & NUTANIX DATA LENS (NDL)

NT-NUS-PRO-PR

NT-NDL-PR/FP

## License Tier:

- PRO (Professional)

## Support Tier:

- PR (Production)
- MC (Mission Critical)
- AP (ASP Production)
- AM (ASP Mission Critical)
- FP (US Federal Production)
- FM (US Federal Mission Critical)

- **Available Feature Add-Ons:**
- **Security**
  - SKU: NT-A-NUS-SEC-PR
- **Advanced Replication**
  - SKU: NT-A-NUS-ADR-PR
- **Feature Add-on license can only be added to NCI PRO tier licenses**
- **Note:**
  - *Meter = Used TiB*
  - *Tiered pricing*

# NUTANIX AI (NAI)

NT-NAI-PRO-C-PR  
NT-NAI-NKP-PRO-C-PR  
NT-NAI-GPT-PRO-C-PR

## License options

- NAI – A la Carte
- NAI-NKP – NAI + NKP
- NAI-GPT – NAI + NKP FS  
(includes NCI, NKP, NDK) +  
NCM Starter

## License Tier:

- For Compute Meter**
- PRO (Professional)
- For GPU Meter**
- PRO (Professional)
  - ULT (Ultimate)

- **Built to Solve make it easy to deploy a wide range of GenAI models**
- **Nutanix AI Platform has 2 ordering requirements**
  - CPU ( Meter vCPU/Core)
  - GB (memory on GPU)


## Meter:

- C – Meter (vCPU)
- GB – Meter( GB GPU RAM )

## Support Tier:

- PR (Production)
- MC (Mission Critical)
- AP (ASP Production)
- AM (ASP Mission Critical)
- FP (US Federal Production)
- FM (US Federal Mission Critical)

# NUTANIX KUBERNETES PLATFORM (NKP)



ステップ 28.

**NUTANIX SOFTWARE**

**Offer Configuration**  
NTX-SW (Part of HCIX-M8-NTNX-MLB)

**Estimated Lead Time**  
NA

**Price**  
Global 0.00

**Total (USD)**  
0.00

**Requested Terms and Billing**

**Requested Start Date** 25-Jul-2025  
**Requested For** 36 Months From 25-Jul-2025 To 24-Jul-2028  
**Automatically Renews For** No Auto Renewal  
**Billing Frequency** Prepaid Term

1: Cisco will apply a standard lead time to your requested start date based on the selected product. Cisco may not be able to honor the requested start date (RSD). In some cases, our systems may require additional lead-time to provision your services. Submitting a RSD that is too early could cause customer subscription billing issues. Verify the requested start date with your implementation team that aligns with customer deployment readiness. (C0742)  
2: Your subscription will start and be eligible to be invoiced: i) 30 days or less (7 days for A-FLEX/A-FLEX-3/A-WHOLESALE) after Cisco notifies you that any portion of the subscription is ready for you to provision OR, ii) the day any portion of the subscription is provisioned by Cisco, whichever of the two events happens first. (C01007)

**REQUESTED FOR** 36 Months | From 25-Jul-2025 To 24-Jul-2028

**Requested Start Date**  
Day Month Year  
25 Jul 2025 

**End Date**  
Effective For 36 Months   
Enter any whole month value from 24-84

**Automatically Renews On**  **No Auto Renewal** 

**Auto Renewal**  Off

**Billing Frequency**  Prepaid Term  
 Prepaid Term

**Cancel** **Save Changes**

- 希望開始日（RSD）は、HW Ship Date に依存するようになり、HW が出荷されると自動的に開始されます。RSD を変更すると、ソフトウェアは選択した RSD またはハードウェア出荷日のいずれか遅い方から開始されます。
- [終了日（End Date）]（月単位の期間）はデフォルトで [36 か月（36 Months）] に設定され、[自動更新（オン/オフ）（Auto Renewal (on/off)）] はデフォルトで [オフ（Off）] に設定され、[請求頻度

**(Billing Frequency)** ] はデフォルトで【前払い期間 (Prepaid Term)】に設定されます。それに応じて設定を変更することもできます。

### ステップ 29.

The screenshot shows the Nutanix Software configuration interface. At the top, there's a summary section for "Offer Configuration" (NTX-SW/ Part of HCIX-M8-NTNX-MLB), "Estimated Lead Time" (NA), and "Requested Terms and Billing". The "Requested Start Date" is 25-Jul-2025, and "Requested For" is 36 Months From 25-Jul-2025 To 24-Jul-2028. The "Billing Frequency" is set to "Prepaid Term". Below this, there are two warning messages:

- A yellow warning: "1: To complete your order, please review product terms and acknowledge checkbox under EULA category from Configuration Summary (left-hand side). (CE202343)"
- A blue warning: "2: The items marked with "--" do not have a List Price available. Enter a different Quantity, Initial Term or Prepay Term. (C0808)"

On the left, a sidebar titled "Configuration Summary" lists various Nutanix components: NCI, NCI-D, NCM, NCM-E, NCM-U, NAI, NKP, and NUS. The "Total" value is \$0.00. At the bottom of the sidebar are "Restore Configuration", "Cancel", and "Review Changes" buttons.

The main area is titled "NUTANIX SOFTWARE" and shows a flowchart-like diagram where "NTX-SW" and "NTX-SW-1Y" lead to "NCI", "NCM", and "NUS". A blue arrow points from "NTX-SW" to "NCI". Below the diagram, there's a table titled "STR" (Software License Request) with columns for "Core", "SKU", "Description", "Unit List Price (USD)", and "Action". The table contains six rows, each with a "Qty" input field and a "List Price" link. The descriptions for the SKUs include "NCI Starter SW LIC & Production SW Supp per Core", "NCI Starter SW LIC & Mission Critical SW Supp per Core", "NCI Starter SW Lic & L3 Production SW Sup Serv per Core", "NCI Starter SW Lic & L3 Mission Critical SW Sup Serv perCore", "NCI Starter SW LIC & Fed Production SW Supp per Core", and "NCI Starter SW LIC & Fed Mission Critical SW Supp per Core".

- NCI、NCI-D または NCM または (NCPのNCIとNCM) ライセンスの数量は、「サーバー (Servers)」上で選択したプロセッサ コアの数量と一致する必要があります。NCI-E、EUC、NCM-E、EUC、NCM-U、NAI、NKP、NUS、および NDL ライセンスの数量は、推奨されるシステム要件ごとに選択できます。

### ステップ 30.

**NUTANIX SOFTWARE**

Offer Configuration NTX-SW( Part of HCIX-M8-NTNX-MLB)	Estimated Lead Time NA	<b>NTX-SW</b>	Total (USD) 126,894.18
<b>Requested Terms and Billing</b>		P G <b>NCI</b> A N <b>NCM</b> N <b>NUS</b>	Billing Frequency Prepaid Term
Requested Start Date 25-Jul-2025	Requested For 36 Months From 25-Jul-2025 To 24-Jul-2028	A N	

**⚠ 1:** To complete your order, please review product terms and acknowledge checkbox under EULA category from Configuration Summary (left-hand side). (CE202343)  
**2:** The items marked with "--" do not have a List Price available. Enter a different Quantity, Initial Term or Prepay Term. (C0808)

**ⓘ Your subscription will start and be eligible to be invoiced: i) 30 days or less (7 days for A-FLEX/A-FLEX-3/A-WHOLESALE) after Cisco notifies you that any portion of the subscription is ready for you to provision OR, ii) the day any portion of the subscription is provisioned by Cisco, whichever of the two events happens first. (C01007)**

**Configuration Summary**

Nutanix Cloud Platform (NCP)	NTX-SW > EULA		
Nutanix Enterprise AI (NAI)	EULA		
Nutanix Unified Storage (NUS)	To complete your order, please check the box to the right to acknowledge and agree to the EULA Terms: <input checked="" type="checkbox"/> a		
Nutanix Data Lens (NDL)	By checking this box or otherwise placing an order for a Nutanix product or service, you agree that: (1) use of Nutanix products and receipt of Nutanix services is governed solely by the Nutanix License and Services Agreement located at <a href="https://www.nutanix.com/legal/eula">https://www.nutanix.com/legal/eula</a> ; (2) if you are a partner or distributor, or are otherwise placing an order on behalf of another person (a "Customer"), you have included a statement in your written order with the Customer that use of Nutanix products is governed solely by the Nutanix License and Services Agreement located at <a href="https://www.nutanix.com/legal/eula">https://www.nutanix.com/legal/eula</a> , and have obtained an acknowledgment from the Customer accepting the foregoing terms, and you agree to provide reasonable evidence of the Customer's acceptance of such terms to Nutanix upon the direct request of Nutanix; (3) Cisco makes no warranty regarding Nutanix products and Nutanix makes no warranty regarding Cisco products and services; (4) Cisco does not provide support for Nutanix products and services and Nutanix does not provide support for Cisco products and services; and (5) Cisco may provide the Customer's name, address, and other order details to Nutanix (and the customer has provided all necessary consents to permit the same).		
Nutanix Kubernetes Platform (NKP)			
<b>EULA</b> <input checked="" type="checkbox"/> a			
Nutanix Support			
<b>SKU</b>	<b>Qty</b>	<b>List Price</b>	
SVS-NT-SUP	1 Each	\$0.00 Per Each/Month	
<b>Total</b>		<b>\$126,894.18</b>	
<b>Restore Configuration</b>		<b>Cancel</b>	<b>Review Changes</b> b

- 注文を完了するには、右側のチェックボックスをオンにして、EULA 条件を確認して同意してください
- [変更の確認 (Review Changes) ] をクリックして、[完了 (Done) ] をクリックします。

### ステップ 31.

**NUTANIX SOFTWARE**

Available Components		Unit List Price (USD)	NTX-NCI-USE-CASE		
HCI X 9508 CHASSIS > 1 Selected (Min 0, Max 1)			Qty	Extended List Price (USD)	
<input checked="" type="checkbox"/>	Product				
<input checked="" type="checkbox"/>	HCIXNX-9508-U Valid	Cisco Compute Hyperconverged 9508 Nutanix Chassis Configured	66,236.10	1	180,637.38
Add a HCI X 9508 CHASSIS from the left panel					
HCI X MODULAR SERVER > 1 Selected (Min 0, Max 99999)			Qty	Extended List Price (USD)	
<input checked="" type="checkbox"/>	Product	Unit List Price (USD)	Adjusted List Price (USD)	Qty	Extended List Price (USD)
<input checked="" type="checkbox"/>	HCIXNX210C-M8SN-U Valid	210Gb/s All NVMe Hyperconverged Nutanix Node w/o CPU,Mem,Strg	38,032.25	1	135,020.16
Add a HCI X MODULAR SERVER from the left panel					
FABRIC INTERCONNECT > 0 Selected (Min 0, Max 99999)			Qty	Extended List Price (USD)	
Add a FABRIC INTERCONNECT from the left panel					
NUTANIX SOFTWARE > 2 Selected (Min 0, Max 2)			Qty	Extended List Price (USD)	
<input checked="" type="checkbox"/>	Product	Unit List Price (USD)	Adjusted List Price (USD)	Qty	Extended List Price (USD)
<input checked="" type="checkbox"/>	NTX-SW Valid	Nutanix Software 3Y and above	27.54	1	126,894.18
Add Custom Name   Edit Options   Remove Line   Dependent Hardware					
Requested Start Date 25-Jul-2025	Requested For 36 Months From 25-Jul-2025 To 24-Jul-2028	Automatically Renews For	No Auto Renewal	Billing Frequency Prepaid Term	
NTX-NCI-USE-CASE		NTX-NCI-USE-CASE	0.00	1	0.00
Add Custom Name   Select Options   Remove Line   Dependent Hardware					

- a. Nutanix Software ATO で NCI/NCI-D/ NCI-E ライセンスを選択する場合は、NTX-NCI-USE-CASEを選択する必要があります。

ステップ 32.

The screenshot shows the Nutanix Software ATO configuration interface. At the top, a green bar displays 'NUTANIX SOFTWARE' and a blue arrow points to a green box labeled 'NTX-NCI-USE-CASE'. Below this, the configuration summary table includes:

Product Configuration	Estimated Lead Time	Price List	Total (USD)
NTX-NCI-USE-CASE part of HCIX-M8-NTNX-MLB	7 days	Global Price List in US Dollars (USD)	0.00

A warning message at the top states: 'NTX-NCI-USE-CASE quantity 1 requires a minimum quantity of 1 from Use Case (CE100012)'. The 'Configuration Summary' section shows:

Category	Qty	Extended List Price (USD)
Use Case	1	0.00

The 'Use Case' section lists three options:

SKU	Qty	Estimated Lead Time	Unit List Price (USD)
NT-ON-PREM-UCS	1	3 days	0.00
NT-PUBLIC-CLOUD	1	3 days	0.00
NT-OTHER	1	3 days	0.00

At the bottom, there are 'Reset Configuration' and 'Done' buttons.

- a. 適切なユース ケースを選択してください

Nutanix Professional Services SKU

ステップ 33.

**NUTANIX PROF SERVICE**

**DESIGN**

**DEPLOYMENT**

**WORKSHOP**

Available Components	Unit List Price (USD)	Adjusted List Price (USD)	Qty	Extended List Price (USD)
HCI X 9508 CHASSIS > 1 Selected (Min 0, Max 999999)				
Product				
NTX-SW-PS	54,911.24		1	153,138.24
Cisco Compute Hyperconverged 9508 Chassis Configure				
Add Custom Name   Edit Options   Edit Services/Subscriptions   Remove Line				
HCI X MODULAR SERVER > 2 Selected (Min 0, Max 999999)				
Product				
HCX210C-M7584U	25,473.91		1	106,287.54
Cisco Compute Hyperconverged Node w/o CPU/Memory/Storage				
Add Custom Name   Edit Options   Edit Services/Subscriptions   Remove Line				
HCX-448P-U	3,912.87		1	4,509.24
HCI X-Series Gen4 PCIe node				
Add Custom Name   Edit Options   Remove Line				
Add a HCI X MODULAR SERVER from the left panel				
FABRIC INTERCONNECT > 2 Selected (Min 0, Max 999999)				
Product				
HCX210C-6538	38,292.74		2	76,585.48
Cisco Compute Hyperconverged X Fabric Interconnect 6538				
Add Custom Name   Edit Options   Edit Services/Subscriptions   Remove Line				
Add a FABRIC INTERCONNECT from the left panel				
NUTANIX SOFTWARE > 2 Selected (Min 0, Max 2)				
Product				
NTX-SW	36.12		1	166,446.49
Valid				
Nutanix Software 3Y and above				
Add Custom Name   Edit Options   Remove Line   Dependent Hardware				
Requested Start Date	Requested For	Automatically Renews For	Billing Frequency	
16-Jan-2025	36 Months From 16-Jan-2025 To 15-Jan-2028	No Auto Renewal	Prepaid Term	
NTX-NCI-USC-CASE	0.00		1	0.00
Valid				
Nutanix NCI Software License Use case				
Add Custom Name   Edit Options   Remove Line				
NUTANIX PROF SERVICE > 1 Selected (Min 0, Max 1)				
Product				
NTX-SW-PS	-		1	-
Invalid				
Nutanix Professional Service				
Add Custom Name   Edit Options   Remove Line				
Requested Start Date	Requested For	Automatically Renews For	Billing Frequency	
16-Jan-2025	1 Months From 16-Jan-2025 To 15-Feb-2025	No Auto Renewal	Prepaid Term	

- ユーザーは NTX-SW-PS を購入することをお勧めします。「PLUS」をクリックして選択してください
- [編集 (Edit)] オプションをクリックして、製品を構成します。

注： Nutanix Professional Service は、NTX-SW-1Y に基づく NCI、NCM、NCP ライセンスの場合、または NTX-SW に基づく NCM PRO または NCM ULT ライセンスを選択した場合に必須です。

## Nutanix Professional Services SKU

- Each professional SKU is 1-Year Term.
- The professional services needs to consumed within 1-Year period

Product	Stage	Professional Services Offerings
NCI	Design	NCI Design Workshop
	Deploy	NCI Cluster Deployment or Expansion
	Migrate	Virtual Machine Migration Workshop
	Migrate	Virtual Machine Migration
NCM	Design	NCM Intelligent Operations Design Workshop
	Design	NCM Self-Service Design Workshop
	Deploy	NCM Intelligent Operations Deployment
	Deploy	FastTrack for NCM Self-Service
	Deploy	FastTrack for NCM Cost Governance

# Nutanix Professional Service (PS) ordering rules

- 1- year Terms:** Mandatory professional services attach for NCI, NCM and NCP.
  - Select NCI Design Workshop + NCI Cluster Deployment or Expansion for NCI
  - Select NCM Intelligent Operations Design + NCM Intelligent Operations Deployment for NCM
  - PS Tiers match (or greater) the software license Tier is recommended.
- 3- year & above Terms:** Mandatory professional services attach for NCM Pro and NCM Ultimate only
  - Select NCM Intelligent Operations Design + NCM Intelligent Operations Deployment
  - PS Tiers match (or greater) the software license Tier is recommended
  - PS for NCI License is recommended
- Exceptions on (1) and (2)**
  - Existing Nutanix customers
  - Cisco Partners who are Nutanix authorized partners offering their own professional services SKUs
- Any expand opportunity should not require mandatory services.

ステップ 34.

The screenshot shows the Nutanix Professional Service configuration interface. At the top, it displays the service category: **NUTANIX PROF SERVICE**. Below this, there are three main service categories: **DESIGN**, **DEPLOYMENT**, and **WORKSHOP**. A large blue arrow points from the **NTX-SW-PS** button down to the **DESIGN** section. The **DESIGN** section contains several service items, each with a red arrow labeled 'a' pointing to the 'SKU' column. The items include:

- NT-W-DS-STR
- NT-W-DS-STR-SD
- NT-W-DS-STR-ED AEOL
- NT-W-DS-PRO
- NT-W-DS-PRO-SD
- NT-W-DS-PRO-ED AEOL
- NT-W-DS-ULT-SD
- NT-W-DS-ULT-ED AEOL

The **DEPLOYMENT** section also has a red arrow labeled 'a' pointing to the 'SKU' column, listing:

- NT-S-DP-STR-AVS
- NT-S-DP-STR-AVV

The **WORKSHOP** section is currently empty. At the bottom left, there is a configuration summary table with a red arrow labeled 'a' pointing to the 'SKU' column for the NCI Design Workshop row. The table includes columns for **SKU**, **Qty**, and **List Price**. The total cost is \$0.00. At the bottom right, there is a note about subscription start dates and provisioning timelines, with a red arrow labeled 'b' pointing to the note area.

- NTX-SW 下で NCI ライセンスを選択しているため、Nutanix Professional Services : NCI Design Workshop + NCI Cluster Deployment または Expansion SKU を選択することをお勧めします。

- b. NCI Cluster Deployment または Expansion Variable SKU の数量は、サーバー QTY と一致する必要があります。

### ステップ 35.

**NUTANIX PROF SERVICE**

**NTX-SW-PS**

**DESIGN**

**DEPLOYMENT**

**WORKSHOP**

Offer Configuration: NTX-SW-PS( Part of HCIX-M8-NTNX-MLB )

Estimated Lead Time: NA

Global Price List: [View](#)

Total (USD): \$27,657.74

**Requested Terms and Billing**

Requested Start Date: 22-Jul-2025

Requested For: 1 Months From 22-Jul-2025 To 21-Aug-2025

Automatically Renewal: No Auto Renewal

Billing Frequency: Prepaid Term

**Configuration Summary**

SKU	Qty	List Price
NT-W-DS-STR	1 Each	\$18,132.4000 Per Each/Month
NT-S-DP-STR-AVB	1 Each	\$7,975.0000 Per Each/Month
NT-S-DP-STR-AVV	2 Each	\$775.1700 Per Each/Month

**Nutanix Cloud Infrastructure (NCI) Services**

**EULA** a

To complete your order, please check the box to the right to acknowledge and agree to the EULA Terms:

By checking this box or otherwise placing an order for a Nutanix product or service, you agree that: (1) use of Nutanix products and receipt of Nutanix services is governed solely by the Nutanix License and Services Agreement located at <https://www.nutanix.com/legal/eula>; (2) if you are a partner or distributor, or are otherwise placing an order on behalf of another person ("Customer"), you have included a statement in your written order with the Customer that use of Nutanix products is governed solely by the Nutanix License and Services Agreement located at <https://www.nutanix.com/legal/eula>, and have obtained an acknowledgment from the Customer accepting the foregoing terms, and you agree to provide reasonable evidence of the Customer's acceptance of such terms to Nutanix upon the direct request of Nutanix; (3) Cisco makes no warranty regarding Nutanix products and services and Nutanix makes no warranty regarding Cisco products and services; (4) Cisco does not provide support for Nutanix products and services and Nutanix does not provide support for Cisco products and services; and (5) Cisco may provide the Customer's name, address, and other order details to Nutanix (and the customer has provided all necessary consents to permit the same).

**Nutanix Cloud Management (NCM) Services**

**EULA** a

**Total**: \$27,657.74

**Restore Configuration** b **Cancel** **Review Changes**

- a. 注文を完了するには、右側のチェックボックスをオンにして、EULA 条件を確認して同意してください
- b. [変更の確認 (Review Changes) ] をクリックして、[完了 (Done) ] をクリックします。

### ステップ 36.

**Cisco Intersight**

Available Components	Unit List Price (USD)	Adjusted List Price (USD)	Qty	Extended List Price (USD)
HCI X 9508 CHASSIS				
HCI X MODULAR SERVER				
FABRIC INTERCONNECT				
NUTANIX SOFTWARE				
NUTANIX PROF SERVICE				
CISCO INTERSIGHT				
<b>DC-MGT-SAAS</b>				
Cisco Intersight SaaS (Min 0, Max 1)	0.00			
<b>CHNL_DESELECT_D</b>				
Conditional Select				
Estimated Lead Time: -				
(Min 0, Max 1)				
<b>b</b>				
<b>HCIX-9508-U</b>				
Cisco Compute Hyperconverged 9508 Nutanix Chassis Configured				
Add Custom Name   Edit Options   Edit Services/Subscriptions   Copy   Remove Line				
<b>DC-MGT-SAAS</b>				
<b>HCIX-X210C-M88N-U</b>				
210xM8 All NVMe Hyperconverged Nutanix Node w/o CPU,Mem,Strg				
Add Custom Name   Edit Options   Edit Services/Subscriptions   Copy   Remove Line				
<b>HCIX-X MODULAR SERVER</b>				
<b>FABRIC INTERCONNECT</b>				
<b>NUTANIX SOFTWARE</b>				
<b>NUTANIX PROF SERVICE</b>				
<b>CISCO INTERSIGHT</b>				
<b>a</b>				

- ハードウェア サポートの期間は、ソフトウェア サブスクリプション期間と同調させることをお勧めします。
- Cisco Intersight ソフトウェアを以前に購入していない場合は、Intersight を選択する必要があります。構成するには、「PLUS」をクリックして、[オプションの編集 (Edit Options) ] をクリックします。

## ステップ 37.

**Cisco Intersight**

↓

**DC-MGT-SAAS**

Offer Configuration DC-MGT-SAAS( Part of HCIX-M8-NTNX-MLB)	Estimated Lead Time NA	Price List Global Price List (USD)	Total (USD) 0.00
<b>Requested Terms and Billing</b>			
Requested Start Date 25-Jul-2025	Requested For 36 Months From 25-Jul-2025 To 24-Jul-2028	Automatically Renews For 12 Months On 25-Jul-2028	Billing Frequency Prepaid Term
<small>1: Cisco will apply a standard lead time to your requested start date based on the selected product. Cisco may not be able to honor the requested start date (RSD). In some cases, our systems may require additional lead-time to provision your services. Submitting a RSD that is too early could cause customer subscription billing issues. Verify the requested start date with your implementation team that aligns with customer deployment readiness. (C0742)</small> <small>2: Your subscription will start and be eligible to be invoked: i) 30 days or less (7 days for A-FLEX/A-FLEX-3/A-WHOLESALE) after Cisco notifies you that any portion of the subscription is ready for you to provision OR, ii) the day any portion of the subscription is provisioned by Cisco, whichever of the two events happens first. (C01007)</small>			
<b>REQUESTED FOR</b> 36 Months   From 25-Jul-2025 To 24-Jul-2028			
<b>Requested Start Date</b> <input type="text" value="25"/> Day <input type="text" value="Jul"/> Month <input type="text" value="2025"/> Year <span style="color: red;">a</span> <small>Enter any date up between 22-Jul-2025 and 19-Oct-2025</small>	<b>End Date</b> <input checked="" type="radio"/> Effective For <input type="text" value="36"/> Months <small>Enter any whole month value from 1-96</small>		
<input type="radio"/> Co-Term to an End Date <span style="color: red;">b</span> <input type="text" value="24"/> Day <input type="text" value="Jul"/> Month <input type="text" value="2028"/> Year <small>Enter any date up between 22-Oct-2025 and 24-Jul-2033</small>			
<b>Automatically Renews For</b> <span style="color: red;">b</span> 12 Months On 25-Jul-2028			
<b>Billing Frequency</b> <input checked="" type="radio"/> Prepaid Term <input type="radio"/> Annual Billing <input type="radio"/> Quarterly Billing <input type="radio"/> Monthly Billing			
<span style="border: 1px solid #ccc; padding: 2px 10px; border-radius: 10px; color: #ccc;">Cancel</span> <span style="border: 1px solid #0070C0; background-color: #0070C0; color: white; border-radius: 10px; padding: 2px 10px; font-weight: bold;">Save Changes</span>			

- 希望開始日（RSD）は、HW Ship Date に依存するようになり、HW が出荷されると自動的に開始されます。RSD を変更すると、ソフトウェアは選択した RSD またはハードウェア出荷日のいずれか遅い方から開始されます。
- [終了日（End Date）]（月単位の期間）はデフォルトで [36 か月（36 Months）] に設定され、[自動更新（オン/オフ）（Auto Renewal (on/off)）] はデフォルトで [オフ（Off）] に設定され、[請求頻度（Billing Frequency）] はデフォルトで [前払い期間（Prepaid Term）] に設定されます。それに応じて設定を変更することもできます。

ステップ 38.

**Cisco Intersight**

Offer Configuration DC-MGT-SAAS( Part of HCIX-M8-NTNX-MLB)	Estimated Lead Time NA	Price List Global Price List (USD)	<b>DC-MGT-SAAS</b> 2,520.00																																																											
<b>Requested Terms and Billing</b>																																																														
Requested Start Date 25-Jul-2025	Requested For 36 Months From 25-Jul-2025 To 24-Jul-2028	Automatically Renews For 12 Months On 25-Jul-2028	Billing Frequency Prepaid Term																																																											
<p><b>⚠ 1:</b> Please note that Cisco recommends Solution Support with Intersight which solves complex issues on average 44% faster than product support. For complete details, please refer to the following URL: <a href="https://www.cisco.com/cmen_us/customer-experience/support/solution-support.html">https://www.cisco.com/cmen_us/customer-experience/support/solution-support.html</a> (CE202322)</p> <p><b>2:</b> We recommend a selection of AI Intent to indicate whether this purchase is being made for an AI deployment. (CORE-1137)</p> <p><b>ⓘ</b> Your subscription will start and be eligible to be invoiced: i) 30 days or less (7 days for A-FLEX/A-FLEX-3/A-WHOLESALE) after Cisco notifies you that any portion of the subscription is ready for you to provision OR, ii) the day any portion of the subscription is provisioned by Cisco, whichever of the two events happens first. (C01007)</p>																																																														
<b>Configuration Summary</b> <table border="1"> <tr> <td colspan="3"><b>AI Intent</b></td> <td><b>DC-MGT-SAAS &gt; Cisco Intersight 2.0 Infrastructure Services</b></td> </tr> <tr> <td colspan="3"></td> <td><b>Cisco Intersight 2.0 Infrastructure Services</b></td> </tr> <tr> <td colspan="3"></td> <td> <table border="1"> <thead> <tr> <th>Device</th> <th>SKU</th> <th>Description</th> <th>Unit List Price (USD)</th> <th>Action</th> </tr> </thead> <tbody> <tr> <td>2</td> <td>DC-MGT-IS-SAAS-ES SA AI-C</td> <td>Infrastructure Services SaaS/CVA - Essentials</td> <td>\$35.00 Per Device/Month</td> <td><input type="button" value="Delete"/></td> </tr> <tr> <td>Qty</td> <td>DC-MGT-IS-SAAS-AD SA AI-C</td> <td>Infrastructure Services SaaS/CVA - Advantage</td> <td>Enter Qty to see List Price Per Device/Month</td> <td><input type="button" value="Delete"/></td> </tr> <tr> <td>Qty</td> <td>DC-MGT-IS-PVAPP-ES SA AI-C</td> <td>Infrastructure Services PVA - Essentials</td> <td>Enter Qty to see List Price Per Device/Month</td> <td><input type="button" value="Delete"/></td> </tr> <tr> <td>Qty</td> <td>DC-MGT-IS-PVAPP-AD SA AI-C</td> <td>Infrastructure Services PVA - Advantage</td> <td>Enter Qty to see List Price Per Device/Month</td> <td><input type="button" value="Delete"/></td> </tr> </tbody> </table> </td> </tr> <tr> <td colspan="3"><b>Cisco Intersight Support</b></td> <td><b>Add-Ons</b></td> </tr> <tr> <td colspan="3"></td> <td> <table border="1"> <thead> <tr> <th>Device</th> <th>SKU</th> <th>Description</th> <th>Unit List Price (USD)</th> <th>Action</th> </tr> </thead> <tbody> <tr> <td>Qty</td> <td>DC-MGT-IS-UCSD</td> <td>UCS Director - 1 Server License (includes Network, Storage)</td> <td>Enter Qty to see List Price Per Device/Month</td> <td><input type="button" value="Delete"/></td> </tr> </tbody> </table> </td> </tr> <tr> <td>Total <b>\$2,520.00</b></td> <td><input type="button" value="Restore Configuration"/></td> <td><input type="button" value="Cancel"/></td> <td><input type="button" value="Review Changes"/></td> </tr> </table>				<b>AI Intent</b>			<b>DC-MGT-SAAS &gt; Cisco Intersight 2.0 Infrastructure Services</b>				<b>Cisco Intersight 2.0 Infrastructure Services</b>				<table border="1"> <thead> <tr> <th>Device</th> <th>SKU</th> <th>Description</th> <th>Unit List Price (USD)</th> <th>Action</th> </tr> </thead> <tbody> <tr> <td>2</td> <td>DC-MGT-IS-SAAS-ES SA AI-C</td> <td>Infrastructure Services SaaS/CVA - Essentials</td> <td>\$35.00 Per Device/Month</td> <td><input type="button" value="Delete"/></td> </tr> <tr> <td>Qty</td> <td>DC-MGT-IS-SAAS-AD SA AI-C</td> <td>Infrastructure Services SaaS/CVA - Advantage</td> <td>Enter Qty to see List Price Per Device/Month</td> <td><input type="button" value="Delete"/></td> </tr> <tr> <td>Qty</td> <td>DC-MGT-IS-PVAPP-ES SA AI-C</td> <td>Infrastructure Services PVA - Essentials</td> <td>Enter Qty to see List Price Per Device/Month</td> <td><input type="button" value="Delete"/></td> </tr> <tr> <td>Qty</td> <td>DC-MGT-IS-PVAPP-AD SA AI-C</td> <td>Infrastructure Services PVA - Advantage</td> <td>Enter Qty to see List Price Per Device/Month</td> <td><input type="button" value="Delete"/></td> </tr> </tbody> </table>	Device	SKU	Description	Unit List Price (USD)	Action	2	DC-MGT-IS-SAAS-ES SA AI-C	Infrastructure Services SaaS/CVA - Essentials	\$35.00 Per Device/Month	<input type="button" value="Delete"/>	Qty	DC-MGT-IS-SAAS-AD SA AI-C	Infrastructure Services SaaS/CVA - Advantage	Enter Qty to see List Price Per Device/Month	<input type="button" value="Delete"/>	Qty	DC-MGT-IS-PVAPP-ES SA AI-C	Infrastructure Services PVA - Essentials	Enter Qty to see List Price Per Device/Month	<input type="button" value="Delete"/>	Qty	DC-MGT-IS-PVAPP-AD SA AI-C	Infrastructure Services PVA - Advantage	Enter Qty to see List Price Per Device/Month	<input type="button" value="Delete"/>	<b>Cisco Intersight Support</b>			<b>Add-Ons</b>				<table border="1"> <thead> <tr> <th>Device</th> <th>SKU</th> <th>Description</th> <th>Unit List Price (USD)</th> <th>Action</th> </tr> </thead> <tbody> <tr> <td>Qty</td> <td>DC-MGT-IS-UCSD</td> <td>UCS Director - 1 Server License (includes Network, Storage)</td> <td>Enter Qty to see List Price Per Device/Month</td> <td><input type="button" value="Delete"/></td> </tr> </tbody> </table>	Device	SKU	Description	Unit List Price (USD)	Action	Qty	DC-MGT-IS-UCSD	UCS Director - 1 Server License (includes Network, Storage)	Enter Qty to see List Price Per Device/Month	<input type="button" value="Delete"/>	Total <b>\$2,520.00</b>	<input type="button" value="Restore Configuration"/>	<input type="button" value="Cancel"/>	<input type="button" value="Review Changes"/>
<b>AI Intent</b>			<b>DC-MGT-SAAS &gt; Cisco Intersight 2.0 Infrastructure Services</b>																																																											
			<b>Cisco Intersight 2.0 Infrastructure Services</b>																																																											
			<table border="1"> <thead> <tr> <th>Device</th> <th>SKU</th> <th>Description</th> <th>Unit List Price (USD)</th> <th>Action</th> </tr> </thead> <tbody> <tr> <td>2</td> <td>DC-MGT-IS-SAAS-ES SA AI-C</td> <td>Infrastructure Services SaaS/CVA - Essentials</td> <td>\$35.00 Per Device/Month</td> <td><input type="button" value="Delete"/></td> </tr> <tr> <td>Qty</td> <td>DC-MGT-IS-SAAS-AD SA AI-C</td> <td>Infrastructure Services SaaS/CVA - Advantage</td> <td>Enter Qty to see List Price Per Device/Month</td> <td><input type="button" value="Delete"/></td> </tr> <tr> <td>Qty</td> <td>DC-MGT-IS-PVAPP-ES SA AI-C</td> <td>Infrastructure Services PVA - Essentials</td> <td>Enter Qty to see List Price Per Device/Month</td> <td><input type="button" value="Delete"/></td> </tr> <tr> <td>Qty</td> <td>DC-MGT-IS-PVAPP-AD SA AI-C</td> <td>Infrastructure Services PVA - Advantage</td> <td>Enter Qty to see List Price Per Device/Month</td> <td><input type="button" value="Delete"/></td> </tr> </tbody> </table>	Device	SKU	Description	Unit List Price (USD)	Action	2	DC-MGT-IS-SAAS-ES SA AI-C	Infrastructure Services SaaS/CVA - Essentials	\$35.00 Per Device/Month	<input type="button" value="Delete"/>	Qty	DC-MGT-IS-SAAS-AD SA AI-C	Infrastructure Services SaaS/CVA - Advantage	Enter Qty to see List Price Per Device/Month	<input type="button" value="Delete"/>	Qty	DC-MGT-IS-PVAPP-ES SA AI-C	Infrastructure Services PVA - Essentials	Enter Qty to see List Price Per Device/Month	<input type="button" value="Delete"/>	Qty	DC-MGT-IS-PVAPP-AD SA AI-C	Infrastructure Services PVA - Advantage	Enter Qty to see List Price Per Device/Month	<input type="button" value="Delete"/>																																		
Device	SKU	Description	Unit List Price (USD)	Action																																																										
2	DC-MGT-IS-SAAS-ES SA AI-C	Infrastructure Services SaaS/CVA - Essentials	\$35.00 Per Device/Month	<input type="button" value="Delete"/>																																																										
Qty	DC-MGT-IS-SAAS-AD SA AI-C	Infrastructure Services SaaS/CVA - Advantage	Enter Qty to see List Price Per Device/Month	<input type="button" value="Delete"/>																																																										
Qty	DC-MGT-IS-PVAPP-ES SA AI-C	Infrastructure Services PVA - Essentials	Enter Qty to see List Price Per Device/Month	<input type="button" value="Delete"/>																																																										
Qty	DC-MGT-IS-PVAPP-AD SA AI-C	Infrastructure Services PVA - Advantage	Enter Qty to see List Price Per Device/Month	<input type="button" value="Delete"/>																																																										
<b>Cisco Intersight Support</b>			<b>Add-Ons</b>																																																											
			<table border="1"> <thead> <tr> <th>Device</th> <th>SKU</th> <th>Description</th> <th>Unit List Price (USD)</th> <th>Action</th> </tr> </thead> <tbody> <tr> <td>Qty</td> <td>DC-MGT-IS-UCSD</td> <td>UCS Director - 1 Server License (includes Network, Storage)</td> <td>Enter Qty to see List Price Per Device/Month</td> <td><input type="button" value="Delete"/></td> </tr> </tbody> </table>	Device	SKU	Description	Unit List Price (USD)	Action	Qty	DC-MGT-IS-UCSD	UCS Director - 1 Server License (includes Network, Storage)	Enter Qty to see List Price Per Device/Month	<input type="button" value="Delete"/>																																																	
Device	SKU	Description	Unit List Price (USD)	Action																																																										
Qty	DC-MGT-IS-UCSD	UCS Director - 1 Server License (includes Network, Storage)	Enter Qty to see List Price Per Device/Month	<input type="button" value="Delete"/>																																																										
Total <b>\$2,520.00</b>	<input type="button" value="Restore Configuration"/>	<input type="button" value="Cancel"/>	<input type="button" value="Review Changes"/>																																																											

- a. オファー DC-MGT-SAAS の下の Cisco Intersight 2.0 インフラストラクチャ サービス ライセンスの数量は、選択されたサーバの数量と同じである必要があります。数量を入力します。

### ステップ 39.

**Cisco Intersight**

Offer Configuration DC-MGT-SAAS( Part of HCIX-M8-NTNX-MLB)	Estimated Lead Time NA	Price List Global Price List (USD)	Total (USD) 2,520.00																																			
<b>Requested Terms and Billing</b>																																						
Requested Start Date 25-Jul-2025	Requested For 36 Months From 25-Jul-2025 To 24-Jul-2028	Automatically Renews For 12 Months On 25-Jul-2028	Billing Frequency Prepaid Term																																			
<p><b>⚠ 1:</b> We recommend a selection of AI Intent to indicate whether this purchase is being made for an AI deployment. (CORE-1137)</p> <p><b>2:</b> Please note that Cisco recommends Solution Support with Intersight which solves complex issues on average 44% faster than product support. For complete details, please refer to the following URL: <a href="https://www.cisco.com/cmen_us/customer-experience/support/solution-support.html">https://www.cisco.com/cmen_us/customer-experience/support/solution-support.html</a> (CE202322)</p> <p><b>ⓘ</b> Your subscription will start and be eligible to be invoiced: i) 30 days or less (7 days for A-FLEX/A-FLEX-3/A-WHOLESALE) after Cisco notifies you that any portion of the subscription is ready for you to provision OR, ii) the day any portion of the subscription is provisioned by Cisco, whichever of the two events happens first. (C01007)</p>																																						
<b>Configuration Summary</b> <table border="1"> <tr> <td colspan="3"><b>AI Intent</b></td> <td><b>DC-MGT-SAAS &gt; AI Intent</b></td> </tr> <tr> <td colspan="3"></td> <td><b>AI Intent</b></td> </tr> <tr> <td colspan="3"></td> <td> <table border="1"> <thead> <tr> <th>License</th> <th>SKU</th> <th>Description</th> <th>Unit List Price (USD)</th> <th>Action</th> </tr> </thead> <tbody> <tr> <td>Qty</td> <td>SAAS-AI AGT</td> <td>Artificial Intelligence Use Case</td> <td>Enter Qty to see List Price Per License</td> <td><input type="button" value="Delete"/></td> </tr> <tr> <td>Qty</td> <td>SAAS-OTHER AGT</td> <td>Other Use Case</td> <td>Enter Qty to see List Price Per License</td> <td><input type="button" value="Delete"/></td> </tr> </tbody> </table> </td> </tr> <tr> <td colspan="3"><b>Cisco Intersight Support</b></td> <td></td> </tr> <tr> <td>Total <b>\$2,520.00</b></td> <td><input type="button" value="Restore Configuration"/></td> <td><input type="button" value="Cancel"/></td> <td><input type="button" value="Review Changes"/></td> </tr> </table>				<b>AI Intent</b>			<b>DC-MGT-SAAS &gt; AI Intent</b>				<b>AI Intent</b>				<table border="1"> <thead> <tr> <th>License</th> <th>SKU</th> <th>Description</th> <th>Unit List Price (USD)</th> <th>Action</th> </tr> </thead> <tbody> <tr> <td>Qty</td> <td>SAAS-AI AGT</td> <td>Artificial Intelligence Use Case</td> <td>Enter Qty to see List Price Per License</td> <td><input type="button" value="Delete"/></td> </tr> <tr> <td>Qty</td> <td>SAAS-OTHER AGT</td> <td>Other Use Case</td> <td>Enter Qty to see List Price Per License</td> <td><input type="button" value="Delete"/></td> </tr> </tbody> </table>	License	SKU	Description	Unit List Price (USD)	Action	Qty	SAAS-AI AGT	Artificial Intelligence Use Case	Enter Qty to see List Price Per License	<input type="button" value="Delete"/>	Qty	SAAS-OTHER AGT	Other Use Case	Enter Qty to see List Price Per License	<input type="button" value="Delete"/>	<b>Cisco Intersight Support</b>				Total <b>\$2,520.00</b>	<input type="button" value="Restore Configuration"/>	<input type="button" value="Cancel"/>	<input type="button" value="Review Changes"/>
<b>AI Intent</b>			<b>DC-MGT-SAAS &gt; AI Intent</b>																																			
			<b>AI Intent</b>																																			
			<table border="1"> <thead> <tr> <th>License</th> <th>SKU</th> <th>Description</th> <th>Unit List Price (USD)</th> <th>Action</th> </tr> </thead> <tbody> <tr> <td>Qty</td> <td>SAAS-AI AGT</td> <td>Artificial Intelligence Use Case</td> <td>Enter Qty to see List Price Per License</td> <td><input type="button" value="Delete"/></td> </tr> <tr> <td>Qty</td> <td>SAAS-OTHER AGT</td> <td>Other Use Case</td> <td>Enter Qty to see List Price Per License</td> <td><input type="button" value="Delete"/></td> </tr> </tbody> </table>	License	SKU	Description	Unit List Price (USD)	Action	Qty	SAAS-AI AGT	Artificial Intelligence Use Case	Enter Qty to see List Price Per License	<input type="button" value="Delete"/>	Qty	SAAS-OTHER AGT	Other Use Case	Enter Qty to see List Price Per License	<input type="button" value="Delete"/>																				
License	SKU	Description	Unit List Price (USD)	Action																																		
Qty	SAAS-AI AGT	Artificial Intelligence Use Case	Enter Qty to see List Price Per License	<input type="button" value="Delete"/>																																		
Qty	SAAS-OTHER AGT	Other Use Case	Enter Qty to see List Price Per License	<input type="button" value="Delete"/>																																		
<b>Cisco Intersight Support</b>																																						
Total <b>\$2,520.00</b>	<input type="button" value="Restore Configuration"/>	<input type="button" value="Cancel"/>	<input type="button" value="Review Changes"/>																																			

- a. ユーザーは [AI インテントオプションクラス (AI Intent Option Class) ] から選択する必要があります。

## ステップ 40.

The screenshot shows the Cisco Intersight configuration interface. At the top, a green bar labeled "Cisco Intersight" has a blue arrow pointing down to a green box labeled "DC-MGT-SAAS".

**Offer Configuration:**  
Offer Configuration: DC-MGT-SAAS( Part of HCIX-M8-NTNX-MLB)  
Estimated Lead Time: NA  
Price List: Global Price List (USD)  
Total (USD): 2,520.00

**Requested Terms and Billing:**  
Requested Start Date: 25-Jul-2025  
Requested For: 36 Months From 25-Jul-2025 To 24-Jul-2028  
Automatically Renews For: 12 Months On 25-Jul-2028  
Billing Frequency: Prepaid Term

**Configuration Summary:**

Cisco Intersight 2.0 Infrastructure Services		
SKU	Qty	List Price
DC-MGT-IS-SAAS-ES AI-C	2 Device	\$35.00 Per Device/Month
<b>Cisco Intersight Support</b>		
SKU	Qty	List Price
SVS-DCM-SUPT-BAS	1 Each	\$0.00 Per Each/Month
<b>Auto Expansion</b>		
SKU	Qty	List Price
Total		\$2,520.00

**Cisco Intersight Support:**

Each	SKU	Description	Unit List Price (USD)	Action
Qty	SVS-SSTCS-DCMGMT SA	Solution Support for DC Mgmt	Enter Qty to see List Price Per Each/Month	
Qty	SVS-L1DCS-INTER SA	Cisco Support Enhanced for INTERSIGHT	Enter Qty to see List Price Per Each/Month	
Qty	SVS-L2DCS-INTER SA	Cisco Support Signature for INTERSIGHT	Enter Qty to see List Price Per Each/Month	
1	SVS-DCM-SUPT-BAS	Cisco Support Standard for DCM	\$0.00 Per Each/Month	

Buttons at the bottom: Restore Configuration, Cancel, Review Changes.

A red box labeled "a" highlights the "List Price" column in the Cisco Intersight Support section.

- Cisco Intersight License には、個別のサポートが付属しています。基本組み込み型サポートはデフォルトの選択です。顧客は、必要に応じてソリューション サポート、CX、サクセス トラッック L1 および L2 (SAAS でのみサポート) にアップグレード可能です。

## ステップ 41.

**Available Components**

- HCX X 9000 CHASSIS (1 Selected)
- HCX X 9000 SERVER (1 Selected)
- HCX X MODULAR SERVER (1 Selected)
- FAIRVIEW INTERCONNECT
- NUTANIX SOFTWARE
- NUTANIX PROF SERVICE
- CISCO INTERSIGHT

**Product**

HCX X 9000 CHASSIS = 1 Selected (Min 0, Max 9999999)

HCX X 9000 SERVER = 1 Selected (Min 0, Max 9999999)

HCX X MODULAR SERVER = 1 Selected (Min 0, Max 9999999)

FABRIC INTERCONNECT = 0 Selected (Min 0, Max 9999999)

NUTANIX SOFTWARE = 2 Selected (Min 0, Max 2)

NUTANIX PROF SERVICE = 1 Selected (Min 0, Max 1)

CISCO INTERSIGHT = 1 Selected (Min 0, Max 1)

**Service Preferences**

1: Please refer to the Nutanix Sase Tool. Miss these Nutanix constraints before you proceed to do the Product Configuration.  
2: Please note that if Nutanix Mission Critical Software Support is purchased, it is recommended that Customer upgrade to Cisco Critical Support.

**Estimated Lead Time**: 21 days

**Price List**: Global Price List (USD)

**Total**: 472,729.46

**Buttons**: Cancel, Done

- 各製品のステータスが【有効 (Valid)】であり、警告メッセージがなくなると MLB の構成が完了します。
- 「PLUS」をクリックして、展開して、各製品に行った選択を表示します。
- MLB 構成を完了するために、【完了 (Done)】をクリックします。

## ステップ 42.

**Cisco Intersight**

Available Components	Unit List Price (USD)	Extended List Price (USD)
<input checked="" type="checkbox"/> HCI X 9508 CHASSIS	66,236.10	180,637.38
<input checked="" type="checkbox"/> HCI X MODULAR SERVER	38,032.25	135,020.16
<input checked="" type="checkbox"/> FABRIC INTERCONNECT		
<input checked="" type="checkbox"/> NUTANIX SOFTWARE	27.54	126,894.18
<input checked="" type="checkbox"/> NUTANIX PROF SERVICE	26,882.57	27,857.74
<input checked="" type="checkbox"/> CISCO INTERSIGHT	0.00	0.00
<b>CNDL-DESELECT-D</b> Conditional Deselected Estimated Lead Time: 7 days (Min 0, Max 1)		

- a. CNDL-DESELECT-D は、お客様が EA 契約を介して Cisco Intersight ライセンスをすでに購入している場合、または注文が Disti Fulfillment である場合にのみ選択することを意図しています。

#### ステップ 43.

**Cisco Intersight**

Product Configuration		Estimated Lead Time	Price List	Total (USD)
CNDL-DESELECT-D part of HCIX-M8-NTNX-MLB		7 days	Global Price List in US Dollars (USD)	0.00

**Reason Codes** ⚠

A CNDL-DESELECT-D quantity 1 requires a minimum quantity of 1 from Reason Codes (CE100012)

Configuration Summary		View Full Summary	
Category	Qty	Extended List Price (USD)	
<input checked="" type="checkbox"/> Reason Codes <span style="color: orange;">⚠</span>			

**CNDL-DESELECT-D > Reason Codes**

**Reason Codes** ⚠

SKU	Qty	Estimated Lead Time	Unit List Price (USD)
<input type="radio"/> OPTOUT-DISTI-ONLY For Disti when ordering mandatory licenses separately	1	3 days	0.00
<input type="radio"/> OPTOUT-EA-ONLY License not needed: Customer already owns Licenses in an EA	1	3 days	0.00
<input type="radio"/> OPTOUT-ENTL-SWAP License not needed: Entitlements updated in Smart Account. <a href="#">More</a>	1	3 days	0.00

Total: 0.00  
Estimated Lead Time: 7 days

Reset Configuration Cancel Done

- a. 適切な【理由コード（Reason Code）】を選択してください

## ステップ 44.

Bundle Configuration  
HCIX-MLB-NTNX-MLB

Estimated Lead Time: 21 days

Total: 470,299.45

Set service preferences for this configuration ▾

**HCX 9508 CHASSIS**

Unit List Price (USD): 8,530.06

Cisco Context-aware Management 9508 Nutanix Chassis Configured  
Estimated Lead Time: 21 day (Min 0, Max 9999)

**HCX MODULAR SERVER**

Unit List Price (USD): 36,032.25

Cisco Context-aware Management 9508 Nutanix Chassis Configured  
Estimated Lead Time: 21 day (Min 0, Max 9999)

**FABRIC INTERCONNECT**

Unit List Price (USD): 126,894.18

**NUTANIX SOFTWARE**

Unit List Price (USD): 27.54

Nutanix Software 3 and above  
Add Custom Name | Edit Options | Remove Line | Dependent Hardware 0

Requested Start Date: 25-Jul-2025  
Requested For: 36 Months From 25-Jul-2025 To 24-Jul-2028  
Automatically Renews For: No Auto Renewal  
Billing Frequency: Prepaid Term

**NUTANIX PROFESSIONAL SERVICES**

Unit List Price (USD): 26,882.57

Nutanix Professional Service  
Add Custom Name | Edit Options | Remove Line | Dependent Hardware 0

Requested Start Date: 22-Jul-2025  
Requested For: 1 Month From 22-Jul-2025 To 21-Aug-2025  
Automatically Renews For: No Auto Renewal  
Billing Frequency: Prepaid Term

**CISCO INTERIGHT**

Unit List Price (USD): 0.00

Cisco Interight  
Conditional Services  
Add Custom Name | Edit Options | Remove Line | Dependent Hardware 0

- 各製品のステータスが【有効 (Valid)】であり、警告メッセージがなくなると MLB の構成が完了します。
- 「PLUS」をクリックして、展開して、各製品に行った選択を表示します。
- MLB 構成を完了するために、【完了 (Done)】をクリックします。

## 翻訳について

このドキュメントは、米国シスコ発行ドキュメントの参考和訳です。リンク情報につきましては、日本語版掲載時点で、英語版にアップデートがあり、リンク先のページが移動/変更されている場合がありますことをご了承ください。あくまでも参考和訳となりますので、正式な内容については米国サイトのドキュメントを参照ください。