



Cisco ASA 5500 シリーズおよび PIX 500 シリーズ セキュリティ アプライアンス ハードウェアおよびソフトウェアの互換性

Cisco ASA 5500 Series and PIX 500 Series Security Appliance Hardware and Software Compatibility

OL-5892-04-J

【注意】 シスコ製品をご使用になる前に、安全上の注意 (www.cisco.com/jp/go/safety_warning/) をご確認ください。

本書は、米国シスコシステムズ発行ドキュメントの参考和訳です。米国サイト掲載ドキュメントとの差異が生じる場合があるため、正式な内容については米国サイトのドキュメントを参照ください。また、契約等の記述については、弊社販売パートナー、または、弊社担当者にご確認ください。

このドキュメントでは、Cisco ASA 5500 シリーズおよび PIX 500 シリーズのセキュリティ アプライアンス ソフトウェアとハードウェアの、ASDM、IPS ソフトウェア、CSC ソフトウェア、および 4GE SSM ハードウェアとの互換性を記載します。

表 1 ASA/PIX の互換性

ハードウェア	ソフトウェア
PIX ハードウェア	
501、506E	PIX 6.3/PDM 3.0
515/515E、525、535	PIX 6.3/PDM 3.0 PIX 7.0/ASDM 5.0 PIX 7.1/ASDM 5.1 PIX 7.2/ASDM 5.2 PIX 8.0/ASDM 6.0、6.1、および 6.2



表 1 ASA/PIX の互換性 (続き)

ハードウェア	ソフトウェア
ASA ハードウェア	
5505	ASA 7.2/ASDM 5.2 ASA 8.0/ASDM 6.0、6.1、および 6.2 ASA 8.2/ASDM 6.2
5510, 5520, 5540	ASA 7.0/ASDM 5.0 ASA 7.1/ASDM 5.1 ASA 7.2/ASDM 5.2 ASA 8.0/ASDM 6.0、6.1、および 6.2 ASA 8.2/ASDM 6.2
5550	ASA 7.1 (2) /ASDM 5.1 (2) 以上 ASA 7.2/ASDM 5.2 ASA 8.0/ASDM 6.0、6.1、および 6.2 ASA 8.2/ASDM 6.2
5580	ASA 8.1/ASDM 6.1 および 6.2 ASA 8.2/ASDM 6.2
ASA 5505 対応の SSC	
Advanced Inspection and Prevention (AIP) SSC 上の IPS ソフトウェア	
6.2	ASA 8.2/ASDM 6.2
ASA 5510、5520、および 5540 対応の SSC	
AIP SSM 上の IPS ソフトウェア	
5.0、5.1 ^{1,2}	ASA 7.0/ASDM 5.0 ASA 7.1/ASDM 5.1 ASA 7.2/ASDM 5.2 ASA 8.0/ASDM 6.0、6.1、および 6.2 ASA 8.2/ASDM 6.2
6.0	ASA 7.2/ASDM 5.2 ASA 8.0/ASDM 6.0、6.1、および 6.2 ² ASA 8.2/ASDM 6.2
6.1	ASA 8.0/ASDM 6.1 および 6.2 ASA 8.2/ASDM 6.2
6.2	ASA 8.0/ASDM 6.1 および 6.2 ASA 8.2/ASDM 6.2

表 1 ASA/PIX の互換性 (続き)

ハードウェア	ソフトウェア
CSC SSM 上の Content Security and Control (CSC) ソフトウェア³	
6.0	ASA 7.1/ASDM 5.1
6.1	ASA 7.1/ASDM 5.1 ASA 7.2/ASDM 5.2 ASA 8.0/ASDM 6.0、6.1、および 6.2 ASA 8.2/ASDM 6.2
6.2	ASA 7.1/ASDM 5.1 ASA 7.2/ASDM 5.2 ASA 8.0/ASDM 6.0、6.1、および 6.2 ASA 8.2/ASDM 6.2
4GE SSM⁴	ASA 7.0 (4) /ASDM 5.0 (4) 以上 ASA 7.1/ASDM 5.1 ASA 7.2/ASDM 5.2 ASA 8.0/ASDM 6.0、6.1、および 6.2 ASA 8.2/ASDM 6.2

1. IPS 5.1 (4) は、シグニチャ アップデートをサポートする最小バージョンです。
2. ASDM 5.2 以降では、ASDM から IDM を起動して IPS リリース 5.0 と 5.1 を管理できます。ネイティブに統合された管理を行うには、IPS 6.0 以上を使用する必要があります。
3. ASA 5540 適応型セキュリティ アプライアンスに CSC SSM を導入する場合は、スキャン対象のトラフィックに対してのみ CSC SSM が送信されるようにセキュリティ アプライアンスを設定してください。CSC SSM ライセンスは、最大 1000 人のユーザをサポートしますが、Cisco ASA 5540 適応型セキュリティ アプライアンスは、さらに多数のユーザをサポートできます。
4. ASA 5550 では、4GE SSM が標準でインストールされており、ユーザは削除できません。4GE SSM はインテリジェント SSM ではなく、単体ではリリースされていません。

CCDE, CCSI, CCENT, Cisco Eos, Cisco HealthPresence, the Cisco logo, Cisco Lumin, Cisco Nexus, Cisco Nurse Connect, Cisco Stackpower, Cisco StadiumVision, Cisco TelePresence, Cisco WebEx, DCE, and Welcome to the Human Network are trademarks; Changing the Way We Work, Live, Play, and Learn and Cisco Store are service marks; and Access Registrar, Aironet, AsyncOS, Bringing the Meeting To You, Catalyst, CCDA, CCDP, CCIE, CCIP, CCNA, CCNP, CCSP, CCVP, Cisco, the Cisco Certified Internetwork Expert logo, Cisco IOS, Cisco Press, Cisco Systems, Cisco Systems Capital, the Cisco Systems logo, Cisco Unity, Collaboration Without Limitation, EtherFast, EtherSwitch, Event Center, Fast Step, Follow Me Browsing, FormShare, GigaDrive, HomeLink, Internet Quotient, IOS, iPhone, iQuick Study, IronPort, the IronPort logo, LightStream, Linksys, MediaTone, MeetingPlace, MeetingPlace Chime Sound, MGX, Networkers, Networking Academy, Network Registrar, PCNow, PIX, PowerPanels, ProConnect, ScriptShare, SenderBase, SMARTnet, Spectrum Expert, StackWise, The Fastest Way to Increase Your Internet Quotient, TransPath, WebEx, and the WebEx logo are registered trademarks of Cisco Systems, Inc. and/or its affiliates in the United States and certain other countries.

All other trademarks mentioned in this document or website are the property of their respective owners. The use of the word partner does not imply a partnership relationship between Cisco and any other company. (0903R)

Copyright © 2009 Cisco Systems, Inc.
All rights reserved.

Copyright © 2009, シスコシステムズ合同会社.
All rights reserved.

