



予想される出力エラー

- [予想される出力エラー \(1 ページ\)](#)

予想される出力エラー

Cisco Nexus ハードウェア -EX、-FX1-3、および N93xxC は、内部インターフェイス カウンタに出力エラーを表示し、ACI 環境で障害 (F119936) を発生させる可能性があります。 **show interface** の出力エラー カウンタが変更されていない限り、これは予期される動作です。

また、 **show platform internal counters** ポート出力エラーが増加することに注意してください。ただし、 **show interface** で同じポートをチェックすると、出力エラー率は増加しません。

このセクションでは、予想される出力エラーの例を示します。

```
module-1# show platform internal counters port 51
Stats for port 51
(note: forward drops includes sup redirected packets too)
IF          LPort          Input              Output
          LPort          Packets    Bytes    Packets    Bytes
eth-1/51    51    Total      669974    110547179    692398    194500094
          Unicast    112138     30292113    439809    161274739
          Multicast    0           0           251315    33075023
          Flood      261736     32880023    1274      150332
          Total Drops 296100           261736
          Buffer      0           0
          Error      0           261736
          <...>

leaf-101# show interface ethernet 1/51
Ethernet1/51 is up
admin state is up, Dedicated Interface
Hardware: 1000/10000/100000/40000 Ethernet, address: 0000.0000.0000 (bia a023.9f56.48f3)

MTU 9366 bytes, BW 40000000 Kbit, DLY 1 usec
reliability 255/255, txload 1/255, rxload 1/255
Encapsulation ARPA, medium is broadcast
Port mode is routed
full-duplex, 40 Gb/s, media type is 40G
FEC (forward-error-correction) : disable-fec
Beacon is turned off
Auto-Negotiation is turned on
Input flow-control is off, output flow-control is off
Auto-mdix is turned off
```

```
Rate mode is dedicated
Switchport monitor is off
EtherType is 0x8100
EEE (efficient-ethernet) : n/a
Last link flapped 1d14h
Last clearing of "show interface" counters never
1 interface resets
30 seconds input rate 4912 bits/sec, 3 packets/sec
30 seconds output rate 1944 bits/sec, 2 packets/sec
Load-Interval #2: 5 minute (300 seconds)
  input rate 3360 bps, 2 pps; output rate 10504 bps, 4 pps
L3 in Switched:
  ucast: 0 pkts, 0 bytes - mcast: 0 pkts, 0 bytes
L3 out Switched:
  ucast: 0 pkts, 0 bytes - mcast: 0 pkts, 0 bytes
RX
 352942 unicast packets  317417 multicast packets  0 broadcast packets
 670359 input packets  110608007 bytes
 8643 jumbo packets  0 storm suppression bytes
 0 runts  0 giants  0 CRC  0 no buffer
 0 input error  0 short frame  0 overrun  0 underrun  0 ignored
 0 watchdog  0 bad etype drop  0 bad proto drop  0 if down drop
 0 input with dribble  0 input discard
 0 Rx pause
TX
 417109 unicast packets  275682 multicast packets  0 broadcast packets
 692791 output packets  194559643 bytes
 7173 jumbo packets
0 output error  0 collision  0 deferred  0 late collision
 0 lost carrier  0 no carrier  0 babble  0 output discard
 0 Tx pause
```

翻訳について

このドキュメントは、米国シスコ発行ドキュメントの参考和訳です。リンク情報につきましては、日本語版掲載時点で、英語版にアップデートがあり、リンク先のページが移動/変更されている場合がありますことをご了承ください。あくまでも参考和訳となりますので、正式な内容については米国サイトのドキュメントを参照ください。