

Установившийся Контроллер доступа / Устранение неполадок Проблемы Соединения AP NGWC с Трассировками

Содержание

[Введение](#)

[Предварительные условия](#)

[Требования](#)

[Используемые компоненты](#)

[Родственные продукты](#)

[Последовательность соединения AP](#)

[Устранение неполадок](#)

[Основные шаги](#)

[Трассировки от контроллера](#)

[Обычные причины для сбоя соединения AP](#)

[Проблема 1: AP на Catalyst Коммутатор серии 3850 не находится в VLAN беспроводного управления.](#)

[Проблема 2: Использованная модель точки доступа является неподдерживаемой.](#)

[Проблема 3: Лицензия количества AP не включена на контроллере.](#)

[Проблема 4: управляющему домен не соответствуют.](#)

[Проблема 5: беспроводной контроллер мобильности не определен.](#)

[Проблема 6: AP имеет код сетки на нем.](#)

[Проблема 7: AP3700 связан с Catalyst Коммутатор серии 3850, который выполняется 3.3.0SE.](#)

[Проблема 8: время контроллера вне интервала Достоверности сертификата AP.](#)

[Проблема 9: список авторизации AP включен на WLC; AP не находится в списке авторизации.](#)

[Проблема 10: Политика AP MIC отключена.](#)

[Общие практические указания](#)

Введение

Этот документ описывает команды трассировки, которые используются, чтобы решить проблемы соединения Точки доступа (AP) на установившихся контроллерах доступа и описывают некоторые обычные причины для сбоя соединения AP.

Предварительные условия

Требования

Cisco рекомендует иметь базовые знания об этих темах:

- Протокол LWAPP / Контроль и Инициализация Точек беспроводного доступа (CAPWAP)
- Облегченная точка доступа (LAP) и конфигурации Контроллера беспроводной локальной сети (WLC) для главной операции

Используемые компоненты

Сведения в этом документе основываются на Cisco Catalyst Коммутатор серии 3850, который работает под управлением ПО версии 3.3.0 SE.

Сведения, представленные в этом документе, были получены от устройств, работающих в специальной лабораторной среде. Все устройства, описанные в этом документе, были запущены с чистой (стандартной) конфигурацией. В рабочей сети необходимо изучить потенциальное воздействие всех команд до их использования.

Родственные продукты

Этот документ применим ко всем установившимся контроллерам доступа.

- Cisco контроллеры беспроводной локальной сети серии 5760
- Cisco Catalyst 3560 Series Switches
- Cisco Catalyst коммутаторы серии 3850

Последовательность соединения AP

Устранение неполадок

Основные шаги

Для решения проблемы соединения AP на установившихся контроллерах доступа выполните эти шаги:

1. Подтвердите, что AP в состоянии вытянуть IP-адрес. От коммутатора, где AP включен, войдите:

```
#show cdp neighbor <port_id> detail
```

Примечание: Для Catalyst Коммутатор серии 3850 AP должен напрямую подключиться к Catalyst, которым должны быть Коммутатор серии 3850 и конфигурация порта коммутатора:

```
Интерфейсный концерт <>
```

```
Switchport mode access
```

```
Switchport access vlan x>> , где x является interface vlan беспроводного управления x
```

настроенный на Catalyst Коммутатор серии 3850.

2. Удостоверьтесь, что WLC может пропинговать IP-адрес и наоборот.
3. Проверьте, что беспроводной контроллер мобильности (MC) настроен в сети. Если вы зарегистрированы в Агента Мобильности, гарантируете, что туннельный контроллер мобильности активен.

```
#show wireless mobility summary
```

4. Гарантируйте, что лицензия AP включена на MC:

```
#show license right-to-use summary
```

5. Подтвердите, что включен надлежащий код страны:

```
#show wireless country configured
```

Трассировки от контроллера

Как только правильная конфигурация существует, если AP отказывает, команды трассировки могут быть усилены для дальнейшего диагноза. Эти команды трассировки доступны на контроллере для устранения проблем Соединения AP и CAPWAP:

- **#Set** отслеживают capwap
- **#Set** отслеживают capwap AP
- **#Set** отслеживают AP группы

На основе анализа выходных данных трассировки трассировки AP группы предоставили более соответствующие выходные данные для устранения неполадок соединения AP. Поэтому эта (нефильтруемая) трассировка обсуждена подробно в этом документе. См. Общий раздел Практических указаний этого документа для получения дополнительной информации о параметрах фильтра и ограничениях на эту трассировку.

Примечание: Пример выходных данных (фильтруемый и нефильтруемый) для capwap и capwap AP включен для ссылки.

- Для просмотра настроек по умолчанию трассировки войдите:

```
#show trace settings group-ap
```

```
Buffer Properties:
```

```
Feature-
```

```
Name
```

```
Size
```

```
Level
```

```
-----  
-----
```

```
capwap/ap/event  
warning
```

```
0
```

```
dtls/ap/event  
warning
```

```
0
```

```
iosd-  
wireless/capwap  
g
```

```
0
```

```
warnin
```

```
Feature-Name: capwap/ap/event
```

```
Filters: None
```

```
Feature-Name: dtls/ap/event
```

```
Filters: None
```

```
Feature-Name: iosd-wireless/capwap
```

```
Filters: None
```

Примечание: По умолчанию нет никакого набора фильтров ни на одной из трассировок.

- Для очистки буфера трассировки, который соответствует трассировке AP группы, войти `#set trace control group-ap clear`

- Для установки уровня трассировки для трассировки AP группы войдите:

```
#set trace group-ap level ?
debug   Debug-level messages (7)
default Unset Trace Level Value
err     Error conditions (3)
info    Informational (6)
warning Warning conditions (4)
```

Используйте отладку отладки уровня AP группы трассировки `#set`, в то время как вы устраняете неполадки.

- Для проверки уровня трассировки войдите:

```
# show trace settings group-ap
```

Buffer Properties:

Feature-

Name	Size	Level
capwap/ap/event	0	
debug		
dtls/ap/event	0	
debug		
iosd-		
wireless/capwap	0	debug

Feature-Name: capwap/ap/event

Filters: None

Feature-Name: dtls/ap/event

Filters: None

Feature-Name: iosd-wireless/capwap

Filters: None

- Для просмотра выходных данных трассировки войдите:

```
# show trace messages group-ap
```

Discovery-Request/Respose

```
[11/14/13 14:50:17.484 UTC 702f4a 8528] f84f.57ca.3860 Discovery Request from
10.201.234.24:18759
```

```
[11/14/13 14:50:17.484 UTC 702f4b 8528] f84f.57ca.3860 Discovery apType = 0,
apModel = AIR-CAP2602I-A-K9, Discovery supportedRadios = 0, incomingRadJoinPriority
= 1, Discovery versionNum = 167863296
```

```
[11/14/13 14:50:17.484 UTC 702f4c 8528] f84f.57ca.3860 Join Priority Processing
status =0, Incoming Ap's Priority 1, MaxLrads = 50, joined Aps =0
```

```
[11/14/13 14:50:17.484 UTC 702f4d 8528] f84f.57ca.3860 Validated Discovery request
with dest ip : 255.255.255.255 from AP 10.201.234.24. Response to be sent using
ip : 10.201.234.4
```

```
[11/14/13 14:50:17.484 UTC 702f4e 8528] Encode static AP manager 10.201.234.4,
AP count 0
```

[11/14/13 14:50:17.484 UTC 702f4f 8528] acEncodeMwarTypePayload encode mwarType = 0 in capwapMwarTypePayload.

[11/14/13 14:50:17.484 UTC 702f50 8528] f84f.57ca.3860 **Discovery Response** sent to 10.201.234.24:18759

[11/14/13 14:50:27.484 UTC 57 8528] Connection not found in hash table - Table empty.

DTLS-квитирование

Примечание: Это с точки зрения AP, поэтому только обменивается сообщениями передаваемый AP, замечены.

[11/14/13 14:50:27.484 UTC 702f51 8528] DTLS connection not found, creating new connection for 10:201:234:24 (18759) 10:201:234:4 (5246)

[11/14/13 14:50:27.484 UTC 702f52 8528] acDtlsCallback: entering...

[11/14/13 14:50:27.484 UTC 702f53 8528] acDtlsCallback: cb->code 10

[11/14/13 14:50:27.484 UTC 58 8528] Certificate installed for PKI based authentication.

[11/14/13 14:50:27.484 UTC 59 8528] Incremented concurrent handshaking count 1

[11/14/13 14:50:27.484 UTC 5a 8528] f84f.57ca.3860 record=Handshake epoch=0 seq=0

[11/14/13 14:50:27.484 UTC 5b 8528] f84f.57ca.3860 **msg=ClientHello** len=44 seq=0 frag_off=0 frag_len=44

[11/14/13 14:50:27.485 UTC 5c 8528] f84f.57ca.3860 Handshake in progress...

[11/14/13 14:50:27.489 UTC 5d 8528] f84f.57ca.3860 record=Handshake epoch=0 seq=1

[11/14/13 14:50:27.489 UTC 5e 8528] f84f.57ca.3860 **msg=ClientHello** len=76 seq=1 frag_off=0 frag_len=76 (**with cookie**)

[11/14/13 14:50:27.490 UTC 5f 8528] f84f.57ca.3860 Handshake in progress...

[11/14/13 14:50:27.670 UTC 60 8528] f84f.57ca.3860 record=Handshake epoch=0 seq=2

[11/14/13 14:50:27.670 UTC 61 8528] f84f.57ca.3860 **msg=Certificate** len=1146 seq=2 frag_off=0 frag_len=519

[11/14/13 14:50:27.670 UTC 62 8528] f84f.57ca.3860 Handshake in progress...

[11/14/13 14:50:27.670 UTC 63 8528] f84f.57ca.3860 record=Handshake epoch=0 seq=3

[11/14/13 14:50:27.670 UTC 64 8528] f84f.57ca.3860 msg=Certificate len=1146 seq=2 frag_off=519 frag_len=519

[11/14/13 14:50:27.670 UTC 65 8528] f84f.57ca.3860 Handshake in progress...

[11/14/13 14:50:27.670 UTC 66 8528] f84f.57ca.3860 record=Handshake epoch=0 seq=4

[11/14/13 14:50:27.670 UTC 67 8528] f84f.57ca.3860 msg=Certificate len=1146 seq=2 frag_off=1038 frag_len=108

[11/14/13 14:50:27.671 UTC 702f54 8528] acDtlsCallback: entering...

[11/14/13 14:50:27.671 UTC 702f55 8528] acDtlsCallback: cb->code 3

[11/14/13 14:50:27.672 UTC 68 8528] Verify X.509 certificate from wtp
7c69.f604.9460

[11/14/13 14:50:27.673 UTC 702f56 8528] acDtlsCallback Cert validation PENDING

[11/14/13 14:50:27.673 UTC 69 8528] f84f.57ca.3860 Certificate verification -
pending...

[11/14/13 14:50:27.673 UTC 6a 8528] f84f.57ca.3860 Handshake in process..
awaiting certificate verification result..

[11/14/13 14:50:27.673 UTC 6b 8528] f84f.57ca.3860 record=Handshake epoch=0 seq=5

[11/14/13 14:50:27.673 UTC 6c 8528] f84f.57ca.3860 **msg=ClientKeyExchange**
len=130 seq=3 frag_off=0 frag_len=130

[11/14/13 14:50:27.673 UTC 702f57 8528] acDtlsCallback: entering...

[11/14/13 14:50:27.673 UTC 702f58 8528] acDtlsCallback: cb->code 3

[11/14/13 14:50:27.674 UTC 6d 8528] Verify X.509 certificate from wtp
7c69.f604.9460

[11/14/13 14:50:27.675 UTC 702f59 8528] acDtlsCallback Cert validation PENDING

[11/14/13 14:50:27.675 UTC 6e 8528] f84f.57ca.3860 Certificate verification -
pending...

[11/14/13 14:50:27.675 UTC 6f 8528] f84f.57ca.3860 Handshake in process..
awaiting certificate verification result..

[11/14/13 14:50:27.675 UTC 70 8528] f84f.57ca.3860 record=Handshake epoch=0 seq=6

[11/14/13 14:50:27.675 UTC 71 8528] f84f.57ca.3860 **msg=CertificateVerify**
len=258 seq=4 frag_off=0 frag_len=258

[11/14/13 14:50:27.675 UTC 702f5a 8528] acDtlsCallback: entering...

[11/14/13 14:50:27.675 UTC 702f5b 8528] acDtlsCallback: cb->code 3

[11/14/13 14:50:27.676 UTC 72 8528] Verify X.509 certificate from wtp 7c69.f604.9460

[11/14/13 14:50:27.676 UTC 702f5c 8528] acDtlsCallback Cert validation PENDING

[11/14/13 14:50:27.676 UTC 73 8528] f84f.57ca.3860 Certificate verification -
pending...

[11/14/13 14:50:27.676 UTC 74 8528] f84f.57ca.3860 Handshake in process..
awaiting certificate verification result..

[11/14/13 14:50:27.677 UTC 75 8528] f84f.57ca.3860 **record=ChangeCipherSpec**
epoch=0 seq=7

[11/14/13 14:50:27.677 UTC 702f5d 8528] acDtlsCallback: entering...

[11/14/13 14:50:27.677 UTC 702f5e 8528] acDtlsCallback: cb->code 3

[11/14/13 14:50:27.677 UTC 76 8528] Verify X.509 certificate from wtp 7c69.f604.9460

[11/14/13 14:50:27.678 UTC 702f5f 8528] acDtlsCallback Cert validation PENDING

[11/14/13 14:50:27.678 UTC 77 8528] f84f.57ca.3860 Certificate verification -
pending...

[11/14/13 14:50:27.678 UTC 78 8528] f84f.57ca.3860 Handshake in process..
awaiting certificate verification result..

[11/14/13 14:50:27.678 UTC 79 8528] f84f.57ca.3860 record=Handshake epoch=1 seq=0

[11/14/13 14:50:27.678 UTC 7a 8528] f84f.57ca.3860 **msg=Unknown or Encrypted**

[11/14/13 14:50:27.679 UTC 702f60 8528] acDtlsCallback: entering...

[11/14/13 14:50:27.679 UTC 702f61 8528] acDtlsCallback: cb->code 3

[11/14/13 14:50:27.679 UTC 7b 8528] Verify X.509 certificate from wtp 7c69.f604.9460

[11/14/13 14:50:27.680 UTC 702f62 8528] acDtlsCallback Cert validation PENDING

[11/14/13 14:50:27.680 UTC 7c 8528] f84f.57ca.3860 Certificate verification -
pending...

[11/14/13 14:50:27.680 UTC 7d 8528] f84f.57ca.3860 Handshake in process..
awaiting certificate verification result..

[11/14/13 14:50:27.681 UTC 7e 8528] Tickling the connection: 10.201.234.4:5246
<-> 10.201.234.24:18759.

[11/14/13 14:50:27.681 UTC 702f63 8528] acDtlsCallback: entering...

[11/14/13 14:50:27.681 UTC 702f64 8528] acDtlsCallback: cb->code 3

[11/14/13 14:50:27.682 UTC 7f 8528] **Verify X.509 certificate from wtp
7c69.f604.9460 >> AP Ethernet mac**

[11/14/13 14:50:27.683 UTC 702f65 8528] acDtlsCallback Cert validation SUCCESS.

[11/14/13 14:50:27.683 UTC 80 8528] f84f.57ca.3860 **Certificate verification -
passed!**

[11/14/13 14:50:27.706 UTC 81 8528] f84f.57ca.3860 **Connection established!**

[11/14/13 14:50:27.706 UTC 702f66 8528] acDtlsCallback: entering...

[11/14/13 14:50:27.706 UTC 702f67 8528] acDtlsCallback: cb->code 0

[11/14/13 14:50:27.706 UTC 82 8528] f84f.57ca.3860 **DTLS Connection 0x5789a5e0
established on local port 5246**

[11/14/13 14:50:27.706 UTC 83 8528] f84f.57ca.3860 Setting DTLS MTU for link to
peer 10.201.234.24:18759

[11/14/13 14:50:27.706 UTC 84 8528] Load Balancer: Platform Not supported,
Exiting from ctrl_tunnel_lb

[11/14/13 14:50:27.706 UTC 85 8528] Capwap Control DTLS key plumbing: Get SA
resources from LB for AP IP 10.201.234.24, rc = 4

[11/14/13 14:50:27.706 UTC 86 8528] Plumbing DTLS keys for local 10.201.234.4:5246
and peer 10.201.234.24:18759, anc_sw_id 0, anc_asic_id 0, res_sw_id 0, res_asic_id 0

[11/14/13 14:50:27.706 UTC 87 8528] Created CAPWAP control DTLS engine session
10.201.234.4:5246 <-> 10.201.234.24:18759.

[11/14/13 14:50:27.706 UTC 88 8528] f84f.57ca.3860 Sending Finished using epoch 1

[11/14/13 14:50:27.706 UTC 702f68 8528] DTLS Session established server

(10.201.234.4:5246), client (10.201.234.24:18759)

[11/14/13 14:50:27.706 UTC 702f69 8528] Starting wait join timer for AP:
10.201.234.24:18759

[11/14/13 14:50:27.707 UTC 30e2 267] %DTLS: entering dtls_add_dtls_session_db_entry

[11/14/13 14:50:27.707 UTC 30e3 267] %DTLS: sip = 0xac9ea04 dip = 0xac9ea18
sport =5246 dport=18759

[11/14/13 14:50:27.707 UTC 30e4 267] %DTLS: dtls_add_dtls_session_db_entry:
anchor_port iifd : 1088ec00000003b : capwap_iifd : 0 : session type : 0 :
sw_num : 0 : asic : 0

[11/14/13 14:50:27.707 UTC 30e5 267] %DTLS: bk_sw_num : 0 bk_asic : 0

[11/14/13 14:50:27.710 UTC 89 8528] Received DTLS engine action feedback for
CAPWAP connection

[11/14/13 14:50:27.711 UTC 8a 8528] DTLS Engine Add Success received for
connection 10.201.234.4:5246 / 10.201.234.24:18759

[11/14/13 14:50:27.711 UTC 8b 8528] Key plumb succeeded

[11/14/13 14:50:27.711 UTC 8c 8528] Decrement concurrent handshaking count 0

[11/14/13 14:50:27.711 UTC 8d 8528] Updating state for wtp f84f.57ca.3860 ip
10.201.234.24

[11/14/13 14:50:27.711 UTC 8e 8528] CAPWAP WTP entry not yet created.

[11/14/13 14:50:27.712 UTC 702f6a 8528] Unable to find the First RCB index.
Return Value: 2

Ответ запроса соединения

[11/14/13 14:50:27.712 UTC 702f6b 8528] f84f.57ca.3860 **Join Request** from
10.201.234.24:18759

[11/14/13 14:50:27.712 UTC 702f6c 8528] f84f.57ca.3860 For phy port iif id
0x01088ec00000003b, control session - anc sw id 0, anc asic id 0, res sw id 0,
res asic id 0 in RCB for AP 10.201.234.24

[11/14/13 14:50:27.712 UTC 8f 8528] Creating WTP 0x3823a0f0 for AP f84f.57ca.3860
with hardware encryption flag = TRUE

[11/14/13 14:50:27.712 UTC 702f6d 8528] f84f.57ca.3860 Deleting AP entry
10.201.234.24:18759 from temporary database.

[11/14/13 14:50:27.712 UTC 702f6e 8528] CAPWAP Interface-Name CAPWAP WCM Client
f84f57ca3860 used for IIF ID allocation

[11/14/13 14:50:27.712 UTC 702f6f 8528] **CAPWAP IIF ID Allocation Successful!**
ID:0x00d2a98000000796 for AP 10.201.234.24, AP hash 1 **[This indicates generation
of a capwapx interface seen in show ip interface brief]**

[11/14/13 14:50:27.712 UTC 702f70 8528] Adding Node to AVL Tree with IIF
Id:0xd2a98000000796

[11/14/13 14:50:27.712 UTC 702f71 8528] WTP IIF ID Type: 0

[11/14/13 14:50:27.712 UTC 702f72 8528] Timer created successfully for WTP
IIF ID: 0xd2a98000000796

[11/14/13 14:50:27.712 UTC 702f73 8528] Added IIF ID to AVL Tree Database
0xd2a98000000796

[11/14/13 14:50:27.712 UTC 702f74 8528] f84f.57ca.3860 Join Version: =
167863296

[11/14/13 14:50:27.712 UTC 702f75 8528] Encode static AP manager 10.201.234.4,
AP count 0

[11/14/13 14:50:27.712 UTC 702f76 8528] f84f.57ca.3860 Join resp: CAPWAP Maximum
Msg element len = 87

[11/14/13 14:50:27.712 UTC 702f77 8528] f84f.57ca.3860 **Join Response sent** to
10.201.234.24:18759

[11/14/13 14:50:27.712 UTC 702f78 8528] f84f.57ca.3860 **CAPWAP State: Join**

[11/14/13 14:50:27.712 UTC 702f79 8528] f84f.57ca.3860 capwap_ac_platform.c:767 -
Operation State 0 ==> 4

[11/14/13 14:50:27.713 UTC 702f7a 8528] f84f.57ca.3860 Register LWAPP event for AP
f84f.57ca.3860 slot 0

[11/14/13 14:50:27.713 UTC 702f7b 8528] capwap_iif_client_action_func: myid = 1,
myid_len=1

[11/14/13 14:50:27.713 UTC 702f7c 8528] CAPWAP Interface ID Acked
Id=0x00d2a98000000796 by IIF - IIF status = 0x1001, for AP 10.201.234.24,
rcb->ap_registered = 1

[11/14/13 14:50:27.713 UTC 702f7d 8528] f84f.57ca.3860 Not ready to send
Config Status Response to AP 10.201.234.24 as SPI ACK is not received

[11/14/13 14:50:27.713 UTC 702f7e 8528] Unable to find entry for PhyIifId:
0x1088ec00000003b from AVL Tree

[11/14/13 14:50:27.713 UTC 702f7f 8528] Adding Node to Physical Iif Id AVL Tree
with PhyIifId:0x1088ec00000003b

[11/14/13 14:50:27.713 UTC 702f80 8528] Unable to find entry for PhyIifId:
0x1088ec00000003b from AVL Tree

[11/14/13 14:50:27.713 UTC 702f81 8528] f84f.57ca.3860 Register LWAPP event for
AP f84f.57ca.3860 slot 1

[11/14/13 14:50:27.713 UTC 702f82 8528] Added PhyIifId: 0x1088ec00000003b to AVL
Tree Database

[11/14/13 14:50:27.714 UTC 702f83 8528] Get the Interface name from the
Phy-Port-IIF-ID:0x1088ec00000003b

[11/14/13 14:50:27.714 UTC 702f84 8528]

---Phy-IIF-ID = 0x1088ec00000003b-----

[11/14/13 14:50:27.714 UTC 702f85 8528] f84f.57ca.3860 Not ready to send Config
Status Response to AP 10.201.234.24 as SPI ACK is not received

[11/14/13 14:50:27.714 UTC 702f86 8528] CSM-SPAM:Input monitor name after copying
from vapcb to vap data is wireless-avc-basic

[11/14/13 14:50:27.714 UTC 702f87 8528] CSM-SPAM:Output monitor name after copying
from vapcb to vapdata is wireless-avc-basic

[11/14/13 14:50:27.714 UTC 702f88 8528] CSM-SPAM:Input monitor name after copying from vapcb to vap data is wireless-avc-basic

[11/14/13 14:50:27.714 UTC 702f89 8528] CSM-SPAM:Output monitor name after copying from vapcb to vapdata is wireless-avc-basic

[11/14/13 14:50:27.714 UTC 702f8a 8528] RSN Capabilities: (26)

[11/14/13 14:50:27.714 UTC 702f8b 8528] [0000] 30 18 01 00 00 0f ac 02 02 00 00 0f ac 02 00 0f

[11/14/13 14:50:27.714 UTC 702f8c 8528] [0016] ac 04 01 00 00 0f ac 02 28 00

[11/14/13 14:50:27.714 UTC 702f8d 8528] WARP IEs: (12)

[11/14/13 14:50:27.714 UTC 702f8e 8528] [0000] dd 0a 00 c0 b9 01 00 00 00 08 01 01

[11/14/13 14:50:27.714 UTC 702f8f 8528] f84f.57ca.3860 Not ready to send Config Status Response to AP 10.201.234.24 as SPI ACK is not received

[11/14/13 14:50:27.715 UTC 702f90 8528] Physical interface Info: IIF-ID = 0x1088ec00000003b, Message Code = 0x802, Interface Name ->gigabitethernet1/0/24, Interface Type = 0x92, Client N<truncated>

[11/14/13 14:50:27.715 UTC 702f91 8528] Updated AVL entry for phyIifid: 0x1088ec00000003b macAddr:f84f.57ca.3860, phyIfName: gigabitethernet1/0/24 Number of APs on this Phy <truncated>

[11/14/13 14:50:27.725 UTC 702f92 8528] capwap opaque data f84f.57ca.3860 length = 0

[11/14/13 14:50:27.725 UTC 702f93 8528] No update; will insert f84f.57ca.3860

Статус конфигурации Ответ Запроса Request-Response/Update

[11/14/13 14:50:27.869 UTC 702f94 8528] f84f.57ca.3860 **Configuration Status from** 10.201.234.24:18759

[11/14/13 14:50:27.870 UTC 702f95 8528] f84f.57ca.3860 **CAPWAP State: Configure**

[11/14/13 14:50:27.870 UTC 702f96 8528] f84f.57ca.3860 New unsupported Payload 254 in message from AP f84f.57ca.3860, Return SUCCESS

[11/14/13 14:50:27.870 UTC 702f97 8528] f84f.57ca.3860 Decoding new unsupported Payload 254 in message from AP f84f.57ca.3860, Return SUCCESS

[11/14/13 14:50:27.870 UTC 702f98 8528] Invalid channel 11 spacificed for the AP AP2602I-1, slotId = 0

[11/14/13 14:50:27.870 UTC 702f99 8528] Invalid channel 56 spacificed for the AP AP2602I-1, slotId = 1

[11/14/13 14:50:27.870 UTC 702f9a 8528] f84f.57ca.3860 Updating IP info for AP f84f.57ca.3860 -- static 0, 10.201.234.24/255.255.255.224, gw 10.201.234.2

[11/14/13 14:50:27.870 UTC 702f9b 8528] f84f.57ca.3860 Updating IP 10.201.234.24 ==> 10.201.234.24 for AP f84f.57ca.3860

|

[11/14/13 14:50:27.870 UTC 702fab 8528] f84f.57ca.3860 LWAPP message validation

failed for SPAM Vendor Specific Payload(104) in message of len=7 from AP
f84f.57ca.3860

[11/14/13 14:50:27.870 UTC 702fac 8528] f84f.57ca.3860 Failed to validate vendor
specific message element

[11/14/13 14:50:27.871 UTC 702fad 8528] f84f.57ca.3860 **Setting MTU to 1485**

[11/14/13 14:50:27.871 UTC 702fae 8528] f84f.57ca.3860 Platform not Supported,
exiting Load Balancer function

[11/14/13 14:50:27.871 UTC 702faf 8528] load balancer rc=4 for AP 10.201.234.24,
IIF ID:0x00d2a98000000796

[11/14/13 14:50:27.871 UTC 702fb0 8528] opaque data size 0 with capwap interface
create f84f.57ca.3860

[11/14/13 14:50:27.871 UTC 702fb1 8528] spiCapwapParams->
data_tunnel.opaque_data.opaque_data_len: 0

[11/14/13 14:50:27.871 UTC 702fb2 8528] f84f.57ca.3860 Data Tunnel Create timer
started for 240 seconds timeout

[11/14/13 14:50:27.871 UTC 702fb3 8528] f84f.57ca.3860 **Data Tunnel created -
tunnel type NON_CRYPTO**, load balancer support Not supported, tunnel mtu 1449,

anc_sw_id 0, anc_asic_id 0, res_sw_id 0, res_asic_id 0

anc_wp_iif_id 0x0000000000000000, res_wp_iif_id 0x0000000000000000

[11/14/13 14:50:27.871 UTC 702fb4 8528] f84f.57ca.3860 Not ready to send Config
Status Response to AP 10.201.234.24 as SPI ACK is not received

[11/14/13 14:50:27.871 UTC 702fb5 8528] f84f.57ca.3860 AP f84f.57ca.3860
associated. Last AP failure was due to Configuration changes,reason:
controller reboot command

[11/14/13 14:50:27.871 UTC 30e6 260] [CAPWAP]: CAPWAP data tunnel create message.

[11/14/13 14:50:27.871 UTC 30e7 260] [CAPWAP]: capwap_data_tunnel_create called

[11/14/13 14:50:27.871 UTC 30e8 260] [CAPWAP]: Data tunnel id = 0xd2a98000000796

[11/14/13 14:50:27.871 UTC 30e9 260] [CAPWAP]: Tunnel Entry not found for AP
(10.201.234.24, 18759)

[11/14/13 14:50:27.873 UTC 30ea 260] [CAPWAP]: CAPWAP IDB init complete

[11/14/13 14:50:27.882 UTC 30eb 260] [CAPWAP]: capwap_interface_status_update:
tunnel 0xd2a98000000796 status 0

[11/14/13 14:50:27.882 UTC 30ec 260] [CAPWAP]: csb pd flag 0 opaque_data_len 0
attr opaque_data 0x00000000

[11/14/13 14:50:27.882 UTC 30ed 260] [CAPWAP]: Send capwap_data_tunnel_status_update
0 Slot-Unit 1 Unit 1 for iif_id 0xd2a98000000796 to WCM.

[11/14/13 14:50:27.882 UTC 30ee 260] [CAPWAP]: (capwap_process_fed_results) CAPWAP
FED result (0) for IIF ID: 0xd2a98000000796

[11/14/13 14:50:27.882 UTC 702fb6 8528

Received CAPWAP Tunnel SPI update opaque size 0

[11/14/13 14:50:27.882 UTC 702fb7 8528] opaque data len 0 with capwap server update

[11/14/13 14:50:27.883 UTC 702fb8 8528] f84f.57ca.3860 SPI ACK : Capwap Data Tunnel create successful for iifid:0x00d2a98000000796 AP:10.201.234.24

[11/14/13 14:50:27.883 UTC 702fb9 8528]

Received CAPWAP interface update opaque len 0

[11/14/13 14:50:27.883 UTC 702fba 8528] **SPI IifId ACK: Capwap Data Tunnel Created Successfully for IifId: 0x00d2a98000000796 AP: 10.201.234.24**

[11/14/13 14:50:27.883 UTC 702fbb 8528] f84f.57ca.3860 **OK to send Config Status Response to AP 10.201.234.24**

[11/14/13 14:50:27.888 UTC 30ef 260] [CAPWAP]: Notify PM (done).

[11/14/13 14:50:27.888 UTC 30f0 260] [CAPWAP]: SNMP Register: Cal HWIDB 32f44570

[11/14/13 14:50:27.888 UTC 30f1 260] [CAPWAP]: capwap_port_hashitem added: slot 1 slotunit 24 vlan 1104

[11/14/13 14:50:27.888 UTC 30f2 260] [CAPWAP]: 7c69.f604.9460 is AP's mac addr

[11/14/13 14:50:27.932 UTC 702fbc 8528] Sending multicast payload to ap AP2602I-1, mcast_mode 0, mcast group 0.0.0.0

[11/14/13 14:50:27.933 UTC 702fbd 8528] f84f.57ca.3860 Config status response sent to 10.201.234.24:18759

[11/14/13 14:50:27.933 UTC 702fbe 8528] f84f.57ca.3860 Configuration Status Response sent to 10:201:234:24

[11/14/13 14:50:27.933 UTC 702fbf 8528] f84f.57ca.3860 Configuration update request for Band Select Cfg sent to 10.201.234.24:18759

[11/14/13 14:50:27.933 UTC 702fc0 8528] f84f.57ca.3860 Configuration update request for HaConfig message sent to 10.201.234.24:18759

[11/14/13 14:50:27.934 UTC 702fc1 8528] f84f.57ca.3860 Configuration update request for AP NGWC Qos sent to 10.201.234.24:18759

[11/14/13 14:50:28.121 UTC 702fc2 8528] f84f.57ca.3860 Change State Event Request from 10.201.234.24:18759

[11/14/13 14:50:28.122 UTC 702fc3 8528] f84f.57ca.3860 Received LWAPP Up event for AP f84f.57ca.3860 slot 0!

[11/14/13 14:50:28.122 UTC 702fc4 8528] f84f.57ca.3860 Radio state change for slot: 0 state: 2 cause: 0 detail cause: 0

[11/14/13 14:50:28.122 UTC 702fc5 8528] f84f.57ca.3860 Change State Event Response sent to 10.201.234.24:18759

[11/14/13 14:50:28.122 UTC 702fc6 8528] f84f.57ca.3860 CAPWAP State: Run

[11/14/13 14:50:28.122 UTC 702fc7 8528] f84f.57ca.3860 Sending the remaining config to AP 10.201.234.24:18759

[11/14/13 14:50:28.122 UTC 702fc8 8528] f84f.57ca.3860 AP Going to RUN 10.201.234.24: ConcurrentJoins: 0

[11/14/13 14:50:28.122 UTC 702fc9 8528] f84f.57ca.3860 **Configuration update request** for Init VAP-DATA for slot 1 sent to 10.201.234.24:18759

[11/14/13 14:50:28.122 UTC 702fca 8528] f84f.57ca.3860 Configuration update request for configuring association limit params sent to 10.201.234.24:18759

[11/14/13 14:50:28.122 UTC 702fcb 8528] f84f.57ca.3860 Configuration update request for Band Select Cfg sent to 10.201.234.24:18759

[11/14/13 14:50:28.122 UTC 702fcc 8528] f84f.57ca.3860 Configuration update request for HaConfig message sent to 10.201.234.24:18759

[11/14/13 14:50:28.123 UTC 702fcd 8528] CAPWAP: No update, will insert f84f.57ca.3860

[11/14/13 14:50:28.123 UTC 702fce 8528] capwap opaque data f84f.57ca.3860 length = 0

[11/14/13 14:50:28.124 UTC 702fcf 8528] CAPWAP HA insert f84f.57ca.3860

[11/14/13 14:50:28.124 UTC 702fd0 8528] CAPWAP HA insert f84f.57ca.3860

[11/14/13 14:50:28.124 UTC 702fd1 8528] f84f.57ca.3860 Configuration update request for PHY payload sent to 10:201:234:24

[11/14/13 14:50:28.126 UTC 702fd2 8528] f84f.57ca.3860 **Configuration Update Response** from 10.201.234.24:18759

[11/14/13 14:50:28.126 UTC 702fd3 8528] f84f.57ca.3860 Configuration update request for RrmInterferenceCtrl payload sent to 10:201:234:24

[11/14/13 14:50:28.126 UTC 702fd4 8528] f84f.57ca.3860 Configuration update request for RrmNeighbourCtrl payload sent to 10.201.234.24

[11/14/13 14:50:28.126 UTC 702fd5 8528] f84f.57ca.3860 Configuration update request for RrmReceiveCtrl payload sent to 10:201:234:24

[11/14/13 14:50:28.126 UTC 702fd6 8528] f84f.57ca.3860 Configuration update request for CcxRmMeas payload sent to 10.201.234.24

[11/14/13 14:50:28.132 UTC 702fd7 8528] f84f.57ca.3860 Change State Event Request from 10.201.234.24:18759

[11/14/13 14:50:28.132 UTC 702fd8 8528] f84f.57ca.3860 Radio state change for slot: 1 state: 2 cause: 0 detail cause: 0

[11/14/13 14:50:28.132 UTC 702fd9 8528] f84f.57ca.3860 Change State Event Response sent to 10.201.234.24:18759

[11/14/13 14:50:28.132 UTC 702fda 8528] f84f.57ca.3860 CAPWAP State: Run

[11/14/13 14:50:28.132 UTC 702fdb 8528] f84f.57ca.3860 Sending the remaining config to AP 10.201.234.24:18759

[11/14/13 14:50:28.133 UTC 702fdc 8528] f84f.57ca.3860 Configuration update request for qos pm payload payload sent to 10.201.234.24:18759

[11/14/13 14:50:28.133 UTC 702fdd 8528] f84f.57ca.3860 Received LWAPP Up event for AP f84f.57ca.3860 slot 1!

[11/14/13 14:50:28.133 UTC 702fde 8528] f84f.57ca.3860 Configuration update request for PHY payload sent to 10:201:234:24

[11/14/13 14:50:28.133 UTC 702fdf 8528] f84f.57ca.3860 Configuration update request for RrmInterferenceCtrl payload sent to 10:201:234:24

[11/14/13 14:50:28.133 UTC 702fe0 8528] f84f.57ca.3860 Configuration update request for RrmNeighbourCtrl payload sent to 10.201.234.24

[11/14/13 14:50:28.134 UTC 702fe1 8528] f84f.57ca.3860 Configuration update request for RrmReceiveCtrl payload sent to 10:201:234:24

[11/14/13 14:50:28.134 UTC 702fe2 8528] f84f.57ca.3860 Configuration update request for CcxRmMeas payload sent to 10.201.234.24

[11/14/13 14:50:28.188 UTC 702fe3 8528] f84f.57ca.3860 Configuration Update Response from 10.201.234.24:18759

[11/14/13 14:50:28.188 UTC 702fe4 8528] f84f.57ca.3860 Change State Event Request from 10.201.234.24:18759

[11/14/13 14:50:28.188 UTC 702fe5 8528] f84f.57ca.3860 Change State Event Response sent to 10.201.234.24:18759

[11/14/13 14:50:28.188 UTC 702fe6 8528] f84f.57ca.3860 CAPWAP State: Run

[11/14/13 14:50:28.188 UTC 702fe7 8528] f84f.57ca.3860 Sending the remaining config to AP 10.201.234.24:18759

[11/14/13 14:50:28.194 UTC 702fe8 8528] f84f.57ca.3860 Configuration Update Response from 10.201.234.24:18759

[11/14/13 14:50:28.194 UTC 702fe9 8528] f84f.57ca.3860 **WTP Event Request** from 10.201.234.24:18759

[11/14/13 14:50:28.194 UTC 702fea 8528] f84f.57ca.3860 **WTP Event Response** sent to 10.201.234.24:18759

Обычные причины для сбоя соединения AP

В этом разделе описываются типичные причины сбоя соединения AP.

Проблема 1: AP на Catalyst Коммутатор серии 3850 не находится в VLAN беспроводного управления.

#show выполненный интерфейс gig1/0/22

[11/14/13 14:50:27.869 UTC 702f94 8528] f84f.57ca.3860 **Configuration Status** from 10.201.234.24:18759

[11/14/13 14:50:27.870 UTC 702f95 8528] f84f.57ca.3860 **CAPWAP State: Configure**

[11/14/13 14:50:27.870 UTC 702f96 8528] f84f.57ca.3860 New unsupported Payload 254 in message from AP f84f.57ca.3860, Return SUCCESS

[11/14/13 14:50:27.870 UTC 702f97 8528] f84f.57ca.3860 Decoding new unsupported Payload 254 in message from AP f84f.57ca.3860, Return SUCCESS

[11/14/13 14:50:27.870 UTC 702f98 8528] Invalid channel 11 spacificed for the AP AP2602I-1, slotId = 0

[11/14/13 14:50:27.870 UTC 702f99 8528] Invalid channel 56 spacificed for the AP AP2602I-1, slotId = 1

[11/14/13 14:50:27.870 UTC 702f9a 8528] f84f.57ca.3860 Updating IP info for AP

f84f.57ca.3860 -- static 0, 10.201.234.24/255.255.255.224, gw 10.201.234.2

[11/14/13 14:50:27.870 UTC 702f9b 8528] f84f.57ca.3860 Updating IP
10.201.234.24 ==> 10.201.234.24 for AP f84f.57ca.3860

|

[11/14/13 14:50:27.870 UTC 702fab 8528] f84f.57ca.3860 LWAPP message validation
failed for SPAM Vendor Specific Payload(104) in message of len=7 from AP
f84f.57ca.3860

[11/14/13 14:50:27.870 UTC 702fac 8528] f84f.57ca.3860 Failed to validate vendor
specific message element

[11/14/13 14:50:27.871 UTC 702fad 8528] f84f.57ca.3860 **Setting MTU to 1485**

[11/14/13 14:50:27.871 UTC 702fae 8528] f84f.57ca.3860 Platform not Supported,
exiting Load Balancer function

[11/14/13 14:50:27.871 UTC 702faf 8528] load balancer rc=4 for AP 10.201.234.24,
IIF ID:0x00d2a98000000796

[11/14/13 14:50:27.871 UTC 702fb0 8528] opaque data size 0 with capwap interface
create f84f.57ca.3860

[11/14/13 14:50:27.871 UTC 702fb1 8528] spiCapwapParams->
data_tunnel.opaque_data.opaque_data_len: 0

[11/14/13 14:50:27.871 UTC 702fb2 8528] f84f.57ca.3860 Data Tunnel Create timer
started for 240 seconds timeout

[11/14/13 14:50:27.871 UTC 702fb3 8528] f84f.57ca.3860 **Data Tunnel created -
tunnel type NON_CRYPTO**, load balancer support Not supported, tunnel mtu 1449,

anc_sw_id 0, anc_asic_id 0, res_sw_id 0, res_asic_id 0

anc_wp_iif_id 0x0000000000000000, res_wp_iif_id 0x0000000000000000

[11/14/13 14:50:27.871 UTC 702fb4 8528] f84f.57ca.3860 Not ready to send Config
Status Response to AP 10.201.234.24 as SPI ACK is not received

[11/14/13 14:50:27.871 UTC 702fb5 8528] f84f.57ca.3860 AP f84f.57ca.3860
associated. Last AP failure was due to Configuration changes,reason:
controller reboot command

[11/14/13 14:50:27.871 UTC 30e6 260] [CAPWAP]: CAPWAP data tunnel create message.

[11/14/13 14:50:27.871 UTC 30e7 260] [CAPWAP]: capwap_data_tunnel_create called

[11/14/13 14:50:27.871 UTC 30e8 260] [CAPWAP]: Data tunnel id = 0xd2a98000000796

[11/14/13 14:50:27.871 UTC 30e9 260] [CAPWAP]: Tunnel Entry not found for AP
(10.201.234.24, 18759)

[11/14/13 14:50:27.873 UTC 30ea 260] [CAPWAP]: CAPWAP IDB init complete

[11/14/13 14:50:27.882 UTC 30eb 260] [CAPWAP]: capwap_interface_status_update:
tunnel 0xd2a98000000796 status 0

[11/14/13 14:50:27.882 UTC 30ec 260] [CAPWAP]: csb pd flag 0 opaque_data_len 0
attr opaque_data 0x00000000

[11/14/13 14:50:27.882 UTC 30ed 260] [CAPWAP]: Send capwap_data_tunnel_status_update
0 Slot-Unit 1 Unit 1 for iif_id 0xd2a98000000796 to WCM.

[11/14/13 14:50:27.882 UTC 30ee 260] [CAPWAP]: (capwap_process_fed_results) CAPWAP FED result (0) for IIF ID: 0xd2a98000000796

[11/14/13 14:50:27.882 UTC 702fb6 8528

Received CAPWAP Tunnel SPI update opaque size 0

[11/14/13 14:50:27.882 UTC 702fb7 8528] opaque data len 0 with capwap server update

[11/14/13 14:50:27.883 UTC 702fb8 8528] f84f.57ca.3860 SPI ACK : Capwap Data Tunnel create successful for iifid:0x00d2a98000000796 AP:10.201.234.24

[11/14/13 14:50:27.883 UTC 702fb9 8528]

Received CAPWAP interface update opaque len 0

[11/14/13 14:50:27.883 UTC 702fba 8528] **SPI IifId ACK: Capwap Data Tunnel Created Successfully for IifId: 0x00d2a98000000796 AP: 10.201.234.24**

[11/14/13 14:50:27.883 UTC 702fbb 8528] f84f.57ca.3860 **OK to send Config Status Response to AP 10.201.234.24**

[11/14/13 14:50:27.888 UTC 30ef 260] [CAPWAP]: Notify PM (done).

[11/14/13 14:50:27.888 UTC 30f0 260] [CAPWAP]: SNMP Register: Cal HWIDB 32f44570

[11/14/13 14:50:27.888 UTC 30f1 260] [CAPWAP]: capwap_port_hashitem added: slot 1 slotunit 24 vlan 1104

[11/14/13 14:50:27.888 UTC 30f2 260] [CAPWAP]: 7c69.f604.9460 is AP's mac addr

[11/14/13 14:50:27.932 UTC 702fbc 8528] Sending multicast payload to ap AP2602I-1, mcast_mode 0, mcast group 0.0.0.0

[11/14/13 14:50:27.933 UTC 702fbd 8528] f84f.57ca.3860 Config status response sent to 10.201.234.24:18759

[11/14/13 14:50:27.933 UTC 702fbe 8528] f84f.57ca.3860 Configuration Status Response sent to 10:201:234:24

[11/14/13 14:50:27.933 UTC 702fbf 8528] f84f.57ca.3860 Configuration update request for Band Select Cfg sent to 10.201.234.24:18759

[11/14/13 14:50:27.933 UTC 702fc0 8528] f84f.57ca.3860 Configuration update request for HaConfig message sent to 10.201.234.24:18759

[11/14/13 14:50:27.934 UTC 702fc1 8528] f84f.57ca.3860 Configuration update request for AP NGWC Qos sent to 10.201.234.24:18759

[11/14/13 14:50:28.121 UTC 702fc2 8528] f84f.57ca.3860 Change State Event Request from 10.201.234.24:18759

[11/14/13 14:50:28.122 UTC 702fc3 8528] f84f.57ca.3860 Received LWAPP Up event for AP f84f.57ca.3860 slot 0!

[11/14/13 14:50:28.122 UTC 702fc4 8528] f84f.57ca.3860 Radio state change for slot: 0 state: 2 cause: 0 detail cause: 0

[11/14/13 14:50:28.122 UTC 702fc5 8528] f84f.57ca.3860 Change State Event Response sent to 10.201.234.24:18759

[11/14/13 14:50:28.122 UTC 702fc6 8528] f84f.57ca.3860 CAPWAP State: Run

[11/14/13 14:50:28.122 UTC 702fc7 8528] f84f.57ca.3860 Sending the remaining config to AP 10.201.234.24:18759

[11/14/13 14:50:28.122 UTC 702fc8 8528] f84f.57ca.3860 AP Going to RUN 10.201.234.24: ConcurrentJoins: 0

[11/14/13 14:50:28.122 UTC 702fc9 8528] f84f.57ca.3860 **Configuration update request** for Init VAP-DATA for slot 1 sent to 10.201.234.24:18759

[11/14/13 14:50:28.122 UTC 702fca 8528] f84f.57ca.3860 Configuration update request for configuring association limit params sent to 10.201.234.24:18759

[11/14/13 14:50:28.122 UTC 702fcb 8528] f84f.57ca.3860 Configuration update request for Band Select Cfg sent to 10.201.234.24:18759

[11/14/13 14:50:28.122 UTC 702fcc 8528] f84f.57ca.3860 Configuration update request for HaConfig message sent to 10.201.234.24:18759

[11/14/13 14:50:28.123 UTC 702fcd 8528] CAPWAP: No update, will insert f84f.57ca.3860

[11/14/13 14:50:28.123 UTC 702fce 8528] capwap opaque data f84f.57ca.3860 length = 0

[11/14/13 14:50:28.124 UTC 702fcf 8528] CAPWAP HA insert f84f.57ca.3860

[11/14/13 14:50:28.124 UTC 702fd0 8528] CAPWAP HA insert f84f.57ca.3860

[11/14/13 14:50:28.124 UTC 702fd1 8528] f84f.57ca.3860 Configuration update request for PHY payload sent to 10:201:234:24

[11/14/13 14:50:28.126 UTC 702fd2 8528] f84f.57ca.3860 **Configuration Update Response** from 10.201.234.24:18759

[11/14/13 14:50:28.126 UTC 702fd3 8528] f84f.57ca.3860 Configuration update request for RrmInterferenceCtrl payload sent to 10:201:234:24

[11/14/13 14:50:28.126 UTC 702fd4 8528] f84f.57ca.3860 Configuration update request for RrmNeighbourCtrl payload sent to 10.201.234.24

[11/14/13 14:50:28.126 UTC 702fd5 8528] f84f.57ca.3860 Configuration update request for RrmReceiveCtrl payload sent to 10:201:234:24

[11/14/13 14:50:28.126 UTC 702fd6 8528] f84f.57ca.3860 Configuration update request for CcxRmMeas payload sent to 10.201.234.24

[11/14/13 14:50:28.132 UTC 702fd7 8528] f84f.57ca.3860 Change State Event Request from 10.201.234.24:18759

[11/14/13 14:50:28.132 UTC 702fd8 8528] f84f.57ca.3860 Radio state change for slot: 1 state: 2 cause: 0 detail cause: 0

[11/14/13 14:50:28.132 UTC 702fd9 8528] f84f.57ca.3860 Change State Event Response sent to 10.201.234.24:18759

[11/14/13 14:50:28.132 UTC 702fda 8528] f84f.57ca.3860 CAPWAP State: Run

[11/14/13 14:50:28.132 UTC 702fdb 8528] f84f.57ca.3860 Sending the remaining config to AP 10.201.234.24:18759

[11/14/13 14:50:28.133 UTC 702fdc 8528] f84f.57ca.3860 Configuration update request for qos pm payload payload sent to 10.201.234.24:18759

[11/14/13 14:50:28.133 UTC 702fdd 8528] f84f.57ca.3860 Received LWAPP Up

event for AP f84f.57ca.3860 slot 1!

[11/14/13 14:50:28.133 UTC 702fde 8528] f84f.57ca.3860 Configuration update request for PHY payload sent to 10:201:234:24

[11/14/13 14:50:28.133 UTC 702fdf 8528] f84f.57ca.3860 Configuration update request for RrmInterferenceCtrl payload sent to 10:201:234:24

[11/14/13 14:50:28.133 UTC 702fe0 8528] f84f.57ca.3860 Configuration update request for RrmNeighbourCtrl payload sent to 10.201.234.24

[11/14/13 14:50:28.134 UTC 702fe1 8528] f84f.57ca.3860 Configuration update request for RrmReceiveCtrl payload sent to 10:201:234:24

[11/14/13 14:50:28.134 UTC 702fe2 8528] f84f.57ca.3860 Configuration update request for CcxRmMeas payload sent to 10.201.234.24

[11/14/13 14:50:28.188 UTC 702fe3 8528] f84f.57ca.3860 Configuration Update Response from 10.201.234.24:18759

[11/14/13 14:50:28.188 UTC 702fe4 8528] f84f.57ca.3860 Change State Event Request from 10.201.234.24:18759

[11/14/13 14:50:28.188 UTC 702fe5 8528] f84f.57ca.3860 Change State Event Response sent to 10.201.234.24:18759

[11/14/13 14:50:28.188 UTC 702fe6 8528] f84f.57ca.3860 CAPWAP State: Run

[11/14/13 14:50:28.188 UTC 702fe7 8528] f84f.57ca.3860 Sending the remaining config to AP 10.201.234.24:18759

[11/14/13 14:50:28.194 UTC 702fe8 8528] f84f.57ca.3860 Configuration Update Response from 10.201.234.24:18759

[11/14/13 14:50:28.194 UTC 702fe9 8528] f84f.57ca.3860 **WTP Event Request** from 10.201.234.24:18759

[11/14/13 14:50:28.194 UTC 702fea 8528] f84f.57ca.3860 **WTP Event Response** sent to 10.201.234.24:18759

#show, выполненный | inc радио

[11/14/13 14:50:27.869 UTC 702f94 8528] f84f.57ca.3860 **Configuration Status** from 10.201.234.24:18759

[11/14/13 14:50:27.870 UTC 702f95 8528] f84f.57ca.3860 **CAPWAP State: Configure**

[11/14/13 14:50:27.870 UTC 702f96 8528] f84f.57ca.3860 New unsupported Payload 254 in message from AP f84f.57ca.3860, Return SUCCESS

[11/14/13 14:50:27.870 UTC 702f97 8528] f84f.57ca.3860 Decoding new unsupported Payload 254 in message from AP f84f.57ca.3860, Return SUCCESS

[11/14/13 14:50:27.870 UTC 702f98 8528] Invalid channel 11 spacificied for the AP AP2602I-1, slotId = 0

[11/14/13 14:50:27.870 UTC 702f99 8528] Invalid channel 56 spacificied for the AP AP2602I-1, slotId = 1

[11/14/13 14:50:27.870 UTC 702f9a 8528] f84f.57ca.3860 Updating IP info for AP f84f.57ca.3860 -- static 0, 10.201.234.24/255.255.255.224, gtw 10.201.234.2

[11/14/13 14:50:27.870 UTC 702f9b 8528] f84f.57ca.3860 Updating IP 10.201.234.24 ==> 10.201.234.24 for AP f84f.57ca.3860

|

[11/14/13 14:50:27.870 UTC 702fab 8528] f84f.57ca.3860 LWAPP message validation failed for SPAM Vendor Specific Payload(104) in message of len=7 from AP f84f.57ca.3860

[11/14/13 14:50:27.870 UTC 702fac 8528] f84f.57ca.3860 Failed to validate vendor specific message element

[11/14/13 14:50:27.871 UTC 702fad 8528] f84f.57ca.3860 **Setting MTU to 1485**

[11/14/13 14:50:27.871 UTC 702fae 8528] f84f.57ca.3860 Platform not Supported, exiting Load Balancer function

[11/14/13 14:50:27.871 UTC 702faf 8528] load balancer rc=4 for AP 10.201.234.24, IIF ID:0x00d2a98000000796

[11/14/13 14:50:27.871 UTC 702fb0 8528] opaque data size 0 with capwap interface create f84f.57ca.3860

[11/14/13 14:50:27.871 UTC 702fb1 8528] spiCapwapParams-> data_tunnel.opaque_data.opaque_data_len: 0

[11/14/13 14:50:27.871 UTC 702fb2 8528] f84f.57ca.3860 Data Tunnel Create timer started for 240 seconds timeout

[11/14/13 14:50:27.871 UTC 702fb3 8528] f84f.57ca.3860 **Data Tunnel created - tunnel type NON_CRYPTO**, load balancer support Not supported, tunnel mtu 1449,

anc_sw_id 0, anc_asic_id 0, res_sw_id 0, res_asic_id 0

anc_wp_iif_id 0x0000000000000000, res_wp_iif_id 0x0000000000000000

[11/14/13 14:50:27.871 UTC 702fb4 8528] f84f.57ca.3860 Not ready to send Config Status Response to AP 10.201.234.24 as SPI ACK is not received

[11/14/13 14:50:27.871 UTC 702fb5 8528] f84f.57ca.3860 AP f84f.57ca.3860 associated. Last AP failure was due to Configuration changes,reason: controller reboot command

[11/14/13 14:50:27.871 UTC 30e6 260] [CAPWAP]: CAPWAP data tunnel create message.

[11/14/13 14:50:27.871 UTC 30e7 260] [CAPWAP]: capwap_data_tunnel_create called

[11/14/13 14:50:27.871 UTC 30e8 260] [CAPWAP]: Data tunnel id = 0xd2a98000000796

[11/14/13 14:50:27.871 UTC 30e9 260] [CAPWAP]: Tunnel Entry not found for AP (10.201.234.24, 18759)

[11/14/13 14:50:27.873 UTC 30ea 260] [CAPWAP]: CAPWAP IDB init complete

[11/14/13 14:50:27.882 UTC 30eb 260] [CAPWAP]: capwap_interface_status_update: tunnel 0xd2a98000000796 status 0

[11/14/13 14:50:27.882 UTC 30ec 260] [CAPWAP]: csb pd flag 0 opaque_data_len 0 attr opaque_data 0x00000000

[11/14/13 14:50:27.882 UTC 30ed 260] [CAPWAP]: Send capwap_data_tunnel_status_update 0 Slot-Unit 1 Unit 1 for iif_id 0xd2a98000000796 to WCM.

[11/14/13 14:50:27.882 UTC 30ee 260] [CAPWAP]: (capwap_process_fed_results) CAPWAP FED result (0) for IIF ID: 0xd2a98000000796

[11/14/13 14:50:27.882 UTC 702fb6 8528
Received CAPWAP Tunnel SPI update opaque size 0
[11/14/13 14:50:27.882 UTC 702fb7 8528] opaque data len 0 with capwap server update
[11/14/13 14:50:27.883 UTC 702fb8 8528] f84f.57ca.3860 SPI ACK : Capwap Data
Tunnel create successful for iifid:0x00d2a98000000796 AP:10.201.234.24
[11/14/13 14:50:27.883 UTC 702fb9 8528]
Received CAPWAP interface update opaque len 0
[11/14/13 14:50:27.883 UTC 702fba 8528] **SPI IifId ACK: Capwap Data Tunnel Created
Successfully for IifId: 0x00d2a98000000796 AP: 10.201.234.24**
[11/14/13 14:50:27.883 UTC 702fbb 8528] f84f.57ca.3860 **OK to send Config Status
Response to AP 10.201.234.24**
[11/14/13 14:50:27.888 UTC 30ef 260] [CAPWAP]: Notify PM (done).
[11/14/13 14:50:27.888 UTC 30f0 260] [CAPWAP]: SNMP Register: Cal HWIDB 32f44570
[11/14/13 14:50:27.888 UTC 30f1 260] [CAPWAP]: capwap_port_hashitem added: slot 1
slotunit 24 vlan 1104
[11/14/13 14:50:27.888 UTC 30f2 260] [CAPWAP]: 7c69.f604.9460 is AP's mac addr
[11/14/13 14:50:27.932 UTC 702fbc 8528] Sending multicast payload to ap AP2602I-1,
mcast_mode 0, mcast group 0.0.0.0
[11/14/13 14:50:27.933 UTC 702fbd 8528] f84f.57ca.3860 Config status response sent
to 10.201.234.24:18759
[11/14/13 14:50:27.933 UTC 702fbe 8528] f84f.57ca.3860 Configuration Status
Response sent to 10:201:234:24
[11/14/13 14:50:27.933 UTC 702fbf 8528] f84f.57ca.3860 Configuration update
request for Band Select Cfg sent to 10.201.234.24:18759
[11/14/13 14:50:27.933 UTC 702fc0 8528] f84f.57ca.3860 Configuration update
request for HaConfig message sent to 10.201.234.24:18759
[11/14/13 14:50:27.934 UTC 702fc1 8528] f84f.57ca.3860 Configuration update
request for AP NGWC Qos sent to 10.201.234.24:18759
[11/14/13 14:50:28.121 UTC 702fc2 8528] f84f.57ca.3860 Change State Event
Request from 10.201.234.24:18759
[11/14/13 14:50:28.122 UTC 702fc3 8528] f84f.57ca.3860 Received LWAPP Up event
for AP f84f.57ca.3860 slot 0!
[11/14/13 14:50:28.122 UTC 702fc4 8528] f84f.57ca.3860 Radio state change for
slot: 0 state: 2 cause: 0 detail cause: 0
[11/14/13 14:50:28.122 UTC 702fc5 8528] f84f.57ca.3860 Change State Event
Response sent to 10.201.234.24:18759
[11/14/13 14:50:28.122 UTC 702fc6 8528] f84f.57ca.3860 CAPWAP State: Run
[11/14/13 14:50:28.122 UTC 702fc7 8528] f84f.57ca.3860 Sending the remaining
config to AP 10.201.234.24:18759
[11/14/13 14:50:28.122 UTC 702fc8 8528] f84f.57ca.3860 AP Going to RUN

10.201.234.24: ConcurrentJoins: 0

[11/14/13 14:50:28.122 UTC 702fc9 8528] f84f.57ca.3860 **Configuration update request** for Init VAP-DATA for slot 1 sent to 10.201.234.24:18759

[11/14/13 14:50:28.122 UTC 702fca 8528] f84f.57ca.3860 Configuration update request for configuring association limit params sent to 10.201.234.24:18759

[11/14/13 14:50:28.122 UTC 702fcb 8528] f84f.57ca.3860 Configuration update request for Band Select Cfg sent to 10.201.234.24:18759

[11/14/13 14:50:28.122 UTC 702fcc 8528] f84f.57ca.3860 Configuration update request for HaConfig message sent to 10.201.234.24:18759

[11/14/13 14:50:28.123 UTC 702fcd 8528] CAPWAP: No update, will insert f84f.57ca.3860

[11/14/13 14:50:28.123 UTC 702fce 8528] capwap opaque data f84f.57ca.3860 length = 0

[11/14/13 14:50:28.124 UTC 702fcf 8528] CAPWAP HA insert f84f.57ca.3860

[11/14/13 14:50:28.124 UTC 702fd0 8528] CAPWAP HA insert f84f.57ca.3860

[11/14/13 14:50:28.124 UTC 702fd1 8528] f84f.57ca.3860 Configuration update request for PHY payload sent to 10:201:234:24

[11/14/13 14:50:28.126 UTC 702fd2 8528] f84f.57ca.3860 **Configuration Update Response** from 10.201.234.24:18759

[11/14/13 14:50:28.126 UTC 702fd3 8528] f84f.57ca.3860 Configuration update request for RrmInterferenceCtrl payload sent to 10:201:234:24

[11/14/13 14:50:28.126 UTC 702fd4 8528] f84f.57ca.3860 Configuration update request for RrmNeighbourCtrl payload sent to 10.201.234.24

[11/14/13 14:50:28.126 UTC 702fd5 8528] f84f.57ca.3860 Configuration update request for RrmReceiveCtrl payload sent to 10:201:234:24

[11/14/13 14:50:28.126 UTC 702fd6 8528] f84f.57ca.3860 Configuration update request for CcxRmMeas payload sent to 10.201.234.24

[11/14/13 14:50:28.132 UTC 702fd7 8528] f84f.57ca.3860 Change State Event Request from 10.201.234.24:18759

[11/14/13 14:50:28.132 UTC 702fd8 8528] f84f.57ca.3860 Radio state change for slot: 1 state: 2 cause: 0 detail cause: 0

[11/14/13 14:50:28.132 UTC 702fd9 8528] f84f.57ca.3860 Change State Event Response sent to 10.201.234.24:18759

[11/14/13 14:50:28.132 UTC 702fda 8528] f84f.57ca.3860 CAPWAP State: Run

[11/14/13 14:50:28.132 UTC 702fdb 8528] f84f.57ca.3860 Sending the remaining config to AP 10.201.234.24:18759

[11/14/13 14:50:28.133 UTC 702fdc 8528] f84f.57ca.3860 Configuration update request for qos pm payload payload sent to 10.201.234.24:18759

[11/14/13 14:50:28.133 UTC 702fdd 8528] f84f.57ca.3860 Received LWAPP Up event for AP f84f.57ca.3860 slot 1!

[11/14/13 14:50:28.133 UTC 702fde 8528] f84f.57ca.3860 Configuration update request for PHY payload sent to 10:201:234:24

[11/14/13 14:50:28.133 UTC 702fdf 8528] f84f.57ca.3860 Configuration update request for RrmInterferenceCtrl payload sent to 10:201:234:24

[11/14/13 14:50:28.133 UTC 702fe0 8528] f84f.57ca.3860 Configuration update request for RrmNeighbourCtrl payload sent to 10.201.234.24

[11/14/13 14:50:28.134 UTC 702fe1 8528] f84f.57ca.3860 Configuration update request for RrmReceiveCtrl payload sent to 10:201:234:24

[11/14/13 14:50:28.134 UTC 702fe2 8528] f84f.57ca.3860 Configuration update request for CcxRmMeas payload sent to 10.201.234.24

[11/14/13 14:50:28.188 UTC 702fe3 8528] f84f.57ca.3860 Configuration Update Response from 10.201.234.24:18759

[11/14/13 14:50:28.188 UTC 702fe4 8528] f84f.57ca.3860 Change State Event Request from 10.201.234.24:18759

[11/14/13 14:50:28.188 UTC 702fe5 8528] f84f.57ca.3860 Change State Event Response sent to 10.201.234.24:18759

[11/14/13 14:50:28.188 UTC 702fe6 8528] f84f.57ca.3860 CAPWAP State: Run

[11/14/13 14:50:28.188 UTC 702fe7 8528] f84f.57ca.3860 Sending the remaining config to AP 10.201.234.24:18759

[11/14/13 14:50:28.194 UTC 702fe8 8528] f84f.57ca.3860 Configuration Update Response from 10.201.234.24:18759

[11/14/13 14:50:28.194 UTC 702fe9 8528] f84f.57ca.3860 **WTP Event Request** from 10.201.234.24:18759

[11/14/13 14:50:28.194 UTC 702fea 8528] f84f.57ca.3860 **WTP Event Response** sent to 10.201.234.24:18759

show log

[11/14/13 14:50:27.869 UTC 702f94 8528] f84f.57ca.3860 **Configuration Status** from 10.201.234.24:18759

[11/14/13 14:50:27.870 UTC 702f95 8528] f84f.57ca.3860 **CAPWAP State: Configure**

[11/14/13 14:50:27.870 UTC 702f96 8528] f84f.57ca.3860 New unsupported Payload 254 in message from AP f84f.57ca.3860, Return SUCCESS

[11/14/13 14:50:27.870 UTC 702f97 8528] f84f.57ca.3860 Decoding new unsupported Payload 254 in message from AP f84f.57ca.3860, Return SUCCESS

[11/14/13 14:50:27.870 UTC 702f98 8528] Invalid channel 11 spacificied for the AP AP2602I-1, slotId = 0

[11/14/13 14:50:27.870 UTC 702f99 8528] Invalid channel 56 spacificied for the AP AP2602I-1, slotId = 1

[11/14/13 14:50:27.870 UTC 702f9a 8528] f84f.57ca.3860 Updating IP info for AP f84f.57ca.3860 -- static 0, 10.201.234.24/255.255.255.224, gtw 10.201.234.2

[11/14/13 14:50:27.870 UTC 702f9b 8528] f84f.57ca.3860 Updating IP 10.201.234.24 ==> 10.201.234.24 for AP f84f.57ca.3860

|
[11/14/13 14:50:27.870 UTC 702fab 8528] f84f.57ca.3860 LWAPP message validation

failed for SPAM Vendor Specific Payload(104) in message of len=7 from AP
f84f.57ca.3860

[11/14/13 14:50:27.870 UTC 702fac 8528] f84f.57ca.3860 Failed to validate vendor
specific message element

[11/14/13 14:50:27.871 UTC 702fad 8528] f84f.57ca.3860 **Setting MTU to 1485**

[11/14/13 14:50:27.871 UTC 702fae 8528] f84f.57ca.3860 Platform not Supported,
exiting Load Balancer function

[11/14/13 14:50:27.871 UTC 702faf 8528] load balancer rc=4 for AP 10.201.234.24,
IIF ID:0x00d2a98000000796

[11/14/13 14:50:27.871 UTC 702fb0 8528] opaque data size 0 with capwap interface
create f84f.57ca.3860

[11/14/13 14:50:27.871 UTC 702fb1 8528] spiCapwapParams->
data_tunnel.opaque_data.opaque_data_len: 0

[11/14/13 14:50:27.871 UTC 702fb2 8528] f84f.57ca.3860 Data Tunnel Create timer
started for 240 seconds timeout

[11/14/13 14:50:27.871 UTC 702fb3 8528] f84f.57ca.3860 **Data Tunnel created -
tunnel type NON_CRYPTO**, load balancer support Not supported, tunnel mtu 1449,

anc_sw_id 0, anc_asic_id 0, res_sw_id 0, res_asic_id 0

anc_wp_iif_id 0x0000000000000000, res_wp_iif_id 0x0000000000000000

[11/14/13 14:50:27.871 UTC 702fb4 8528] f84f.57ca.3860 Not ready to send Config
Status Response to AP 10.201.234.24 as SPI ACK is not received

[11/14/13 14:50:27.871 UTC 702fb5 8528] f84f.57ca.3860 AP f84f.57ca.3860
associated. Last AP failure was due to Configuration changes,reason:
controller reboot command

[11/14/13 14:50:27.871 UTC 30e6 260] [CAPWAP]: CAPWAP data tunnel create message.

[11/14/13 14:50:27.871 UTC 30e7 260] [CAPWAP]: capwap_data_tunnel_create called

[11/14/13 14:50:27.871 UTC 30e8 260] [CAPWAP]: Data tunnel id = 0xd2a98000000796

[11/14/13 14:50:27.871 UTC 30e9 260] [CAPWAP]: Tunnel Entry not found for AP
(10.201.234.24, 18759)

[11/14/13 14:50:27.873 UTC 30ea 260] [CAPWAP]: CAPWAP IDB init complete

[11/14/13 14:50:27.882 UTC 30eb 260] [CAPWAP]: capwap_interface_status_update:
tunnel 0xd2a98000000796 status 0

[11/14/13 14:50:27.882 UTC 30ec 260] [CAPWAP]: csb pd flag 0 opaque_data_len 0
attr opaque_data 0x00000000

[11/14/13 14:50:27.882 UTC 30ed 260] [CAPWAP]: Send capwap_data_tunnel_status_update
0 Slot-Unit 1 Unit 1 for iif_id 0xd2a98000000796 to WCM.

[11/14/13 14:50:27.882 UTC 30ee 260] [CAPWAP]: (capwap_process_fed_results) CAPWAP
FED result (0) for IIF ID: 0xd2a98000000796

[11/14/13 14:50:27.882 UTC 702fb6 8528

Received CAPWAP Tunnel SPI update opaque size 0

[11/14/13 14:50:27.882 UTC 702fb7 8528] opaque data len 0 with capwap server update

[11/14/13 14:50:27.883 UTC 702fb8 8528] f84f.57ca.3860 SPI ACK : Capwap Data Tunnel create successful for iifid:0x00d2a98000000796 AP:10.201.234.24

[11/14/13 14:50:27.883 UTC 702fb9 8528]

Received CAPWAP interface update opaque len 0

[11/14/13 14:50:27.883 UTC 702fba 8528] **SPI IifId ACK: Capwap Data Tunnel Created Successfully for IifId: 0x00d2a98000000796 AP: 10.201.234.24**

[11/14/13 14:50:27.883 UTC 702fbb 8528] f84f.57ca.3860 **OK to send Config Status Response to AP 10.201.234.24**

[11/14/13 14:50:27.888 UTC 30ef 260] [CAPWAP]: Notify PM (done).

[11/14/13 14:50:27.888 UTC 30f0 260] [CAPWAP]: SNMP Register: Ca1 HWIDB 32f44570

[11/14/13 14:50:27.888 UTC 30f1 260] [CAPWAP]: capwap_port_hashitem added: slot 1 slotunit 24 vlan 1104

[11/14/13 14:50:27.888 UTC 30f2 260] [CAPWAP]: 7c69.f604.9460 is AP's mac addr

[11/14/13 14:50:27.932 UTC 702fbc 8528] Sending multicast payload to ap AP2602I-1, mcast_mode 0, mcast group 0.0.0.0

[11/14/13 14:50:27.933 UTC 702fbd 8528] f84f.57ca.3860 Config status response sent to 10.201.234.24:18759

[11/14/13 14:50:27.933 UTC 702fbe 8528] f84f.57ca.3860 Configuration Status Response sent to 10:201:234:24

[11/14/13 14:50:27.933 UTC 702fbf 8528] f84f.57ca.3860 Configuration update request for Band Select Cfg sent to 10.201.234.24:18759

[11/14/13 14:50:27.933 UTC 702fc0 8528] f84f.57ca.3860 Configuration update request for HaConfig message sent to 10.201.234.24:18759

[11/14/13 14:50:27.934 UTC 702fc1 8528] f84f.57ca.3860 Configuration update request for AP NGWC Qos sent to 10.201.234.24:18759

[11/14/13 14:50:28.121 UTC 702fc2 8528] f84f.57ca.3860 Change State Event Request from 10.201.234.24:18759

[11/14/13 14:50:28.122 UTC 702fc3 8528] f84f.57ca.3860 Received LWAPP Up event for AP f84f.57ca.3860 slot 0!

[11/14/13 14:50:28.122 UTC 702fc4 8528] f84f.57ca.3860 Radio state change for slot: 0 state: 2 cause: 0 detail cause: 0

[11/14/13 14:50:28.122 UTC 702fc5 8528] f84f.57ca.3860 Change State Event Response sent to 10.201.234.24:18759

[11/14/13 14:50:28.122 UTC 702fc6 8528] f84f.57ca.3860 CAPWAP State: Run

[11/14/13 14:50:28.122 UTC 702fc7 8528] f84f.57ca.3860 Sending the remaining config to AP 10.201.234.24:18759

[11/14/13 14:50:28.122 UTC 702fc8 8528] f84f.57ca.3860 AP Going to RUN 10.201.234.24: ConcurrentJoins: 0

[11/14/13 14:50:28.122 UTC 702fc9 8528] f84f.57ca.3860 **Configuration update request** for Init VAP-DATA for slot 1 sent to 10.201.234.24:18759

[11/14/13 14:50:28.122 UTC 702fca 8528] f84f.57ca.3860 Configuration update request for configuring association limit params sent to 10.201.234.24:18759

[11/14/13 14:50:28.122 UTC 702fcb 8528] f84f.57ca.3860 Configuration update request for Band Select Cfg sent to 10.201.234.24:18759

[11/14/13 14:50:28.122 UTC 702fcc 8528] f84f.57ca.3860 Configuration update request for HaConfig message sent to 10.201.234.24:18759

[11/14/13 14:50:28.123 UTC 702fcd 8528] CAPWAP: No update, will insert f84f.57ca.3860

[11/14/13 14:50:28.123 UTC 702fce 8528] capwap opaque data f84f.57ca.3860 length = 0

[11/14/13 14:50:28.124 UTC 702fcf 8528] CAPWAP HA insert f84f.57ca.3860

[11/14/13 14:50:28.124 UTC 702fd0 8528] CAPWAP HA insert f84f.57ca.3860

[11/14/13 14:50:28.124 UTC 702fd1 8528] f84f.57ca.3860 Configuration update request for PHY payload sent to 10:201:234:24

[11/14/13 14:50:28.126 UTC 702fd2 8528] f84f.57ca.3860 **Configuration Update Response** from 10.201.234.24:18759

[11/14/13 14:50:28.126 UTC 702fd3 8528] f84f.57ca.3860 Configuration update request for RrmInterferenceCtrl payload sent to 10:201:234:24

[11/14/13 14:50:28.126 UTC 702fd4 8528] f84f.57ca.3860 Configuration update request for RrmNeighbourCtrl payload sent to 10.201.234.24

[11/14/13 14:50:28.126 UTC 702fd5 8528] f84f.57ca.3860 Configuration update request for RrmReceiveCtrl payload sent to 10:201:234:24

[11/14/13 14:50:28.126 UTC 702fd6 8528] f84f.57ca.3860 Configuration update request for CcxRmMeas payload sent to 10.201.234.24

[11/14/13 14:50:28.132 UTC 702fd7 8528] f84f.57ca.3860 Change State Event Request from 10.201.234.24:18759

[11/14/13 14:50:28.132 UTC 702fd8 8528] f84f.57ca.3860 Radio state change for slot: 1 state: 2 cause: 0 detail cause: 0

[11/14/13 14:50:28.132 UTC 702fd9 8528] f84f.57ca.3860 Change State Event Response sent to 10.201.234.24:18759

[11/14/13 14:50:28.132 UTC 702fda 8528] f84f.57ca.3860 CAPWAP State: Run

[11/14/13 14:50:28.132 UTC 702fdb 8528] f84f.57ca.3860 Sending the remaining config to AP 10.201.234.24:18759

[11/14/13 14:50:28.133 UTC 702fdc 8528] f84f.57ca.3860 Configuration update request for qos pm payload payload sent to 10.201.234.24:18759

[11/14/13 14:50:28.133 UTC 702fdd 8528] f84f.57ca.3860 Received LWAPP Up event for AP f84f.57ca.3860 slot 1!

[11/14/13 14:50:28.133 UTC 702fde 8528] f84f.57ca.3860 Configuration update request for PHY payload sent to 10:201:234:24

[11/14/13 14:50:28.133 UTC 702fdf 8528] f84f.57ca.3860 Configuration update request for RrmInterferenceCtrl payload sent to 10:201:234:24

[11/14/13 14:50:28.133 UTC 702fe0 8528] f84f.57ca.3860 Configuration update request for RrmNeighbourCtrl payload sent to 10.201.234.24

[11/14/13 14:50:28.134 UTC 702fe1 8528] f84f.57ca.3860 Configuration update request for RrmReceiveCtrl payload sent to 10:201:234:24

[11/14/13 14:50:28.134 UTC 702fe2 8528] f84f.57ca.3860 Configuration update request for CcxRmMeas payload sent to 10.201.234.24

[11/14/13 14:50:28.188 UTC 702fe3 8528] f84f.57ca.3860 Configuration Update Response from 10.201.234.24:18759

[11/14/13 14:50:28.188 UTC 702fe4 8528] f84f.57ca.3860 Change State Event Request from 10.201.234.24:18759

[11/14/13 14:50:28.188 UTC 702fe5 8528] f84f.57ca.3860 Change State Event Response sent to 10.201.234.24:18759

[11/14/13 14:50:28.188 UTC 702fe6 8528] f84f.57ca.3860 CAPWAP State: Run

[11/14/13 14:50:28.188 UTC 702fe7 8528] f84f.57ca.3860 Sending the remaining config to AP 10.201.234.24:18759

[11/14/13 14:50:28.194 UTC 702fe8 8528] f84f.57ca.3860 Configuration Update Response from 10.201.234.24:18759

[11/14/13 14:50:28.194 UTC 702fe9 8528] f84f.57ca.3860 **WTP Event Request** from 10.201.234.24:18759

[11/14/13 14:50:28.194 UTC 702fea 8528] f84f.57ca.3860 **WTP Event Response** sent to 10.201.234.24:18759

AP находится в VLAN 25, и нет никакой конфигурации интерфейса беспроводного управления для VLAN 25.

Проблема 2: Используемая модель точки доступа является неподдерживаемой.

Вот тест AP1131.

show log

[11/14/13 14:50:27.869 UTC 702f94 8528] f84f.57ca.3860 **Configuration Status** from 10.201.234.24:18759

[11/14/13 14:50:27.870 UTC 702f95 8528] f84f.57ca.3860 **CAPWAP State: Configure**

[11/14/13 14:50:27.870 UTC 702f96 8528] f84f.57ca.3860 New unsupported Payload 254 in message from AP f84f.57ca.3860, Return SUCCESS

[11/14/13 14:50:27.870 UTC 702f97 8528] f84f.57ca.3860 Decoding new unsupported Payload 254 in message from AP f84f.57ca.3860, Return SUCCESS

[11/14/13 14:50:27.870 UTC 702f98 8528] Invalid channel 11 spacificed for the AP AP2602I-1, slotId = 0

[11/14/13 14:50:27.870 UTC 702f99 8528] Invalid channel 56 spacificed for the AP AP2602I-1, slotId = 1

[11/14/13 14:50:27.870 UTC 702f9a 8528] f84f.57ca.3860 Updating IP info for AP f84f.57ca.3860 -- static 0, 10.201.234.24/255.255.255.224, gtw 10.201.234.2

[11/14/13 14:50:27.870 UTC 702f9b 8528] f84f.57ca.3860 Updating IP
10.201.234.24 ==> 10.201.234.24 for AP f84f.57ca.3860

|

[11/14/13 14:50:27.870 UTC 702fab 8528] f84f.57ca.3860 LWAPP message validation
failed for SPAM Vendor Specific Payload(104) in message of len=7 from AP
f84f.57ca.3860

[11/14/13 14:50:27.870 UTC 702fac 8528] f84f.57ca.3860 Failed to validate vendor
specific message element

[11/14/13 14:50:27.871 UTC 702fad 8528] f84f.57ca.3860 **Setting MTU to 1485**

[11/14/13 14:50:27.871 UTC 702fae 8528] f84f.57ca.3860 Platform not Supported,
exiting Load Balancer function

[11/14/13 14:50:27.871 UTC 702faf 8528] load balancer rc=4 for AP 10.201.234.24,
IIF ID:0x00d2a98000000796

[11/14/13 14:50:27.871 UTC 702fb0 8528] opaque data size 0 with capwap interface
create f84f.57ca.3860

[11/14/13 14:50:27.871 UTC 702fb1 8528] spiCapwapParams->
data_tunnel.opaque_data.opaque_data_len: 0

[11/14/13 14:50:27.871 UTC 702fb2 8528] f84f.57ca.3860 Data Tunnel Create timer
started for 240 seconds timeout

[11/14/13 14:50:27.871 UTC 702fb3 8528] f84f.57ca.3860 **Data Tunnel created -
tunnel type NON_CRYPTO**, load balancer support Not supported, tunnel mtu 1449,

anc_sw_id 0, anc_asic_id 0, res_sw_id 0, res_asic_id 0

anc_wp_iif_id 0x0000000000000000, res_wp_iif_id 0x0000000000000000

[11/14/13 14:50:27.871 UTC 702fb4 8528] f84f.57ca.3860 Not ready to send Config
Status Response to AP 10.201.234.24 as SPI ACK is not received

[11/14/13 14:50:27.871 UTC 702fb5 8528] f84f.57ca.3860 AP f84f.57ca.3860
associated. Last AP failure was due to Configuration changes,reason:
controller reboot command

[11/14/13 14:50:27.871 UTC 30e6 260] [CAPWAP]: CAPWAP data tunnel create message.

[11/14/13 14:50:27.871 UTC 30e7 260] [CAPWAP]: capwap_data_tunnel_create called

[11/14/13 14:50:27.871 UTC 30e8 260] [CAPWAP]: Data tunnel id = 0xd2a98000000796

[11/14/13 14:50:27.871 UTC 30e9 260] [CAPWAP]: Tunnel Entry not found for AP
(10.201.234.24, 18759)

[11/14/13 14:50:27.873 UTC 30ea 260] [CAPWAP]: CAPWAP IDB init complete

[11/14/13 14:50:27.882 UTC 30eb 260] [CAPWAP]: capwap_interface_status_update:
tunnel 0xd2a98000000796 status 0

[11/14/13 14:50:27.882 UTC 30ec 260] [CAPWAP]: csb pd flag 0 opaque_data_len 0
attr opaque_data 0x00000000

[11/14/13 14:50:27.882 UTC 30ed 260] [CAPWAP]: Send capwap_data_tunnel_status_update
0 Slot-Unit 1 Unit 1 for iif_id 0xd2a98000000796 to WCM.

[11/14/13 14:50:27.882 UTC 30ee 260] [CAPWAP]: (capwap_process_fed_results) CAPWAP FED result (0) for IIF ID: 0xd2a98000000796

[11/14/13 14:50:27.882 UTC 702fb6 8528

Received CAPWAP Tunnel SPI update opaque size 0

[11/14/13 14:50:27.882 UTC 702fb7 8528] opaque data len 0 with capwap server update

[11/14/13 14:50:27.883 UTC 702fb8 8528] f84f.57ca.3860 SPI ACK : Capwap Data Tunnel create successful for iifid:0x00d2a98000000796 AP:10.201.234.24

[11/14/13 14:50:27.883 UTC 702fb9 8528]

Received CAPWAP interface update opaque len 0

[11/14/13 14:50:27.883 UTC 702fba 8528] **SPI IifId ACK: Capwap Data Tunnel Created Successfully for IifId: 0x00d2a98000000796 AP: 10.201.234.24**

[11/14/13 14:50:27.883 UTC 702fbb 8528] f84f.57ca.3860 **OK to send Config Status Response to AP 10.201.234.24**

[11/14/13 14:50:27.888 UTC 30ef 260] [CAPWAP]: Notify PM (done).

[11/14/13 14:50:27.888 UTC 30f0 260] [CAPWAP]: SNMP Register: Cal HWIDB 32f44570

[11/14/13 14:50:27.888 UTC 30f1 260] [CAPWAP]: capwap_port_hashitem added: slot 1 slotunit 24 vlan 1104

[11/14/13 14:50:27.888 UTC 30f2 260] [CAPWAP]: 7c69.f604.9460 is AP's mac addr

[11/14/13 14:50:27.932 UTC 702fbc 8528] Sending multicast payload to ap AP2602I-1, mcast_mode 0, mcast group 0.0.0.0

[11/14/13 14:50:27.933 UTC 702fbd 8528] f84f.57ca.3860 Config status response sent to 10.201.234.24:18759

[11/14/13 14:50:27.933 UTC 702fbe 8528] f84f.57ca.3860 Configuration Status Response sent to 10:201:234:24

[11/14/13 14:50:27.933 UTC 702fbf 8528] f84f.57ca.3860 Configuration update request for Band Select Cfg sent to 10.201.234.24:18759

[11/14/13 14:50:27.933 UTC 702fc0 8528] f84f.57ca.3860 Configuration update request for HaConfig message sent to 10.201.234.24:18759

[11/14/13 14:50:27.934 UTC 702fc1 8528] f84f.57ca.3860 Configuration update request for AP NGWC Qos sent to 10.201.234.24:18759

[11/14/13 14:50:28.121 UTC 702fc2 8528] f84f.57ca.3860 Change State Event Request from 10.201.234.24:18759

[11/14/13 14:50:28.122 UTC 702fc3 8528] f84f.57ca.3860 Received LWAPP Up event for AP f84f.57ca.3860 slot 0!

[11/14/13 14:50:28.122 UTC 702fc4 8528] f84f.57ca.3860 Radio state change for slot: 0 state: 2 cause: 0 detail cause: 0

[11/14/13 14:50:28.122 UTC 702fc5 8528] f84f.57ca.3860 Change State Event Response sent to 10.201.234.24:18759

[11/14/13 14:50:28.122 UTC 702fc6 8528] f84f.57ca.3860 CAPWAP State: Run

[11/14/13 14:50:28.122 UTC 702fc7 8528] f84f.57ca.3860 Sending the remaining

config to AP 10.201.234.24:18759

[11/14/13 14:50:28.122 UTC 702fc8 8528] f84f.57ca.3860 AP Going to RUN
10.201.234.24: ConcurrentJoins: 0

[11/14/13 14:50:28.122 UTC 702fc9 8528] f84f.57ca.3860 **Configuration update request** for Init VAP-DATA for slot 1 sent to 10.201.234.24:18759

[11/14/13 14:50:28.122 UTC 702fca 8528] f84f.57ca.3860 Configuration update request for configuring association limit params sent to 10.201.234.24:18759

[11/14/13 14:50:28.122 UTC 702fcb 8528] f84f.57ca.3860 Configuration update request for Band Select Cfg sent to 10.201.234.24:18759

[11/14/13 14:50:28.122 UTC 702fcc 8528] f84f.57ca.3860 Configuration update request for HaConfig message sent to 10.201.234.24:18759

[11/14/13 14:50:28.123 UTC 702fcd 8528] CAPWAP: No update, will insert f84f.57ca.3860

[11/14/13 14:50:28.123 UTC 702fce 8528] capwap opaque data f84f.57ca.3860 length = 0

[11/14/13 14:50:28.124 UTC 702fcf 8528] CAPWAP HA insert f84f.57ca.3860

[11/14/13 14:50:28.124 UTC 702fd0 8528] CAPWAP HA insert f84f.57ca.3860

[11/14/13 14:50:28.124 UTC 702fd1 8528] f84f.57ca.3860 Configuration update request for PHY payload sent to 10:201:234:24

[11/14/13 14:50:28.126 UTC 702fd2 8528] f84f.57ca.3860 **Configuration Update Response** from 10.201.234.24:18759

[11/14/13 14:50:28.126 UTC 702fd3 8528] f84f.57ca.3860 Configuration update request for RrmInterferenceCtrl payload sent to 10:201:234:24

[11/14/13 14:50:28.126 UTC 702fd4 8528] f84f.57ca.3860 Configuration update request for RrmNeighbourCtrl payload sent to 10.201.234.24

[11/14/13 14:50:28.126 UTC 702fd5 8528] f84f.57ca.3860 Configuration update request for RrmReceiveCtrl payload sent to 10:201:234:24

[11/14/13 14:50:28.126 UTC 702fd6 8528] f84f.57ca.3860 Configuration update request for CcxRmMeas payload sent to 10.201.234.24

[11/14/13 14:50:28.132 UTC 702fd7 8528] f84f.57ca.3860 Change State Event Request from 10.201.234.24:18759

[11/14/13 14:50:28.132 UTC 702fd8 8528] f84f.57ca.3860 Radio state change for slot: 1 state: 2 cause: 0 detail cause: 0

[11/14/13 14:50:28.132 UTC 702fd9 8528] f84f.57ca.3860 Change State Event Response sent to 10.201.234.24:18759

[11/14/13 14:50:28.132 UTC 702fda 8528] f84f.57ca.3860 CAPWAP State: Run

[11/14/13 14:50:28.132 UTC 702fdb 8528] f84f.57ca.3860 Sending the remaining config to AP 10.201.234.24:18759

[11/14/13 14:50:28.133 UTC 702fdc 8528] f84f.57ca.3860 Configuration update request for qos pm payload payload sent to 10.201.234.24:18759

[11/14/13 14:50:28.133 UTC 702fdd 8528] f84f.57ca.3860 Received LWAPP Up event for AP f84f.57ca.3860 slot 1!

[11/14/13 14:50:28.133 UTC 702fde 8528] f84f.57ca.3860 Configuration update request for PHY payload sent to 10:201:234:24

[11/14/13 14:50:28.133 UTC 702fdf 8528] f84f.57ca.3860 Configuration update request for RrmInterferenceCtrl payload sent to 10:201:234:24

[11/14/13 14:50:28.133 UTC 702fe0 8528] f84f.57ca.3860 Configuration update request for RrmNeighbourCtrl payload sent to 10.201.234.24

[11/14/13 14:50:28.134 UTC 702fe1 8528] f84f.57ca.3860 Configuration update request for RrmReceiveCtrl payload sent to 10:201:234:24

[11/14/13 14:50:28.134 UTC 702fe2 8528] f84f.57ca.3860 Configuration update request for CcxRmMeas payload sent to 10.201.234.24

[11/14/13 14:50:28.188 UTC 702fe3 8528] f84f.57ca.3860 Configuration Update Response from 10.201.234.24:18759

[11/14/13 14:50:28.188 UTC 702fe4 8528] f84f.57ca.3860 Change State Event Request from 10.201.234.24:18759

[11/14/13 14:50:28.188 UTC 702fe5 8528] f84f.57ca.3860 Change State Event Response sent to 10.201.234.24:18759

[11/14/13 14:50:28.188 UTC 702fe6 8528] f84f.57ca.3860 CAPWAP State: Run

[11/14/13 14:50:28.188 UTC 702fe7 8528] f84f.57ca.3860 Sending the remaining config to AP 10.201.234.24:18759

[11/14/13 14:50:28.194 UTC 702fe8 8528] f84f.57ca.3860 Configuration Update Response from 10.201.234.24:18759

[11/14/13 14:50:28.194 UTC 702fe9 8528] f84f.57ca.3860 **WTP Event Request** from 10.201.234.24:18759

[11/14/13 14:50:28.194 UTC 702fea 8528] f84f.57ca.3860 **WTP Event Response** sent to 10.201.234.24:18759

Проблема 3: Лицензия количества AP не включена на контроллере.

Право на использование лицензии #show summ

[11/14/13 14:50:27.869 UTC 702f94 8528] f84f.57ca.3860 **Configuration Status** from 10.201.234.24:18759

[11/14/13 14:50:27.870 UTC 702f95 8528] f84f.57ca.3860 **CAPWAP State: Configure**

[11/14/13 14:50:27.870 UTC 702f96 8528] f84f.57ca.3860 New unsupported Payload 254 in message from AP f84f.57ca.3860, Return SUCCESS

[11/14/13 14:50:27.870 UTC 702f97 8528] f84f.57ca.3860 Decoding new unsupported Payload 254 in message from AP f84f.57ca.3860, Return SUCCESS

[11/14/13 14:50:27.870 UTC 702f98 8528] Invalid channel 11 spacificied for the AP AP2602I-1, slotId = 0

[11/14/13 14:50:27.870 UTC 702f99 8528] Invalid channel 56 spacificied for the AP AP2602I-1, slotId = 1

[11/14/13 14:50:27.870 UTC 702f9a 8528] f84f.57ca.3860 Updating IP info for AP f84f.57ca.3860 -- static 0, 10.201.234.24/255.255.255.224, gtw 10.201.234.2

[11/14/13 14:50:27.870 UTC 702f9b 8528] f84f.57ca.3860 Updating IP
10.201.234.24 ==> 10.201.234.24 for AP f84f.57ca.3860

|

[11/14/13 14:50:27.870 UTC 702fab 8528] f84f.57ca.3860 LWAPP message validation
failed for SPAM Vendor Specific Payload(104) in message of len=7 from AP
f84f.57ca.3860

[11/14/13 14:50:27.870 UTC 702fac 8528] f84f.57ca.3860 Failed to validate vendor
specific message element

[11/14/13 14:50:27.871 UTC 702fad 8528] f84f.57ca.3860 **Setting MTU to 1485**

[11/14/13 14:50:27.871 UTC 702fae 8528] f84f.57ca.3860 Platform not Supported,
exiting Load Balancer function

[11/14/13 14:50:27.871 UTC 702faf 8528] load balancer rc=4 for AP 10.201.234.24,
IIF ID:0x00d2a98000000796

[11/14/13 14:50:27.871 UTC 702fb0 8528] opaque data size 0 with capwap interface
create f84f.57ca.3860

[11/14/13 14:50:27.871 UTC 702fb1 8528] spiCapwapParams->
data_tunnel.opaque_data.opaque_data_len: 0

[11/14/13 14:50:27.871 UTC 702fb2 8528] f84f.57ca.3860 Data Tunnel Create timer
started for 240 seconds timeout

[11/14/13 14:50:27.871 UTC 702fb3 8528] f84f.57ca.3860 **Data Tunnel created -
tunnel type NON_CRYPTO**, load balancer support Not supported, tunnel mtu 1449,

anc_sw_id 0, anc_asic_id 0, res_sw_id 0, res_asic_id 0

anc_wp_iif_id 0x0000000000000000, res_wp_iif_id 0x0000000000000000

[11/14/13 14:50:27.871 UTC 702fb4 8528] f84f.57ca.3860 Not ready to send Config
Status Response to AP 10.201.234.24 as SPI ACK is not received

[11/14/13 14:50:27.871 UTC 702fb5 8528] f84f.57ca.3860 AP f84f.57ca.3860
associated. Last AP failure was due to Configuration changes,reason:
controller reboot command

[11/14/13 14:50:27.871 UTC 30e6 260] [CAPWAP]: CAPWAP data tunnel create message.

[11/14/13 14:50:27.871 UTC 30e7 260] [CAPWAP]: capwap_data_tunnel_create called

[11/14/13 14:50:27.871 UTC 30e8 260] [CAPWAP]: Data tunnel id = 0xd2a98000000796

[11/14/13 14:50:27.871 UTC 30e9 260] [CAPWAP]: Tunnel Entry not found for AP
(10.201.234.24, 18759)

[11/14/13 14:50:27.873 UTC 30ea 260] [CAPWAP]: CAPWAP IDB init complete

[11/14/13 14:50:27.882 UTC 30eb 260] [CAPWAP]: capwap_interface_status_update:
tunnel 0xd2a98000000796 status 0

[11/14/13 14:50:27.882 UTC 30ec 260] [CAPWAP]: csb pd flag 0 opaque_data_len 0
attr opaque_data 0x00000000

[11/14/13 14:50:27.882 UTC 30ed 260] [CAPWAP]: Send capwap_data_tunnel_status_update
0 Slot-Unit 1 Unit 1 for iif_id 0xd2a98000000796 to WCM.

[11/14/13 14:50:27.882 UTC 30ee 260] [CAPWAP]: (capwap_process_fed_results) CAPWAP FED result (0) for IIF ID: 0xd2a98000000796

[11/14/13 14:50:27.882 UTC 702fb6 8528

Received CAPWAP Tunnel SPI update opaque size 0

[11/14/13 14:50:27.882 UTC 702fb7 8528] opaque data len 0 with capwap server update

[11/14/13 14:50:27.883 UTC 702fb8 8528] f84f.57ca.3860 SPI ACK : Capwap Data Tunnel create successful for iifid:0x00d2a98000000796 AP:10.201.234.24

[11/14/13 14:50:27.883 UTC 702fb9 8528]

Received CAPWAP interface update opaque len 0

[11/14/13 14:50:27.883 UTC 702fba 8528] **SPI IifId ACK: Capwap Data Tunnel Created Successfully for IifId: 0x00d2a98000000796 AP: 10.201.234.24**

[11/14/13 14:50:27.883 UTC 702fbb 8528] f84f.57ca.3860 **OK to send Config Status Response to AP 10.201.234.24**

[11/14/13 14:50:27.888 UTC 30ef 260] [CAPWAP]: Notify PM (done).

[11/14/13 14:50:27.888 UTC 30f0 260] [CAPWAP]: SNMP Register: Cal HWIDB 32f44570

[11/14/13 14:50:27.888 UTC 30f1 260] [CAPWAP]: capwap_port_hashitem added: slot 1 slotunit 24 vlan 1104

[11/14/13 14:50:27.888 UTC 30f2 260] [CAPWAP]: 7c69.f604.9460 is AP's mac addr

[11/14/13 14:50:27.932 UTC 702fbc 8528] Sending multicast payload to ap AP2602I-1, mcast_mode 0, mcast group 0.0.0.0

[11/14/13 14:50:27.933 UTC 702fbd 8528] f84f.57ca.3860 Config status response sent to 10.201.234.24:18759

[11/14/13 14:50:27.933 UTC 702fbe 8528] f84f.57ca.3860 Configuration Status Response sent to 10:201:234:24

[11/14/13 14:50:27.933 UTC 702fbf 8528] f84f.57ca.3860 Configuration update request for Band Select Cfg sent to 10.201.234.24:18759

[11/14/13 14:50:27.933 UTC 702fc0 8528] f84f.57ca.3860 Configuration update request for HaConfig message sent to 10.201.234.24:18759

[11/14/13 14:50:27.934 UTC 702fc1 8528] f84f.57ca.3860 Configuration update request for AP NGWC Qos sent to 10.201.234.24:18759

[11/14/13 14:50:28.121 UTC 702fc2 8528] f84f.57ca.3860 Change State Event Request from 10.201.234.24:18759

[11/14/13 14:50:28.122 UTC 702fc3 8528] f84f.57ca.3860 Received LWAPP Up event for AP f84f.57ca.3860 slot 0!

[11/14/13 14:50:28.122 UTC 702fc4 8528] f84f.57ca.3860 Radio state change for slot: 0 state: 2 cause: 0 detail cause: 0

[11/14/13 14:50:28.122 UTC 702fc5 8528] f84f.57ca.3860 Change State Event Response sent to 10.201.234.24:18759

[11/14/13 14:50:28.122 UTC 702fc6 8528] f84f.57ca.3860 CAPWAP State: Run

[11/14/13 14:50:28.122 UTC 702fc7 8528] f84f.57ca.3860 Sending the remaining

config to AP 10.201.234.24:18759

[11/14/13 14:50:28.122 UTC 702fc8 8528] f84f.57ca.3860 AP Going to RUN
10.201.234.24: ConcurrentJoins: 0

[11/14/13 14:50:28.122 UTC 702fc9 8528] f84f.57ca.3860 **Configuration update request** for Init VAP-DATA for slot 1 sent to 10.201.234.24:18759

[11/14/13 14:50:28.122 UTC 702fca 8528] f84f.57ca.3860 Configuration update request for configuring association limit params sent to 10.201.234.24:18759

[11/14/13 14:50:28.122 UTC 702fcb 8528] f84f.57ca.3860 Configuration update request for Band Select Cfg sent to 10.201.234.24:18759

[11/14/13 14:50:28.122 UTC 702fcc 8528] f84f.57ca.3860 Configuration update request for HaConfig message sent to 10.201.234.24:18759

[11/14/13 14:50:28.123 UTC 702fcd 8528] CAPWAP: No update, will insert f84f.57ca.3860

[11/14/13 14:50:28.123 UTC 702fce 8528] capwap opaque data f84f.57ca.3860 length = 0

[11/14/13 14:50:28.124 UTC 702fcf 8528] CAPWAP HA insert f84f.57ca.3860

[11/14/13 14:50:28.124 UTC 702fd0 8528] CAPWAP HA insert f84f.57ca.3860

[11/14/13 14:50:28.124 UTC 702fd1 8528] f84f.57ca.3860 Configuration update request for PHY payload sent to 10:201:234:24

[11/14/13 14:50:28.126 UTC 702fd2 8528] f84f.57ca.3860 **Configuration Update Response** from 10.201.234.24:18759

[11/14/13 14:50:28.126 UTC 702fd3 8528] f84f.57ca.3860 Configuration update request for RrmInterferenceCtrl payload sent to 10:201:234:24

[11/14/13 14:50:28.126 UTC 702fd4 8528] f84f.57ca.3860 Configuration update request for RrmNeighbourCtrl payload sent to 10.201.234.24

[11/14/13 14:50:28.126 UTC 702fd5 8528] f84f.57ca.3860 Configuration update request for RrmReceiveCtrl payload sent to 10:201:234:24

[11/14/13 14:50:28.126 UTC 702fd6 8528] f84f.57ca.3860 Configuration update request for CcxRmMeas payload sent to 10.201.234.24

[11/14/13 14:50:28.132 UTC 702fd7 8528] f84f.57ca.3860 Change State Event Request from 10.201.234.24:18759

[11/14/13 14:50:28.132 UTC 702fd8 8528] f84f.57ca.3860 Radio state change for slot: 1 state: 2 cause: 0 detail cause: 0

[11/14/13 14:50:28.132 UTC 702fd9 8528] f84f.57ca.3860 Change State Event Response sent to 10.201.234.24:18759

[11/14/13 14:50:28.132 UTC 702fda 8528] f84f.57ca.3860 CAPWAP State: Run

[11/14/13 14:50:28.132 UTC 702fdb 8528] f84f.57ca.3860 Sending the remaining config to AP 10.201.234.24:18759

[11/14/13 14:50:28.133 UTC 702fdc 8528] f84f.57ca.3860 Configuration update request for qos pm payload payload sent to 10.201.234.24:18759

[11/14/13 14:50:28.133 UTC 702fdd 8528] f84f.57ca.3860 Received LWAPP Up event for AP f84f.57ca.3860 slot 1!

[11/14/13 14:50:28.133 UTC 702fde 8528] f84f.57ca.3860 Configuration update request for PHY payload sent to 10:201:234:24

[11/14/13 14:50:28.133 UTC 702fdf 8528] f84f.57ca.3860 Configuration update request for RrmInterferenceCtrl payload sent to 10:201:234:24

[11/14/13 14:50:28.133 UTC 702fe0 8528] f84f.57ca.3860 Configuration update request for RrmNeighbourCtrl payload sent to 10.201.234.24

[11/14/13 14:50:28.134 UTC 702fe1 8528] f84f.57ca.3860 Configuration update request for RrmReceiveCtrl payload sent to 10:201:234:24

[11/14/13 14:50:28.134 UTC 702fe2 8528] f84f.57ca.3860 Configuration update request for CcxRmMeas payload sent to 10.201.234.24

[11/14/13 14:50:28.188 UTC 702fe3 8528] f84f.57ca.3860 Configuration Update Response from 10.201.234.24:18759

[11/14/13 14:50:28.188 UTC 702fe4 8528] f84f.57ca.3860 Change State Event Request from 10.201.234.24:18759

[11/14/13 14:50:28.188 UTC 702fe5 8528] f84f.57ca.3860 Change State Event Response sent to 10.201.234.24:18759

[11/14/13 14:50:28.188 UTC 702fe6 8528] f84f.57ca.3860 CAPWAP State: Run

[11/14/13 14:50:28.188 UTC 702fe7 8528] f84f.57ca.3860 Sending the remaining config to AP 10.201.234.24:18759

[11/14/13 14:50:28.194 UTC 702fe8 8528] f84f.57ca.3860 Configuration Update Response from 10.201.234.24:18759

[11/14/13 14:50:28.194 UTC 702fe9 8528] f84f.57ca.3860 **WTP Event Request** from 10.201.234.24:18759

[11/14/13 14:50:28.194 UTC 702fea 8528] f84f.57ca.3860 **WTP Event Response** sent to 10.201.234.24:18759

show log

[11/14/13 14:50:27.869 UTC 702f94 8528] f84f.57ca.3860 **Configuration Status** from 10.201.234.24:18759

[11/14/13 14:50:27.870 UTC 702f95 8528] f84f.57ca.3860 **CAPWAP State: Configure**

[11/14/13 14:50:27.870 UTC 702f96 8528] f84f.57ca.3860 New unsupported Payload 254 in message from AP f84f.57ca.3860, Return SUCCESS

[11/14/13 14:50:27.870 UTC 702f97 8528] f84f.57ca.3860 Decoding new unsupported Payload 254 in message from AP f84f.57ca.3860, Return SUCCESS

[11/14/13 14:50:27.870 UTC 702f98 8528] Invalid channel 11 spacificied for the AP AP2602I-1, slotId = 0

[11/14/13 14:50:27.870 UTC 702f99 8528] Invalid channel 56 spacificied for the AP AP2602I-1, slotId = 1

[11/14/13 14:50:27.870 UTC 702f9a 8528] f84f.57ca.3860 Updating IP info for AP f84f.57ca.3860 -- static 0, 10.201.234.24/255.255.255.224, gtw 10.201.234.2

[11/14/13 14:50:27.870 UTC 702f9b 8528] f84f.57ca.3860 Updating IP 10.201.234.24 ==> 10.201.234.24 for AP f84f.57ca.3860

|

[11/14/13 14:50:27.870 UTC 702fab 8528] f84f.57ca.3860 LWAPP message validation failed for SPAM Vendor Specific Payload(104) in message of len=7 from AP f84f.57ca.3860

[11/14/13 14:50:27.870 UTC 702fac 8528] f84f.57ca.3860 Failed to validate vendor specific message element

[11/14/13 14:50:27.871 UTC 702fad 8528] f84f.57ca.3860 **Setting MTU to 1485**

[11/14/13 14:50:27.871 UTC 702fae 8528] f84f.57ca.3860 Platform not Supported, exiting Load Balancer function

[11/14/13 14:50:27.871 UTC 702faf 8528] load balancer rc=4 for AP 10.201.234.24, IIF ID:0x00d2a98000000796

[11/14/13 14:50:27.871 UTC 702fb0 8528] opaque data size 0 with capwap interface create f84f.57ca.3860

[11/14/13 14:50:27.871 UTC 702fb1 8528] spiCapwapParams-> data_tunnel.opaque_data.opaque_data_len: 0

[11/14/13 14:50:27.871 UTC 702fb2 8528] f84f.57ca.3860 Data Tunnel Create timer started for 240 seconds timeout

[11/14/13 14:50:27.871 UTC 702fb3 8528] f84f.57ca.3860 **Data Tunnel created - tunnel type NON_CRYPTO**, load balancer support Not supported, tunnel mtu 1449, anc_sw_id 0, anc_asic_id 0, res_sw_id 0, res_asic_id 0
anc_wp_iif_id 0x0000000000000000, res_wp_iif_id 0x0000000000000000

[11/14/13 14:50:27.871 UTC 702fb4 8528] f84f.57ca.3860 Not ready to send Config Status Response to AP 10.201.234.24 as SPI ACK is not received

[11/14/13 14:50:27.871 UTC 702fb5 8528] f84f.57ca.3860 AP f84f.57ca.3860 associated. Last AP failure was due to Configuration changes,reason: controller reboot command

[11/14/13 14:50:27.871 UTC 30e6 260] [CAPWAP]: CAPWAP data tunnel create message.

[11/14/13 14:50:27.871 UTC 30e7 260] [CAPWAP]: capwap_data_tunnel_create called

[11/14/13 14:50:27.871 UTC 30e8 260] [CAPWAP]: Data tunnel id = 0xd2a98000000796

[11/14/13 14:50:27.871 UTC 30e9 260] [CAPWAP]: Tunnel Entry not found for AP (10.201.234.24, 18759)

[11/14/13 14:50:27.873 UTC 30ea 260] [CAPWAP]: CAPWAP IDB init complete

[11/14/13 14:50:27.882 UTC 30eb 260] [CAPWAP]: capwap_interface_status_update: tunnel 0xd2a98000000796 status 0

[11/14/13 14:50:27.882 UTC 30ec 260] [CAPWAP]: csb pd flag 0 opaque_data_len 0 attr opaque_data 0x00000000

[11/14/13 14:50:27.882 UTC 30ed 260] [CAPWAP]: Send capwap_data_tunnel_status_update 0 Slot-Unit 1 Unit 1 for iif_id 0xd2a98000000796 to WCM.

[11/14/13 14:50:27.882 UTC 30ee 260] [CAPWAP]: (capwap_process_fed_results) CAPWAP FED result (0) for IIF ID: 0xd2a98000000796

[11/14/13 14:50:27.882 UTC 702fb6 8528

Received CAPWAP Tunnel SPI update opaque size 0

[11/14/13 14:50:27.882 UTC 702fb7 8528] opaque data len 0 with capwap server update

[11/14/13 14:50:27.883 UTC 702fb8 8528] f84f.57ca.3860 SPI ACK : Capwap Data Tunnel create successful for iifid:0x00d2a98000000796 AP:10.201.234.24

[11/14/13 14:50:27.883 UTC 702fb9 8528]

Received CAPWAP interface update opaque len 0

[11/14/13 14:50:27.883 UTC 702fba 8528] **SPI IifId ACK: Capwap Data Tunnel Created Successfully for IifId: 0x00d2a98000000796 AP: 10.201.234.24**

[11/14/13 14:50:27.883 UTC 702fbb 8528] f84f.57ca.3860 **OK to send Config Status Response to AP** 10.201.234.24

[11/14/13 14:50:27.888 UTC 30ef 260] [CAPWAP]: Notify PM (done).

[11/14/13 14:50:27.888 UTC 30f0 260] [CAPWAP]: SNMP Register: Cal HWIDB 32f44570

[11/14/13 14:50:27.888 UTC 30f1 260] [CAPWAP]: capwap_port_hashitem added: slot 1 slotunit 24 vlan 1104

[11/14/13 14:50:27.888 UTC 30f2 260] [CAPWAP]: 7c69.f604.9460 is AP's mac addr

[11/14/13 14:50:27.932 UTC 702fbc 8528] Sending multicast payload to ap AP2602I-1, mcast_mode 0, mcast group 0.0.0.0

[11/14/13 14:50:27.933 UTC 702fbd 8528] f84f.57ca.3860 Config status response sent to 10.201.234.24:18759

[11/14/13 14:50:27.933 UTC 702fbe 8528] f84f.57ca.3860 Configuration Status Response sent to 10:201:234:24

[11/14/13 14:50:27.933 UTC 702fbf 8528] f84f.57ca.3860 Configuration update request for Band Select Cfg sent to 10.201.234.24:18759

[11/14/13 14:50:27.933 UTC 702fc0 8528] f84f.57ca.3860 Configuration update request for HaConfig message sent to 10.201.234.24:18759

[11/14/13 14:50:27.934 UTC 702fc1 8528] f84f.57ca.3860 Configuration update request for AP NGWC Qos sent to 10.201.234.24:18759

[11/14/13 14:50:28.121 UTC 702fc2 8528] f84f.57ca.3860 Change State Event Request from 10.201.234.24:18759

[11/14/13 14:50:28.122 UTC 702fc3 8528] f84f.57ca.3860 Received LWAPP Up event for AP f84f.57ca.3860 slot 0!

[11/14/13 14:50:28.122 UTC 702fc4 8528] f84f.57ca.3860 Radio state change for slot: 0 state: 2 cause: 0 detail cause: 0

[11/14/13 14:50:28.122 UTC 702fc5 8528] f84f.57ca.3860 Change State Event Response sent to 10.201.234.24:18759

[11/14/13 14:50:28.122 UTC 702fc6 8528] f84f.57ca.3860 CAPWAP State: Run

[11/14/13 14:50:28.122 UTC 702fc7 8528] f84f.57ca.3860 Sending the remaining config to AP 10.201.234.24:18759

[11/14/13 14:50:28.122 UTC 702fc8 8528] f84f.57ca.3860 AP Going to RUN 10.201.234.24: ConcurrentJoins: 0

[11/14/13 14:50:28.122 UTC 702fc9 8528] f84f.57ca.3860 **Configuration update request** for Init VAP-DATA for slot 1 sent to 10.201.234.24:18759

[11/14/13 14:50:28.122 UTC 702fca 8528] f84f.57ca.3860 Configuration update request for configuring association limit params sent to 10.201.234.24:18759

[11/14/13 14:50:28.122 UTC 702fcb 8528] f84f.57ca.3860 Configuration update request for Band Select Cfg sent to 10.201.234.24:18759

[11/14/13 14:50:28.122 UTC 702fcc 8528] f84f.57ca.3860 Configuration update request for HaConfig message sent to 10.201.234.24:18759

[11/14/13 14:50:28.123 UTC 702fcd 8528] CAPWAP: No update, will insert f84f.57ca.3860

[11/14/13 14:50:28.123 UTC 702fce 8528] capwap opaque data f84f.57ca.3860 length = 0

[11/14/13 14:50:28.124 UTC 702fcf 8528] CAPWAP HA insert f84f.57ca.3860

[11/14/13 14:50:28.124 UTC 702fd0 8528] CAPWAP HA insert f84f.57ca.3860

[11/14/13 14:50:28.124 UTC 702fd1 8528] f84f.57ca.3860 Configuration update request for PHY payload sent to 10:201:234:24

[11/14/13 14:50:28.126 UTC 702fd2 8528] f84f.57ca.3860 **Configuration Update Response** from 10.201.234.24:18759

[11/14/13 14:50:28.126 UTC 702fd3 8528] f84f.57ca.3860 Configuration update request for RrmInterferenceCtrl payload sent to 10:201:234:24

[11/14/13 14:50:28.126 UTC 702fd4 8528] f84f.57ca.3860 Configuration update request for RrmNeighbourCtrl payload sent to 10.201.234.24

[11/14/13 14:50:28.126 UTC 702fd5 8528] f84f.57ca.3860 Configuration update request for RrmReceiveCtrl payload sent to 10:201:234:24

[11/14/13 14:50:28.126 UTC 702fd6 8528] f84f.57ca.3860 Configuration update request for CcxRmMeas payload sent to 10.201.234.24

[11/14/13 14:50:28.132 UTC 702fd7 8528] f84f.57ca.3860 Change State Event Request from 10.201.234.24:18759

[11/14/13 14:50:28.132 UTC 702fd8 8528] f84f.57ca.3860 Radio state change for slot: 1 state: 2 cause: 0 detail cause: 0

[11/14/13 14:50:28.132 UTC 702fd9 8528] f84f.57ca.3860 Change State Event Response sent to 10.201.234.24:18759

[11/14/13 14:50:28.132 UTC 702fda 8528] f84f.57ca.3860 CAPWAP State: Run

[11/14/13 14:50:28.132 UTC 702fdb 8528] f84f.57ca.3860 Sending the remaining config to AP 10.201.234.24:18759

[11/14/13 14:50:28.133 UTC 702fdc 8528] f84f.57ca.3860 Configuration update request for qos pm payload payload sent to 10.201.234.24:18759

[11/14/13 14:50:28.133 UTC 702fdd 8528] f84f.57ca.3860 Received LWAPP Up event for AP f84f.57ca.3860 slot 1!

[11/14/13 14:50:28.133 UTC 702fde 8528] f84f.57ca.3860 Configuration update request for PHY payload sent to 10:201:234:24

[11/14/13 14:50:28.133 UTC 702fdf 8528] f84f.57ca.3860 Configuration update request for RrmInterferenceCtrl payload sent to 10:201:234:24

[11/14/13 14:50:28.133 UTC 702fe0 8528] f84f.57ca.3860 Configuration update request for RrmNeighbourCtrl payload sent to 10.201.234.24

[11/14/13 14:50:28.134 UTC 702fe1 8528] f84f.57ca.3860 Configuration update request for RrmReceiveCtrl payload sent to 10:201:234:24

[11/14/13 14:50:28.134 UTC 702fe2 8528] f84f.57ca.3860 Configuration update request for CcxRmMeas payload sent to 10.201.234.24

[11/14/13 14:50:28.188 UTC 702fe3 8528] f84f.57ca.3860 Configuration Update Response from 10.201.234.24:18759

[11/14/13 14:50:28.188 UTC 702fe4 8528] f84f.57ca.3860 Change State Event Request from 10.201.234.24:18759

[11/14/13 14:50:28.188 UTC 702fe5 8528] f84f.57ca.3860 Change State Event Response sent to 10.201.234.24:18759

[11/14/13 14:50:28.188 UTC 702fe6 8528] f84f.57ca.3860 CAPWAP State: Run

[11/14/13 14:50:28.188 UTC 702fe7 8528] f84f.57ca.3860 Sending the remaining config to AP 10.201.234.24:18759

[11/14/13 14:50:28.194 UTC 702fe8 8528] f84f.57ca.3860 Configuration Update Response from 10.201.234.24:18759

[11/14/13 14:50:28.194 UTC 702fe9 8528] f84f.57ca.3860 **WTP Event Request** from 10.201.234.24:18759

[11/14/13 14:50:28.194 UTC 702fea 8528] f84f.57ca.3860 **WTP Event Response** sent to 10.201.234.24:18759

Проблема 4: управляющему домен не соответствуют.

Страна радио #show настроена

[11/14/13 14:50:27.869 UTC 702f94 8528] f84f.57ca.3860 **Configuration Status** from 10.201.234.24:18759

[11/14/13 14:50:27.870 UTC 702f95 8528] f84f.57ca.3860 **CAPWAP State: Configure**

[11/14/13 14:50:27.870 UTC 702f96 8528] f84f.57ca.3860 New unsupported Payload 254 in message from AP f84f.57ca.3860, Return SUCCESS

[11/14/13 14:50:27.870 UTC 702f97 8528] f84f.57ca.3860 Decoding new unsupported Payload 254 in message from AP f84f.57ca.3860, Return SUCCESS

[11/14/13 14:50:27.870 UTC 702f98 8528] Invalid channel 11 spacificied for the AP AP2602I-1, slotId = 0

[11/14/13 14:50:27.870 UTC 702f99 8528] Invalid channel 56 spacificied for the AP AP2602I-1, slotId = 1

[11/14/13 14:50:27.870 UTC 702f9a 8528] f84f.57ca.3860 Updating IP info for AP f84f.57ca.3860 -- static 0, 10.201.234.24/255.255.255.224, gtw 10.201.234.2

[11/14/13 14:50:27.870 UTC 702f9b 8528] f84f.57ca.3860 Updating IP 10.201.234.24 ==> 10.201.234.24 for AP f84f.57ca.3860

|

[11/14/13 14:50:27.870 UTC 702fab 8528] f84f.57ca.3860 LWAPP message validation failed for SPAM Vendor Specific Payload(104) in message of len=7 from AP f84f.57ca.3860

[11/14/13 14:50:27.870 UTC 702fac 8528] f84f.57ca.3860 Failed to validate vendor specific message element

[11/14/13 14:50:27.871 UTC 702fad 8528] f84f.57ca.3860 **Setting MTU to 1485**

[11/14/13 14:50:27.871 UTC 702fae 8528] f84f.57ca.3860 Platform not Supported, exiting Load Balancer function

[11/14/13 14:50:27.871 UTC 702faf 8528] load balancer rc=4 for AP 10.201.234.24, IIF ID:0x00d2a98000000796

[11/14/13 14:50:27.871 UTC 702fb0 8528] opaque data size 0 with capwap interface create f84f.57ca.3860

[11/14/13 14:50:27.871 UTC 702fb1 8528] spiCapwapParams-> data_tunnel.opaque_data.opaque_data_len: 0

[11/14/13 14:50:27.871 UTC 702fb2 8528] f84f.57ca.3860 Data Tunnel Create timer started for 240 seconds timeout

[11/14/13 14:50:27.871 UTC 702fb3 8528] f84f.57ca.3860 **Data Tunnel created - tunnel type NON_CRYPTO**, load balancer support Not supported, tunnel mtu 1449, anc_sw_id 0, anc_asic_id 0, res_sw_id 0, res_asic_id 0 anc_wp_iif_id 0x0000000000000000, res_wp_iif_id 0x0000000000000000

[11/14/13 14:50:27.871 UTC 702fb4 8528] f84f.57ca.3860 Not ready to send Config Status Response to AP 10.201.234.24 as SPI ACK is not received

[11/14/13 14:50:27.871 UTC 702fb5 8528] f84f.57ca.3860 AP f84f.57ca.3860 associated. Last AP failure was due to Configuration changes,reason: controller reboot command

[11/14/13 14:50:27.871 UTC 30e6 260] [CAPWAP]: CAPWAP data tunnel create message.

[11/14/13 14:50:27.871 UTC 30e7 260] [CAPWAP]: capwap_data_tunnel_create called

[11/14/13 14:50:27.871 UTC 30e8 260] [CAPWAP]: Data tunnel id = 0xd2a98000000796

[11/14/13 14:50:27.871 UTC 30e9 260] [CAPWAP]: Tunnel Entry not found for AP (10.201.234.24, 18759)

[11/14/13 14:50:27.873 UTC 30ea 260] [CAPWAP]: CAPWAP IDB init complete

[11/14/13 14:50:27.882 UTC 30eb 260] [CAPWAP]: capwap_interface_status_update: tunnel 0xd2a98000000796 status 0

[11/14/13 14:50:27.882 UTC 30ec 260] [CAPWAP]: csb pd flag 0 opaque_data_len 0 attr opaque_data 0x00000000

[11/14/13 14:50:27.882 UTC 30ed 260] [CAPWAP]: Send capwap_data_tunnel_status_update 0 Slot-Unit 1 Unit 1 for iif_id 0xd2a98000000796 to WCM.

[11/14/13 14:50:27.882 UTC 30ee 260] [CAPWAP]: (capwap_process_fed_results) CAPWAP FED result (0) for IIF ID: 0xd2a98000000796

[11/14/13 14:50:27.882 UTC 702fb6 8528

Received CAPWAP Tunnel SPI update opaque size 0

[11/14/13 14:50:27.882 UTC 702fb7 8528] opaque data len 0 with capwap server update

[11/14/13 14:50:27.883 UTC 702fb8 8528] f84f.57ca.3860 SPI ACK : Capwap Data Tunnel create successful for iifid:0x00d2a98000000796 AP:10.201.234.24

[11/14/13 14:50:27.883 UTC 702fb9 8528]

Received CAPWAP interface update opaque len 0

[11/14/13 14:50:27.883 UTC 702fba 8528] **SPI IifId ACK: Capwap Data Tunnel Created Successfully for IifId: 0x00d2a98000000796 AP: 10.201.234.24**

[11/14/13 14:50:27.883 UTC 702fbb 8528] f84f.57ca.3860 **OK to send Config Status Response to AP** 10.201.234.24

[11/14/13 14:50:27.888 UTC 30ef 260] [CAPWAP]: Notify PM (done).

[11/14/13 14:50:27.888 UTC 30f0 260] [CAPWAP]: SNMP Register: Cal HWIDB 32f44570

[11/14/13 14:50:27.888 UTC 30f1 260] [CAPWAP]: capwap_port_hashitem added: slot 1 slotunit 24 vlan 1104

[11/14/13 14:50:27.888 UTC 30f2 260] [CAPWAP]: 7c69.f604.9460 is AP's mac addr

[11/14/13 14:50:27.932 UTC 702fbc 8528] Sending multicast payload to ap AP2602I-1, mcast_mode 0, mcast group 0.0.0.0

[11/14/13 14:50:27.933 UTC 702fbd 8528] f84f.57ca.3860 Config status response sent to 10.201.234.24:18759

[11/14/13 14:50:27.933 UTC 702fbe 8528] f84f.57ca.3860 Configuration Status Response sent to 10:201:234:24

[11/14/13 14:50:27.933 UTC 702fbf 8528] f84f.57ca.3860 Configuration update request for Band Select Cfg sent to 10.201.234.24:18759

[11/14/13 14:50:27.933 UTC 702fc0 8528] f84f.57ca.3860 Configuration update request for HaConfig message sent to 10.201.234.24:18759

[11/14/13 14:50:27.934 UTC 702fc1 8528] f84f.57ca.3860 Configuration update request for AP NGWC Qos sent to 10.201.234.24:18759

[11/14/13 14:50:28.121 UTC 702fc2 8528] f84f.57ca.3860 Change State Event Request from 10.201.234.24:18759

[11/14/13 14:50:28.122 UTC 702fc3 8528] f84f.57ca.3860 Received LWAPP Up event for AP f84f.57ca.3860 slot 0!

[11/14/13 14:50:28.122 UTC 702fc4 8528] f84f.57ca.3860 Radio state change for slot: 0 state: 2 cause: 0 detail cause: 0

[11/14/13 14:50:28.122 UTC 702fc5 8528] f84f.57ca.3860 Change State Event Response sent to 10.201.234.24:18759

[11/14/13 14:50:28.122 UTC 702fc6 8528] f84f.57ca.3860 CAPWAP State: Run

[11/14/13 14:50:28.122 UTC 702fc7 8528] f84f.57ca.3860 Sending the remaining config to AP 10.201.234.24:18759

[11/14/13 14:50:28.122 UTC 702fc8 8528] f84f.57ca.3860 AP Going to RUN 10.201.234.24: ConcurrentJoins: 0

[11/14/13 14:50:28.122 UTC 702fc9 8528] f84f.57ca.3860 **Configuration update request** for Init VAP-DATA for slot 1 sent to 10.201.234.24:18759

[11/14/13 14:50:28.122 UTC 702fca 8528] f84f.57ca.3860 Configuration update request for configuring association limit params sent to 10.201.234.24:18759

[11/14/13 14:50:28.122 UTC 702fcb 8528] f84f.57ca.3860 Configuration update request for Band Select Cfg sent to 10.201.234.24:18759

[11/14/13 14:50:28.122 UTC 702fcc 8528] f84f.57ca.3860 Configuration update request for HaConfig message sent to 10.201.234.24:18759

[11/14/13 14:50:28.123 UTC 702fcd 8528] CAPWAP: No update, will insert f84f.57ca.3860

[11/14/13 14:50:28.123 UTC 702fce 8528] capwap opaque data f84f.57ca.3860 length = 0

[11/14/13 14:50:28.124 UTC 702fcf 8528] CAPWAP HA insert f84f.57ca.3860

[11/14/13 14:50:28.124 UTC 702fd0 8528] CAPWAP HA insert f84f.57ca.3860

[11/14/13 14:50:28.124 UTC 702fd1 8528] f84f.57ca.3860 Configuration update request for PHY payload sent to 10:201:234:24

[11/14/13 14:50:28.126 UTC 702fd2 8528] f84f.57ca.3860 **Configuration Update Response** from 10.201.234.24:18759

[11/14/13 14:50:28.126 UTC 702fd3 8528] f84f.57ca.3860 Configuration update request for RrmInterferenceCtrl payload sent to 10:201:234:24

[11/14/13 14:50:28.126 UTC 702fd4 8528] f84f.57ca.3860 Configuration update request for RrmNeighbourCtrl payload sent to 10.201.234.24

[11/14/13 14:50:28.126 UTC 702fd5 8528] f84f.57ca.3860 Configuration update request for RrmReceiveCtrl payload sent to 10:201:234:24

[11/14/13 14:50:28.126 UTC 702fd6 8528] f84f.57ca.3860 Configuration update request for CcxRmMeas payload sent to 10.201.234.24

[11/14/13 14:50:28.132 UTC 702fd7 8528] f84f.57ca.3860 Change State Event Request from 10.201.234.24:18759

[11/14/13 14:50:28.132 UTC 702fd8 8528] f84f.57ca.3860 Radio state change for slot: 1 state: 2 cause: 0 detail cause: 0

[11/14/13 14:50:28.132 UTC 702fd9 8528] f84f.57ca.3860 Change State Event Response sent to 10.201.234.24:18759

[11/14/13 14:50:28.132 UTC 702fda 8528] f84f.57ca.3860 CAPWAP State: Run

[11/14/13 14:50:28.132 UTC 702fdb 8528] f84f.57ca.3860 Sending the remaining config to AP 10.201.234.24:18759

[11/14/13 14:50:28.133 UTC 702fdc 8528] f84f.57ca.3860 Configuration update request for qos pm payload payload sent to 10.201.234.24:18759

[11/14/13 14:50:28.133 UTC 702fdd 8528] f84f.57ca.3860 Received LWAPP Up event for AP f84f.57ca.3860 slot 1!

[11/14/13 14:50:28.133 UTC 702fde 8528] f84f.57ca.3860 Configuration update request for PHY payload sent to 10:201:234:24

[11/14/13 14:50:28.133 UTC 702fdf 8528] f84f.57ca.3860 Configuration update request for RrmInterferenceCtrl payload sent to 10:201:234:24

[11/14/13 14:50:28.133 UTC 702fe0 8528] f84f.57ca.3860 Configuration update request for RrmNeighbourCtrl payload sent to 10.201.234.24

[11/14/13 14:50:28.134 UTC 702fe1 8528] f84f.57ca.3860 Configuration update request for RrmReceiveCtrl payload sent to 10:201:234:24

[11/14/13 14:50:28.134 UTC 702fe2 8528] f84f.57ca.3860 Configuration update request for CcxRmMeas payload sent to 10.201.234.24

[11/14/13 14:50:28.188 UTC 702fe3 8528] f84f.57ca.3860 Configuration Update Response from 10.201.234.24:18759

[11/14/13 14:50:28.188 UTC 702fe4 8528] f84f.57ca.3860 Change State Event Request from 10.201.234.24:18759

[11/14/13 14:50:28.188 UTC 702fe5 8528] f84f.57ca.3860 Change State Event Response sent to 10.201.234.24:18759

[11/14/13 14:50:28.188 UTC 702fe6 8528] f84f.57ca.3860 CAPWAP State: Run

[11/14/13 14:50:28.188 UTC 702fe7 8528] f84f.57ca.3860 Sending the remaining config to AP 10.201.234.24:18759

[11/14/13 14:50:28.194 UTC 702fe8 8528] f84f.57ca.3860 Configuration Update Response from 10.201.234.24:18759

[11/14/13 14:50:28.194 UTC 702fe9 8528] f84f.57ca.3860 **WTP Event Request** from 10.201.234.24:18759

[11/14/13 14:50:28.194 UTC 702fea 8528] f84f.57ca.3860 **WTP Event Response** sent to 10.201.234.24:18759

show log

[11/14/13 14:50:27.869 UTC 702f94 8528] f84f.57ca.3860 **Configuration Status** from 10.201.234.24:18759

[11/14/13 14:50:27.870 UTC 702f95 8528] f84f.57ca.3860 **CAPWAP State: Configure**

[11/14/13 14:50:27.870 UTC 702f96 8528] f84f.57ca.3860 New unsupported Payload 254 in message from AP f84f.57ca.3860, Return SUCCESS

[11/14/13 14:50:27.870 UTC 702f97 8528] f84f.57ca.3860 Decoding new unsupported Payload 254 in message from AP f84f.57ca.3860, Return SUCCESS

[11/14/13 14:50:27.870 UTC 702f98 8528] Invalid channel 11 spacificied for the AP AP2602I-1, slotId = 0

[11/14/13 14:50:27.870 UTC 702f99 8528] Invalid channel 56 spacificied for the AP AP2602I-1, slotId = 1

[11/14/13 14:50:27.870 UTC 702f9a 8528] f84f.57ca.3860 Updating IP info for AP f84f.57ca.3860 -- static 0, 10.201.234.24/255.255.255.224, gtw 10.201.234.2

[11/14/13 14:50:27.870 UTC 702f9b 8528] f84f.57ca.3860 Updating IP 10.201.234.24 ==> 10.201.234.24 for AP f84f.57ca.3860

[11/14/13 14:50:27.870 UTC 702fab 8528] f84f.57ca.3860 LWAPP message validation failed for SPAM Vendor Specific Payload(104) in message of len=7 from AP

f84f.57ca.3860

[11/14/13 14:50:27.870 UTC 702fac 8528] f84f.57ca.3860 Failed to validate vendor specific message element

[11/14/13 14:50:27.871 UTC 702fad 8528] f84f.57ca.3860 **Setting MTU to 1485**

[11/14/13 14:50:27.871 UTC 702fae 8528] f84f.57ca.3860 Platform not Supported, exiting Load Balancer function

[11/14/13 14:50:27.871 UTC 702faf 8528] load balancer rc=4 for AP 10.201.234.24, IIF ID:0x00d2a98000000796

[11/14/13 14:50:27.871 UTC 702fb0 8528] opaque data size 0 with capwap interface create f84f.57ca.3860

[11/14/13 14:50:27.871 UTC 702fb1 8528] spiCapwapParams-> data_tunnel.opaque_data.opaque_data_len: 0

[11/14/13 14:50:27.871 UTC 702fb2 8528] f84f.57ca.3860 Data Tunnel Create timer started for 240 seconds timeout

[11/14/13 14:50:27.871 UTC 702fb3 8528] f84f.57ca.3860 **Data Tunnel created - tunnel type NON_CRYPTO**, load balancer support Not supported, tunnel mtu 1449,

anc_sw_id 0, anc_asic_id 0, res_sw_id 0, res_asic_id 0

anc_wp_iif_id 0x0000000000000000, res_wp_iif_id 0x0000000000000000

[11/14/13 14:50:27.871 UTC 702fb4 8528] f84f.57ca.3860 Not ready to send Config Status Response to AP 10.201.234.24 as SPI ACK is not received

[11/14/13 14:50:27.871 UTC 702fb5 8528] f84f.57ca.3860 AP f84f.57ca.3860 associated. Last AP failure was due to Configuration changes,reason: controller reboot command

[11/14/13 14:50:27.871 UTC 30e6 260] [CAPWAP]: CAPWAP data tunnel create message.

[11/14/13 14:50:27.871 UTC 30e7 260] [CAPWAP]: capwap_data_tunnel_create called

[11/14/13 14:50:27.871 UTC 30e8 260] [CAPWAP]: Data tunnel id = 0xd2a98000000796

[11/14/13 14:50:27.871 UTC 30e9 260] [CAPWAP]: Tunnel Entry not found for AP (10.201.234.24, 18759)

[11/14/13 14:50:27.873 UTC 30ea 260] [CAPWAP]: CAPWAP IDB init complete

[11/14/13 14:50:27.882 UTC 30eb 260] [CAPWAP]: capwap_interface_status_update: tunnel 0xd2a98000000796 status 0

[11/14/13 14:50:27.882 UTC 30ec 260] [CAPWAP]: csb pd flag 0 opaque_data_len 0 attr opaque_data 0x00000000

[11/14/13 14:50:27.882 UTC 30ed 260] [CAPWAP]: Send capwap_data_tunnel_status_update 0 Slot-Unit 1 Unit 1 for iif_id 0xd2a98000000796 to WCM.

[11/14/13 14:50:27.882 UTC 30ee 260] [CAPWAP]: (capwap_process_fed_results) CAPWAP FED result (0) for IIF ID: 0xd2a98000000796

[11/14/13 14:50:27.882 UTC 702fb6 8528

Received CAPWAP Tunnel SPI update opaque size 0

[11/14/13 14:50:27.882 UTC 702fb7 8528] opaque data len 0 with capwap server update

[11/14/13 14:50:27.883 UTC 702fb8 8528] f84f.57ca.3860 SPI ACK : Capwap Data Tunnel create successful for iifid:0x00d2a98000000796 AP:10.201.234.24

[11/14/13 14:50:27.883 UTC 702fb9 8528]

Received CAPWAP interface update opaque len 0

[11/14/13 14:50:27.883 UTC 702fba 8528] **SPI IifId ACK: Capwap Data Tunnel Created Successfully for IifId: 0x00d2a98000000796 AP: 10.201.234.24**

[11/14/13 14:50:27.883 UTC 702fbb 8528] f84f.57ca.3860 **OK to send Config Status Response to AP 10.201.234.24**

[11/14/13 14:50:27.888 UTC 30ef 260] [CAPWAP]: Notify PM (done).

[11/14/13 14:50:27.888 UTC 30f0 260] [CAPWAP]: SNMP Register: Ca1 HWIDB 32f44570

[11/14/13 14:50:27.888 UTC 30f1 260] [CAPWAP]: capwap_port_hashitem added: slot 1 slotunit 24 vlan 1104

[11/14/13 14:50:27.888 UTC 30f2 260] [CAPWAP]: 7c69.f604.9460 is AP's mac addr

[11/14/13 14:50:27.932 UTC 702fbc 8528] Sending multicast payload to ap AP2602I-1, mcast_mode 0, mcast group 0.0.0.0

[11/14/13 14:50:27.933 UTC 702fbd 8528] f84f.57ca.3860 Config status response sent to 10.201.234.24:18759

[11/14/13 14:50:27.933 UTC 702fbe 8528] f84f.57ca.3860 Configuration Status Response sent to 10:201:234:24

[11/14/13 14:50:27.933 UTC 702fbf 8528] f84f.57ca.3860 Configuration update request for Band Select Cfg sent to 10.201.234.24:18759

[11/14/13 14:50:27.933 UTC 702fc0 8528] f84f.57ca.3860 Configuration update request for HaConfig message sent to 10.201.234.24:18759

[11/14/13 14:50:27.934 UTC 702fc1 8528] f84f.57ca.3860 Configuration update request for AP NGWC Qos sent to 10.201.234.24:18759

[11/14/13 14:50:28.121 UTC 702fc2 8528] f84f.57ca.3860 Change State Event Request from 10.201.234.24:18759

[11/14/13 14:50:28.122 UTC 702fc3 8528] f84f.57ca.3860 Received LWAPP Up event for AP f84f.57ca.3860 slot 0!

[11/14/13 14:50:28.122 UTC 702fc4 8528] f84f.57ca.3860 Radio state change for slot: 0 state: 2 cause: 0 detail cause: 0

[11/14/13 14:50:28.122 UTC 702fc5 8528] f84f.57ca.3860 Change State Event Response sent to 10.201.234.24:18759

[11/14/13 14:50:28.122 UTC 702fc6 8528] f84f.57ca.3860 CAPWAP State: Run

[11/14/13 14:50:28.122 UTC 702fc7 8528] f84f.57ca.3860 Sending the remaining config to AP 10.201.234.24:18759

[11/14/13 14:50:28.122 UTC 702fc8 8528] f84f.57ca.3860 AP Going to RUN 10.201.234.24: ConcurrentJoins: 0

[11/14/13 14:50:28.122 UTC 702fc9 8528] f84f.57ca.3860 **Configuration update request** for Init VAP-DATA for slot 1 sent to 10.201.234.24:18759

[11/14/13 14:50:28.122 UTC 702fca 8528] f84f.57ca.3860 Configuration update request for configuring association limit params sent to 10.201.234.24:18759

[11/14/13 14:50:28.122 UTC 702fcb 8528] f84f.57ca.3860 Configuration update request for Band Select Cfg sent to 10.201.234.24:18759

[11/14/13 14:50:28.122 UTC 702fcc 8528] f84f.57ca.3860 Configuration update request for HaConfig message sent to 10.201.234.24:18759

[11/14/13 14:50:28.123 UTC 702fcd 8528] CAPWAP: No update, will insert f84f.57ca.3860

[11/14/13 14:50:28.123 UTC 702fce 8528] capwap opaque data f84f.57ca.3860 length = 0

[11/14/13 14:50:28.124 UTC 702fcf 8528] CAPWAP HA insert f84f.57ca.3860

[11/14/13 14:50:28.124 UTC 702fd0 8528] CAPWAP HA insert f84f.57ca.3860

[11/14/13 14:50:28.124 UTC 702fd1 8528] f84f.57ca.3860 Configuration update request for PHY payload sent to 10:201:234:24

[11/14/13 14:50:28.126 UTC 702fd2 8528] f84f.57ca.3860 **Configuration Update Response** from 10.201.234.24:18759

[11/14/13 14:50:28.126 UTC 702fd3 8528] f84f.57ca.3860 Configuration update request for RrmInterferenceCtrl payload sent to 10:201:234:24

[11/14/13 14:50:28.126 UTC 702fd4 8528] f84f.57ca.3860 Configuration update request for RrmNeighbourCtrl payload sent to 10.201.234.24

[11/14/13 14:50:28.126 UTC 702fd5 8528] f84f.57ca.3860 Configuration update request for RrmReceiveCtrl payload sent to 10:201:234:24

[11/14/13 14:50:28.126 UTC 702fd6 8528] f84f.57ca.3860 Configuration update request for CcxRmMeas payload sent to 10.201.234.24

[11/14/13 14:50:28.132 UTC 702fd7 8528] f84f.57ca.3860 Change State Event Request from 10.201.234.24:18759

[11/14/13 14:50:28.132 UTC 702fd8 8528] f84f.57ca.3860 Radio state change for slot: 1 state: 2 cause: 0 detail cause: 0

[11/14/13 14:50:28.132 UTC 702fd9 8528] f84f.57ca.3860 Change State Event Response sent to 10.201.234.24:18759

[11/14/13 14:50:28.132 UTC 702fda 8528] f84f.57ca.3860 CAPWAP State: Run

[11/14/13 14:50:28.132 UTC 702fdb 8528] f84f.57ca.3860 Sending the remaining config to AP 10.201.234.24:18759

[11/14/13 14:50:28.133 UTC 702fdc 8528] f84f.57ca.3860 Configuration update request for qos pm payload payload sent to 10.201.234.24:18759

[11/14/13 14:50:28.133 UTC 702fdd 8528] f84f.57ca.3860 Received LWAPP Up event for AP f84f.57ca.3860 slot 1!

[11/14/13 14:50:28.133 UTC 702fde 8528] f84f.57ca.3860 Configuration update request for PHY payload sent to 10:201:234:24

[11/14/13 14:50:28.133 UTC 702fdf 8528] f84f.57ca.3860 Configuration update request for RrmInterferenceCtrl payload sent to 10:201:234:24

[11/14/13 14:50:28.133 UTC 702fe0 8528] f84f.57ca.3860 Configuration update

request for RrmNeighbourCtrl payload sent to 10.201.234.24

[11/14/13 14:50:28.134 UTC 702fe1 8528] f84f.57ca.3860 Configuration update request for RrmReceiveCtrl payload sent to 10:201:234:24

[11/14/13 14:50:28.134 UTC 702fe2 8528] f84f.57ca.3860 Configuration update request for CcxRmMeas payload sent to 10.201.234.24

[11/14/13 14:50:28.188 UTC 702fe3 8528] f84f.57ca.3860 Configuration Update Response from 10.201.234.24:18759

[11/14/13 14:50:28.188 UTC 702fe4 8528] f84f.57ca.3860 Change State Event Request from 10.201.234.24:18759

[11/14/13 14:50:28.188 UTC 702fe5 8528] f84f.57ca.3860 Change State Event Response sent to 10.201.234.24:18759

[11/14/13 14:50:28.188 UTC 702fe6 8528] f84f.57ca.3860 CAPWAP State: Run

[11/14/13 14:50:28.188 UTC 702fe7 8528] f84f.57ca.3860 Sending the remaining config to AP 10.201.234.24:18759

[11/14/13 14:50:28.194 UTC 702fe8 8528] f84f.57ca.3860 Configuration Update Response from 10.201.234.24:18759

[11/14/13 14:50:28.194 UTC 702fe9 8528] f84f.57ca.3860 **WTP Event Request** from 10.201.234.24:18759

[11/14/13 14:50:28.194 UTC 702fea 8528] f84f.57ca.3860 **WTP Event Response** sent to 10.201.234.24:18759

Проблема 5: беспроводной контроллер мобильности не определен.

Сводка мобильности радио #show

[11/14/13 14:50:27.869 UTC 702f94 8528] f84f.57ca.3860 **Configuration Status** from 10.201.234.24:18759

[11/14/13 14:50:27.870 UTC 702f95 8528] f84f.57ca.3860 **CAPWAP State: Configure**

[11/14/13 14:50:27.870 UTC 702f96 8528] f84f.57ca.3860 New unsupported Payload 254 in message from AP f84f.57ca.3860, Return SUCCESS

[11/14/13 14:50:27.870 UTC 702f97 8528] f84f.57ca.3860 Decoding new unsupported Payload 254 in message from AP f84f.57ca.3860, Return SUCCESS

[11/14/13 14:50:27.870 UTC 702f98 8528] Invalid channel 11 spacificied for the AP AP2602I-1, slotId = 0

[11/14/13 14:50:27.870 UTC 702f99 8528] Invalid channel 56 spacificied for the AP AP2602I-1, slotId = 1

[11/14/13 14:50:27.870 UTC 702f9a 8528] f84f.57ca.3860 Updating IP info for AP f84f.57ca.3860 -- static 0, 10.201.234.24/255.255.255.224, gtw 10.201.234.2

[11/14/13 14:50:27.870 UTC 702f9b 8528] f84f.57ca.3860 Updating IP 10.201.234.24 ==> 10.201.234.24 for AP f84f.57ca.3860

|

[11/14/13 14:50:27.870 UTC 702fab 8528] f84f.57ca.3860 LWAPP message validation failed for SPAM Vendor Specific Payload(104) in message of len=7 from AP

f84f.57ca.3860

[11/14/13 14:50:27.870 UTC 702fac 8528] f84f.57ca.3860 Failed to validate vendor specific message element

[11/14/13 14:50:27.871 UTC 702fad 8528] f84f.57ca.3860 **Setting MTU to 1485**

[11/14/13 14:50:27.871 UTC 702fae 8528] f84f.57ca.3860 Platform not Supported, exiting Load Balancer function

[11/14/13 14:50:27.871 UTC 702faf 8528] load balancer rc=4 for AP 10.201.234.24, IIF ID:0x00d2a98000000796

[11/14/13 14:50:27.871 UTC 702fb0 8528] opaque data size 0 with capwap interface create f84f.57ca.3860

[11/14/13 14:50:27.871 UTC 702fb1 8528] spiCapwapParams-> data_tunnel.opaque_data.opaque_data_len: 0

[11/14/13 14:50:27.871 UTC 702fb2 8528] f84f.57ca.3860 Data Tunnel Create timer started for 240 seconds timeout

[11/14/13 14:50:27.871 UTC 702fb3 8528] f84f.57ca.3860 **Data Tunnel created - tunnel type NON_CRYPTO**, load balancer support Not supported, tunnel mtu 1449,

anc_sw_id 0, anc_asic_id 0, res_sw_id 0, res_asic_id 0

anc_wp_iif_id 0x0000000000000000, res_wp_iif_id 0x0000000000000000

[11/14/13 14:50:27.871 UTC 702fb4 8528] f84f.57ca.3860 Not ready to send Config Status Response to AP 10.201.234.24 as SPI ACK is not received

[11/14/13 14:50:27.871 UTC 702fb5 8528] f84f.57ca.3860 AP f84f.57ca.3860 associated. Last AP failure was due to Configuration changes,reason: controller reboot command

[11/14/13 14:50:27.871 UTC 30e6 260] [CAPWAP]: CAPWAP data tunnel create message.

[11/14/13 14:50:27.871 UTC 30e7 260] [CAPWAP]: capwap_data_tunnel_create called

[11/14/13 14:50:27.871 UTC 30e8 260] [CAPWAP]: Data tunnel id = 0xd2a98000000796

[11/14/13 14:50:27.871 UTC 30e9 260] [CAPWAP]: Tunnel Entry not found for AP (10.201.234.24, 18759)

[11/14/13 14:50:27.873 UTC 30ea 260] [CAPWAP]: CAPWAP IDB init complete

[11/14/13 14:50:27.882 UTC 30eb 260] [CAPWAP]: capwap_interface_status_update: tunnel 0xd2a98000000796 status 0

[11/14/13 14:50:27.882 UTC 30ec 260] [CAPWAP]: csb pd flag 0 opaque_data_len 0 attr opaque_data 0x00000000

[11/14/13 14:50:27.882 UTC 30ed 260] [CAPWAP]: Send capwap_data_tunnel_status_update 0 Slot-Unit 1 Unit 1 for iif_id 0xd2a98000000796 to WCM.

[11/14/13 14:50:27.882 UTC 30ee 260] [CAPWAP]: (capwap_process_fed_results) CAPWAP FED result (0) for IIF ID: 0xd2a98000000796

[11/14/13 14:50:27.882 UTC 702fb6 8528

Received CAPWAP Tunnel SPI update opaque size 0

[11/14/13 14:50:27.882 UTC 702fb7 8528] opaque data len 0 with capwap server update

[11/14/13 14:50:27.883 UTC 702fb8 8528] f84f.57ca.3860 SPI ACK : Capwap Data Tunnel create successful for iifid:0x00d2a98000000796 AP:10.201.234.24

[11/14/13 14:50:27.883 UTC 702fb9 8528]

Received CAPWAP interface update opaque len 0

[11/14/13 14:50:27.883 UTC 702fba 8528] **SPI IifId ACK: Capwap Data Tunnel Created Successfully for IifId: 0x00d2a98000000796 AP: 10.201.234.24**

[11/14/13 14:50:27.883 UTC 702fbb 8528] f84f.57ca.3860 **OK to send Config Status Response to AP 10.201.234.24**

[11/14/13 14:50:27.888 UTC 30ef 260] [CAPWAP]: Notify PM (done).

[11/14/13 14:50:27.888 UTC 30f0 260] [CAPWAP]: SNMP Register: Cal HWIDB 32f44570

[11/14/13 14:50:27.888 UTC 30f1 260] [CAPWAP]: capwap_port_hashitem added: slot 1 slotunit 24 vlan 1104

[11/14/13 14:50:27.888 UTC 30f2 260] [CAPWAP]: 7c69.f604.9460 is AP's mac addr

[11/14/13 14:50:27.932 UTC 702fbc 8528] Sending multicast payload to ap AP2602I-1, mcast_mode 0, mcast group 0.0.0.0

[11/14/13 14:50:27.933 UTC 702fbd 8528] f84f.57ca.3860 Config status response sent to 10.201.234.24:18759

[11/14/13 14:50:27.933 UTC 702fbe 8528] f84f.57ca.3860 Configuration Status Response sent to 10:201:234:24

[11/14/13 14:50:27.933 UTC 702fbf 8528] f84f.57ca.3860 Configuration update request for Band Select Cfg sent to 10.201.234.24:18759

[11/14/13 14:50:27.933 UTC 702fc0 8528] f84f.57ca.3860 Configuration update request for HaConfig message sent to 10.201.234.24:18759

[11/14/13 14:50:27.934 UTC 702fc1 8528] f84f.57ca.3860 Configuration update request for AP NGWC Qos sent to 10.201.234.24:18759

[11/14/13 14:50:28.121 UTC 702fc2 8528] f84f.57ca.3860 Change State Event Request from 10.201.234.24:18759

[11/14/13 14:50:28.122 UTC 702fc3 8528] f84f.57ca.3860 Received LWAPP Up event for AP f84f.57ca.3860 slot 0!

[11/14/13 14:50:28.122 UTC 702fc4 8528] f84f.57ca.3860 Radio state change for slot: 0 state: 2 cause: 0 detail cause: 0

[11/14/13 14:50:28.122 UTC 702fc5 8528] f84f.57ca.3860 Change State Event Response sent to 10.201.234.24:18759

[11/14/13 14:50:28.122 UTC 702fc6 8528] f84f.57ca.3860 CAPWAP State: Run

[11/14/13 14:50:28.122 UTC 702fc7 8528] f84f.57ca.3860 Sending the remaining config to AP 10.201.234.24:18759

[11/14/13 14:50:28.122 UTC 702fc8 8528] f84f.57ca.3860 AP Going to RUN 10.201.234.24: ConcurrentJoins: 0

[11/14/13 14:50:28.122 UTC 702fc9 8528] f84f.57ca.3860 **Configuration update request** for Init VAP-DATA for slot 1 sent to 10.201.234.24:18759

[11/14/13 14:50:28.122 UTC 702fca 8528] f84f.57ca.3860 Configuration update request for configuring association limit params sent to 10.201.234.24:18759

[11/14/13 14:50:28.122 UTC 702fcb 8528] f84f.57ca.3860 Configuration update request for Band Select Cfg sent to 10.201.234.24:18759

[11/14/13 14:50:28.122 UTC 702fcc 8528] f84f.57ca.3860 Configuration update request for HaConfig message sent to 10.201.234.24:18759

[11/14/13 14:50:28.123 UTC 702fcd 8528] CAPWAP: No update, will insert f84f.57ca.3860

[11/14/13 14:50:28.123 UTC 702fce 8528] capwap opaque data f84f.57ca.3860 length = 0

[11/14/13 14:50:28.124 UTC 702fcf 8528] CAPWAP HA insert f84f.57ca.3860

[11/14/13 14:50:28.124 UTC 702fd0 8528] CAPWAP HA insert f84f.57ca.3860

[11/14/13 14:50:28.124 UTC 702fd1 8528] f84f.57ca.3860 Configuration update request for PHY payload sent to 10:201:234:24

[11/14/13 14:50:28.126 UTC 702fd2 8528] f84f.57ca.3860 **Configuration Update Response** from 10.201.234.24:18759

[11/14/13 14:50:28.126 UTC 702fd3 8528] f84f.57ca.3860 Configuration update request for RrmInterferenceCtrl payload sent to 10:201:234:24

[11/14/13 14:50:28.126 UTC 702fd4 8528] f84f.57ca.3860 Configuration update request for RrmNeighbourCtrl payload sent to 10.201.234.24

[11/14/13 14:50:28.126 UTC 702fd5 8528] f84f.57ca.3860 Configuration update request for RrmReceiveCtrl payload sent to 10:201:234:24

[11/14/13 14:50:28.126 UTC 702fd6 8528] f84f.57ca.3860 Configuration update request for CcxRmMeas payload sent to 10.201.234.24

[11/14/13 14:50:28.132 UTC 702fd7 8528] f84f.57ca.3860 Change State Event Request from 10.201.234.24:18759

[11/14/13 14:50:28.132 UTC 702fd8 8528] f84f.57ca.3860 Radio state change for slot: 1 state: 2 cause: 0 detail cause: 0

[11/14/13 14:50:28.132 UTC 702fd9 8528] f84f.57ca.3860 Change State Event Response sent to 10.201.234.24:18759

[11/14/13 14:50:28.132 UTC 702fda 8528] f84f.57ca.3860 CAPWAP State: Run

[11/14/13 14:50:28.132 UTC 702fdb 8528] f84f.57ca.3860 Sending the remaining config to AP 10.201.234.24:18759

[11/14/13 14:50:28.133 UTC 702fdc 8528] f84f.57ca.3860 Configuration update request for qos pm payload payload sent to 10.201.234.24:18759

[11/14/13 14:50:28.133 UTC 702fdd 8528] f84f.57ca.3860 Received LWAPP Up event for AP f84f.57ca.3860 slot 1!

[11/14/13 14:50:28.133 UTC 702fde 8528] f84f.57ca.3860 Configuration update request for PHY payload sent to 10:201:234:24

[11/14/13 14:50:28.133 UTC 702fdf 8528] f84f.57ca.3860 Configuration update request for RrmInterferenceCtrl payload sent to 10:201:234:24

[11/14/13 14:50:28.133 UTC 702fe0 8528] f84f.57ca.3860 Configuration update

request for RrmNeighbourCtrl payload sent to 10.201.234.24

[11/14/13 14:50:28.134 UTC 702fe1 8528] f84f.57ca.3860 Configuration update request for RrmReceiveCtrl payload sent to 10:201:234:24

[11/14/13 14:50:28.134 UTC 702fe2 8528] f84f.57ca.3860 Configuration update request for CcxRmMeas payload sent to 10.201.234.24

[11/14/13 14:50:28.188 UTC 702fe3 8528] f84f.57ca.3860 Configuration Update Response from 10.201.234.24:18759

[11/14/13 14:50:28.188 UTC 702fe4 8528] f84f.57ca.3860 Change State Event Request from 10.201.234.24:18759

[11/14/13 14:50:28.188 UTC 702fe5 8528] f84f.57ca.3860 Change State Event Response sent to 10.201.234.24:18759

[11/14/13 14:50:28.188 UTC 702fe6 8528] f84f.57ca.3860 CAPWAP State: Run

[11/14/13 14:50:28.188 UTC 702fe7 8528] f84f.57ca.3860 Sending the remaining config to AP 10.201.234.24:18759

[11/14/13 14:50:28.194 UTC 702fe8 8528] f84f.57ca.3860 Configuration Update Response from 10.201.234.24:18759

[11/14/13 14:50:28.194 UTC 702fe9 8528] f84f.57ca.3860 **WTP Event Request** from 10.201.234.24:18759

[11/14/13 14:50:28.194 UTC 702fea 8528] f84f.57ca.3860 **WTP Event Response** sent to 10.201.234.24:18759

show log

[11/14/13 14:50:27.869 UTC 702f94 8528] f84f.57ca.3860 **Configuration Status** from 10.201.234.24:18759

[11/14/13 14:50:27.870 UTC 702f95 8528] f84f.57ca.3860 **CAPWAP State: Configure**

[11/14/13 14:50:27.870 UTC 702f96 8528] f84f.57ca.3860 New unsupported Payload 254 in message from AP f84f.57ca.3860, Return SUCCESS

[11/14/13 14:50:27.870 UTC 702f97 8528] f84f.57ca.3860 Decoding new unsupported Payload 254 in message from AP f84f.57ca.3860, Return SUCCESS

[11/14/13 14:50:27.870 UTC 702f98 8528] Invalid channel 11 spacificied for the AP AP2602I-1, slotId = 0

[11/14/13 14:50:27.870 UTC 702f99 8528] Invalid channel 56 spacificied for the AP AP2602I-1, slotId = 1

[11/14/13 14:50:27.870 UTC 702f9a 8528] f84f.57ca.3860 Updating IP info for AP f84f.57ca.3860 -- static 0, 10.201.234.24/255.255.255.224, gtw 10.201.234.2

[11/14/13 14:50:27.870 UTC 702f9b 8528] f84f.57ca.3860 Updating IP 10.201.234.24 ==> 10.201.234.24 for AP f84f.57ca.3860

|

[11/14/13 14:50:27.870 UTC 702fab 8528] f84f.57ca.3860 LWAPP message validation failed for SPAM Vendor Specific Payload(104) in message of len=7 from AP f84f.57ca.3860

[11/14/13 14:50:27.870 UTC 702fac 8528] f84f.57ca.3860 Failed to validate vendor specific message element

[11/14/13 14:50:27.871 UTC 702fad 8528] f84f.57ca.3860 **Setting MTU to 1485**

[11/14/13 14:50:27.871 UTC 702fae 8528] f84f.57ca.3860 Platform not Supported, exiting Load Balancer function

[11/14/13 14:50:27.871 UTC 702faf 8528] load balancer rc=4 for AP 10.201.234.24, IIF ID:0x00d2a98000000796

[11/14/13 14:50:27.871 UTC 702fb0 8528] opaque data size 0 with capwap interface create f84f.57ca.3860

[11/14/13 14:50:27.871 UTC 702fb1 8528] spiCapwapParams-> data_tunnel.opaque_data.opaque_data_len: 0

[11/14/13 14:50:27.871 UTC 702fb2 8528] f84f.57ca.3860 Data Tunnel Create timer started for 240 seconds timeout

[11/14/13 14:50:27.871 UTC 702fb3 8528] f84f.57ca.3860 **Data Tunnel created - tunnel type NON_CRYPTO**, load balancer support Not supported, tunnel mtu 1449, anc_sw_id 0, anc_asic_id 0, res_sw_id 0, res_asic_id 0
anc_wp_iif_id 0x0000000000000000, res_wp_iif_id 0x0000000000000000

[11/14/13 14:50:27.871 UTC 702fb4 8528] f84f.57ca.3860 Not ready to send Config Status Response to AP 10.201.234.24 as SPI ACK is not received

[11/14/13 14:50:27.871 UTC 702fb5 8528] f84f.57ca.3860 AP f84f.57ca.3860 associated. Last AP failure was due to Configuration changes,reason: controller reboot command

[11/14/13 14:50:27.871 UTC 30e6 260] [CAPWAP]: CAPWAP data tunnel create message.

[11/14/13 14:50:27.871 UTC 30e7 260] [CAPWAP]: capwap_data_tunnel_create called

[11/14/13 14:50:27.871 UTC 30e8 260] [CAPWAP]: Data tunnel id = 0xd2a98000000796

[11/14/13 14:50:27.871 UTC 30e9 260] [CAPWAP]: Tunnel Entry not found for AP (10.201.234.24, 18759)

[11/14/13 14:50:27.873 UTC 30ea 260] [CAPWAP]: CAPWAP IDB init complete

[11/14/13 14:50:27.882 UTC 30eb 260] [CAPWAP]: capwap_interface_status_update: tunnel 0xd2a98000000796 status 0

[11/14/13 14:50:27.882 UTC 30ec 260] [CAPWAP]: csb pd flag 0 opaque_data_len 0 attr opaque_data 0x00000000

[11/14/13 14:50:27.882 UTC 30ed 260] [CAPWAP]: Send capwap_data_tunnel_status_update 0 Slot-Unit 1 Unit 1 for iif_id 0xd2a98000000796 to WCM.

[11/14/13 14:50:27.882 UTC 30ee 260] [CAPWAP]: (capwap_process_fed_results) CAPWAP FED result (0) for IIF ID: 0xd2a98000000796

[11/14/13 14:50:27.882 UTC 702fb6 8528]
Received CAPWAP Tunnel SPI update opaque size 0

[11/14/13 14:50:27.882 UTC 702fb7 8528] opaque data len 0 with capwap server update

[11/14/13 14:50:27.883 UTC 702fb8 8528] f84f.57ca.3860 SPI ACK : Capwap Data Tunnel create successful for iifid:0x00d2a98000000796 AP:10.201.234.24

[11/14/13 14:50:27.883 UTC 702fb9 8528]

Received CAPWAP interface update opaque len 0

[11/14/13 14:50:27.883 UTC 702fba 8528] **SPI IifId ACK: Capwap Data Tunnel Created Successfully for IifId: 0x00d2a98000000796 AP: 10.201.234.24**

[11/14/13 14:50:27.883 UTC 702fbb 8528] f84f.57ca.3860 **OK to send Config Status Response to AP 10.201.234.24**

[11/14/13 14:50:27.888 UTC 30ef 260] [CAPWAP]: Notify PM (done).

[11/14/13 14:50:27.888 UTC 30f0 260] [CAPWAP]: SNMP Register: Ca1 HWIDB 32f44570

[11/14/13 14:50:27.888 UTC 30f1 260] [CAPWAP]: capwap_port_hashitem added: slot 1 slotunit 24 vlan 1104

[11/14/13 14:50:27.888 UTC 30f2 260] [CAPWAP]: 7c69.f604.9460 is AP's mac addr

[11/14/13 14:50:27.932 UTC 702fbc 8528] Sending multicast payload to ap AP2602I-1, mcast_mode 0, mcast group 0.0.0.0

[11/14/13 14:50:27.933 UTC 702fbd 8528] f84f.57ca.3860 Config status response sent to 10.201.234.24:18759

[11/14/13 14:50:27.933 UTC 702fbe 8528] f84f.57ca.3860 Configuration Status Response sent to 10:201:234:24

[11/14/13 14:50:27.933 UTC 702fbf 8528] f84f.57ca.3860 Configuration update request for Band Select Cfg sent to 10.201.234.24:18759

[11/14/13 14:50:27.933 UTC 702fc0 8528] f84f.57ca.3860 Configuration update request for HaConfig message sent to 10.201.234.24:18759

[11/14/13 14:50:27.934 UTC 702fc1 8528] f84f.57ca.3860 Configuration update request for AP NGWC Qos sent to 10.201.234.24:18759

[11/14/13 14:50:28.121 UTC 702fc2 8528] f84f.57ca.3860 Change State Event Request from 10.201.234.24:18759

[11/14/13 14:50:28.122 UTC 702fc3 8528] f84f.57ca.3860 Received LWAPP Up event for AP f84f.57ca.3860 slot 0!

[11/14/13 14:50:28.122 UTC 702fc4 8528] f84f.57ca.3860 Radio state change for slot: 0 state: 2 cause: 0 detail cause: 0

[11/14/13 14:50:28.122 UTC 702fc5 8528] f84f.57ca.3860 Change State Event Response sent to 10.201.234.24:18759

[11/14/13 14:50:28.122 UTC 702fc6 8528] f84f.57ca.3860 CAPWAP State: Run

[11/14/13 14:50:28.122 UTC 702fc7 8528] f84f.57ca.3860 Sending the remaining config to AP 10.201.234.24:18759

[11/14/13 14:50:28.122 UTC 702fc8 8528] f84f.57ca.3860 AP Going to RUN 10.201.234.24: ConcurrentJoins: 0

[11/14/13 14:50:28.122 UTC 702fc9 8528] f84f.57ca.3860 **Configuration update request** for Init VAP-DATA for slot 1 sent to 10.201.234.24:18759

[11/14/13 14:50:28.122 UTC 702fca 8528] f84f.57ca.3860 Configuration update request for configuring association limit params sent to 10.201.234.24:18759

[11/14/13 14:50:28.122 UTC 702fcb 8528] f84f.57ca.3860 Configuration update

request for Band Select Cfg sent to 10.201.234.24:18759

[11/14/13 14:50:28.122 UTC 702fcc 8528] f84f.57ca.3860 Configuration update request for HaConfig message sent to 10.201.234.24:18759

[11/14/13 14:50:28.123 UTC 702fcd 8528] CAPWAP: No update, will insert f84f.57ca.3860

[11/14/13 14:50:28.123 UTC 702fce 8528] capwap opaque data f84f.57ca.3860 length = 0

[11/14/13 14:50:28.124 UTC 702fcf 8528] CAPWAP HA insert f84f.57ca.3860

[11/14/13 14:50:28.124 UTC 702fd0 8528] CAPWAP HA insert f84f.57ca.3860

[11/14/13 14:50:28.124 UTC 702fd1 8528] f84f.57ca.3860 Configuration update request for PHY payload sent to 10:201:234:24

[11/14/13 14:50:28.126 UTC 702fd2 8528] f84f.57ca.3860 **Configuration Update Response** from 10.201.234.24:18759

[11/14/13 14:50:28.126 UTC 702fd3 8528] f84f.57ca.3860 Configuration update request for RrmInterferenceCtrl payload sent to 10:201:234:24

[11/14/13 14:50:28.126 UTC 702fd4 8528] f84f.57ca.3860 Configuration update request for RrmNeighbourCtrl payload sent to 10.201.234.24

[11/14/13 14:50:28.126 UTC 702fd5 8528] f84f.57ca.3860 Configuration update request for RrmReceiveCtrl payload sent to 10:201:234:24

[11/14/13 14:50:28.126 UTC 702fd6 8528] f84f.57ca.3860 Configuration update request for CcxRmMeas payload sent to 10.201.234.24

[11/14/13 14:50:28.132 UTC 702fd7 8528] f84f.57ca.3860 Change State Event Request from 10.201.234.24:18759

[11/14/13 14:50:28.132 UTC 702fd8 8528] f84f.57ca.3860 Radio state change for slot: 1 state: 2 cause: 0 detail cause: 0

[11/14/13 14:50:28.132 UTC 702fd9 8528] f84f.57ca.3860 Change State Event Response sent to 10.201.234.24:18759

[11/14/13 14:50:28.132 UTC 702fda 8528] f84f.57ca.3860 CAPWAP State: Run

[11/14/13 14:50:28.132 UTC 702fdb 8528] f84f.57ca.3860 Sending the remaining config to AP 10.201.234.24:18759

[11/14/13 14:50:28.133 UTC 702fdc 8528] f84f.57ca.3860 Configuration update request for qos pm payload payload sent to 10.201.234.24:18759

[11/14/13 14:50:28.133 UTC 702fdd 8528] f84f.57ca.3860 Received LWAPP Up event for AP f84f.57ca.3860 slot 1!

[11/14/13 14:50:28.133 UTC 702fde 8528] f84f.57ca.3860 Configuration update request for PHY payload sent to 10:201:234:24

[11/14/13 14:50:28.133 UTC 702fdf 8528] f84f.57ca.3860 Configuration update request for RrmInterferenceCtrl payload sent to 10:201:234:24

[11/14/13 14:50:28.133 UTC 702fe0 8528] f84f.57ca.3860 Configuration update request for RrmNeighbourCtrl payload sent to 10.201.234.24

[11/14/13 14:50:28.134 UTC 702fe1 8528] f84f.57ca.3860 Configuration update request for RrmReceiveCtrl payload sent to 10:201:234:24

[11/14/13 14:50:28.134 UTC 702fe2 8528] f84f.57ca.3860 Configuration update request for CcxRmMeas payload sent to 10.201.234.24

[11/14/13 14:50:28.188 UTC 702fe3 8528] f84f.57ca.3860 Configuration Update Response from 10.201.234.24:18759

[11/14/13 14:50:28.188 UTC 702fe4 8528] f84f.57ca.3860 Change State Event Request from 10.201.234.24:18759

[11/14/13 14:50:28.188 UTC 702fe5 8528] f84f.57ca.3860 Change State Event Response sent to 10.201.234.24:18759

[11/14/13 14:50:28.188 UTC 702fe6 8528] f84f.57ca.3860 CAPWAP State: Run

[11/14/13 14:50:28.188 UTC 702fe7 8528] f84f.57ca.3860 Sending the remaining config to AP 10.201.234.24:18759

[11/14/13 14:50:28.194 UTC 702fe8 8528] f84f.57ca.3860 Configuration Update Response from 10.201.234.24:18759

[11/14/13 14:50:28.194 UTC 702fe9 8528] f84f.57ca.3860 **WTP Event Request** from 10.201.234.24:18759

[11/14/13 14:50:28.194 UTC 702fea 8528] f84f.57ca.3860 **WTP Event Response** sent to 10.201.234.24:18759

Проблема 6: AP имеет код сетки на нем.

[11/14/13 14:50:27.869 UTC 702f94 8528] f84f.57ca.3860 **Configuration Status** from 10.201.234.24:18759

[11/14/13 14:50:27.870 UTC 702f95 8528] f84f.57ca.3860 **CAPWAP State: Configure**

[11/14/13 14:50:27.870 UTC 702f96 8528] f84f.57ca.3860 New unsupported Payload 254 in message from AP f84f.57ca.3860, Return SUCCESS

[11/14/13 14:50:27.870 UTC 702f97 8528] f84f.57ca.3860 Decoding new unsupported Payload 254 in message from AP f84f.57ca.3860, Return SUCCESS

[11/14/13 14:50:27.870 UTC 702f98 8528] Invalid channel 11 spacificied for the AP AP2602I-1, slotId = 0

[11/14/13 14:50:27.870 UTC 702f99 8528] Invalid channel 56 spacificied for the AP AP2602I-1, slotId = 1

[11/14/13 14:50:27.870 UTC 702f9a 8528] f84f.57ca.3860 Updating IP info for AP f84f.57ca.3860 -- static 0, 10.201.234.24/255.255.255.224, gw 10.201.234.2

[11/14/13 14:50:27.870 UTC 702f9b 8528] f84f.57ca.3860 Updating IP 10.201.234.24 ==> 10.201.234.24 for AP f84f.57ca.3860

|

[11/14/13 14:50:27.870 UTC 702fab 8528] f84f.57ca.3860 LWAPP message validation failed for SPAM Vendor Specific Payload(104) in message of len=7 from AP f84f.57ca.3860

[11/14/13 14:50:27.870 UTC 702fac 8528] f84f.57ca.3860 Failed to validate vendor specific message element

[11/14/13 14:50:27.871 UTC 702fad 8528] f84f.57ca.3860 **Setting MTU to 1485**

[11/14/13 14:50:27.871 UTC 702fae 8528] f84f.57ca.3860 Platform not Supported, exiting Load Balancer function

[11/14/13 14:50:27.871 UTC 702faf 8528] load balancer rc=4 for AP 10.201.234.24, IIF ID:0x00d2a98000000796

[11/14/13 14:50:27.871 UTC 702fb0 8528] opaque data size 0 with capwap interface create f84f.57ca.3860

[11/14/13 14:50:27.871 UTC 702fb1 8528] spiCapwapParams-> data_tunnel.opaque_data.opaque_data_len: 0

[11/14/13 14:50:27.871 UTC 702fb2 8528] f84f.57ca.3860 Data Tunnel Create timer started for 240 seconds timeout

[11/14/13 14:50:27.871 UTC 702fb3 8528] f84f.57ca.3860 **Data Tunnel created - tunnel type NON_CRYPTO**, load balancer support Not supported, tunnel mtu 1449, anc_sw_id 0, anc_asic_id 0, res_sw_id 0, res_asic_id 0 anc_wp_iif_id 0x0000000000000000, res_wp_iif_id 0x0000000000000000

[11/14/13 14:50:27.871 UTC 702fb4 8528] f84f.57ca.3860 Not ready to send Config Status Response to AP 10.201.234.24 as SPI ACK is not received

[11/14/13 14:50:27.871 UTC 702fb5 8528] f84f.57ca.3860 AP f84f.57ca.3860 associated. Last AP failure was due to Configuration changes,reason: controller reboot command

[11/14/13 14:50:27.871 UTC 30e6 260] [CAPWAP]: CAPWAP data tunnel create message.

[11/14/13 14:50:27.871 UTC 30e7 260] [CAPWAP]: capwap_data_tunnel_create called

[11/14/13 14:50:27.871 UTC 30e8 260] [CAPWAP]: Data tunnel id = 0xd2a98000000796

[11/14/13 14:50:27.871 UTC 30e9 260] [CAPWAP]: Tunnel Entry not found for AP (10.201.234.24, 18759)

[11/14/13 14:50:27.873 UTC 30ea 260] [CAPWAP]: CAPWAP IDB init complete

[11/14/13 14:50:27.882 UTC 30eb 260] [CAPWAP]: capwap_interface_status_update: tunnel 0xd2a98000000796 status 0

[11/14/13 14:50:27.882 UTC 30ec 260] [CAPWAP]: csb pd flag 0 opaque_data_len 0 attr opaque_data 0x00000000

[11/14/13 14:50:27.882 UTC 30ed 260] [CAPWAP]: Send capwap_data_tunnel_status_update 0 Slot-Unit 1 Unit 1 for iif_id 0xd2a98000000796 to WCM.

[11/14/13 14:50:27.882 UTC 30ee 260] [CAPWAP]: (capwap_process_fed_results) CAPWAP FED result (0) for IIF ID: 0xd2a98000000796

[11/14/13 14:50:27.882 UTC 702fb6 8528] Received CAPWAP Tunnel SPI update opaque size 0

[11/14/13 14:50:27.882 UTC 702fb7 8528] opaque data len 0 with capwap server update

[11/14/13 14:50:27.883 UTC 702fb8 8528] f84f.57ca.3860 SPI ACK : Capwap Data Tunnel create successful for iifid:0x00d2a98000000796 AP:10.201.234.24

[11/14/13 14:50:27.883 UTC 702fb9 8528] Received CAPWAP interface update opaque len 0

[11/14/13 14:50:27.883 UTC 702fba 8528] **SPI IifId ACK: Capwap Data Tunnel Created Successfully for IifId: 0x00d2a98000000796 AP: 10.201.234.24**

[11/14/13 14:50:27.883 UTC 702fbb 8528] f84f.57ca.3860 **OK to send Config Status Response to AP 10.201.234.24**

[11/14/13 14:50:27.888 UTC 30ef 260] [CAPWAP]: Notify PM (done).

[11/14/13 14:50:27.888 UTC 30f0 260] [CAPWAP]: SNMP Register: Cal HWIDB 32f44570

[11/14/13 14:50:27.888 UTC 30f1 260] [CAPWAP]: capwap_port_hashitem added: slot 1 slotunit 24 vlan 1104

[11/14/13 14:50:27.888 UTC 30f2 260] [CAPWAP]: 7c69.f604.9460 is AP's mac addr

[11/14/13 14:50:27.932 UTC 702fbc 8528] Sending multicast payload to ap AP2602I-1, mcast_mode 0, mcast group 0.0.0.0

[11/14/13 14:50:27.933 UTC 702fbd 8528] f84f.57ca.3860 Config status response sent to 10.201.234.24:18759

[11/14/13 14:50:27.933 UTC 702fbe 8528] f84f.57ca.3860 Configuration Status Response sent to 10:201:234:24

[11/14/13 14:50:27.933 UTC 702fbf 8528] f84f.57ca.3860 Configuration update request for Band Select Cfg sent to 10.201.234.24:18759

[11/14/13 14:50:27.933 UTC 702fc0 8528] f84f.57ca.3860 Configuration update request for HaConfig message sent to 10.201.234.24:18759

[11/14/13 14:50:27.934 UTC 702fc1 8528] f84f.57ca.3860 Configuration update request for AP NGWC Qos sent to 10.201.234.24:18759

[11/14/13 14:50:28.121 UTC 702fc2 8528] f84f.57ca.3860 Change State Event Request from 10.201.234.24:18759

[11/14/13 14:50:28.122 UTC 702fc3 8528] f84f.57ca.3860 Received LWAPP Up event for AP f84f.57ca.3860 slot 0!

[11/14/13 14:50:28.122 UTC 702fc4 8528] f84f.57ca.3860 Radio state change for slot: 0 state: 2 cause: 0 detail cause: 0

[11/14/13 14:50:28.122 UTC 702fc5 8528] f84f.57ca.3860 Change State Event Response sent to 10.201.234.24:18759

[11/14/13 14:50:28.122 UTC 702fc6 8528] f84f.57ca.3860 CAPWAP State: Run

[11/14/13 14:50:28.122 UTC 702fc7 8528] f84f.57ca.3860 Sending the remaining config to AP 10.201.234.24:18759

[11/14/13 14:50:28.122 UTC 702fc8 8528] f84f.57ca.3860 AP Going to RUN 10.201.234.24: ConcurrentJoins: 0

[11/14/13 14:50:28.122 UTC 702fc9 8528] f84f.57ca.3860 **Configuration update request** for Init VAP-DATA for slot 1 sent to 10.201.234.24:18759

[11/14/13 14:50:28.122 UTC 702fca 8528] f84f.57ca.3860 Configuration update request for configuring association limit params sent to 10.201.234.24:18759

[11/14/13 14:50:28.122 UTC 702fcb 8528] f84f.57ca.3860 Configuration update request for Band Select Cfg sent to 10.201.234.24:18759

[11/14/13 14:50:28.122 UTC 702fcc 8528] f84f.57ca.3860 Configuration update

request for HaConfig message sent to 10.201.234.24:18759

[11/14/13 14:50:28.123 UTC 702fcd 8528] CAPWAP: No update, will insert f84f.57ca.3860

[11/14/13 14:50:28.123 UTC 702fce 8528] capwap opaque data f84f.57ca.3860 length = 0

[11/14/13 14:50:28.124 UTC 702fcf 8528] CAPWAP HA insert f84f.57ca.3860

[11/14/13 14:50:28.124 UTC 702fd0 8528] CAPWAP HA insert f84f.57ca.3860

[11/14/13 14:50:28.124 UTC 702fd1 8528] f84f.57ca.3860 Configuration update request for PHY payload sent to 10:201:234:24

[11/14/13 14:50:28.126 UTC 702fd2 8528] f84f.57ca.3860 **Configuration Update Response** from 10.201.234.24:18759

[11/14/13 14:50:28.126 UTC 702fd3 8528] f84f.57ca.3860 Configuration update request for RrmInterferenceCtrl payload sent to 10:201:234:24

[11/14/13 14:50:28.126 UTC 702fd4 8528] f84f.57ca.3860 Configuration update request for RrmNeighbourCtrl payload sent to 10.201.234.24

[11/14/13 14:50:28.126 UTC 702fd5 8528] f84f.57ca.3860 Configuration update request for RrmReceiveCtrl payload sent to 10:201:234:24

[11/14/13 14:50:28.126 UTC 702fd6 8528] f84f.57ca.3860 Configuration update request for CcxRmMeas payload sent to 10.201.234.24

[11/14/13 14:50:28.132 UTC 702fd7 8528] f84f.57ca.3860 Change State Event Request from 10.201.234.24:18759

[11/14/13 14:50:28.132 UTC 702fd8 8528] f84f.57ca.3860 Radio state change for slot: 1 state: 2 cause: 0 detail cause: 0

[11/14/13 14:50:28.132 UTC 702fd9 8528] f84f.57ca.3860 Change State Event Response sent to 10.201.234.24:18759

[11/14/13 14:50:28.132 UTC 702fda 8528] f84f.57ca.3860 CAPWAP State: Run

[11/14/13 14:50:28.132 UTC 702fdb 8528] f84f.57ca.3860 Sending the remaining config to AP 10.201.234.24:18759

[11/14/13 14:50:28.133 UTC 702fdc 8528] f84f.57ca.3860 Configuration update request for qos pm payload payload sent to 10.201.234.24:18759

[11/14/13 14:50:28.133 UTC 702fdd 8528] f84f.57ca.3860 Received LWAPP Up event for AP f84f.57ca.3860 slot 1!

[11/14/13 14:50:28.133 UTC 702fde 8528] f84f.57ca.3860 Configuration update request for PHY payload sent to 10:201:234:24

[11/14/13 14:50:28.133 UTC 702fdf 8528] f84f.57ca.3860 Configuration update request for RrmInterferenceCtrl payload sent to 10:201:234:24

[11/14/13 14:50:28.133 UTC 702fe0 8528] f84f.57ca.3860 Configuration update request for RrmNeighbourCtrl payload sent to 10.201.234.24

[11/14/13 14:50:28.134 UTC 702fe1 8528] f84f.57ca.3860 Configuration update request for RrmReceiveCtrl payload sent to 10:201:234:24

[11/14/13 14:50:28.134 UTC 702fe2 8528] f84f.57ca.3860 Configuration update request for CcxRmMeas payload sent to 10.201.234.24

[11/14/13 14:50:28.188 UTC 702fe3 8528] f84f.57ca.3860 Configuration Update Response from 10.201.234.24:18759

[11/14/13 14:50:28.188 UTC 702fe4 8528] f84f.57ca.3860 Change State Event Request from 10.201.234.24:18759

[11/14/13 14:50:28.188 UTC 702fe5 8528] f84f.57ca.3860 Change State Event Response sent to 10.201.234.24:18759

[11/14/13 14:50:28.188 UTC 702fe6 8528] f84f.57ca.3860 CAPWAP State: Run

[11/14/13 14:50:28.188 UTC 702fe7 8528] f84f.57ca.3860 Sending the remaining config to AP 10.201.234.24:18759

[11/14/13 14:50:28.194 UTC 702fe8 8528] f84f.57ca.3860 Configuration Update Response from 10.201.234.24:18759

[11/14/13 14:50:28.194 UTC 702fe9 8528] f84f.57ca.3860 **WTP Event Request** from 10.201.234.24:18759

[11/14/13 14:50:28.194 UTC 702fea 8528] f84f.57ca.3860 **WTP Event Response** sent to 10.201.234.24:18759

Это сообщение довольно общего назначения и не показательно из текущей проблемы. Для диагностирования далее, пока дополнительная регистрация не добавлена для этого конкретного вопроса, исследуйте console log AP.

Проблема 7: AP3700 связан с Catalyst Коммутатор серии 3850, который выполняется 3.3.0SE.

show log

[11/14/13 14:50:27.869 UTC 702f94 8528] f84f.57ca.3860 **Configuration Status** from 10.201.234.24:18759

[11/14/13 14:50:27.870 UTC 702f95 8528] f84f.57ca.3860 **CAPWAP State: Configure**

[11/14/13 14:50:27.870 UTC 702f96 8528] f84f.57ca.3860 New unsupported Payload 254 in message from AP f84f.57ca.3860, Return SUCCESS

[11/14/13 14:50:27.870 UTC 702f97 8528] f84f.57ca.3860 Decoding new unsupported Payload 254 in message from AP f84f.57ca.3860, Return SUCCESS

[11/14/13 14:50:27.870 UTC 702f98 8528] Invalid channel 11 spacificed for the AP AP2602I-1, slotId = 0

[11/14/13 14:50:27.870 UTC 702f99 8528] Invalid channel 56 spacificed for the AP AP2602I-1, slotId = 1

[11/14/13 14:50:27.870 UTC 702f9a 8528] f84f.57ca.3860 Updating IP info for AP f84f.57ca.3860 -- static 0, 10.201.234.24/255.255.255.224, gtw 10.201.234.2

[11/14/13 14:50:27.870 UTC 702f9b 8528] f84f.57ca.3860 Updating IP 10.201.234.24 ==> 10.201.234.24 for AP f84f.57ca.3860

|

[11/14/13 14:50:27.870 UTC 702fab 8528] f84f.57ca.3860 LWAPP message validation failed for SPAM Vendor Specific Payload(104) in message of len=7 from AP f84f.57ca.3860

[11/14/13 14:50:27.870 UTC 702fac 8528] f84f.57ca.3860 Failed to validate vendor specific message element

[11/14/13 14:50:27.871 UTC 702fad 8528] f84f.57ca.3860 **Setting MTU to 1485**

[11/14/13 14:50:27.871 UTC 702fae 8528] f84f.57ca.3860 Platform not Supported, exiting Load Balancer function

[11/14/13 14:50:27.871 UTC 702faf 8528] load balancer rc=4 for AP 10.201.234.24, IIF ID:0x00d2a98000000796

[11/14/13 14:50:27.871 UTC 702fb0 8528] opaque data size 0 with capwap interface create f84f.57ca.3860

[11/14/13 14:50:27.871 UTC 702fb1 8528] spiCapwapParams-> data_tunnel.opaque_data.opaque_data_len: 0

[11/14/13 14:50:27.871 UTC 702fb2 8528] f84f.57ca.3860 Data Tunnel Create timer started for 240 seconds timeout

[11/14/13 14:50:27.871 UTC 702fb3 8528] f84f.57ca.3860 **Data Tunnel created - tunnel type NON_CRYPTO**, load balancer support Not supported, tunnel mtu 1449,

anc_sw_id 0, anc_asic_id 0, res_sw_id 0, res_asic_id 0

anc_wp_iif_id 0x0000000000000000, res_wp_iif_id 0x0000000000000000

[11/14/13 14:50:27.871 UTC 702fb4 8528] f84f.57ca.3860 Not ready to send Config Status Response to AP 10.201.234.24 as SPI ACK is not received

[11/14/13 14:50:27.871 UTC 702fb5 8528] f84f.57ca.3860 AP f84f.57ca.3860 associated. Last AP failure was due to Configuration changes,reason: controller reboot command

[11/14/13 14:50:27.871 UTC 30e6 260] [CAPWAP]: CAPWAP data tunnel create message.

[11/14/13 14:50:27.871 UTC 30e7 260] [CAPWAP]: capwap_data_tunnel_create called

[11/14/13 14:50:27.871 UTC 30e8 260] [CAPWAP]: Data tunnel id = 0xd2a98000000796

[11/14/13 14:50:27.871 UTC 30e9 260] [CAPWAP]: Tunnel Entry not found for AP (10.201.234.24, 18759)

[11/14/13 14:50:27.873 UTC 30ea 260] [CAPWAP]: CAPWAP IDB init complete

[11/14/13 14:50:27.882 UTC 30eb 260] [CAPWAP]: capwap_interface_status_update: tunnel 0xd2a98000000796 status 0

[11/14/13 14:50:27.882 UTC 30ec 260] [CAPWAP]: csb pd flag 0 opaque_data_len 0 attr opaque_data 0x00000000

[11/14/13 14:50:27.882 UTC 30ed 260] [CAPWAP]: Send capwap_data_tunnel_status_update 0 Slot-Unit 1 Unit 1 for iif_id 0xd2a98000000796 to WCM.

[11/14/13 14:50:27.882 UTC 30ee 260] [CAPWAP]: (capwap_process_fed_results) CAPWAP FED result (0) for IIF ID: 0xd2a98000000796

[11/14/13 14:50:27.882 UTC 702fb6 8528

Received CAPWAP Tunnel SPI update opaque size 0

[11/14/13 14:50:27.882 UTC 702fb7 8528] opaque data len 0 with capwap server update

[11/14/13 14:50:27.883 UTC 702fb8 8528] f84f.57ca.3860 SPI ACK : Capwap Data Tunnel create successful for iifid:0x00d2a98000000796 AP:10.201.234.24

[11/14/13 14:50:27.883 UTC 702fb9 8528]

Received CAPWAP interface update opaque len 0

[11/14/13 14:50:27.883 UTC 702fba 8528] **SPI IifId ACK: Capwap Data Tunnel Created Successfully for IifId: 0x00d2a98000000796 AP: 10.201.234.24**

[11/14/13 14:50:27.883 UTC 702fbb 8528] f84f.57ca.3860 **OK to send Config Status Response to AP 10.201.234.24**

[11/14/13 14:50:27.888 UTC 30ef 260] [CAPWAP]: Notify PM (done).

[11/14/13 14:50:27.888 UTC 30f0 260] [CAPWAP]: SNMP Register: Ca1 HWIDB 32f44570

[11/14/13 14:50:27.888 UTC 30f1 260] [CAPWAP]: capwap_port_hashitem added: slot 1 slotunit 24 vlan 1104

[11/14/13 14:50:27.888 UTC 30f2 260] [CAPWAP]: 7c69.f604.9460 is AP's mac addr

[11/14/13 14:50:27.932 UTC 702fbc 8528] Sending multicast payload to ap AP2602I-1, mcast_mode 0, mcast group 0.0.0.0

[11/14/13 14:50:27.933 UTC 702fbd 8528] f84f.57ca.3860 Config status response sent to 10.201.234.24:18759

[11/14/13 14:50:27.933 UTC 702fbe 8528] f84f.57ca.3860 Configuration Status Response sent to 10:201:234:24

[11/14/13 14:50:27.933 UTC 702fbf 8528] f84f.57ca.3860 Configuration update request for Band Select Cfg sent to 10.201.234.24:18759

[11/14/13 14:50:27.933 UTC 702fc0 8528] f84f.57ca.3860 Configuration update request for HaConfig message sent to 10.201.234.24:18759

[11/14/13 14:50:27.934 UTC 702fc1 8528] f84f.57ca.3860 Configuration update request for AP NGWC Qos sent to 10.201.234.24:18759

[11/14/13 14:50:28.121 UTC 702fc2 8528] f84f.57ca.3860 Change State Event Request from 10.201.234.24:18759

[11/14/13 14:50:28.122 UTC 702fc3 8528] f84f.57ca.3860 Received LWAPP Up event for AP f84f.57ca.3860 slot 0!

[11/14/13 14:50:28.122 UTC 702fc4 8528] f84f.57ca.3860 Radio state change for slot: 0 state: 2 cause: 0 detail cause: 0

[11/14/13 14:50:28.122 UTC 702fc5 8528] f84f.57ca.3860 Change State Event Response sent to 10.201.234.24:18759

[11/14/13 14:50:28.122 UTC 702fc6 8528] f84f.57ca.3860 CAPWAP State: Run

[11/14/13 14:50:28.122 UTC 702fc7 8528] f84f.57ca.3860 Sending the remaining config to AP 10.201.234.24:18759

[11/14/13 14:50:28.122 UTC 702fc8 8528] f84f.57ca.3860 AP Going to RUN 10.201.234.24: ConcurrentJoins: 0

[11/14/13 14:50:28.122 UTC 702fc9 8528] f84f.57ca.3860 **Configuration update request** for Init VAP-DATA for slot 1 sent to 10.201.234.24:18759

[11/14/13 14:50:28.122 UTC 702fca 8528] f84f.57ca.3860 Configuration update

request for configuring association limit params sent to 10.201.234.24:18759

[11/14/13 14:50:28.122 UTC 702fcb 8528] f84f.57ca.3860 Configuration update request for Band Select Cfg sent to 10.201.234.24:18759

[11/14/13 14:50:28.122 UTC 702fcc 8528] f84f.57ca.3860 Configuration update request for HaConfig message sent to 10.201.234.24:18759

[11/14/13 14:50:28.123 UTC 702fcd 8528] CAPWAP: No update, will insert f84f.57ca.3860

[11/14/13 14:50:28.123 UTC 702fce 8528] capwap opaque data f84f.57ca.3860 length = 0

[11/14/13 14:50:28.124 UTC 702fcf 8528] CAPWAP HA insert f84f.57ca.3860

[11/14/13 14:50:28.124 UTC 702fd0 8528] CAPWAP HA insert f84f.57ca.3860

[11/14/13 14:50:28.124 UTC 702fd1 8528] f84f.57ca.3860 Configuration update request for PHY payload sent to 10:201:234:24

[11/14/13 14:50:28.126 UTC 702fd2 8528] f84f.57ca.3860 **Configuration Update Response** from 10.201.234.24:18759

[11/14/13 14:50:28.126 UTC 702fd3 8528] f84f.57ca.3860 Configuration update request for RrmInterferenceCtrl payload sent to 10:201:234:24

[11/14/13 14:50:28.126 UTC 702fd4 8528] f84f.57ca.3860 Configuration update request for RrmNeighbourCtrl payload sent to 10.201.234.24

[11/14/13 14:50:28.126 UTC 702fd5 8528] f84f.57ca.3860 Configuration update request for RrmReceiveCtrl payload sent to 10:201:234:24

[11/14/13 14:50:28.126 UTC 702fd6 8528] f84f.57ca.3860 Configuration update request for CcxRmMeas payload sent to 10.201.234.24

[11/14/13 14:50:28.132 UTC 702fd7 8528] f84f.57ca.3860 Change State Event Request from 10.201.234.24:18759

[11/14/13 14:50:28.132 UTC 702fd8 8528] f84f.57ca.3860 Radio state change for slot: 1 state: 2 cause: 0 detail cause: 0

[11/14/13 14:50:28.132 UTC 702fd9 8528] f84f.57ca.3860 Change State Event Response sent to 10.201.234.24:18759

[11/14/13 14:50:28.132 UTC 702fda 8528] f84f.57ca.3860 CAPWAP State: Run

[11/14/13 14:50:28.132 UTC 702fdb 8528] f84f.57ca.3860 Sending the remaining config to AP 10.201.234.24:18759

[11/14/13 14:50:28.133 UTC 702fdc 8528] f84f.57ca.3860 Configuration update request for qos pm payload payload sent to 10.201.234.24:18759

[11/14/13 14:50:28.133 UTC 702fdd 8528] f84f.57ca.3860 Received LWAPP Up event for AP f84f.57ca.3860 slot 1!

[11/14/13 14:50:28.133 UTC 702fde 8528] f84f.57ca.3860 Configuration update request for PHY payload sent to 10:201:234:24

[11/14/13 14:50:28.133 UTC 702fdf 8528] f84f.57ca.3860 Configuration update request for RrmInterferenceCtrl payload sent to 10:201:234:24

[11/14/13 14:50:28.133 UTC 702fe0 8528] f84f.57ca.3860 Configuration update request for RrmNeighbourCtrl payload sent to 10.201.234.24

[11/14/13 14:50:28.134 UTC 702fe1 8528] f84f.57ca.3860 Configuration update request for RrmReceiveCtrl payload sent to 10:201:234:24

[11/14/13 14:50:28.134 UTC 702fe2 8528] f84f.57ca.3860 Configuration update request for CcxRmMeas payload sent to 10.201.234.24

[11/14/13 14:50:28.188 UTC 702fe3 8528] f84f.57ca.3860 Configuration Update Response from 10.201.234.24:18759

[11/14/13 14:50:28.188 UTC 702fe4 8528] f84f.57ca.3860 Change State Event Request from 10.201.234.24:18759

[11/14/13 14:50:28.188 UTC 702fe5 8528] f84f.57ca.3860 Change State Event Response sent to 10.201.234.24:18759

[11/14/13 14:50:28.188 UTC 702fe6 8528] f84f.57ca.3860 CAPWAP State: Run

[11/14/13 14:50:28.188 UTC 702fe7 8528] f84f.57ca.3860 Sending the remaining config to AP 10.201.234.24:18759

[11/14/13 14:50:28.194 UTC 702fe8 8528] f84f.57ca.3860 Configuration Update Response from 10.201.234.24:18759

[11/14/13 14:50:28.194 UTC 702fe9 8528] f84f.57ca.3860 **WTP Event Request** from 10.201.234.24:18759

[11/14/13 14:50:28.194 UTC 702fea 8528] f84f.57ca.3860 **WTP Event Response** sent to 10.201.234.24:18759

Проблема 8: время контроллера вне интервала Достоверности сертификата AP.

show clock

[11/14/13 14:50:27.869 UTC 702f94 8528] f84f.57ca.3860 **Configuration Status** from 10.201.234.24:18759

[11/14/13 14:50:27.870 UTC 702f95 8528] f84f.57ca.3860 **CAPWAP State: Configure**

[11/14/13 14:50:27.870 UTC 702f96 8528] f84f.57ca.3860 New unsupported Payload 254 in message from AP f84f.57ca.3860, Return SUCCESS

[11/14/13 14:50:27.870 UTC 702f97 8528] f84f.57ca.3860 Decoding new unsupported Payload 254 in message from AP f84f.57ca.3860, Return SUCCESS

[11/14/13 14:50:27.870 UTC 702f98 8528] Invalid channel 11 spacificed for the AP AP2602I-1, slotId = 0

[11/14/13 14:50:27.870 UTC 702f99 8528] Invalid channel 56 spacificed for the AP AP2602I-1, slotId = 1

[11/14/13 14:50:27.870 UTC 702f9a 8528] f84f.57ca.3860 Updating IP info for AP f84f.57ca.3860 -- static 0, 10.201.234.24/255.255.255.224, gtw 10.201.234.2

[11/14/13 14:50:27.870 UTC 702f9b 8528] f84f.57ca.3860 Updating IP 10.201.234.24 ==> 10.201.234.24 for AP f84f.57ca.3860

[11/14/13 14:50:27.870 UTC 702fab 8528] f84f.57ca.3860 LWAPP message validation failed for SPAM Vendor Specific Payload(104) in message of len=7 from AP

f84f.57ca.3860

[11/14/13 14:50:27.870 UTC 702fac 8528] f84f.57ca.3860 Failed to validate vendor specific message element

[11/14/13 14:50:27.871 UTC 702fad 8528] f84f.57ca.3860 **Setting MTU to 1485**

[11/14/13 14:50:27.871 UTC 702fae 8528] f84f.57ca.3860 Platform not Supported, exiting Load Balancer function

[11/14/13 14:50:27.871 UTC 702faf 8528] load balancer rc=4 for AP 10.201.234.24, IIF ID:0x00d2a98000000796

[11/14/13 14:50:27.871 UTC 702fb0 8528] opaque data size 0 with capwap interface create f84f.57ca.3860

[11/14/13 14:50:27.871 UTC 702fb1 8528] spiCapwapParams-> data_tunnel.opaque_data.opaque_data_len: 0

[11/14/13 14:50:27.871 UTC 702fb2 8528] f84f.57ca.3860 Data Tunnel Create timer started for 240 seconds timeout

[11/14/13 14:50:27.871 UTC 702fb3 8528] f84f.57ca.3860 **Data Tunnel created - tunnel type NON_CRYPTO**, load balancer support Not supported, tunnel mtu 1449,

anc_sw_id 0, anc_asic_id 0, res_sw_id 0, res_asic_id 0

anc_wp_iif_id 0x0000000000000000, res_wp_iif_id 0x0000000000000000

[11/14/13 14:50:27.871 UTC 702fb4 8528] f84f.57ca.3860 Not ready to send Config Status Response to AP 10.201.234.24 as SPI ACK is not received

[11/14/13 14:50:27.871 UTC 702fb5 8528] f84f.57ca.3860 AP f84f.57ca.3860 associated. Last AP failure was due to Configuration changes,reason: controller reboot command

[11/14/13 14:50:27.871 UTC 30e6 260] [CAPWAP]: CAPWAP data tunnel create message.

[11/14/13 14:50:27.871 UTC 30e7 260] [CAPWAP]: capwap_data_tunnel_create called

[11/14/13 14:50:27.871 UTC 30e8 260] [CAPWAP]: Data tunnel id = 0xd2a98000000796

[11/14/13 14:50:27.871 UTC 30e9 260] [CAPWAP]: Tunnel Entry not found for AP (10.201.234.24, 18759)

[11/14/13 14:50:27.873 UTC 30ea 260] [CAPWAP]: CAPWAP IDB init complete

[11/14/13 14:50:27.882 UTC 30eb 260] [CAPWAP]: capwap_interface_status_update: tunnel 0xd2a98000000796 status 0

[11/14/13 14:50:27.882 UTC 30ec 260] [CAPWAP]: csb pd flag 0 opaque_data_len 0 attr opaque_data 0x00000000

[11/14/13 14:50:27.882 UTC 30ed 260] [CAPWAP]: Send capwap_data_tunnel_status_update 0 Slot-Unit 1 Unit 1 for iif_id 0xd2a98000000796 to WCM.

[11/14/13 14:50:27.882 UTC 30ee 260] [CAPWAP]: (capwap_process_fed_results) CAPWAP FED result (0) for IIF ID: 0xd2a98000000796

[11/14/13 14:50:27.882 UTC 702fb6 8528

Received CAPWAP Tunnel SPI update opaque size 0

[11/14/13 14:50:27.882 UTC 702fb7 8528] opaque data len 0 with capwap server update

[11/14/13 14:50:27.883 UTC 702fb8 8528] f84f.57ca.3860 SPI ACK : Capwap Data Tunnel create successful for iifid:0x00d2a98000000796 AP:10.201.234.24

[11/14/13 14:50:27.883 UTC 702fb9 8528]

Received CAPWAP interface update opaque len 0

[11/14/13 14:50:27.883 UTC 702fba 8528] **SPI IifId ACK: Capwap Data Tunnel Created Successfully for IifId: 0x00d2a98000000796 AP: 10.201.234.24**

[11/14/13 14:50:27.883 UTC 702fbb 8528] f84f.57ca.3860 **OK to send Config Status Response to AP 10.201.234.24**

[11/14/13 14:50:27.888 UTC 30ef 260] [CAPWAP]: Notify PM (done).

[11/14/13 14:50:27.888 UTC 30f0 260] [CAPWAP]: SNMP Register: Ca1 HWIDB 32f44570

[11/14/13 14:50:27.888 UTC 30f1 260] [CAPWAP]: capwap_port_hashitem added: slot 1 slotunit 24 vlan 1104

[11/14/13 14:50:27.888 UTC 30f2 260] [CAPWAP]: 7c69.f604.9460 is AP's mac addr

[11/14/13 14:50:27.932 UTC 702fbc 8528] Sending multicast payload to ap AP2602I-1, mcast_mode 0, mcast group 0.0.0.0

[11/14/13 14:50:27.933 UTC 702fbd 8528] f84f.57ca.3860 Config status response sent to 10.201.234.24:18759

[11/14/13 14:50:27.933 UTC 702fbe 8528] f84f.57ca.3860 Configuration Status Response sent to 10:201:234:24

[11/14/13 14:50:27.933 UTC 702fbf 8528] f84f.57ca.3860 Configuration update request for Band Select Cfg sent to 10.201.234.24:18759

[11/14/13 14:50:27.933 UTC 702fc0 8528] f84f.57ca.3860 Configuration update request for HaConfig message sent to 10.201.234.24:18759

[11/14/13 14:50:27.934 UTC 702fc1 8528] f84f.57ca.3860 Configuration update request for AP NGWC Qos sent to 10.201.234.24:18759

[11/14/13 14:50:28.121 UTC 702fc2 8528] f84f.57ca.3860 Change State Event Request from 10.201.234.24:18759

[11/14/13 14:50:28.122 UTC 702fc3 8528] f84f.57ca.3860 Received LWAPP Up event for AP f84f.57ca.3860 slot 0!

[11/14/13 14:50:28.122 UTC 702fc4 8528] f84f.57ca.3860 Radio state change for slot: 0 state: 2 cause: 0 detail cause: 0

[11/14/13 14:50:28.122 UTC 702fc5 8528] f84f.57ca.3860 Change State Event Response sent to 10.201.234.24:18759

[11/14/13 14:50:28.122 UTC 702fc6 8528] f84f.57ca.3860 CAPWAP State: Run

[11/14/13 14:50:28.122 UTC 702fc7 8528] f84f.57ca.3860 Sending the remaining config to AP 10.201.234.24:18759

[11/14/13 14:50:28.122 UTC 702fc8 8528] f84f.57ca.3860 AP Going to RUN 10.201.234.24: ConcurrentJoins: 0

[11/14/13 14:50:28.122 UTC 702fc9 8528] f84f.57ca.3860 **Configuration update request** for Init VAP-DATA for slot 1 sent to 10.201.234.24:18759

[11/14/13 14:50:28.122 UTC 702fca 8528] f84f.57ca.3860 Configuration update request for configuring association limit params sent to 10.201.234.24:18759

[11/14/13 14:50:28.122 UTC 702fcb 8528] f84f.57ca.3860 Configuration update request for Band Select Cfg sent to 10.201.234.24:18759

[11/14/13 14:50:28.122 UTC 702fcc 8528] f84f.57ca.3860 Configuration update request for HaConfig message sent to 10.201.234.24:18759

[11/14/13 14:50:28.123 UTC 702fcd 8528] CAPWAP: No update, will insert f84f.57ca.3860

[11/14/13 14:50:28.123 UTC 702fce 8528] capwap opaque data f84f.57ca.3860 length = 0

[11/14/13 14:50:28.124 UTC 702fcf 8528] CAPWAP HA insert f84f.57ca.3860

[11/14/13 14:50:28.124 UTC 702fd0 8528] CAPWAP HA insert f84f.57ca.3860

[11/14/13 14:50:28.124 UTC 702fd1 8528] f84f.57ca.3860 Configuration update request for PHY payload sent to 10:201:234:24

[11/14/13 14:50:28.126 UTC 702fd2 8528] f84f.57ca.3860 **Configuration Update Response** from 10.201.234.24:18759

[11/14/13 14:50:28.126 UTC 702fd3 8528] f84f.57ca.3860 Configuration update request for RrmInterferenceCtrl payload sent to 10:201:234:24

[11/14/13 14:50:28.126 UTC 702fd4 8528] f84f.57ca.3860 Configuration update request for RrmNeighbourCtrl payload sent to 10.201.234.24

[11/14/13 14:50:28.126 UTC 702fd5 8528] f84f.57ca.3860 Configuration update request for RrmReceiveCtrl payload sent to 10:201:234:24

[11/14/13 14:50:28.126 UTC 702fd6 8528] f84f.57ca.3860 Configuration update request for CcxRmMeas payload sent to 10.201.234.24

[11/14/13 14:50:28.132 UTC 702fd7 8528] f84f.57ca.3860 Change State Event Request from 10.201.234.24:18759

[11/14/13 14:50:28.132 UTC 702fd8 8528] f84f.57ca.3860 Radio state change for slot: 1 state: 2 cause: 0 detail cause: 0

[11/14/13 14:50:28.132 UTC 702fd9 8528] f84f.57ca.3860 Change State Event Response sent to 10.201.234.24:18759

[11/14/13 14:50:28.132 UTC 702fda 8528] f84f.57ca.3860 CAPWAP State: Run

[11/14/13 14:50:28.132 UTC 702fdb 8528] f84f.57ca.3860 Sending the remaining config to AP 10.201.234.24:18759

[11/14/13 14:50:28.133 UTC 702fdc 8528] f84f.57ca.3860 Configuration update request for qos pm payload payload sent to 10.201.234.24:18759

[11/14/13 14:50:28.133 UTC 702fdd 8528] f84f.57ca.3860 Received LWAPP Up event for AP f84f.57ca.3860 slot 1!

[11/14/13 14:50:28.133 UTC 702fde 8528] f84f.57ca.3860 Configuration update request for PHY payload sent to 10:201:234:24

[11/14/13 14:50:28.133 UTC 702fdf 8528] f84f.57ca.3860 Configuration update request for RrmInterferenceCtrl payload sent to 10:201:234:24

[11/14/13 14:50:28.133 UTC 702fe0 8528] f84f.57ca.3860 Configuration update

request for RrmNeighbourCtrl payload sent to 10.201.234.24

[11/14/13 14:50:28.134 UTC 702fe1 8528] f84f.57ca.3860 Configuration update request for RrmReceiveCtrl payload sent to 10:201:234:24

[11/14/13 14:50:28.134 UTC 702fe2 8528] f84f.57ca.3860 Configuration update request for CcxRmMeas payload sent to 10.201.234.24

[11/14/13 14:50:28.188 UTC 702fe3 8528] f84f.57ca.3860 Configuration Update Response from 10.201.234.24:18759

[11/14/13 14:50:28.188 UTC 702fe4 8528] f84f.57ca.3860 Change State Event Request from 10.201.234.24:18759

[11/14/13 14:50:28.188 UTC 702fe5 8528] f84f.57ca.3860 Change State Event Response sent to 10.201.234.24:18759

[11/14/13 14:50:28.188 UTC 702fe6 8528] f84f.57ca.3860 CAPWAP State: Run

[11/14/13 14:50:28.188 UTC 702fe7 8528] f84f.57ca.3860 Sending the remaining config to AP 10.201.234.24:18759

[11/14/13 14:50:28.194 UTC 702fe8 8528] f84f.57ca.3860 Configuration Update Response from 10.201.234.24:18759

[11/14/13 14:50:28.194 UTC 702fe9 8528] f84f.57ca.3860 **WTP Event Request** from 10.201.234.24:18759

[11/14/13 14:50:28.194 UTC 702fea 8528] f84f.57ca.3860 **WTP Event Response** sent to 10.201.234.24:18759

show log

[11/14/13 14:50:27.869 UTC 702f94 8528] f84f.57ca.3860 **Configuration Status** from 10.201.234.24:18759

[11/14/13 14:50:27.870 UTC 702f95 8528] f84f.57ca.3860 **CAPWAP State: Configure**

[11/14/13 14:50:27.870 UTC 702f96 8528] f84f.57ca.3860 New unsupported Payload 254 in message from AP f84f.57ca.3860, Return SUCCESS

[11/14/13 14:50:27.870 UTC 702f97 8528] f84f.57ca.3860 Decoding new unsupported Payload 254 in message from AP f84f.57ca.3860, Return SUCCESS

[11/14/13 14:50:27.870 UTC 702f98 8528] Invalid channel 11 spacificied for the AP AP2602I-1, slotId = 0

[11/14/13 14:50:27.870 UTC 702f99 8528] Invalid channel 56 spacificied for the AP AP2602I-1, slotId = 1

[11/14/13 14:50:27.870 UTC 702f9a 8528] f84f.57ca.3860 Updating IP info for AP f84f.57ca.3860 -- static 0, 10.201.234.24/255.255.255.224, gtw 10.201.234.2

[11/14/13 14:50:27.870 UTC 702f9b 8528] f84f.57ca.3860 Updating IP 10.201.234.24 ==> 10.201.234.24 for AP f84f.57ca.3860

[11/14/13 14:50:27.870 UTC 702fab 8528] f84f.57ca.3860 LWAPP message validation failed for SPAM Vendor Specific Payload(104) in message of len=7 from AP f84f.57ca.3860

[11/14/13 14:50:27.870 UTC 702fac 8528] f84f.57ca.3860 Failed to validate vendor specific message element

[11/14/13 14:50:27.871 UTC 702fad 8528] f84f.57ca.3860 **Setting MTU to 1485**

[11/14/13 14:50:27.871 UTC 702fae 8528] f84f.57ca.3860 Platform not Supported, exiting Load Balancer function

[11/14/13 14:50:27.871 UTC 702faf 8528] load balancer rc=4 for AP 10.201.234.24, IIF ID:0x00d2a98000000796

[11/14/13 14:50:27.871 UTC 702fb0 8528] opaque data size 0 with capwap interface create f84f.57ca.3860

[11/14/13 14:50:27.871 UTC 702fb1 8528] spiCapwapParams-> data_tunnel.opaque_data.opaque_data_len: 0

[11/14/13 14:50:27.871 UTC 702fb2 8528] f84f.57ca.3860 Data Tunnel Create timer started for 240 seconds timeout

[11/14/13 14:50:27.871 UTC 702fb3 8528] f84f.57ca.3860 **Data Tunnel created - tunnel type NON_CRYPTO**, load balancer support Not supported, tunnel mtu 1449, anc_sw_id 0, anc_asic_id 0, res_sw_id 0, res_asic_id 0
anc_wp_iif_id 0x0000000000000000, res_wp_iif_id 0x0000000000000000

[11/14/13 14:50:27.871 UTC 702fb4 8528] f84f.57ca.3860 Not ready to send Config Status Response to AP 10.201.234.24 as SPI ACK is not received

[11/14/13 14:50:27.871 UTC 702fb5 8528] f84f.57ca.3860 AP f84f.57ca.3860 associated. Last AP failure was due to Configuration changes,reason: controller reboot command

[11/14/13 14:50:27.871 UTC 30e6 260] [CAPWAP]: CAPWAP data tunnel create message.

[11/14/13 14:50:27.871 UTC 30e7 260] [CAPWAP]: capwap_data_tunnel_create called

[11/14/13 14:50:27.871 UTC 30e8 260] [CAPWAP]: Data tunnel id = 0xd2a98000000796

[11/14/13 14:50:27.871 UTC 30e9 260] [CAPWAP]: Tunnel Entry not found for AP (10.201.234.24, 18759)

[11/14/13 14:50:27.873 UTC 30ea 260] [CAPWAP]: CAPWAP IDB init complete

[11/14/13 14:50:27.882 UTC 30eb 260] [CAPWAP]: capwap_interface_status_update: tunnel 0xd2a98000000796 status 0

[11/14/13 14:50:27.882 UTC 30ec 260] [CAPWAP]: csb pd flag 0 opaque_data_len 0 attr opaque_data 0x00000000

[11/14/13 14:50:27.882 UTC 30ed 260] [CAPWAP]: Send capwap_data_tunnel_status_update 0 Slot-Unit 1 Unit 1 for iif_id 0xd2a98000000796 to WCM.

[11/14/13 14:50:27.882 UTC 30ee 260] [CAPWAP]: (capwap_process_fed_results) CAPWAP FED result (0) for IIF ID: 0xd2a98000000796

[11/14/13 14:50:27.882 UTC 702fb6 8528]
Received CAPWAP Tunnel SPI update opaque size 0

[11/14/13 14:50:27.882 UTC 702fb7 8528] opaque data len 0 with capwap server update

[11/14/13 14:50:27.883 UTC 702fb8 8528] f84f.57ca.3860 SPI ACK : Capwap Data Tunnel create successful for iifid:0x00d2a98000000796 AP:10.201.234.24

[11/14/13 14:50:27.883 UTC 702fb9 8528]

Received CAPWAP interface update opaque len 0

[11/14/13 14:50:27.883 UTC 702fba 8528] **SPI IifId ACK: Capwap Data Tunnel Created Successfully for IifId: 0x00d2a98000000796 AP: 10.201.234.24**

[11/14/13 14:50:27.883 UTC 702fbb 8528] f84f.57ca.3860 **OK to send Config Status Response to AP 10.201.234.24**

[11/14/13 14:50:27.888 UTC 30ef 260] [CAPWAP]: Notify PM (done).

[11/14/13 14:50:27.888 UTC 30f0 260] [CAPWAP]: SNMP Register: Ca1 HWIDB 32f44570

[11/14/13 14:50:27.888 UTC 30f1 260] [CAPWAP]: capwap_port_hashitem added: slot 1 slotunit 24 vlan 1104

[11/14/13 14:50:27.888 UTC 30f2 260] [CAPWAP]: 7c69.f604.9460 is AP's mac addr

[11/14/13 14:50:27.932 UTC 702fbc 8528] Sending multicast payload to ap AP2602I-1, mcast_mode 0, mcast group 0.0.0.0

[11/14/13 14:50:27.933 UTC 702fbd 8528] f84f.57ca.3860 Config status response sent to 10.201.234.24:18759

[11/14/13 14:50:27.933 UTC 702fbe 8528] f84f.57ca.3860 Configuration Status Response sent to 10:201:234:24

[11/14/13 14:50:27.933 UTC 702fbf 8528] f84f.57ca.3860 Configuration update request for Band Select Cfg sent to 10.201.234.24:18759

[11/14/13 14:50:27.933 UTC 702fc0 8528] f84f.57ca.3860 Configuration update request for HaConfig message sent to 10.201.234.24:18759

[11/14/13 14:50:27.934 UTC 702fc1 8528] f84f.57ca.3860 Configuration update request for AP NGWC Qos sent to 10.201.234.24:18759

[11/14/13 14:50:28.121 UTC 702fc2 8528] f84f.57ca.3860 Change State Event Request from 10.201.234.24:18759

[11/14/13 14:50:28.122 UTC 702fc3 8528] f84f.57ca.3860 Received LWAPP Up event for AP f84f.57ca.3860 slot 0!

[11/14/13 14:50:28.122 UTC 702fc4 8528] f84f.57ca.3860 Radio state change for slot: 0 state: 2 cause: 0 detail cause: 0

[11/14/13 14:50:28.122 UTC 702fc5 8528] f84f.57ca.3860 Change State Event Response sent to 10.201.234.24:18759

[11/14/13 14:50:28.122 UTC 702fc6 8528] f84f.57ca.3860 CAPWAP State: Run

[11/14/13 14:50:28.122 UTC 702fc7 8528] f84f.57ca.3860 Sending the remaining config to AP 10.201.234.24:18759

[11/14/13 14:50:28.122 UTC 702fc8 8528] f84f.57ca.3860 AP Going to RUN 10.201.234.24: ConcurrentJoins: 0

[11/14/13 14:50:28.122 UTC 702fc9 8528] f84f.57ca.3860 **Configuration update request** for Init VAP-DATA for slot 1 sent to 10.201.234.24:18759

[11/14/13 14:50:28.122 UTC 702fca 8528] f84f.57ca.3860 Configuration update request for configuring association limit params sent to 10.201.234.24:18759

[11/14/13 14:50:28.122 UTC 702fcb 8528] f84f.57ca.3860 Configuration update

request for Band Select Cfg sent to 10.201.234.24:18759

[11/14/13 14:50:28.122 UTC 702fcc 8528] f84f.57ca.3860 Configuration update request for HaConfig message sent to 10.201.234.24:18759

[11/14/13 14:50:28.123 UTC 702fcd 8528] CAPWAP: No update, will insert f84f.57ca.3860

[11/14/13 14:50:28.123 UTC 702fce 8528] capwap opaque data f84f.57ca.3860 length = 0

[11/14/13 14:50:28.124 UTC 702fcf 8528] CAPWAP HA insert f84f.57ca.3860

[11/14/13 14:50:28.124 UTC 702fd0 8528] CAPWAP HA insert f84f.57ca.3860

[11/14/13 14:50:28.124 UTC 702fd1 8528] f84f.57ca.3860 Configuration update request for PHY payload sent to 10:201:234:24

[11/14/13 14:50:28.126 UTC 702fd2 8528] f84f.57ca.3860 **Configuration Update Response** from 10.201.234.24:18759

[11/14/13 14:50:28.126 UTC 702fd3 8528] f84f.57ca.3860 Configuration update request for RrmInterferenceCtrl payload sent to 10:201:234:24

[11/14/13 14:50:28.126 UTC 702fd4 8528] f84f.57ca.3860 Configuration update request for RrmNeighbourCtrl payload sent to 10.201.234.24

[11/14/13 14:50:28.126 UTC 702fd5 8528] f84f.57ca.3860 Configuration update request for RrmReceiveCtrl payload sent to 10:201:234:24

[11/14/13 14:50:28.126 UTC 702fd6 8528] f84f.57ca.3860 Configuration update request for CcxRmMeas payload sent to 10.201.234.24

[11/14/13 14:50:28.132 UTC 702fd7 8528] f84f.57ca.3860 Change State Event Request from 10.201.234.24:18759

[11/14/13 14:50:28.132 UTC 702fd8 8528] f84f.57ca.3860 Radio state change for slot: 1 state: 2 cause: 0 detail cause: 0

[11/14/13 14:50:28.132 UTC 702fd9 8528] f84f.57ca.3860 Change State Event Response sent to 10.201.234.24:18759

[11/14/13 14:50:28.132 UTC 702fda 8528] f84f.57ca.3860 CAPWAP State: Run

[11/14/13 14:50:28.132 UTC 702fdb 8528] f84f.57ca.3860 Sending the remaining config to AP 10.201.234.24:18759

[11/14/13 14:50:28.133 UTC 702fdc 8528] f84f.57ca.3860 Configuration update request for qos pm payload payload sent to 10.201.234.24:18759

[11/14/13 14:50:28.133 UTC 702fdd 8528] f84f.57ca.3860 Received LWAPP Up event for AP f84f.57ca.3860 slot 1!

[11/14/13 14:50:28.133 UTC 702fde 8528] f84f.57ca.3860 Configuration update request for PHY payload sent to 10:201:234:24

[11/14/13 14:50:28.133 UTC 702fdf 8528] f84f.57ca.3860 Configuration update request for RrmInterferenceCtrl payload sent to 10:201:234:24

[11/14/13 14:50:28.133 UTC 702fe0 8528] f84f.57ca.3860 Configuration update request for RrmNeighbourCtrl payload sent to 10.201.234.24

[11/14/13 14:50:28.134 UTC 702fe1 8528] f84f.57ca.3860 Configuration update request for RrmReceiveCtrl payload sent to 10:201:234:24

[11/14/13 14:50:28.134 UTC 702fe2 8528] f84f.57ca.3860 Configuration update request for CcxRmMeas payload sent to 10.201.234.24

[11/14/13 14:50:28.188 UTC 702fe3 8528] f84f.57ca.3860 Configuration Update Response from 10.201.234.24:18759

[11/14/13 14:50:28.188 UTC 702fe4 8528] f84f.57ca.3860 Change State Event Request from 10.201.234.24:18759

[11/14/13 14:50:28.188 UTC 702fe5 8528] f84f.57ca.3860 Change State Event Response sent to 10.201.234.24:18759

[11/14/13 14:50:28.188 UTC 702fe6 8528] f84f.57ca.3860 CAPWAP State: Run

[11/14/13 14:50:28.188 UTC 702fe7 8528] f84f.57ca.3860 Sending the remaining config to AP 10.201.234.24:18759

[11/14/13 14:50:28.194 UTC 702fe8 8528] f84f.57ca.3860 Configuration Update Response from 10.201.234.24:18759

[11/14/13 14:50:28.194 UTC 702fe9 8528] f84f.57ca.3860 **WTP Event Request** from 10.201.234.24:18759

[11/14/13 14:50:28.194 UTC 702fea 8528] f84f.57ca.3860 **WTP Event Response** sent to 10.201.234.24:18759

Проблема 9: список авторизации AP включен на WLC; AP не находится в списке авторизации.

#show подлинный список AP

[11/14/13 14:50:27.869 UTC 702f94 8528] f84f.57ca.3860 **Configuration Status** from 10.201.234.24:18759

[11/14/13 14:50:27.870 UTC 702f95 8528] f84f.57ca.3860 **CAPWAP State: Configure**

[11/14/13 14:50:27.870 UTC 702f96 8528] f84f.57ca.3860 New unsupported Payload 254 in message from AP f84f.57ca.3860, Return SUCCESS

[11/14/13 14:50:27.870 UTC 702f97 8528] f84f.57ca.3860 Decoding new unsupported Payload 254 in message from AP f84f.57ca.3860, Return SUCCESS

[11/14/13 14:50:27.870 UTC 702f98 8528] Invalid channel 11 spacificed for the AP AP2602I-1, slotId = 0

[11/14/13 14:50:27.870 UTC 702f99 8528] Invalid channel 56 spacificed for the AP AP2602I-1, slotId = 1

[11/14/13 14:50:27.870 UTC 702f9a 8528] f84f.57ca.3860 Updating IP info for AP f84f.57ca.3860 -- static 0, 10.201.234.24/255.255.255.224, gtw 10.201.234.2

[11/14/13 14:50:27.870 UTC 702f9b 8528] f84f.57ca.3860 Updating IP 10.201.234.24 ==> 10.201.234.24 for AP f84f.57ca.3860

|
[11/14/13 14:50:27.870 UTC 702fab 8528] f84f.57ca.3860 LWAPP message validation failed for SPAM Vendor Specific Payload(104) in message of len=7 from AP f84f.57ca.3860

[11/14/13 14:50:27.870 UTC 702fac 8528] f84f.57ca.3860 Failed to validate vendor

specific message element

[11/14/13 14:50:27.871 UTC 702fad 8528] f84f.57ca.3860 **Setting MTU to 1485**

[11/14/13 14:50:27.871 UTC 702fae 8528] f84f.57ca.3860 Platform not Supported, exiting Load Balancer function

[11/14/13 14:50:27.871 UTC 702faf 8528] load balancer rc=4 for AP 10.201.234.24, IIF ID:0x00d2a98000000796

[11/14/13 14:50:27.871 UTC 702fb0 8528] opaque data size 0 with capwap interface create f84f.57ca.3860

[11/14/13 14:50:27.871 UTC 702fb1 8528] spiCapwapParams-> data_tunnel.opaque_data.opaque_data_len: 0

[11/14/13 14:50:27.871 UTC 702fb2 8528] f84f.57ca.3860 Data Tunnel Create timer started for 240 seconds timeout

[11/14/13 14:50:27.871 UTC 702fb3 8528] f84f.57ca.3860 **Data Tunnel created - tunnel type NON_CRYPTO**, load balancer support Not supported, tunnel mtu 1449,

anc_sw_id 0, anc_asic_id 0, res_sw_id 0, res_asic_id 0

anc_wp_iif_id 0x0000000000000000, res_wp_iif_id 0x0000000000000000

[11/14/13 14:50:27.871 UTC 702fb4 8528] f84f.57ca.3860 Not ready to send Config Status Response to AP 10.201.234.24 as SPI ACK is not received

[11/14/13 14:50:27.871 UTC 702fb5 8528] f84f.57ca.3860 AP f84f.57ca.3860 associated. Last AP failure was due to Configuration changes,reason: controller reboot command

[11/14/13 14:50:27.871 UTC 30e6 260] [CAPWAP]: CAPWAP data tunnel create message.

[11/14/13 14:50:27.871 UTC 30e7 260] [CAPWAP]: capwap_data_tunnel_create called

[11/14/13 14:50:27.871 UTC 30e8 260] [CAPWAP]: Data tunnel id = 0xd2a98000000796

[11/14/13 14:50:27.871 UTC 30e9 260] [CAPWAP]: Tunnel Entry not found for AP (10.201.234.24, 18759)

[11/14/13 14:50:27.873 UTC 30ea 260] [CAPWAP]: CAPWAP IDB init complete

[11/14/13 14:50:27.882 UTC 30eb 260] [CAPWAP]: capwap_interface_status_update: tunnel 0xd2a98000000796 status 0

[11/14/13 14:50:27.882 UTC 30ec 260] [CAPWAP]: csb pd flag 0 opaque_data_len 0 attr opaque_data 0x00000000

[11/14/13 14:50:27.882 UTC 30ed 260] [CAPWAP]: Send capwap_data_tunnel_status_update 0 Slot-Unit 1 Unit 1 for iif_id 0xd2a98000000796 to WCM.

[11/14/13 14:50:27.882 UTC 30ee 260] [CAPWAP]: (capwap_process_fed_results) CAPWAP FED result (0) for IIF ID: 0xd2a98000000796

[11/14/13 14:50:27.882 UTC 702fb6 8528

Received CAPWAP Tunnel SPI update opaque size 0

[11/14/13 14:50:27.882 UTC 702fb7 8528] opaque data len 0 with capwap server update

[11/14/13 14:50:27.883 UTC 702fb8 8528] f84f.57ca.3860 SPI ACK : Capwap Data Tunnel create successful for iifid:0x00d2a98000000796 AP:10.201.234.24

[11/14/13 14:50:27.883 UTC 702fb9 8528]

Received CAPWAP interface update opaque len 0

[11/14/13 14:50:27.883 UTC 702fba 8528] **SPI IifId ACK: Capwap Data Tunnel Created Successfully for IifId: 0x00d2a98000000796 AP: 10.201.234.24**

[11/14/13 14:50:27.883 UTC 702fbb 8528] f84f.57ca.3860 **OK to send Config Status Response to AP 10.201.234.24**

[11/14/13 14:50:27.888 UTC 30ef 260] [CAPWAP]: Notify PM (done).

[11/14/13 14:50:27.888 UTC 30f0 260] [CAPWAP]: SNMP Register: Cal HWIDB 32f44570

[11/14/13 14:50:27.888 UTC 30f1 260] [CAPWAP]: capwap_port_hashitem added: slot 1 slotunit 24 vlan 1104

[11/14/13 14:50:27.888 UTC 30f2 260] [CAPWAP]: 7c69.f604.9460 is AP's mac addr

[11/14/13 14:50:27.932 UTC 702fbc 8528] Sending multicast payload to ap AP2602I-1, mcast_mode 0, mcast group 0.0.0.0

[11/14/13 14:50:27.933 UTC 702fbd 8528] f84f.57ca.3860 Config status response sent to 10.201.234.24:18759

[11/14/13 14:50:27.933 UTC 702fbe 8528] f84f.57ca.3860 Configuration Status Response sent to 10:201:234:24

[11/14/13 14:50:27.933 UTC 702fbf 8528] f84f.57ca.3860 Configuration update request for Band Select Cfg sent to 10.201.234.24:18759

[11/14/13 14:50:27.933 UTC 702fc0 8528] f84f.57ca.3860 Configuration update request for HaConfig message sent to 10.201.234.24:18759

[11/14/13 14:50:27.934 UTC 702fc1 8528] f84f.57ca.3860 Configuration update request for AP NGWC Qos sent to 10.201.234.24:18759

[11/14/13 14:50:28.121 UTC 702fc2 8528] f84f.57ca.3860 Change State Event Request from 10.201.234.24:18759

[11/14/13 14:50:28.122 UTC 702fc3 8528] f84f.57ca.3860 Received LWAPP Up event for AP f84f.57ca.3860 slot 0!

[11/14/13 14:50:28.122 UTC 702fc4 8528] f84f.57ca.3860 Radio state change for slot: 0 state: 2 cause: 0 detail cause: 0

[11/14/13 14:50:28.122 UTC 702fc5 8528] f84f.57ca.3860 Change State Event Response sent to 10.201.234.24:18759

[11/14/13 14:50:28.122 UTC 702fc6 8528] f84f.57ca.3860 CAPWAP State: Run

[11/14/13 14:50:28.122 UTC 702fc7 8528] f84f.57ca.3860 Sending the remaining config to AP 10.201.234.24:18759

[11/14/13 14:50:28.122 UTC 702fc8 8528] f84f.57ca.3860 AP Going to RUN 10.201.234.24: ConcurrentJoins: 0

[11/14/13 14:50:28.122 UTC 702fc9 8528] f84f.57ca.3860 **Configuration update request** for Init VAP-DATA for slot 1 sent to 10.201.234.24:18759

[11/14/13 14:50:28.122 UTC 702fca 8528] f84f.57ca.3860 Configuration update request for configuring association limit params sent to 10.201.234.24:18759

[11/14/13 14:50:28.122 UTC 702fcb 8528] f84f.57ca.3860 Configuration update request for Band Select Cfg sent to 10.201.234.24:18759

[11/14/13 14:50:28.122 UTC 702fcc 8528] f84f.57ca.3860 Configuration update request for HaConfig message sent to 10.201.234.24:18759

[11/14/13 14:50:28.123 UTC 702fcd 8528] CAPWAP: No update, will insert f84f.57ca.3860

[11/14/13 14:50:28.123 UTC 702fce 8528] capwap opaque data f84f.57ca.3860 length = 0

[11/14/13 14:50:28.124 UTC 702fcf 8528] CAPWAP HA insert f84f.57ca.3860

[11/14/13 14:50:28.124 UTC 702fd0 8528] CAPWAP HA insert f84f.57ca.3860

[11/14/13 14:50:28.124 UTC 702fd1 8528] f84f.57ca.3860 Configuration update request for PHY payload sent to 10:201:234:24

[11/14/13 14:50:28.126 UTC 702fd2 8528] f84f.57ca.3860 **Configuration Update Response** from 10.201.234.24:18759

[11/14/13 14:50:28.126 UTC 702fd3 8528] f84f.57ca.3860 Configuration update request for RrmInterferenceCtrl payload sent to 10:201:234:24

[11/14/13 14:50:28.126 UTC 702fd4 8528] f84f.57ca.3860 Configuration update request for RrmNeighbourCtrl payload sent to 10.201.234.24

[11/14/13 14:50:28.126 UTC 702fd5 8528] f84f.57ca.3860 Configuration update request for RrmReceiveCtrl payload sent to 10:201:234:24

[11/14/13 14:50:28.126 UTC 702fd6 8528] f84f.57ca.3860 Configuration update request for CcxRmMeas payload sent to 10.201.234.24

[11/14/13 14:50:28.132 UTC 702fd7 8528] f84f.57ca.3860 Change State Event Request from 10.201.234.24:18759

[11/14/13 14:50:28.132 UTC 702fd8 8528] f84f.57ca.3860 Radio state change for slot: 1 state: 2 cause: 0 detail cause: 0

[11/14/13 14:50:28.132 UTC 702fd9 8528] f84f.57ca.3860 Change State Event Response sent to 10.201.234.24:18759

[11/14/13 14:50:28.132 UTC 702fda 8528] f84f.57ca.3860 CAPWAP State: Run

[11/14/13 14:50:28.132 UTC 702fdb 8528] f84f.57ca.3860 Sending the remaining config to AP 10.201.234.24:18759

[11/14/13 14:50:28.133 UTC 702fdc 8528] f84f.57ca.3860 Configuration update request for qos pm payload payload sent to 10.201.234.24:18759

[11/14/13 14:50:28.133 UTC 702fdd 8528] f84f.57ca.3860 Received LWAPP Up event for AP f84f.57ca.3860 slot 1!

[11/14/13 14:50:28.133 UTC 702fde 8528] f84f.57ca.3860 Configuration update request for PHY payload sent to 10:201:234:24

[11/14/13 14:50:28.133 UTC 702fdf 8528] f84f.57ca.3860 Configuration update request for RrmInterferenceCtrl payload sent to 10:201:234:24

[11/14/13 14:50:28.133 UTC 702fe0 8528] f84f.57ca.3860 Configuration update request for RrmNeighbourCtrl payload sent to 10.201.234.24

[11/14/13 14:50:28.134 UTC 702fe1 8528] f84f.57ca.3860 Configuration update

request for RrmReceiveCtrl payload sent to 10:201:234:24

[11/14/13 14:50:28.134 UTC 702fe2 8528] f84f.57ca.3860 Configuration update
request for CcxRmMeas payload sent to 10.201.234.24

[11/14/13 14:50:28.188 UTC 702fe3 8528] f84f.57ca.3860 Configuration Update
Response from 10.201.234.24:18759

[11/14/13 14:50:28.188 UTC 702fe4 8528] f84f.57ca.3860 Change State Event
Request from 10.201.234.24:18759

[11/14/13 14:50:28.188 UTC 702fe5 8528] f84f.57ca.3860 Change State Event
Response sent to 10.201.234.24:18759

[11/14/13 14:50:28.188 UTC 702fe6 8528] f84f.57ca.3860 CAPWAP State: Run

[11/14/13 14:50:28.188 UTC 702fe7 8528] f84f.57ca.3860 Sending the remaining
config to AP 10.201.234.24:18759

[11/14/13 14:50:28.194 UTC 702fe8 8528] f84f.57ca.3860 Configuration Update
Response from 10.201.234.24:18759

[11/14/13 14:50:28.194 UTC 702fe9 8528] f84f.57ca.3860 **WTP Event Request**
from 10.201.234.24:18759

[11/14/13 14:50:28.194 UTC 702fea 8528] f84f.57ca.3860 **WTP Event Response**
sent to 10.201.234.24:18759

show log

[11/14/13 14:50:27.869 UTC 702f94 8528] f84f.57ca.3860 **Configuration Status**
from 10.201.234.24:18759

[11/14/13 14:50:27.870 UTC 702f95 8528] f84f.57ca.3860 **CAPWAP State: Configure**

[11/14/13 14:50:27.870 UTC 702f96 8528] f84f.57ca.3860 New unsupported Payload
254 in message from AP f84f.57ca.3860, Return SUCCESS

[11/14/13 14:50:27.870 UTC 702f97 8528] f84f.57ca.3860 Decoding new unsupported
Payload 254 in message from AP f84f.57ca.3860, Return SUCCESS

[11/14/13 14:50:27.870 UTC 702f98 8528] Invalid channel 11 spacificied for the AP
AP2602I-1, slotId = 0

[11/14/13 14:50:27.870 UTC 702f99 8528] Invalid channel 56 spacificied for the AP
AP2602I-1, slotId = 1

[11/14/13 14:50:27.870 UTC 702f9a 8528] f84f.57ca.3860 Updating IP info for AP
f84f.57ca.3860 -- static 0, 10.201.234.24/255.255.255.224, gtw 10.201.234.2

[11/14/13 14:50:27.870 UTC 702f9b 8528] f84f.57ca.3860 Updating IP
10.201.234.24 ==> 10.201.234.24 for AP f84f.57ca.3860

|
[11/14/13 14:50:27.870 UTC 702fab 8528] f84f.57ca.3860 LWAPP message validation
failed for SPAM Vendor Specific Payload(104) in message of len=7 from AP
f84f.57ca.3860

[11/14/13 14:50:27.870 UTC 702fac 8528] f84f.57ca.3860 Failed to validate vendor
specific message element

[11/14/13 14:50:27.871 UTC 702fad 8528] f84f.57ca.3860 **Setting MTU to 1485**

[11/14/13 14:50:27.871 UTC 702fae 8528] f84f.57ca.3860 Platform not Supported, exiting Load Balancer function

[11/14/13 14:50:27.871 UTC 702faf 8528] load balancer rc=4 for AP 10.201.234.24, IIF ID:0x00d2a98000000796

[11/14/13 14:50:27.871 UTC 702fb0 8528] opaque data size 0 with capwap interface create f84f.57ca.3860

[11/14/13 14:50:27.871 UTC 702fb1 8528] spiCapwapParams-> data_tunnel.opaque_data.opaque_data_len: 0

[11/14/13 14:50:27.871 UTC 702fb2 8528] f84f.57ca.3860 Data Tunnel Create timer started for 240 seconds timeout

[11/14/13 14:50:27.871 UTC 702fb3 8528] f84f.57ca.3860 **Data Tunnel created - tunnel type NON_CRYPTO**, load balancer support Not supported, tunnel mtu 1449, anc_sw_id 0, anc_asic_id 0, res_sw_id 0, res_asic_id 0 anc_wp_iif_id 0x0000000000000000, res_wp_iif_id 0x0000000000000000

[11/14/13 14:50:27.871 UTC 702fb4 8528] f84f.57ca.3860 Not ready to send Config Status Response to AP 10.201.234.24 as SPI ACK is not received

[11/14/13 14:50:27.871 UTC 702fb5 8528] f84f.57ca.3860 AP f84f.57ca.3860 associated. Last AP failure was due to Configuration changes,reason: controller reboot command

[11/14/13 14:50:27.871 UTC 30e6 260] [CAPWAP]: CAPWAP data tunnel create message.

[11/14/13 14:50:27.871 UTC 30e7 260] [CAPWAP]: capwap_data_tunnel_create called

[11/14/13 14:50:27.871 UTC 30e8 260] [CAPWAP]: Data tunnel id = 0xd2a98000000796

[11/14/13 14:50:27.871 UTC 30e9 260] [CAPWAP]: Tunnel Entry not found for AP (10.201.234.24, 18759)

[11/14/13 14:50:27.873 UTC 30ea 260] [CAPWAP]: CAPWAP IDB init complete

[11/14/13 14:50:27.882 UTC 30eb 260] [CAPWAP]: capwap_interface_status_update: tunnel 0xd2a98000000796 status 0

[11/14/13 14:50:27.882 UTC 30ec 260] [CAPWAP]: csb pd flag 0 opaque_data_len 0 attr opaque_data 0x00000000

[11/14/13 14:50:27.882 UTC 30ed 260] [CAPWAP]: Send capwap_data_tunnel_status_update 0 Slot-Unit 1 Unit 1 for iif_id 0xd2a98000000796 to WCM.

[11/14/13 14:50:27.882 UTC 30ee 260] [CAPWAP]: (capwap_process_fed_results) CAPWAP FED result (0) for IIF ID: 0xd2a98000000796

[11/14/13 14:50:27.882 UTC 702fb6 8528] Received CAPWAP Tunnel SPI update opaque size 0

[11/14/13 14:50:27.882 UTC 702fb7 8528] opaque data len 0 with capwap server update

[11/14/13 14:50:27.883 UTC 702fb8 8528] f84f.57ca.3860 SPI ACK : Capwap Data Tunnel create successful for iifid:0x00d2a98000000796 AP:10.201.234.24

[11/14/13 14:50:27.883 UTC 702fb9 8528] Received CAPWAP interface update opaque len 0

[11/14/13 14:50:27.883 UTC 702fba 8528] **SPI IifId ACK: Capwap Data Tunnel Created Successfully for IifId: 0x00d2a98000000796 AP: 10.201.234.24**

[11/14/13 14:50:27.883 UTC 702fbb 8528] f84f.57ca.3860 **OK to send Config Status Response to AP 10.201.234.24**

[11/14/13 14:50:27.888 UTC 30ef 260] [CAPWAP]: Notify PM (done).

[11/14/13 14:50:27.888 UTC 30f0 260] [CAPWAP]: SNMP Register: Cal HWIDB 32f44570

[11/14/13 14:50:27.888 UTC 30f1 260] [CAPWAP]: capwap_port_hashitem added: slot 1 slotunit 24 vlan 1104

[11/14/13 14:50:27.888 UTC 30f2 260] [CAPWAP]: 7c69.f604.9460 is AP's mac addr

[11/14/13 14:50:27.932 UTC 702fbc 8528] Sending multicast payload to ap AP2602I-1, mcast_mode 0, mcast group 0.0.0.0

[11/14/13 14:50:27.933 UTC 702fbd 8528] f84f.57ca.3860 Config status response sent to 10.201.234.24:18759

[11/14/13 14:50:27.933 UTC 702fbe 8528] f84f.57ca.3860 Configuration Status Response sent to 10:201:234:24

[11/14/13 14:50:27.933 UTC 702fbf 8528] f84f.57ca.3860 Configuration update request for Band Select Cfg sent to 10.201.234.24:18759

[11/14/13 14:50:27.933 UTC 702fc0 8528] f84f.57ca.3860 Configuration update request for HaConfig message sent to 10.201.234.24:18759

[11/14/13 14:50:27.934 UTC 702fc1 8528] f84f.57ca.3860 Configuration update request for AP NGWC Qos sent to 10.201.234.24:18759

[11/14/13 14:50:28.121 UTC 702fc2 8528] f84f.57ca.3860 Change State Event Request from 10.201.234.24:18759

[11/14/13 14:50:28.122 UTC 702fc3 8528] f84f.57ca.3860 Received LWAPP Up event for AP f84f.57ca.3860 slot 0!

[11/14/13 14:50:28.122 UTC 702fc4 8528] f84f.57ca.3860 Radio state change for slot: 0 state: 2 cause: 0 detail cause: 0

[11/14/13 14:50:28.122 UTC 702fc5 8528] f84f.57ca.3860 Change State Event Response sent to 10.201.234.24:18759

[11/14/13 14:50:28.122 UTC 702fc6 8528] f84f.57ca.3860 CAPWAP State: Run

[11/14/13 14:50:28.122 UTC 702fc7 8528] f84f.57ca.3860 Sending the remaining config to AP 10.201.234.24:18759

[11/14/13 14:50:28.122 UTC 702fc8 8528] f84f.57ca.3860 AP Going to RUN 10.201.234.24: ConcurrentJoins: 0

[11/14/13 14:50:28.122 UTC 702fc9 8528] f84f.57ca.3860 **Configuration update request** for Init VAP-DATA for slot 1 sent to 10.201.234.24:18759

[11/14/13 14:50:28.122 UTC 702fca 8528] f84f.57ca.3860 Configuration update request for configuring association limit params sent to 10.201.234.24:18759

[11/14/13 14:50:28.122 UTC 702fcb 8528] f84f.57ca.3860 Configuration update request for Band Select Cfg sent to 10.201.234.24:18759

[11/14/13 14:50:28.122 UTC 702fcc 8528] f84f.57ca.3860 Configuration update

request for HaConfig message sent to 10.201.234.24:18759

[11/14/13 14:50:28.123 UTC 702fcd 8528] CAPWAP: No update, will insert f84f.57ca.3860

[11/14/13 14:50:28.123 UTC 702fce 8528] capwap opaque data f84f.57ca.3860 length = 0

[11/14/13 14:50:28.124 UTC 702fcf 8528] CAPWAP HA insert f84f.57ca.3860

[11/14/13 14:50:28.124 UTC 702fd0 8528] CAPWAP HA insert f84f.57ca.3860

[11/14/13 14:50:28.124 UTC 702fd1 8528] f84f.57ca.3860 Configuration update request for PHY payload sent to 10:201:234:24

[11/14/13 14:50:28.126 UTC 702fd2 8528] f84f.57ca.3860 **Configuration Update Response** from 10.201.234.24:18759

[11/14/13 14:50:28.126 UTC 702fd3 8528] f84f.57ca.3860 Configuration update request for RrmInterferenceCtrl payload sent to 10:201:234:24

[11/14/13 14:50:28.126 UTC 702fd4 8528] f84f.57ca.3860 Configuration update request for RrmNeighbourCtrl payload sent to 10.201.234.24

[11/14/13 14:50:28.126 UTC 702fd5 8528] f84f.57ca.3860 Configuration update request for RrmReceiveCtrl payload sent to 10:201:234:24

[11/14/13 14:50:28.126 UTC 702fd6 8528] f84f.57ca.3860 Configuration update request for CcxRmMeas payload sent to 10.201.234.24

[11/14/13 14:50:28.132 UTC 702fd7 8528] f84f.57ca.3860 Change State Event Request from 10.201.234.24:18759

[11/14/13 14:50:28.132 UTC 702fd8 8528] f84f.57ca.3860 Radio state change for slot: 1 state: 2 cause: 0 detail cause: 0

[11/14/13 14:50:28.132 UTC 702fd9 8528] f84f.57ca.3860 Change State Event Response sent to 10.201.234.24:18759

[11/14/13 14:50:28.132 UTC 702fda 8528] f84f.57ca.3860 CAPWAP State: Run

[11/14/13 14:50:28.132 UTC 702fdb 8528] f84f.57ca.3860 Sending the remaining config to AP 10.201.234.24:18759

[11/14/13 14:50:28.133 UTC 702fdc 8528] f84f.57ca.3860 Configuration update request for qos pm payload payload sent to 10.201.234.24:18759

[11/14/13 14:50:28.133 UTC 702fdd 8528] f84f.57ca.3860 Received LWAPP Up event for AP f84f.57ca.3860 slot 1!

[11/14/13 14:50:28.133 UTC 702fde 8528] f84f.57ca.3860 Configuration update request for PHY payload sent to 10:201:234:24

[11/14/13 14:50:28.133 UTC 702fdf 8528] f84f.57ca.3860 Configuration update request for RrmInterferenceCtrl payload sent to 10:201:234:24

[11/14/13 14:50:28.133 UTC 702fe0 8528] f84f.57ca.3860 Configuration update request for RrmNeighbourCtrl payload sent to 10.201.234.24

[11/14/13 14:50:28.134 UTC 702fe1 8528] f84f.57ca.3860 Configuration update request for RrmReceiveCtrl payload sent to 10:201:234:24

[11/14/13 14:50:28.134 UTC 702fe2 8528] f84f.57ca.3860 Configuration update request for CcxRmMeas payload sent to 10.201.234.24

[11/14/13 14:50:28.188 UTC 702fe3 8528] f84f.57ca.3860 Configuration Update Response from 10.201.234.24:18759

[11/14/13 14:50:28.188 UTC 702fe4 8528] f84f.57ca.3860 Change State Event Request from 10.201.234.24:18759

[11/14/13 14:50:28.188 UTC 702fe5 8528] f84f.57ca.3860 Change State Event Response sent to 10.201.234.24:18759

[11/14/13 14:50:28.188 UTC 702fe6 8528] f84f.57ca.3860 CAPWAP State: Run

[11/14/13 14:50:28.188 UTC 702fe7 8528] f84f.57ca.3860 Sending the remaining config to AP 10.201.234.24:18759

[11/14/13 14:50:28.194 UTC 702fe8 8528] f84f.57ca.3860 Configuration Update Response from 10.201.234.24:18759

[11/14/13 14:50:28.194 UTC 702fe9 8528] f84f.57ca.3860 **WTP Event Request** from 10.201.234.24:18759

[11/14/13 14:50:28.194 UTC 702fea 8528] f84f.57ca.3860 **WTP Event Response** sent to 10.201.234.24:18759

Проблема 10: Политика AP MIC отключена.

#show подлинный список AP

[11/14/13 14:50:27.869 UTC 702f94 8528] f84f.57ca.3860 **Configuration Status** from 10.201.234.24:18759

[11/14/13 14:50:27.870 UTC 702f95 8528] f84f.57ca.3860 **CAPWAP State: Configure**

[11/14/13 14:50:27.870 UTC 702f96 8528] f84f.57ca.3860 New unsupported Payload 254 in message from AP f84f.57ca.3860, Return SUCCESS

[11/14/13 14:50:27.870 UTC 702f97 8528] f84f.57ca.3860 Decoding new unsupported Payload 254 in message from AP f84f.57ca.3860, Return SUCCESS

[11/14/13 14:50:27.870 UTC 702f98 8528] Invalid channel 11 spacificied for the AP AP2602I-1, slotId = 0

[11/14/13 14:50:27.870 UTC 702f99 8528] Invalid channel 56 spacificied for the AP AP2602I-1, slotId = 1

[11/14/13 14:50:27.870 UTC 702f9a 8528] f84f.57ca.3860 Updating IP info for AP f84f.57ca.3860 -- static 0, 10.201.234.24/255.255.255.224, gtw 10.201.234.2

[11/14/13 14:50:27.870 UTC 702f9b 8528] f84f.57ca.3860 Updating IP 10.201.234.24 ==> 10.201.234.24 for AP f84f.57ca.3860

|

[11/14/13 14:50:27.870 UTC 702fab 8528] f84f.57ca.3860 LWAPP message validation failed for SPAM Vendor Specific Payload(104) in message of len=7 from AP f84f.57ca.3860

[11/14/13 14:50:27.870 UTC 702fac 8528] f84f.57ca.3860 Failed to validate vendor specific message element

[11/14/13 14:50:27.871 UTC 702fad 8528] f84f.57ca.3860 **Setting MTU to 1485**

[11/14/13 14:50:27.871 UTC 702fae 8528] f84f.57ca.3860 Platform not Supported, exiting Load Balancer function

[11/14/13 14:50:27.871 UTC 702faf 8528] load balancer rc=4 for AP 10.201.234.24, IIF ID:0x00d2a98000000796

[11/14/13 14:50:27.871 UTC 702fb0 8528] opaque data size 0 with capwap interface create f84f.57ca.3860

[11/14/13 14:50:27.871 UTC 702fb1 8528] spiCapwapParams-> data_tunnel.opaque_data.opaque_data_len: 0

[11/14/13 14:50:27.871 UTC 702fb2 8528] f84f.57ca.3860 Data Tunnel Create timer started for 240 seconds timeout

[11/14/13 14:50:27.871 UTC 702fb3 8528] f84f.57ca.3860 **Data Tunnel created - tunnel type NON_CRYPTO**, load balancer support Not supported, tunnel mtu 1449, anc_sw_id 0, anc_asic_id 0, res_sw_id 0, res_asic_id 0 anc_wp_iif_id 0x0000000000000000, res_wp_iif_id 0x0000000000000000

[11/14/13 14:50:27.871 UTC 702fb4 8528] f84f.57ca.3860 Not ready to send Config Status Response to AP 10.201.234.24 as SPI ACK is not received

[11/14/13 14:50:27.871 UTC 702fb5 8528] f84f.57ca.3860 AP f84f.57ca.3860 associated. Last AP failure was due to Configuration changes,reason: controller reboot command

[11/14/13 14:50:27.871 UTC 30e6 260] [CAPWAP]: CAPWAP data tunnel create message.

[11/14/13 14:50:27.871 UTC 30e7 260] [CAPWAP]: capwap_data_tunnel_create called

[11/14/13 14:50:27.871 UTC 30e8 260] [CAPWAP]: Data tunnel id = 0xd2a98000000796

[11/14/13 14:50:27.871 UTC 30e9 260] [CAPWAP]: Tunnel Entry not found for AP (10.201.234.24, 18759)

[11/14/13 14:50:27.873 UTC 30ea 260] [CAPWAP]: CAPWAP IDB init complete

[11/14/13 14:50:27.882 UTC 30eb 260] [CAPWAP]: capwap_interface_status_update: tunnel 0xd2a98000000796 status 0

[11/14/13 14:50:27.882 UTC 30ec 260] [CAPWAP]: csb pd flag 0 opaque_data_len 0 attr opaque_data 0x00000000

[11/14/13 14:50:27.882 UTC 30ed 260] [CAPWAP]: Send capwap_data_tunnel_status_update 0 Slot-Unit 1 Unit 1 for iif_id 0xd2a98000000796 to WCM.

[11/14/13 14:50:27.882 UTC 30ee 260] [CAPWAP]: (capwap_process_fed_results) CAPWAP FED result (0) for IIF ID: 0xd2a98000000796

[11/14/13 14:50:27.882 UTC 702fb6 8528] Received CAPWAP Tunnel SPI update opaque size 0

[11/14/13 14:50:27.882 UTC 702fb7 8528] opaque data len 0 with capwap server update

[11/14/13 14:50:27.883 UTC 702fb8 8528] f84f.57ca.3860 SPI ACK : Capwap Data Tunnel create successful for iifid:0x00d2a98000000796 AP:10.201.234.24

[11/14/13 14:50:27.883 UTC 702fb9 8528] Received CAPWAP interface update opaque len 0

[11/14/13 14:50:27.883 UTC 702fba 8528] **SPI IifId ACK: Capwap Data Tunnel Created Successfully for IifId: 0x00d2a98000000796 AP: 10.201.234.24**

[11/14/13 14:50:27.883 UTC 702fbb 8528] f84f.57ca.3860 **OK to send Config Status Response to AP 10.201.234.24**

[11/14/13 14:50:27.888 UTC 30ef 260] [CAPWAP]: Notify PM (done).

[11/14/13 14:50:27.888 UTC 30f0 260] [CAPWAP]: SNMP Register: Cal HWIDB 32f44570

[11/14/13 14:50:27.888 UTC 30f1 260] [CAPWAP]: capwap_port_hashitem added: slot 1 slotunit 24 vlan 1104

[11/14/13 14:50:27.888 UTC 30f2 260] [CAPWAP]: 7c69.f604.9460 is AP's mac addr

[11/14/13 14:50:27.932 UTC 702fbc 8528] Sending multicast payload to ap AP2602I-1, mcast_mode 0, mcast group 0.0.0.0

[11/14/13 14:50:27.933 UTC 702fbd 8528] f84f.57ca.3860 Config status response sent to 10.201.234.24:18759

[11/14/13 14:50:27.933 UTC 702fbe 8528] f84f.57ca.3860 Configuration Status Response sent to 10:201:234:24

[11/14/13 14:50:27.933 UTC 702fbf 8528] f84f.57ca.3860 Configuration update request for Band Select Cfg sent to 10.201.234.24:18759

[11/14/13 14:50:27.933 UTC 702fc0 8528] f84f.57ca.3860 Configuration update request for HaConfig message sent to 10.201.234.24:18759

[11/14/13 14:50:27.934 UTC 702fc1 8528] f84f.57ca.3860 Configuration update request for AP NGWC Qos sent to 10.201.234.24:18759

[11/14/13 14:50:28.121 UTC 702fc2 8528] f84f.57ca.3860 Change State Event Request from 10.201.234.24:18759

[11/14/13 14:50:28.122 UTC 702fc3 8528] f84f.57ca.3860 Received LWAPP Up event for AP f84f.57ca.3860 slot 0!

[11/14/13 14:50:28.122 UTC 702fc4 8528] f84f.57ca.3860 Radio state change for slot: 0 state: 2 cause: 0 detail cause: 0

[11/14/13 14:50:28.122 UTC 702fc5 8528] f84f.57ca.3860 Change State Event Response sent to 10.201.234.24:18759

[11/14/13 14:50:28.122 UTC 702fc6 8528] f84f.57ca.3860 CAPWAP State: Run

[11/14/13 14:50:28.122 UTC 702fc7 8528] f84f.57ca.3860 Sending the remaining config to AP 10.201.234.24:18759

[11/14/13 14:50:28.122 UTC 702fc8 8528] f84f.57ca.3860 AP Going to RUN 10.201.234.24: ConcurrentJoins: 0

[11/14/13 14:50:28.122 UTC 702fc9 8528] f84f.57ca.3860 **Configuration update request** for Init VAP-DATA for slot 1 sent to 10.201.234.24:18759

[11/14/13 14:50:28.122 UTC 702fca 8528] f84f.57ca.3860 Configuration update request for configuring association limit params sent to 10.201.234.24:18759

[11/14/13 14:50:28.122 UTC 702fcb 8528] f84f.57ca.3860 Configuration update request for Band Select Cfg sent to 10.201.234.24:18759

[11/14/13 14:50:28.122 UTC 702fcc 8528] f84f.57ca.3860 Configuration update

request for HaConfig message sent to 10.201.234.24:18759

[11/14/13 14:50:28.123 UTC 702fcd 8528] CAPWAP: No update, will insert f84f.57ca.3860

[11/14/13 14:50:28.123 UTC 702fce 8528] capwap opaque data f84f.57ca.3860 length = 0

[11/14/13 14:50:28.124 UTC 702fcf 8528] CAPWAP HA insert f84f.57ca.3860

[11/14/13 14:50:28.124 UTC 702fd0 8528] CAPWAP HA insert f84f.57ca.3860

[11/14/13 14:50:28.124 UTC 702fd1 8528] f84f.57ca.3860 Configuration update request for PHY payload sent to 10:201:234:24

[11/14/13 14:50:28.126 UTC 702fd2 8528] f84f.57ca.3860 **Configuration Update Response** from 10.201.234.24:18759

[11/14/13 14:50:28.126 UTC 702fd3 8528] f84f.57ca.3860 Configuration update request for RrmInterferenceCtrl payload sent to 10:201:234:24

[11/14/13 14:50:28.126 UTC 702fd4 8528] f84f.57ca.3860 Configuration update request for RrmNeighbourCtrl payload sent to 10.201.234.24

[11/14/13 14:50:28.126 UTC 702fd5 8528] f84f.57ca.3860 Configuration update request for RrmReceiveCtrl payload sent to 10:201:234:24

[11/14/13 14:50:28.126 UTC 702fd6 8528] f84f.57ca.3860 Configuration update request for CcxRmMeas payload sent to 10.201.234.24

[11/14/13 14:50:28.132 UTC 702fd7 8528] f84f.57ca.3860 Change State Event Request from 10.201.234.24:18759

[11/14/13 14:50:28.132 UTC 702fd8 8528] f84f.57ca.3860 Radio state change for slot: 1 state: 2 cause: 0 detail cause: 0

[11/14/13 14:50:28.132 UTC 702fd9 8528] f84f.57ca.3860 Change State Event Response sent to 10.201.234.24:18759

[11/14/13 14:50:28.132 UTC 702fda 8528] f84f.57ca.3860 CAPWAP State: Run

[11/14/13 14:50:28.132 UTC 702fdb 8528] f84f.57ca.3860 Sending the remaining config to AP 10.201.234.24:18759

[11/14/13 14:50:28.133 UTC 702fdc 8528] f84f.57ca.3860 Configuration update request for qos pm payload payload sent to 10.201.234.24:18759

[11/14/13 14:50:28.133 UTC 702fdd 8528] f84f.57ca.3860 Received LWAPP Up event for AP f84f.57ca.3860 slot 1!

[11/14/13 14:50:28.133 UTC 702fde 8528] f84f.57ca.3860 Configuration update request for PHY payload sent to 10:201:234:24

[11/14/13 14:50:28.133 UTC 702fdf 8528] f84f.57ca.3860 Configuration update request for RrmInterferenceCtrl payload sent to 10:201:234:24

[11/14/13 14:50:28.133 UTC 702fe0 8528] f84f.57ca.3860 Configuration update request for RrmNeighbourCtrl payload sent to 10.201.234.24

[11/14/13 14:50:28.134 UTC 702fe1 8528] f84f.57ca.3860 Configuration update request for RrmReceiveCtrl payload sent to 10:201:234:24

[11/14/13 14:50:28.134 UTC 702fe2 8528] f84f.57ca.3860 Configuration update request for CcxRmMeas payload sent to 10.201.234.24

[11/14/13 14:50:28.188 UTC 702fe3 8528] f84f.57ca.3860 Configuration Update Response from 10.201.234.24:18759

[11/14/13 14:50:28.188 UTC 702fe4 8528] f84f.57ca.3860 Change State Event Request from 10.201.234.24:18759

[11/14/13 14:50:28.188 UTC 702fe5 8528] f84f.57ca.3860 Change State Event Response sent to 10.201.234.24:18759

[11/14/13 14:50:28.188 UTC 702fe6 8528] f84f.57ca.3860 CAPWAP State: Run

[11/14/13 14:50:28.188 UTC 702fe7 8528] f84f.57ca.3860 Sending the remaining config to AP 10.201.234.24:18759

[11/14/13 14:50:28.194 UTC 702fe8 8528] f84f.57ca.3860 Configuration Update Response from 10.201.234.24:18759

[11/14/13 14:50:28.194 UTC 702fe9 8528] f84f.57ca.3860 **WTP Event Request** from 10.201.234.24:18759

[11/14/13 14:50:28.194 UTC 702fea 8528] f84f.57ca.3860 **WTP Event Response** sent to 10.201.234.24:18759

Авторизуйте AP LSC против Подлинного Списка : отключенный

AP, позволенные соединению:

AP с производством установленного сертификата: отключенный

AP с подписанным сертификатом : отключенный

AP с локально значительным сертификатом : отключенный

show log

[11/14/13 14:50:27.869 UTC 702f94 8528] f84f.57ca.3860 **Configuration Status** from 10.201.234.24:18759

[11/14/13 14:50:27.870 UTC 702f95 8528] f84f.57ca.3860 **CAPWAP State: Configure**

[11/14/13 14:50:27.870 UTC 702f96 8528] f84f.57ca.3860 New unsupported Payload 254 in message from AP f84f.57ca.3860, Return SUCCESS

[11/14/13 14:50:27.870 UTC 702f97 8528] f84f.57ca.3860 Decoding new unsupported Payload 254 in message from AP f84f.57ca.3860, Return SUCCESS

[11/14/13 14:50:27.870 UTC 702f98 8528] Invalid channel 11 spacificed for the AP AP2602I-1, slotId = 0

[11/14/13 14:50:27.870 UTC 702f99 8528] Invalid channel 56 spacificed for the AP AP2602I-1, slotId = 1

[11/14/13 14:50:27.870 UTC 702f9a 8528] f84f.57ca.3860 Updating IP info for AP f84f.57ca.3860 -- static 0, 10.201.234.24/255.255.255.224, gtw 10.201.234.2

[11/14/13 14:50:27.870 UTC 702f9b 8528] f84f.57ca.3860 Updating IP 10.201.234.24 ==> 10.201.234.24 for AP f84f.57ca.3860

|

[11/14/13 14:50:27.870 UTC 702fab 8528] f84f.57ca.3860 LWAPP message validation failed for SPAM Vendor Specific Payload(104) in message of len=7 from AP f84f.57ca.3860

[11/14/13 14:50:27.870 UTC 702fac 8528] f84f.57ca.3860 Failed to validate vendor specific message element

[11/14/13 14:50:27.871 UTC 702fad 8528] f84f.57ca.3860 **Setting MTU to 1485**

[11/14/13 14:50:27.871 UTC 702fae 8528] f84f.57ca.3860 Platform not Supported, exiting Load Balancer function

[11/14/13 14:50:27.871 UTC 702faf 8528] load balancer rc=4 for AP 10.201.234.24, IIF ID:0x00d2a98000000796

[11/14/13 14:50:27.871 UTC 702fb0 8528] opaque data size 0 with capwap interface create f84f.57ca.3860

[11/14/13 14:50:27.871 UTC 702fb1 8528] spiCapwapParams-> data_tunnel.opaque_data.opaque_data_len: 0

[11/14/13 14:50:27.871 UTC 702fb2 8528] f84f.57ca.3860 Data Tunnel Create timer started for 240 seconds timeout

[11/14/13 14:50:27.871 UTC 702fb3 8528] f84f.57ca.3860 **Data Tunnel created - tunnel type NON_CRYPTO**, load balancer support Not supported, tunnel mtu 1449, anc_sw_id 0, anc_asic_id 0, res_sw_id 0, res_asic_id 0
anc_wp_iif_id 0x0000000000000000, res_wp_iif_id 0x0000000000000000

[11/14/13 14:50:27.871 UTC 702fb4 8528] f84f.57ca.3860 Not ready to send Config Status Response to AP 10.201.234.24 as SPI ACK is not received

[11/14/13 14:50:27.871 UTC 702fb5 8528] f84f.57ca.3860 AP f84f.57ca.3860 associated. Last AP failure was due to Configuration changes,reason: controller reboot command

[11/14/13 14:50:27.871 UTC 30e6 260] [CAPWAP]: CAPWAP data tunnel create message.

[11/14/13 14:50:27.871 UTC 30e7 260] [CAPWAP]: capwap_data_tunnel_create called

[11/14/13 14:50:27.871 UTC 30e8 260] [CAPWAP]: Data tunnel id = 0xd2a98000000796

[11/14/13 14:50:27.871 UTC 30e9 260] [CAPWAP]: Tunnel Entry not found for AP (10.201.234.24, 18759)

[11/14/13 14:50:27.873 UTC 30ea 260] [CAPWAP]: CAPWAP IDB init complete

[11/14/13 14:50:27.882 UTC 30eb 260] [CAPWAP]: capwap_interface_status_update: tunnel 0xd2a98000000796 status 0

[11/14/13 14:50:27.882 UTC 30ec 260] [CAPWAP]: csb pd flag 0 opaque_data_len 0 attr opaque_data 0x00000000

[11/14/13 14:50:27.882 UTC 30ed 260] [CAPWAP]: Send capwap_data_tunnel_status_update 0 Slot-Unit 1 Unit 1 for iif_id 0xd2a98000000796 to WCM.

[11/14/13 14:50:27.882 UTC 30ee 260] [CAPWAP]: (capwap_process_fed_results) CAPWAP FED result (0) for IIF ID: 0xd2a98000000796

[11/14/13 14:50:27.882 UTC 702fb6 8528

Received CAPWAP Tunnel SPI update opaque size 0

[11/14/13 14:50:27.882 UTC 702fb7 8528] opaque data len 0 with capwap server update

[11/14/13 14:50:27.883 UTC 702fb8 8528] f84f.57ca.3860 SPI ACK : Capwap Data Tunnel create successful for iifid:0x00d2a98000000796 AP:10.201.234.24

[11/14/13 14:50:27.883 UTC 702fb9 8528]

Received CAPWAP interface update opaque len 0

[11/14/13 14:50:27.883 UTC 702fba 8528] **SPI IifId ACK: Capwap Data Tunnel Created Successfully for IifId: 0x00d2a98000000796 AP: 10.201.234.24**

[11/14/13 14:50:27.883 UTC 702fbb 8528] f84f.57ca.3860 **OK to send Config Status Response to AP 10.201.234.24**

[11/14/13 14:50:27.888 UTC 30ef 260] [CAPWAP]: Notify PM (done).

[11/14/13 14:50:27.888 UTC 30f0 260] [CAPWAP]: SNMP Register: Cal HWIDB 32f44570

[11/14/13 14:50:27.888 UTC 30f1 260] [CAPWAP]: capwap_port_hashitem added: slot 1 slotunit 24 vlan 1104

[11/14/13 14:50:27.888 UTC 30f2 260] [CAPWAP]: 7c69.f604.9460 is AP's mac addr

[11/14/13 14:50:27.932 UTC 702fbc 8528] Sending multicast payload to ap AP2602I-1, mcast_mode 0, mcast group 0.0.0.0

[11/14/13 14:50:27.933 UTC 702fbd 8528] f84f.57ca.3860 Config status response sent to 10.201.234.24:18759

[11/14/13 14:50:27.933 UTC 702fbe 8528] f84f.57ca.3860 Configuration Status Response sent to 10:201:234:24

[11/14/13 14:50:27.933 UTC 702fbf 8528] f84f.57ca.3860 Configuration update request for Band Select Cfg sent to 10.201.234.24:18759

[11/14/13 14:50:27.933 UTC 702fc0 8528] f84f.57ca.3860 Configuration update request for HaConfig message sent to 10.201.234.24:18759

[11/14/13 14:50:27.934 UTC 702fc1 8528] f84f.57ca.3860 Configuration update request for AP NGWC Qos sent to 10.201.234.24:18759

[11/14/13 14:50:28.121 UTC 702fc2 8528] f84f.57ca.3860 Change State Event Request from 10.201.234.24:18759

[11/14/13 14:50:28.122 UTC 702fc3 8528] f84f.57ca.3860 Received LWAPP Up event for AP f84f.57ca.3860 slot 0!

[11/14/13 14:50:28.122 UTC 702fc4 8528] f84f.57ca.3860 Radio state change for slot: 0 state: 2 cause: 0 detail cause: 0

[11/14/13 14:50:28.122 UTC 702fc5 8528] f84f.57ca.3860 Change State Event Response sent to 10.201.234.24:18759

[11/14/13 14:50:28.122 UTC 702fc6 8528] f84f.57ca.3860 CAPWAP State: Run

[11/14/13 14:50:28.122 UTC 702fc7 8528] f84f.57ca.3860 Sending the remaining config to AP 10.201.234.24:18759

[11/14/13 14:50:28.122 UTC 702fc8 8528] f84f.57ca.3860 AP Going to RUN 10.201.234.24: ConcurrentJoins: 0

[11/14/13 14:50:28.122 UTC 702fc9 8528] f84f.57ca.3860 **Configuration update**

request for Init VAP-DATA for slot 1 sent to 10.201.234.24:18759

[11/14/13 14:50:28.122 UTC 702fca 8528] f84f.57ca.3860 Configuration update request for configuring association limit params sent to 10.201.234.24:18759

[11/14/13 14:50:28.122 UTC 702fcb 8528] f84f.57ca.3860 Configuration update request for Band Select Cfg sent to 10.201.234.24:18759

[11/14/13 14:50:28.122 UTC 702fcc 8528] f84f.57ca.3860 Configuration update request for HaConfig message sent to 10.201.234.24:18759

[11/14/13 14:50:28.123 UTC 702fcd 8528] CAPWAP: No update, will insert f84f.57ca.3860

[11/14/13 14:50:28.123 UTC 702fce 8528] capwap opaque data f84f.57ca.3860 length = 0

[11/14/13 14:50:28.124 UTC 702fcf 8528] CAPWAP HA insert f84f.57ca.3860

[11/14/13 14:50:28.124 UTC 702fd0 8528] CAPWAP HA insert f84f.57ca.3860

[11/14/13 14:50:28.124 UTC 702fd1 8528] f84f.57ca.3860 Configuration update request for PHY payload sent to 10:201:234:24

[11/14/13 14:50:28.126 UTC 702fd2 8528] f84f.57ca.3860 **Configuration Update Response** from 10.201.234.24:18759

[11/14/13 14:50:28.126 UTC 702fd3 8528] f84f.57ca.3860 Configuration update request for RrmInterferenceCtrl payload sent to 10:201:234:24

[11/14/13 14:50:28.126 UTC 702fd4 8528] f84f.57ca.3860 Configuration update request for RrmNeighbourCtrl payload sent to 10.201.234.24

[11/14/13 14:50:28.126 UTC 702fd5 8528] f84f.57ca.3860 Configuration update request for RrmReceiveCtrl payload sent to 10:201:234:24

[11/14/13 14:50:28.126 UTC 702fd6 8528] f84f.57ca.3860 Configuration update request for CcxRmMeas payload sent to 10.201.234.24

[11/14/13 14:50:28.132 UTC 702fd7 8528] f84f.57ca.3860 Change State Event Request from 10.201.234.24:18759

[11/14/13 14:50:28.132 UTC 702fd8 8528] f84f.57ca.3860 Radio state change for slot: 1 state: 2 cause: 0 detail cause: 0

[11/14/13 14:50:28.132 UTC 702fd9 8528] f84f.57ca.3860 Change State Event Response sent to 10.201.234.24:18759

[11/14/13 14:50:28.132 UTC 702fda 8528] f84f.57ca.3860 CAPWAP State: Run

[11/14/13 14:50:28.132 UTC 702fdb 8528] f84f.57ca.3860 Sending the remaining config to AP 10.201.234.24:18759

[11/14/13 14:50:28.133 UTC 702fdc 8528] f84f.57ca.3860 Configuration update request for qos pm payload payload sent to 10.201.234.24:18759

[11/14/13 14:50:28.133 UTC 702fdd 8528] f84f.57ca.3860 Received LWAPP Up event for AP f84f.57ca.3860 slot 1!

[11/14/13 14:50:28.133 UTC 702fde 8528] f84f.57ca.3860 Configuration update request for PHY payload sent to 10:201:234:24

[11/14/13 14:50:28.133 UTC 702fdf 8528] f84f.57ca.3860 Configuration update request for RrmInterferenceCtrl payload sent to 10:201:234:24

[11/14/13 14:50:28.133 UTC 702fe0 8528] f84f.57ca.3860 Configuration update request for RrmNeighbourCtrl payload sent to 10.201.234.24

[11/14/13 14:50:28.134 UTC 702fe1 8528] f84f.57ca.3860 Configuration update request for RrmReceiveCtrl payload sent to 10:201:234:24

[11/14/13 14:50:28.134 UTC 702fe2 8528] f84f.57ca.3860 Configuration update request for CcxRmMeas payload sent to 10.201.234.24

[11/14/13 14:50:28.188 UTC 702fe3 8528] f84f.57ca.3860 Configuration Update Response from 10.201.234.24:18759

[11/14/13 14:50:28.188 UTC 702fe4 8528] f84f.57ca.3860 Change State Event Request from 10.201.234.24:18759

[11/14/13 14:50:28.188 UTC 702fe5 8528] f84f.57ca.3860 Change State Event Response sent to 10.201.234.24:18759

[11/14/13 14:50:28.188 UTC 702fe6 8528] f84f.57ca.3860 CAPWAP State: Run

[11/14/13 14:50:28.188 UTC 702fe7 8528] f84f.57ca.3860 Sending the remaining config to AP 10.201.234.24:18759

[11/14/13 14:50:28.194 UTC 702fe8 8528] f84f.57ca.3860 Configuration Update Response from 10.201.234.24:18759

[11/14/13 14:50:28.194 UTC 702fe9 8528] f84f.57ca.3860 **WTP Event Request** from 10.201.234.24:18759

[11/14/13 14:50:28.194 UTC 702fea 8528] f84f.57ca.3860 **WTP Event Response** sent to 10.201.234.24:18759

Это сообщение не помогает находить основную причину проблемы. Однако трассировка показывает это сообщение.

Трассировка #show передает AP группы

[11/14/13 14:50:27.869 UTC 702f94 8528] f84f.57ca.3860 **Configuration Status** from 10.201.234.24:18759

[11/14/13 14:50:27.870 UTC 702f95 8528] f84f.57ca.3860 **CAPWAP State: Configure**

[11/14/13 14:50:27.870 UTC 702f96 8528] f84f.57ca.3860 New unsupported Payload 254 in message from AP f84f.57ca.3860, Return SUCCESS

[11/14/13 14:50:27.870 UTC 702f97 8528] f84f.57ca.3860 Decoding new unsupported Payload 254 in message from AP f84f.57ca.3860, Return SUCCESS

[11/14/13 14:50:27.870 UTC 702f98 8528] Invalid channel 11 spacificied for the AP AP2602I-1, slotId = 0

[11/14/13 14:50:27.870 UTC 702f99 8528] Invalid channel 56 spacificied for the AP AP2602I-1, slotId = 1

[11/14/13 14:50:27.870 UTC 702f9a 8528] f84f.57ca.3860 Updating IP info for AP f84f.57ca.3860 -- static 0, 10.201.234.24/255.255.255.224, gtw 10.201.234.2

[11/14/13 14:50:27.870 UTC 702f9b 8528] f84f.57ca.3860 Updating IP 10.201.234.24 ==> 10.201.234.24 for AP f84f.57ca.3860

|
[11/14/13 14:50:27.870 UTC 702fab 8528] f84f.57ca.3860 LWAPP message validation

failed for SPAM Vendor Specific Payload(104) in message of len=7 from AP
f84f.57ca.3860

[11/14/13 14:50:27.870 UTC 702fac 8528] f84f.57ca.3860 Failed to validate vendor
specific message element

[11/14/13 14:50:27.871 UTC 702fad 8528] f84f.57ca.3860 **Setting MTU to 1485**

[11/14/13 14:50:27.871 UTC 702fae 8528] f84f.57ca.3860 Platform not Supported,
exiting Load Balancer function

[11/14/13 14:50:27.871 UTC 702faf 8528] load balancer rc=4 for AP 10.201.234.24,
IIF ID:0x00d2a98000000796

[11/14/13 14:50:27.871 UTC 702fb0 8528] opaque data size 0 with capwap interface
create f84f.57ca.3860

[11/14/13 14:50:27.871 UTC 702fb1 8528] spiCapwapParams->
data_tunnel.opaque_data.opaque_data_len: 0

[11/14/13 14:50:27.871 UTC 702fb2 8528] f84f.57ca.3860 Data Tunnel Create timer
started for 240 seconds timeout

[11/14/13 14:50:27.871 UTC 702fb3 8528] f84f.57ca.3860 **Data Tunnel created -
tunnel type NON_CRYPTO**, load balancer support Not supported, tunnel mtu 1449,

anc_sw_id 0, anc_asic_id 0, res_sw_id 0, res_asic_id 0

anc_wp_iif_id 0x0000000000000000, res_wp_iif_id 0x0000000000000000

[11/14/13 14:50:27.871 UTC 702fb4 8528] f84f.57ca.3860 Not ready to send Config
Status Response to AP 10.201.234.24 as SPI ACK is not received

[11/14/13 14:50:27.871 UTC 702fb5 8528] f84f.57ca.3860 AP f84f.57ca.3860
associated. Last AP failure was due to Configuration changes,reason:
controller reboot command

[11/14/13 14:50:27.871 UTC 30e6 260] [CAPWAP]: CAPWAP data tunnel create message.

[11/14/13 14:50:27.871 UTC 30e7 260] [CAPWAP]: capwap_data_tunnel_create called

[11/14/13 14:50:27.871 UTC 30e8 260] [CAPWAP]: Data tunnel id = 0xd2a98000000796

[11/14/13 14:50:27.871 UTC 30e9 260] [CAPWAP]: Tunnel Entry not found for AP
(10.201.234.24, 18759)

[11/14/13 14:50:27.873 UTC 30ea 260] [CAPWAP]: CAPWAP IDB init complete

[11/14/13 14:50:27.882 UTC 30eb 260] [CAPWAP]: capwap_interface_status_update:
tunnel 0xd2a98000000796 status 0

[11/14/13 14:50:27.882 UTC 30ec 260] [CAPWAP]: csb pd flag 0 opaque_data_len 0
attr opaque_data 0x00000000

[11/14/13 14:50:27.882 UTC 30ed 260] [CAPWAP]: Send capwap_data_tunnel_status_update
0 Slot-Unit 1 Unit 1 for iif_id 0xd2a98000000796 to WCM.

[11/14/13 14:50:27.882 UTC 30ee 260] [CAPWAP]: (capwap_process_fed_results) CAPWAP
FED result (0) for IIF ID: 0xd2a98000000796

[11/14/13 14:50:27.882 UTC 702fb6 8528

Received CAPWAP Tunnel SPI update opaque size 0

[11/14/13 14:50:27.882 UTC 702fb7 8528] opaque data len 0 with capwap server update

[11/14/13 14:50:27.883 UTC 702fb8 8528] f84f.57ca.3860 SPI ACK : Capwap Data Tunnel create successful for iifid:0x00d2a98000000796 AP:10.201.234.24

[11/14/13 14:50:27.883 UTC 702fb9 8528]

Received CAPWAP interface update opaque len 0

[11/14/13 14:50:27.883 UTC 702fba 8528] **SPI IifId ACK: Capwap Data Tunnel Created Successfully for IifId: 0x00d2a98000000796 AP: 10.201.234.24**

[11/14/13 14:50:27.883 UTC 702fbb 8528] f84f.57ca.3860 **OK to send Config Status Response to AP 10.201.234.24**

[11/14/13 14:50:27.888 UTC 30ef 260] [CAPWAP]: Notify PM (done).

[11/14/13 14:50:27.888 UTC 30f0 260] [CAPWAP]: SNMP Register: Ca1 HWIDB 32f44570

[11/14/13 14:50:27.888 UTC 30f1 260] [CAPWAP]: capwap_port_hashitem added: slot 1 slotunit 24 vlan 1104

[11/14/13 14:50:27.888 UTC 30f2 260] [CAPWAP]: 7c69.f604.9460 is AP's mac addr

[11/14/13 14:50:27.932 UTC 702fbc 8528] Sending multicast payload to ap AP2602I-1, mcast_mode 0, mcast group 0.0.0.0

[11/14/13 14:50:27.933 UTC 702fbd 8528] f84f.57ca.3860 Config status response sent to 10.201.234.24:18759

[11/14/13 14:50:27.933 UTC 702fbe 8528] f84f.57ca.3860 Configuration Status Response sent to 10:201:234:24

[11/14/13 14:50:27.933 UTC 702fbf 8528] f84f.57ca.3860 Configuration update request for Band Select Cfg sent to 10.201.234.24:18759

[11/14/13 14:50:27.933 UTC 702fc0 8528] f84f.57ca.3860 Configuration update request for HaConfig message sent to 10.201.234.24:18759

[11/14/13 14:50:27.934 UTC 702fc1 8528] f84f.57ca.3860 Configuration update request for AP NGWC Qos sent to 10.201.234.24:18759

[11/14/13 14:50:28.121 UTC 702fc2 8528] f84f.57ca.3860 Change State Event Request from 10.201.234.24:18759

[11/14/13 14:50:28.122 UTC 702fc3 8528] f84f.57ca.3860 Received LWAPP Up event for AP f84f.57ca.3860 slot 0!

[11/14/13 14:50:28.122 UTC 702fc4 8528] f84f.57ca.3860 Radio state change for slot: 0 state: 2 cause: 0 detail cause: 0

[11/14/13 14:50:28.122 UTC 702fc5 8528] f84f.57ca.3860 Change State Event Response sent to 10.201.234.24:18759

[11/14/13 14:50:28.122 UTC 702fc6 8528] f84f.57ca.3860 CAPWAP State: Run

[11/14/13 14:50:28.122 UTC 702fc7 8528] f84f.57ca.3860 Sending the remaining config to AP 10.201.234.24:18759

[11/14/13 14:50:28.122 UTC 702fc8 8528] f84f.57ca.3860 AP Going to RUN 10.201.234.24: ConcurrentJoins: 0

[11/14/13 14:50:28.122 UTC 702fc9 8528] f84f.57ca.3860 **Configuration update request** for Init VAP-DATA for slot 1 sent to 10.201.234.24:18759

[11/14/13 14:50:28.122 UTC 702fca 8528] f84f.57ca.3860 Configuration update request for configuring association limit params sent to 10.201.234.24:18759

[11/14/13 14:50:28.122 UTC 702fcb 8528] f84f.57ca.3860 Configuration update request for Band Select Cfg sent to 10.201.234.24:18759

[11/14/13 14:50:28.122 UTC 702fcc 8528] f84f.57ca.3860 Configuration update request for HaConfig message sent to 10.201.234.24:18759

[11/14/13 14:50:28.123 UTC 702fcd 8528] CAPWAP: No update, will insert f84f.57ca.3860

[11/14/13 14:50:28.123 UTC 702fce 8528] capwap opaque data f84f.57ca.3860 length = 0

[11/14/13 14:50:28.124 UTC 702fcf 8528] CAPWAP HA insert f84f.57ca.3860

[11/14/13 14:50:28.124 UTC 702fd0 8528] CAPWAP HA insert f84f.57ca.3860

[11/14/13 14:50:28.124 UTC 702fd1 8528] f84f.57ca.3860 Configuration update request for PHY payload sent to 10:201:234:24

[11/14/13 14:50:28.126 UTC 702fd2 8528] f84f.57ca.3860 **Configuration Update Response** from 10.201.234.24:18759

[11/14/13 14:50:28.126 UTC 702fd3 8528] f84f.57ca.3860 Configuration update request for RrmInterferenceCtrl payload sent to 10:201:234:24

[11/14/13 14:50:28.126 UTC 702fd4 8528] f84f.57ca.3860 Configuration update request for RrmNeighbourCtrl payload sent to 10.201.234.24

[11/14/13 14:50:28.126 UTC 702fd5 8528] f84f.57ca.3860 Configuration update request for RrmReceiveCtrl payload sent to 10:201:234:24

[11/14/13 14:50:28.126 UTC 702fd6 8528] f84f.57ca.3860 Configuration update request for CcxRmMeas payload sent to 10.201.234.24

[11/14/13 14:50:28.132 UTC 702fd7 8528] f84f.57ca.3860 Change State Event Request from 10.201.234.24:18759

[11/14/13 14:50:28.132 UTC 702fd8 8528] f84f.57ca.3860 Radio state change for slot: 1 state: 2 cause: 0 detail cause: 0

[11/14/13 14:50:28.132 UTC 702fd9 8528] f84f.57ca.3860 Change State Event Response sent to 10.201.234.24:18759

[11/14/13 14:50:28.132 UTC 702fda 8528] f84f.57ca.3860 CAPWAP State: Run

[11/14/13 14:50:28.132 UTC 702fdb 8528] f84f.57ca.3860 Sending the remaining config to AP 10.201.234.24:18759

[11/14/13 14:50:28.133 UTC 702fdc 8528] f84f.57ca.3860 Configuration update request for qos pm payload payload sent to 10.201.234.24:18759

[11/14/13 14:50:28.133 UTC 702fdd 8528] f84f.57ca.3860 Received LWAPP Up event for AP f84f.57ca.3860 slot 1!

[11/14/13 14:50:28.133 UTC 702fde 8528] f84f.57ca.3860 Configuration update request for PHY payload sent to 10:201:234:24

[11/14/13 14:50:28.133 UTC 702fdf 8528] f84f.57ca.3860 Configuration update request for RrmInterferenceCtrl payload sent to 10:201:234:24

[11/14/13 14:50:28.133 UTC 702fe0 8528] f84f.57ca.3860 Configuration update request for RrmNeighbourCtrl payload sent to 10.201.234.24

[11/14/13 14:50:28.134 UTC 702fe1 8528] f84f.57ca.3860 Configuration update request for RrmReceiveCtrl payload sent to 10:201:234:24

[11/14/13 14:50:28.134 UTC 702fe2 8528] f84f.57ca.3860 Configuration update request for CcxRmMeas payload sent to 10.201.234.24

[11/14/13 14:50:28.188 UTC 702fe3 8528] f84f.57ca.3860 Configuration Update Response from 10.201.234.24:18759

[11/14/13 14:50:28.188 UTC 702fe4 8528] f84f.57ca.3860 Change State Event Request from 10.201.234.24:18759

[11/14/13 14:50:28.188 UTC 702fe5 8528] f84f.57ca.3860 Change State Event Response sent to 10.201.234.24:18759

[11/14/13 14:50:28.188 UTC 702fe6 8528] f84f.57ca.3860 CAPWAP State: Run

[11/14/13 14:50:28.188 UTC 702fe7 8528] f84f.57ca.3860 Sending the remaining config to AP 10.201.234.24:18759

[11/14/13 14:50:28.194 UTC 702fe8 8528] f84f.57ca.3860 Configuration Update Response from 10.201.234.24:18759

[11/14/13 14:50:28.194 UTC 702fe9 8528] f84f.57ca.3860 WTP Event Request from 10.201.234.24:18759

[11/14/13 14:50:28.194 UTC 702fea 8528] f84f.57ca.3860 WTP Event Response sent to 10.201.234.24:18759

Общие практические указания

Этот раздел предоставляет некоторые полезные советы.

- При начале процесса устранения неполадок очистите ранее собранные трассировки для определенной функции. В этом случае, сарвар, AP группы и все фильтруемые трассировки.
Set trace # управляет capwapSet trace # AP группы контроля
Set trace # управляет sys-filtered-trace >>, это очищает фильтруемые трассировки и не может быть выполнено на основе на функцию
- Соединение AP на установившихся контроллерах доступа использует радио-МАС-адрес AP. Так, когда вы устанавливаете фильтр для трассировки, используете радио-или основной МАС-адрес AP. Введите команду **show ap join stats summary** для обнаружения радио-МАС-адреса.
- Проблемы с сертификатами обрабатываются IOSd и требуют использования отладок, не трассировок, для дальнейшего диагноза.
#debug крипто-API pki#debug крипто-обратные вызовы pkiCrypto pki server #debug#debug крипто-транзакции pki#debug крипто-сообщения pki