

配置在Cisco IOS的TCP拦截？/IOS-XE路由器

目录

[简介](#)

[先决条件](#)

[要求](#)

[使用的组件](#)

[问题](#)

[对于ISR G1路由器](#)

[对于ISR G2路由器](#)

[对于ISR G3路由器](#)

[对于ASR1k路由器](#)

[解决方案](#)

[验证](#)

[故障排除](#)

[相关信息](#)

简介

本文描述需求启用在思科IOS/IOS-XE路由器的思科传输控制协议(TCP)截取功能。TCP拦截要求保护从TCP的TCP服务器同步(SYN) -溢出攻击，拒绝服务攻击的类型。

先决条件

要求

本文档没有任何特定的要求。

使用的组件

本文档不限于特定的软件和硬件版本。

本文档中的信息都是基于特定实验室环境中的设备编写的。本文档中使用的所有设备最初均采用原始（默认）配置。如果您的网络实际，请保证您了解所有命令潜在影响。

问题

您无法配置‘ip TCP拦截’在ISR G1/G2/G3和ASR1k路由器。您能看到日志此处：

- 对于ISR G1路由器

```
Router#show ver
```

Cisco IOS® Software, 2800 Software (C2800NM-IPBASEK9-M), Version 15.1(4)M12a, RELEASE SOFTWARE (fcl)

Router uptime is 14 minutes

System returned to ROM by reload at 07:45:56 UTC Tue Nov 1 2016

System image file is "flash:c2800nm-ipbasek9-mz.151-4.M12a(1).bin"

Last reload type: Normal Reload

<omitted>

Cisco 2811 (revision 1.0) with 512000K/12288K bytes of memory.

Processor board ID FHK1404F3U8

2 FastEthernet interfaces

1 Channelized E1/PRI port

DRAM configuration is 64 bits wide with parity enabled.

239K bytes of non-volatile configuration memory.

250368K bytes of ATA CompactFlash (Read/Write)

License Info:

License UDI:

```
-----  
Device#   PID           SN  
-----  
*0        CISCO2811     FHK1404F3U8
```

Configuration register is 0x2102

Router# config t

Enter configuration commands, one per line. End with CNTL/Z.

Router(config)#ip tcp ?

RST-count	Configure RST throttle count
async-mobility	Configure async-mobility
chunk-size	TCP chunk size
ecn	Enable Explicit Congestion Notification
mss	TCP initial maximum segment size
path-mtu-discovery	Enable path-MTU discovery on new TCP connections
queuemax	Maximum queue of outgoing TCP packets
selective-ack	Enable TCP selective-ACK
synwait-time	Set time to wait on new TCP connections
timestamp	Enable TCP timestamp option
window-size	TCP window size

• 对于ISR G2路由器

Router#show ver

Cisco IOS® Software, C1900 Software (C1900-UNIVERSALK9-M), Version 15.4(3)M4, RELEASE SOFTWARE (fcl)

<omitted>

```
Router uptime is 1 minute
System returned to ROM by reload at 10:28:40 UTC Mon Oct 31 2016
System image file is "flash:c1900-universalk9-mz.SPA.154-3.M4.bin"
Last reload type: Normal Reload
Last reload reason: Reload Command
```

<omitted>

```
Cisco CISC01941/K9 (revision 1.0) with 2543552K/77824K bytes of memory.
Processor board ID FHK141571QW
4 FastEthernet interfaces
```

<omitted>

```
Technology Package License Information for Module:'c1900'
```

```
-----
Technology      Technology-package      Technology-package
                Current                Type                Next reboot
-----
ipbase          ipbasek9                Permanent          ipbasek9
security        securityk9              RightToUse         securityk9
data            None                    None               None
NtwkEss         None                    None               None
```

```
Configuration register is 0x2102
```

```
Router# config t
```

```
Enter configuration commands, one per line. End with CNTL/Z.
```

```
Router(config)#ip tcp ?
```

```
RST-count          Configure RST throttle count
async-mobility     Configure async-mobility
chunk-size         TCP chunk size
ecn                Enable Explicit Congestion Notification
keepalive          Configure TCP Keepalive parameters
mss                TCP initial maximum segment size
path-mtu-discovery Enable path-MTU discovery on new TCP connections
queuemax           Maximum queue of outgoing TCP packets
selective-ack      Enable TCP selective-ACK
synwait-time       Set time to wait on new TCP connections
timestamp          Enable TCP timestamp option
window-size        TCP window size
```

• 对于ISR G3路由器

```
Router#sh ver
```

```
Cisco IOS® XE Software, Version 03.15.02.S - Standard Support Release
Cisco IOS® Software, ISR Software (X86_64_LINUX_IOS® D-UNIVERSALK9-M), Version 15.5(2)S2,
RELEASE SOFTWARE (fc1)
Technical Support: http://www.cisco.com/techsupport
Copyright (c) 1986-2015 by Cisco Systems, Inc.
Compiled Fri 16-Oct-15 18:00 by mcpre
```

<omitted>

```
Router uptime is 7 minutes
```

Uptime for this control processor is 8 minutes
System returned to ROM by reload
System image file is "bootflash:isr4300-universalk9.03.15.02.S.155-2.S2-std.SPA.bin"
Last reload reason: Reload Command

<omitted>

Technology Package License Information:

```
-----  
Technology      Technology-package      Technology-package  
                Current      Type                Next reboot  
-----  
appx            None                None                None  
uc              uck9                Permanent           uck9  
security        securityk9          EvalRightToUse     securityk9  
ipbase          ipbasek9            Permanent           ipbasek9  
-----
```

cisco ISR4331/K9 (1RU) processor with 1665776K/6147K bytes of memory.
Processor board ID FDO2012A0AT
3 Gigabit Ethernet interfaces
32768K bytes of non-volatile configuration memory.
4194304K bytes of physical memory.
3223551K bytes of flash memory at bootflash:.

Configuration register is 0x2102

Router# config t

Enter configuration commands, one per line. End with CNTL/Z.

Router(config)#ip tcp ?

```
RST-count          Configure RST throttle count  
async-mobility     Configure async-mobility  
chunk-size         TCP chunk size  
ecn                Enable Explicit Congestion Notification  
keepalive          Configure TCP Keepalive parameters  
mss                TCP initial maximum segment size  
path-mtu-discovery Enable path-MTU discovery on new TCP connections  
queuemax           Maximum queue of outgoing TCP packets  
selective-ack      Enable TCP selective-ACK  
synwait-time       Set time to wait on new TCP connections  
timestamp          Enable TCP timestamp option  
window-size        TCP window size
```

• 对于ASR1k路由器

Router#show version

```
Cisco IOS® XE Software, Version 03.16.01a.S - Extended Support Release  
Cisco IOS® Software, ASR1000 Software (X86_64_LINUX_IOSD-UNIVERSAL-M), Version 15.5(3)S1a,  
RELEASE SOFTWARE (fcl)  
Technical Support: http://www.cisco.com/techsupport  
Copyright (c) 1986-2015 by Cisco Systems, Inc.  
Compiled Wed 04-Nov-15 13:57 by mcpre
```

<omitted>

```
Router uptime is 1 minute
Uptime for this control processor is 2 minutes
System returned to ROM by reload
System image file is "bootflash:asr1001x-universal.03.16.01a.S.155-3.S1a-ext.SPA.bin"
Last reload reason: PowerOn
```

```
License Level: ipbase
License Type: Permanent
Next reload license Level: ipbase
```

```
cisco ASR1001-X (1NG) processor (revision 1NG) with 3753592K/6147K bytes of memory.
Processor board ID FXS1925Q33T
6 Gigabit Ethernet interfaces
2 Ten Gigabit Ethernet interfaces
32768K bytes of non-volatile configuration memory.
8388608K bytes of physical memory.
6684671K bytes of eUSB flash at bootflash:
```

```
Configuration register is 0x2102
Router#config t
Enter configuration commands, one per line. End with CNTL/Z.
```

```
Router(config)#ip tcp ?
RST-count          Configure RST throttle count
async-mobility     Configure async-mobility
chunk-size         TCP chunk size
ecn                Enable Explicit Congestion Notification
keepalive          Configure TCP Keepalive parameters
mss               TCP initial maximum segment size
path-mtu-discovery Enable path-MTU discovery on new TCP connections
queuemax          Maximum queue of outgoing TCP packets
selective-ack     Enable TCP selective-ACK
synwait-time      Set time to wait on new TCP connections
timestamp         Enable TCP timestamp option
window-size       TCP window size
```

解决方案

为了启用功能TCP拦截，您会需要：

- **entbase**特性组最低在ISR G1路由器的
- 在ISR G2和G3系列路由器的Appxk9/ Datak9
- 在ASR1k系列路由器的最低的advipservices许可证

一旦启用在平台的需要的许可证，您能配置同样：

```
Router(config)#ip tcp ?
RST-count          Configure RST throttle count
async-mobility     Configure async-mobility
chunk-size         TCP chunk size
ecn                Enable Explicit Congestion Notification
intercept          Enable TCP intercepting
keepalive          Configure TCP Keepalive parameters
mss               TCP initial maximum segment size
path-mtu-discovery Enable path-MTU discovery on new TCP connections
queuemax          Maximum queue of outgoing TCP packets
selective-ack     Enable TCP selective-ACK
synwait-time      Set time to wait on new TCP connections
timestamp         Enable TCP timestamp option
```

[验证](#)

当前没有可用于此配置的验证过程。

[故障排除](#)

目前没有针对此配置的故障排除信息。

[相关信息](#)

- http://www.cisco.com/c/en/us/td/docs/ios/12_2/security/configuration/guide/fsecur_c/scfdenl.html
- [技术支持和文档 - Cisco Systems](#)