

配置 GRE 隧道的 CET 加密

目录

[简介](#)

[先决条件](#)

[要求](#)

[使用的组件](#)

[规则](#)

[配置](#)

[网络图](#)

[配置](#)

[验证](#)

[故障排除](#)

[相关信息](#)

简介

要配置Cisco加密技术(CET)在隧道上的加密，您必须将加密配置在隧道接口上。另外，您必须配置在朝向通道的最后的目的地物理接口上配置。

注意： CET加密当前是[生命周期结束](#)。IPSec是迁移的推荐的加密机制。

先决条件

要求

本文档没有任何特定的要求。

使用的组件

本文档不限于特定的软件和硬件版本。

规则

有关文档规则的详细信息，请参阅 [Cisco 技术提示规则](#)。

配置

本部分提供有关如何配置本文档所述功能的信息。

注意： 要查找本文档所用命令的其他信息，请使用[命令查找工具](#)（[仅限注册用户](#)）。

网络图

本文档使用以下网络设置：

网络图说明

- 8.8.8.8，在r3-4k后和7.7.7.4，在R6-2500后，是终端站。当他们互相ping时，流量通过通道。
- 通用路由封装(GRE)隧道配置了回环接口作为隧道源及目的地。
- 流量通过通道也加密。实施该功能要求对隧道流量进行加密，并且必须将加密映射附加到隧道接口和实际出局接口上。

配置

本文档使用以下配置：

- [r3-4k](#)
- [R1-AGS](#)
- [R6-2500](#)

r3-4k

```
hostname r3-4k
!
crypto public-key r6-2500 02014544
  F3681B5D 32372A19 0C0CCC4B E707F829 D882CF30 A9B4DBE3
E1911E9C F6A9E162
  732558DF A20FEFAD 2ACC400E 8DDB10B1 3566FA3A E55A9BBE
00916AAD 20A0C75C
quit
!
crypto map my_crypto_map 10
  set algorithm 40-bit-des
  set peer r6-2500
  match address 128
!
interface Loopback0
  ip address 1.1.6.1 255.255.255.0
!
interface Tunnel0
  ip address 5.5.5.1 255.255.255.0
  tunnel source Loopback0
  tunnel destination 2.2.6.3
  crypto map my_crypto_map
!
interface Ethernet0
  ip address 1.1.1.1 255.255.255.0
  description inside interface
  media-type 10BaseT
  crypto map my_crypto_map
!
!
interface Serial0
  encapsulation frame-relay
  no ip route-cache
!
interface Serial0.1 point-to-point
  description outside interface
  ip address 8.8.8.1 255.255.255.0
```

```
frame-relay interface-dlci 100
!
!ip classless
ip route 0.0.0.0 0.0.0.0 1.1.1.2
ip route 7.0.0.0 255.0.0.0 5.5.5.2

access-list 128 permit gre host 1.1.6.1 host 2.2.6.3
!
```

R1-AGS

```
!
hostname R1-AGS
!
interface Ethernet0
 ip address 1.1.1.2 255.255.255.0
!
interface Serial1
 ip address 2.2.5.2 255.255.255.0
!
ip classless
ip route 1.0.0.0 255.0.0.0 1.1.1.1
ip route 2.0.0.0 255.0.0.0 2.2.5.3
```

R6-2500

```
hostname R6-2500
!
crypto public-key r3-4k 04D6265A
 512A7D84 43C348B7 959D2FE2 3122B285 FDA2A362 7272A835
84D03134 DB160DE1
 27CA2D24 D6C23EFE 3BE25A95 D62EA30B 0F2C3BA8 9AB6DB82
D8127238 266AC987
quit
!
crypto map my_crypto_map 10
 set algorithm 40-bit-des
 set peer r3-4k
 match address 128
!
interface Loopback0
 ip address 2.2.6.3 255.255.255.0
!
interface Tunnel0
 ip address 5.5.5.2 255.255.255.0
 tunnel source Loopback0
 tunnel destination 1.1.6.1
 crypto map my_crypto_map
!
interface Ethernet 0
 description inside interface
 ip address 7.7.7.3 255.255.255.0
!
interface Serial0
 description outside interface
 ip address 2.2.5.3 255.255.255.0
 crypto map my_crypto_map
!
ip classless
ip route 0.0.0.0 0.0.0.0 2.2.5.2
ip route 7.0.0.0 255.0.0.0 7.7.7.0
ip route 8.0.0.0 255.0.0.0 5.5.5.1
!
access-list 128 permit gre host 2.2.6.3 host 1.1.6.1
```

验证

当前没有可用于此配置的验证过程。

故障排除

目前没有针对此配置的故障排除信息。

相关信息

- [IPSec 支持页面](#)
- [技术支持 - Cisco Systems](#)