

在安全管理设备上禁用/启用新GUI标语

目录

[简介](#)

[NGUI背景](#)

[禁用横幅](#)

[重新启用横幅](#)

简介

本文档介绍如何在安全管理设备(SMA)上禁用新网络界面的过程。

NGUI背景

从AsyncOS 12.0开始，SMA设备上引入了新的Web界面。通过实施该功能，用户能够在网页顶部（当他们登录到旧版网络界面时）看到新标语，点击该标语将用户路由到新的网络界面。此处可以看到横幅的表示：



注意：子命令NGUIBANNER当前仅在SMA上可用，在邮件安全设备(ESA)上不可用。

禁用横幅

您必须通过安全外壳(SSH)会话连接到设备。连接后，登录CLI并使用命令adminaccessconfig禁用标语，如下所示：

```
sma.cisco.com> adminaccessconfig
```

```
Select the operation you want to perform:
```

```
BANNER - Configure pre-login message (banner) for the appliance administrator login.
WELCOME - Configure welcome message (post-login banner) for the appliance administrator login.
IPACCESS - Configure IP-based access for appliance administrative interface.
CSRF - Configure web UI Cross-Site Request Forgeries protection.
NGUIBANNER - Enable/Disable the Next Generation User Interface Banner.
XSS - Configure Cross-Site Scripting Attack protection.
ENCRYPTCONFIG - Configure encryption of sensitive data in the appliance.
HOSTHEADER - Configure option to use host header in HTTP requests.
TIMEOUT - Configure GUI and CLI session inactivity timeout.
[> nguibanner
```

```
The Next Generation User Interface is currently enabled.
```

```
Would you like to enable Next Generation User Interface? [Y]N.
```

```
sma.cisco.com> commit
```

提交更改后，GUI上将不显示横幅。

重新启用横幅

要重新启用标语，您必须遵循相同的命令链，但是，这次您必须通过键入Y来启用标语，如下所示：

```
[ ]> nguibanner
```

```
Next Generation User Interface is currently disabled.
```

```
Would you like to enable Next Generation User Interface ? [N]Y
```

```
sma.cisco.com> commit
```