

配置在SPA2102电话适配器的特别铃声

目标

不同的用户能独特配置铃声和修改在处理呼叫人的功能。

本文目标将解释如何配置在SPA2102电话适配器的特别铃声。

可适用的设备

- SPA2102

逐步程序

第 1 步：在SPA2102电话适配器的基于web的工具中，请登陆作为高级用户并且去语音> User1并且移下来到环设置地区。

LINKSYS®
A Division of Cisco Systems, Inc.

Linksys Phone Adapter Configuration

Router **Voice**

Info | System **User 1** | User 2 | [Admin Login](#) | [basic](#) | [advanced](#)

Call Forward Settings

Cfwd All Dest:	<input type="text"/>	Cfwd Busy Dest:	<input type="text"/>
Cfwd No Ans Dest:	<input type="text"/>	Cfwd No Ans Delay:	20

Selective Call Forward Settings

Cfwd Sel1 Caller:	<input type="text"/>	Cfwd Sel1 Dest:	<input type="text"/>
Cfwd Sel2 Caller:	<input type="text"/>	Cfwd Sel2 Dest:	<input type="text"/>
Cfwd Sel3 Caller:	<input type="text"/>	Cfwd Sel3 Dest:	<input type="text"/>
Cfwd Sel4 Caller:	<input type="text"/>	Cfwd Sel4 Dest:	<input type="text"/>
Cfwd Sel5 Caller:	<input type="text"/>	Cfwd Sel5 Dest:	<input type="text"/>
Cfwd Sel6 Caller:	<input type="text"/>	Cfwd Sel6 Dest:	<input type="text"/>
Cfwd Sel7 Caller:	<input type="text"/>	Cfwd Sel7 Dest:	<input type="text"/>
Cfwd Sel8 Caller:	<input type="text"/>	Cfwd Sel8 Dest:	<input type="text"/>
Cfwd Last Caller:	<input type="text"/>	Cfwd Last Dest:	<input type="text"/>
Block Last Caller:	<input type="text"/>	Accept Last Caller:	<input type="text"/>

步骤2. 设置一默认振铃并且从1-9选择编号从下拉菜单。

Ring Settings

Default Ring:	1	Default CWT:	1
Hold Reminder Ring:	1	Call Back Ring:	7
Cfwd Ring Splash Len:	<input type="text"/>	Cblk Ring Splash Len:	0
VMWI Ring Splash Len:	<input type="text"/>		

[Admin Login](#) | [basic](#) | [advanced](#)

步骤3.设置 暂挂提示环并且从1-9选择编号从下拉菜单。这是呼叫人将听到的环，当呼叫被保持暂挂时。并且，请选择暂挂中将提醒您呼叫的环模式，当电话挂机时。

The screenshot shows the 'Ring Settings' configuration page. The 'Hold Reminder Ring' dropdown menu is open, displaying options from 1 to 9 and 'none'. The number '8' is selected and highlighted with a red circle. Other settings include Default Ring: 1, Default CWT: 1, Call Back Ring: 7, Cbld Ring Splash Len: 0, and VMWI Ring Splash Len: 0. Buttons for 'Undo All Changes' and 'Submit All Changes' are visible at the bottom.

步骤4.，当传送时，请设置一 Cfwd环飞溅LEN并且输入环飞溅的期限呼叫。范围是从0到10秒。

The screenshot shows the 'Ring Settings' configuration page. The 'Cfwd Ring Splash Len' input field is highlighted with a red circle and contains the value '0'. Other settings include Default Ring: 1, Default CWT: 1, Call Back Ring: 7, and Cbld Ring Splash Len: 0. Buttons for 'Undo All Changes' and 'Submit All Changes' are visible at the bottom.

步骤5.请设置一 VMWI环飞溅LEN并且输入环飞溅的期限，当新的消息到达时，在语音邮件等待的征兆(VMWI)前信号适用。范围是从0到10秒。

The screenshot shows the 'Ring Settings' configuration page. The 'VMWI Ring Splash Len' input field is highlighted with a red circle and contains the value '0'. Other settings include Default Ring: 1, Default CWT: 1, Call Back Ring: 7, and Cbld Ring Splash Len: 0. Buttons for 'Undo All Changes' and 'Submit All Changes' are visible at the bottom.

步骤6.设置默认CWT环并且从1-9选择编号从下拉菜单。这是呼叫人将听到的环，当呼叫继续进行等待时。

The screenshot shows the 'Ring Settings' configuration page. The 'Default CWT' dropdown menu is open, displaying options from 1 to 9. The number '1' is selected and highlighted with a red circle. Other settings include Default Ring: 1, Hold Reminder Ring: 8, Call Back Ring: 7, Cbld Ring Splash Len: 0, and VMWI Ring Splash Len: 0. Buttons for 'Undo All Changes' and 'Submit All Changes' are visible at the bottom.

步骤7.设置一次呼叫从1-9敲响并且选择编号从下拉菜单。这是呼叫人为呼叫通知将听到的环。

Ring Settings			
Default Ring:	1	Default CWT:	1
Hold Reminder Ring:	8	Call Back Ring:	7
Cfwd Ring Splash Len:	0	Cblk Ring Splash Len:	1
VMWI Ring Splash Len:	0		2
			3
			4
			5
			6
			7
			8
			9
Undo All Changes		Submit All Changes	
Admin Login basic advanced			
Copyright © 1992-2009 Cisco Systems, Inc. All Rights Reserved.			

步骤8. , 当呼叫被阻拦时 , 请设置一 *Cblk* 环飞溅 *LEN* 并且输入环飞溅的期限。范围是从0到10秒。

Ring Settings			
Default Ring:	1	Default CWT:	1
Hold Reminder Ring:	8	Call Back Ring:	7
Cfwd Ring Splash Len:	0	Cblk Ring Splash Len:	0
VMWI Ring Splash Len:	0		
Undo All Changes		Submit All Changes	

步骤9. 点击提交所有更改保存当前设置。

Ring Settings			
Default Ring:	1	Default CWT:	1
Hold Reminder Ring:	8	Call Back Ring:	7
Cfwd Ring Splash Len:	0	Cblk Ring Splash Len:	0
VMWI Ring Splash Len:	0		
Undo All Changes		Submit All Changes	