

5000系列的ASR如何在最初的触发以后确定报警的当前故障率

目录

[问题](#)

[答案](#)

[相关的思科支持社区讨论](#)

问题

如何在最初的触发以后在任何时间确定报警的当前故障率。最初的故障率可以是更加显然的查找，但是一是否可能将发现当前失败速率小时以后？

答案

当最初的SNMP陷阱、日志和报警跟踪受监视阈值的最初的故障率时，可能不是显然的如何获得当前失败速率。在底部“请显示阈值”，指令报告所有报警状况关于在最后轮询间隔的当前失败速率。

```
[local]PDSN> show threshold
Friday June 12 04:39:32 UTC 2015
```

Outstanding alarms:

```
      Threshold Name:    aaa-acct-failure-rate
      Alarm Source:      System
Last Measured: 77% Raise Time: 2015-Jun-11+22:15:05
```

```
[local]PDSN> show thresh
Friday June 12 05:34:04 UTC 2015
```

Outstanding alarms:

```
      Threshold Name:    aaa-acct-failure-rate
Alarm Source: System Last Measured: 65%
      Raise Time:        2015-Jun-11+22:15:05
```

```
[local]PDSN> show thresh
Friday June 12 06:06:07 UTC 2015
```

Outstanding alarms:

```
      Threshold Name:    aaa-acct-failure-rate
      Alarm Source:      System
Last Measured: 61%
      Raise Time:        2015-Jun-11+22:15:05
```

```
[local]PDSN> show alarm outstanding verbose
Friday June 12 04:41:28 UTC 2015
```

Severity	Object	Timestamp	Alarm ID
-----	-----	-----	-----

Alarm Details

Minor Chassis Thursday **June 11 22:15:05** U 5770524519230406656
<28:**aaa-acct-failure-rate**> has reached or exceeded the configured threshold <25%>, the measured value is <32%>. It is detected at <System>.

2015-Jun-11+**22:15:05**.418 [alarmctrl 65201 info] [8/0/5185 <evlogd:0> alarmctrl.c:192] [software internal system critical-info syslog] **Alarm condition:** id 5015057a08690000 (Minor): <28:**aaa-acct-failure-rate**> has reached or exceeded the configured threshold <25%>, the measured value is <32%>. It is detected at <System>.

Thu Jun 11 **22:15:05** 2015 Internal trap notification 222 (**ThreshAAAacctFailRate**) threshold 25% measured value 32%

2015-Jun-12+**07:15:05**.210 [alarmctrl 65200 info] [8/0/5185 <evlogd:0> alarmctrl.c:285] [software internal system critical-info syslog] **Alarm cleared:** id 5015057a08690000: <28:**aaa-acct-failure-rate**> has reached or exceeded the configured threshold <25%>, the measured value is <32%>. It is detected at <System>.

Fri Jun 12 07:15:05 2015 Internal trap notification 223 (**ThreshClearAAAacctFailRate**) threshold 20%**measured value 0%**

[local]PDSN> show threshold Friday June 12 13:45:26 UTC 2015

...

No outstanding alarm