在虛擬化語音瀏覽器中配置SNMP

目錄

<u>簡介</u> 必要條件 <u>需求</u> 採用元件 設定 驗證

簡介

本檔案介紹在虛擬化語音瀏覽器(VVB)中設定和設定SNMP的流程。

必要條件

需求

思科建議您瞭解以下主題:

- VVB
- 客戶語音入口網站(CVP)

採用元件

本文檔中的資訊基於VVB版本11.6.1.10000-14。

本文中的資訊是根據特定實驗室環境內的裝置所建立。文中使用到的所有裝置皆從已清除(預設))的組態來啟動。如果您的網路運作中,請確保您瞭解任何指令可能造成的影響。

設定

步驟1. 轉至Cisco Unified Serviceability頁面。

URL:https://<VVB的IP地址>/ccmservice/

步驟2.單擊Snmp \ V1/V2 \ Community String。



步驟3.在Search Options \ Select Server*;從下拉選單中選擇;按一下查詢,然後按一下Add New。

Alarm • Trace • Tools • Snmp • Help •		
SNMP Community String Configuration		
÷		
Status		
(1) 0 records found.		
-		
Search Options		
Find Community Strings where Name heating with	Server* vom	Eind
(Community Strings where Name begins with any)	Server	
(communicy strings where wante begins with any)		
Search Results		
No active query. Please enter your search criteria using the options above		
Add New		
(i)* - indicates required item		

步驟4.提供社群字串名稱;選擇Host IP Addresses Information(主機IP地址資訊),最後提供相應的訪問許可權。

附註:此處為社群字串名稱、主機IP地址資訊和訪問許可權所做的選擇適用於實驗室設定,在 生產中完成時,應考慮相應的選擇。

<u>A</u> larm ▼ <u>T</u> race ▼ T <u>o</u> ols ▼ <u>S</u> nmp ▼ <u>H</u> elp ▼	
SNMP Community String Configuration	
Status	
Status : Ready	
Server* vxml	
Community String Information	
Community String Name* test	
Host IP Addresses Information	
 Accept SNMP Packets from any host 	Accept SNMP Packets only from these hosts Host IP Address
	Insert
	Remove
Access Privileges	
Access Privileges* ReadOnly	
Notify access privilege is required in order	to configure Notification Destinations.
Apply To All Nodes	
Save Clear All Cancel	
Image: sequired item.	
步驟5.按一下 Save ,然後彈出通知,如下圖	圆所示。按一下「 OK 」(確定)。
附註 :請記下預期的服務重新啟動,並	拉確保系統已準備好預期重新載入這些服務。
SNMP master agent needs to be restarted in order for these changes to take completed.	effect. It is recommended to restart the SNMP master agent once all the configuration changes are
Hestarting SNMP Master Agent also restarts the Host Resources Agent if it is Master agent restart will take around 1min	; running.
Press OK to restart the SNMP master agent now or Cancel to restart later.	
	Cancel OK

步驟6.收到Confirmation SNMP Restart Successful,並列出Community String Name和Access Privilege條目。

SNMP Com	munity String Configuration		
-} 🗙 -			
Status			
() SNMP F	Restart Successful		
Status			
🚯 Add Su	ccessful		
-Search O	ntions		
Find Comr	nunity Strings where Name heating with	Convert werel	Cind
Find Com	nunity Strings where Name begins with V	Server* Vxmi	- Fina
(Commun	hity Strings where Name begins with any)		
Search Re	esults		
	Community String Name	Access Privileges	
	test	ReadOnly	
		A	
Apply T	o All Nodes	—	
Add New	Delete Selected		

步驟7.訪問支援MIB資訊的連結:

思科虛擬化語音瀏覽器操作指南,版本11.6(1)

Table 2 SNMP MIBs

MIB	Agent Service
CISCO-VOICE-APPS-MIB	Cisco VVB Voice Subagent
CISCO-CDP-MIB	Cisco CDP Agent
CISCO-SYSLOG-MIB	Cisco Syslog Agent
SYSAPPL-MIB	System Application Agent
MIB-II	MIB2 Agent
HOST-RESOURCES-MIB	Host Resources Agent

- •對於此配置的範圍;**討論CISCO-VOICE-APPS**-MIB。
- 要下載MIB CISCO-VOICE-APPS-MIB.my(v2),請單擊 > <u>MIBv2。</u>
- 搜尋CISCO-VOICE-APPS-MIB和rt。按一下\選擇Save link as並下載CISCO-VOICE-APPS-MIB.my檔案。

驗證

使用本節內容,確認您的組態是否正常運作。

下載並安裝MIB瀏覽器(如iReasoning MIB Browser),上傳MIB;然後是Get Walk結果。

步驟1.上傳MIB(.my檔案)到MIB瀏覽器。按一下「Load MIBs」。

1	iReasoning MB Browser					6	- 6	- 88
Fi	Edit Operations Tools Bo	okmarks Help						
C	Ctrl+L	 Advanced 01D: .1.3 		Operations:	GetNext	•	e 🔿 🗘	lo
L	UnLoad MIBs		Result Table					
	MIB Modules		Name/OID	Value	Type	P	Port	0
	Open Graph Data							*
L	Open Session							
L	Save Session							
	Exit							P
L	-	1						100

步驟2.指向CISCO-VOICE-APPS-MIB.my。

<u></u>							×
Look in:	📃 Desktop		-	3	Þ	•	
Recent Places	File for CISCO MY Fil 14.5 Ki	lder D-VOICE-APPS-MIB.my le B					^
Desktop	freeFT Shorto 982 by	Pd :ut rtes					
Libraries	MIB Bi Shorte 2.36 Ki	rowser :ut B					
(Angle Computer	WCPa Disc Ir 216 M					E	
	winrar-x64-420				\backslash		-
Network	File name:	CISCO-VOICE-APPS-MIB			-		Open
	Files of type:	All Files (*.*)			•	(Cancel

步驟3.下一步鍵入VVB的IP地址;按一下Advanced,在Read Community中輸入Community String Name(請參閱步驟4)值,然後輸入SNMP versionas2。

🚯 iReasoning MIB Browser	(
File Edit Operations Tools Bookmarks Help	😡 Advanced Properties of SNMP Agent	-X
Address: v.y.y.y Advanced OID	Address y.y.y.y	
SNMP MIBs	Port 161	
MIB Tree B-	Read Community test	
	Write Community	
	SNMP Version 2]-]
	Ok Cancel	

步驟4.下一步,展開**Private\Enterprises\Cisco\ciscoMgmt\ciscoVoiceAppsMIB\點選Get Bulk**;獲取 VVB配置詳細資訊等。

