

# RV110W上SSID的MAC過濾

## 目標

每個硬體都有一個介質訪問控制(MAC)地址，該地址用作該硬體的標識碼。在RV110W上，使用者可以允許或拒絕對特定MAC地址的訪問。本文說明如何在RV110W上配置MAC過濾。

## 適用裝置

- RV110W

## 程式步驟

步驟1.使用Web配置實用程式選擇Wireless > Basic Settings。

The screenshot shows the 'Basic Settings' page. The 'Radio' section is checked 'Enable'. 'Wireless Network Mode' is set to 'B/G/N-Mixed'. 'Wireless Band Selection' has '20/40MHz' selected. 'Wireless Channel' is '6-2.437 GHZ'. 'AP Management VLAN' is '1'. 'U-APSD (WMM Power Save)' is unchecked.

	Enable SSID	SSID Name	SSID Broadcast	Security Mode	MAC Filter	VLAN	Wireless Isolation with SSID	WMM	WPS Hardware Button
<input type="checkbox"/>	<input checked="" type="checkbox"/>	ciscosb1	<input checked="" type="checkbox"/>	Disabled	Disabled	1	<input type="checkbox"/>	<input checked="" type="checkbox"/>	<input checked="" type="radio"/>
<input type="checkbox"/>	<input type="checkbox"/>	ciscosb2	<input type="checkbox"/>	Disabled	Disabled	1	<input type="checkbox"/>	<input checked="" type="checkbox"/>	<input type="radio"/>
<input type="checkbox"/>	<input type="checkbox"/>	ciscosb3	<input type="checkbox"/>	Disabled	Disabled	1	<input type="checkbox"/>	<input checked="" type="checkbox"/>	<input type="radio"/>
<input type="checkbox"/>	<input type="checkbox"/>	ciscosb4	<input type="checkbox"/>	Disabled	Disabled	1	<input type="checkbox"/>	<input checked="" type="checkbox"/>	<input type="radio"/>

Buttons: Edit, Edit Security Mode, Edit MAC Filtering, Time of Day Access, Save, Cancel

步驟2.在Wireless (無線)表格中，選中要編輯MAC過濾設定的SSID的覈取方塊。

步驟3.按一下Edit MAC Filtering。

### Wireless MAC Filter

SSID: ciscosb1

Wireless MAC Filter:  Enable

---

**Connection Control**

Prevent PCs listed below from accessing the wireless network.

Permit PCs listed below to access the wireless network.

Show Client List

MAC Address Table		
01	<input type="text"/>	<input type="text"/>
02	<input type="text"/>	<input type="text"/>
03	<input type="text"/>	<input type="text"/>
04	<input type="text"/>	<input type="text"/>
05	<input type="text"/>	<input type="text"/>
06	<input type="text"/>	<input type="text"/>
07	<input type="text"/>	<input type="text"/>
08	<input type="text"/>	<input type="text"/>
09	<input type="text"/>	<input type="text"/>
10	<input type="text"/>	<input type="text"/>
11	<input type="text"/>	<input type="text"/>
12	<input type="text"/>	<input type="text"/>
13	<input type="text"/>	<input type="text"/>
14	<input type="text"/>	<input type="text"/>
15	<input type="text"/>	<input type="text"/>
16	<input type="text"/>	<input type="text"/>
17	<input type="text"/>	<input type="text"/>
18	<input type="text"/>	<input type="text"/>
19	<input type="text"/>	<input type="text"/>
20	<input type="text"/>	<input type="text"/>
21	<input type="text"/>	<input type="text"/>
22	<input type="text"/>	<input type="text"/>
23	<input type="text"/>	<input type="text"/>
24	<input type="text"/>	<input type="text"/>
25	<input type="text"/>	<input type="text"/>
26	<input type="text"/>	<input type="text"/>
27	<input type="text"/>	<input type="text"/>
28	<input type="text"/>	<input type="text"/>
29	<input type="text"/>	<input type="text"/>
30	<input type="text"/>	<input type="text"/>
31	<input type="text"/>	<input type="text"/>
32	<input type="text"/>	<input type="text"/>

Save Cancel Back

步驟4.在「無線MAC過濾器」的右側，勾選**Enable**覈取方塊以過濾MAC地址。

步驟5.在「連線控制」下，按一下**Prevent**以阻止MAC地址表中的MAC地址，或按一下**Permit**以允許相同的MAC地址訪問無線網路。

### Wireless MAC Filter

SSID: ciscob1

Wireless MAC Filter:  Enable

**Connection Control**

Prevent PCs listed below from accessing the wireless network.

Permit PCs listed below to access the wireless network.

Show Client List

MAC Address Table		
01	12:34:56:78:9A:BC	23
02		24
03		25
04		26
05		27
06		28
07		29
08		30
09		31
10		32
11		

Save Cancel Back

步驟6.在MAC地址表中，在編號欄位中輸入最多32個MAC地址。

步驟7.按一下**Save**以儲存變更，**Cancel**以捨棄變更，或**Back**以返回上一頁。