

# RV315W VPN路由器的使用者管理

## 目標

*User Management* 頁面用於建立使用者並更改使用者的密碼。

本文概述如何通過RV315W路由器的使用者管理功能新增使用者。

## 適用的裝置

·RV315W

## 軟體版本

•1.01.03

## 使用者管理配置

步驟1. 登入到Web配置實用程式並選擇 **System Management > User Management**。將開啟 *User Management* 頁面：

Username	Privilege	Action
<input type="checkbox"/> cisco	Administrator	[ Change Password ]
<input type="checkbox"/> guest	Normal User	[ Change Password ]

步驟2. 在Username欄位中輸入使用者名稱。

步驟3. 在「密碼」欄位中輸入使用者的密碼。

附註：Password欄位右側的計量表示所選密碼的強度。大寫字母、小寫字母和符號的組合提供了最強的密碼組合。

步驟4. 在Password Confirm欄位中重新輸入密碼。

Username	Privilege	Action
<input type="checkbox"/> cisco	Administrator	[ Change Password ]
<input type="checkbox"/> guest	Normal User	[ Change Password ]

步驟5. 按一下Add以將該設定檔放在Local User List中。出現確認視窗。

步驟6.按一下OK以完成動作。

**附註：** Privilege欄位指定與每個配置檔案關聯的帳戶型別。管理員使用者型別具有對裝置的完全訪問許可權，可以更改裝置上的任何設定。普通使用者對該裝置的訪問許可權有限，對大多數裝置設定具有只讀許可權。普通使用者仍可訪問其配置檔案，並可隨時編輯其帳戶。

The screenshot shows two parts of a configuration interface. The top part is titled 'Add Local User' and contains three input fields: 'Username:' (with a note '\* (1-55 characters)'), 'Password:' (with a note '\* (0-64 characters)'), and 'Password Confirm:' (with a note '\*'). Below these fields is a red asterisk note: '\* indicates a mandatory option.' To the right of the fields are 'Add' and 'Cancel' buttons. The bottom part is titled 'Local User List' and contains a table with three columns: 'Username', 'Privilege', and 'Action'. The table lists three users: 'cisco' (Administrator), 'guest' (Normal User), and 'Profile1' (Normal User). Each user has a '[ Change Password ]' link in the Action column. A 'Delete' button is located at the bottom left of the table.

Username	Privilege	Action
<input type="checkbox"/> cisco	Administrator	[ Change Password ]
<input type="checkbox"/> guest	Normal User	[ Change Password ]
<input checked="" type="checkbox"/> Profile1	Normal User	[ Change Password ]

步驟7. ( 可選 ) 要刪除本地使用者，請選中要刪除的使用者配置檔案的Local User List覈取方塊，然後按一下Delete。出現確認視窗。

步驟8.按一下OK以完成動作。

步驟9. ( 可選 ) 要更改本地使用者的密碼，請選中要更改的使用者配置檔案密碼的「本地使用者清單」覈取方塊，然後按一下更改密碼。出現「Change Password」視窗。

The screenshot shows a 'Change Password' dialog box with a blue header. It contains three input fields: 'Old Password:', 'New Password:', and 'Password Confirm:'. To the right of the 'New Password:' field is a password strength indicator consisting of a row of colored squares (red, yellow, green) and the text 'Very Strong'. At the bottom of the dialog box are 'Save' and 'Cancel' buttons.

步驟10.根據需要編輯密碼，然後按一下Save。