

# Inscription et activation de ProtectLink Web sur les routeurs VPN RV016 et RV082

## Objectif

Cisco ProtectLink Web est un service de sécurité capable de filtrer le contenu par site Web ou URL et de le protéger contre les attaques Web. Cisco ProtectLink Web est disponible pour les versions RV016 et RV082 avec l'achat d'une licence.

L'objectif de ce document est de décrire l'enregistrement et l'activation de la protection Web ProtectLink pour les routeurs VPN RV016 et RV082.

## Périphériques pertinents

• RV016

• RV082

## Version du logiciel

• 4.2.2.08

## Cisco ProtectLink Configuration Web

### Homologation du produit

Étape 1. Connectez-vous à l'utilitaire de configuration Web et sélectionnez **Cisco ProtectLink Web**. La page *Cisco ProtectLink Web* s'ouvre :



Étape 2. Cliquez sur **Register ProtectLink services et obtenez un code d'activation (AC)** pour enregistrer le routeur pour ProtectLink. Le lien ouvre la page *Register Your Product* dans une fenêtre séparée du navigateur.

### System Summary

**System Information**

Serial Number :	NKS10403550	Firmware Version :	v4.2.2.08 (Apr 26 2013 19:12:26)
PID VID :	RV082 V03	Firmware MD5 Checksum :	9f4450cc2cc023dc0e9d6aef842afd48
LAN		<u>Working Mode</u> :	Gateway
<u>IPv4/ Subnet mask</u> :	192.168.1.1/255.255.255.0		
<u>IPv6/ Prefix</u> :	--- / ---		
System Up Time :	0 Days 1 Hours 5 Minutes 51 Seconds (Now : Thu Aug 15 2013 16:52:28)		

**Cisco ProtectLink**

Vous pouvez également vous connecter à l'utilitaire de configuration Web, choisir **System Summary** et cliquer sur **Register** pour enregistrer le routeur pour ProtectLink.

**TREND MICRO** | **CISCO**

Home | Products | Purchase | **Support** | Security Info | Partners | About Us | Find a product

Knowledge Base  
FAQs  
Update Center  
Supported Versions  
Beta Programs  
Virus Response Service  
Submission Wizard  
Premium Support

**Online Registration**  
» Help

Home > Support > [Online Registration](#) > **Register Your Product**

## Register Your Product

Please enter your Registration Key (for example xx-xxxx-xxxxxx-xxxxxx) below and click **Next**. Contact your reseller if you cannot locate your Registration Key.

If you are a current ProtectLink Gateway user, and have purchased another router, [Click here](#) to register the new router.

For further assistance, contact [www.cisco.com/support](http://www.cisco.com/support)

.....

**Enter your Registration Key:**

-  -  -  -

.....

Copyright 1989-2012 Trend Micro, Inc. All rights reserved. [Legal Notice](#) | [Privacy Policy](#) | [Contact Us](#)

Étape 3. Saisissez la clé d'enregistrement dans le champ Saisissez votre clé d'enregistrement.

Étape 4. Cliquez sur **Next** (Suivant). La page *Confirm License Terms* s'ouvre :

## Confirm License Terms

Trend Micro licenses its products worldwide in accordance with certain terms and conditions. By breaking the seal on the CD jacket in the product box or registering the product's Registration Key, you or your company or organization accepted a Trend Micro license agreement.

Below you will find a representative Trend Micro License Agreement. If you or your company has already entered into a valid written license agreement with Trend Micro, click on the button below to confirm your acceptance of that original written agreement. If, for some reason, you have not already accepted a license agreement with Trend Micro, review the following Trend Micro License Agreement and click on the button below if you accept its terms. If not, or if you have any questions, contact Trend Micro before proceeding.

### Trend Micro License Agreement (Package Version)

READ THESE TERMS CAREFULLY BEFORE BREAKING THE SEAL ON THE ACCOMPANYING CD JACKET OR USING THE SERIAL NUMBER. THESE ACTIONS CONSTITUTE AN ACKNOWLEDGEMENT THAT YOU HAVE READ AND UNDERSTOOD THIS AGREEMENT AND AGREE TO BE BOUND BY ITS TERMS.

IF YOU DO NOT AGREE TO THESE TERMS, LICENSOR IS UNWILLING TO LICENSE THE SOFTWARE TO YOU AND YOU MUST RETURN THE SOFTWARE (INCLUDING THE UNOPENED CD PACKAGE, WRITTEN MATERIALS AND PACKAGING) TO THE SELLER NO LATER THAN 30 DAYS AFTER RECEIPT OF THE SOFTWARE FOR A FULL REFUND.

Except as set forth in the paragraph below, Trend Micro Incorporated ("Trend Micro") offers to license the Trend Micro software (including documentation) in this package ("Software") subject to the terms and conditions of this License Agreement (the "Agreement"). IF YOU ARE ACQUIRING THE SOFTWARE ON BEHALF OF YOUR COMPANY OR ORGANIZATION (COLLECTIVELY "COMPANY"), BY BREAKING THE SEAL ON THE ACCOMPANYING CD JACKET OR INSTALLING THE SERIAL NUMBER, YOU REPRESENT THAT (A) YOU ARE DULY AUTHORIZED TO REPRESENT YOUR COMPANY AND (B) YOU ACCEPT THE TERMS AND CONDITIONS OF THIS AGREEMENT ON BEHALF OF YOUR COMPANY. AN AGREEMENT IS THEN FORMED.

 [Printer-Friendly Format](#)

I Accept  I Don't Accept \*

Étape 5. Cliquez sur la case d'option **I Accept** et cliquez sur **Submit** pour accepter les conditions.

---

## Registration Information

**NOTICES:** The following online form asks you for contact information, including certain personal data. By entering such information and clicking the Submit button at the bottom of the form, you are giving your express consent for Trend Micro and its authorized agents to collect such personal data and to process and store such personal data in countries, such as the United States, where Trend Micro has offices and where the personal data protection laws may not be as strict as in your home country.

As part of its compliance with U.S. export control laws, Trend Micro may also share certain information you provide below with a third-party service provider operating in the U.S. and Canada. This shared data is not retained by the third-party service provider once it verifies that your use of the software will not violate U.S. export control laws.

---

(Required fields \* )

Company name:	<input type="text"/>	*
Company address:	<input type="text"/>	*
City:	<input type="text"/>	*
State/Province:	<input type="text"/>	*
ZIP/Postal code:	<input type="text"/>	*
Country/Region:	<input type="text" value="United States"/>	*

Account Administrator Contacts: The Account Administrator contact listed below will have access to the Trend Micro Online Registration database and can view all Trend Micro products registered in your file. This person will also serve as the technical contact for service activation and setup.

### Account Administrator Contact

First Name:	<input type="text"/>	*
Middle Name:	<input type="text"/>	
Last name:	<input type="text"/>	*
Title:	<input type="text"/>	*
Phone number:	<input type="text" value="Area code"/> * - <input type="text" value="Number"/> * - <input type="text" value="Ext."/>	
Email address:	<input type="text"/>	*

Étape 6. La page *Registration Information* s'affiche. Saisissez les informations d'inscription appropriées et faites défiler la page vers le bas pour cliquer sur **Submit**.

---

## Confirm Registration Information

---

Please confirm that the information displayed below is correct:

Company:  
Street:  
City:  
State/Province:  
Country/Region:  
ZIP/Postal code:

Product purchase date: 2/25/2012

Maintenance expiration date: 3/25/2012

An email notification will be sent to your contact email address before the product maintenance contract expires.

---

### Account Administrator Contact

Name:  
Title:  
Phone number:  
Email address:  
Mailing address:

---

Logon ID:

---

Edit

OK

---

Étape 7. La page *Confirm Registration* s'ouvre et une confirmation finale des informations d'inscription saisies s'affiche. Pour modifier les informations, cliquez sur **Edit**, sinon cliquez sur **OK** pour continuer.

---

## Activation Code

---

**Thank you for registering.**

Your logon ID and an Activation Code will be sent to the following email address:

You can visit <https://olr.trendmicro.com/registration/> and enter the logon ID and password to view your Online Registration account or register additional products.

Product Name	Language	Platform (OS)	Platform (Application)	Activation Code
ProtectLink	English	Windows	Gateway Service	

Questions? Contact [Trend Micro](#).

OK

---

**Remarque :** la page *Activation Code* s'affiche. Cette page confirme l'enregistrement du produit. La page affiche des informations sur le code d'activation requis pour l'activation du produit. Le code d'activation est également envoyé par e-mail à l'adresse indiquée.

## Activation du produit

Étape 1. Connectez-vous à l'utilitaire de configuration Web et sélectionnez **Cisco ProtectLink Web**. La page *Cisco ProtectLink Web* s'ouvre :

### Cisco ProtectLink Web

Cisco ProtectLink Web provides web security for an unlimited number of users. It prevents access to dangerous web sites and includes URL filtering with over 80 categories to control employee access to non-business related web sites.

- Learn more about and request Free Trial for Cisco ProtectLink
- Register ProtectLink services and obtain an Activation Code(AC)
- Use the Activation Code(AC) to activate ProtectLink services

Étape 2. Cliquez sur le lien **Utiliser le code d'activation (AC) pour activer les services ProtectLink**. La page *Activate Your Product* s'ouvre :

Home > Support > Online Registration > **Activate your product**

### Activate your product

> Step 1: Enter Activation Code

Your Activation Code(for example xx-xxxx-xxxxx-xxxxx-xxxxx-xxxxx-xxxxx) is located on the Product Registration Certificate you received. You can contact Trend Micro if you cannot locate your Activation Code. Enter your Activation Code below and click **Next**.

Enter Activation code

-  -  -  -  -  -

Copyright 1989-2012 Trend Micro, Inc. All rights reserved. [Legal Notice](#) | [Privacy Policy](#) | [Contact Us](#)

Étape 3. Saisissez le code d'activation dans le champ Enter Activation Code.

Étape 4. Cliquez sur **Next** (Suivant).

### Activate your product

> Step 2: Verify Product Information

Thank you for choosing Trend Micro. You purchased the following product(s):

Product Group	Application	Activation Code	Registration Key	Seat No.	Expiry Date
ProtectLink	Gateway Service			5	03/25/2012

If the information is correct, click Next to continue; otherwise, please contact [www.cisco.com/support](http://www.cisco.com/support)

Étape 5. Vérifiez l'activation et cliquez sur **Next**.



The screenshot shows a web page titled "Activate your product" with a navigation bar at the top containing "Home", "Products", "Purchase", "Support", "Security Info", "Partners", and "About Us". A search bar on the right says "Find a product". On the left, there is a sidebar menu with items like "FAQs", "Update Center", "Supported Versions", "Beta Programs", "Virus Response Service", "Submission Wizard", "Premium Support", "Online Registration", and "Help". The main content area displays "Activate your product" and a progress indicator "> Step 3: Finish Activation". Below this, a red heading reads "Congratulations! You have activated your product." followed by the text "The Activation Code(s) for your product(s) are listed below:". A table with 6 columns (Product Group, Application, Activation Code, Registration Key, Seat No., Expiry Date) shows one entry for "ProtectLink Gateway Service" with 5 seats and an expiry date of 09/07/2013. A list of three bullet points provides additional instructions and a link to support.

Product Group	Application	Activation Code	Registration Key	Seat No.	Expiry Date
ProtectLink	Gateway Service	[REDACTED]	[REDACTED]	5	09/07/2013

- Your product will be active shortly. Internet speeds affect the process.
- Your Account Administrator ([REDACTED]) will initiate email message redirection (for InterScan Messaging Hosted Security IP Addresses).
- For further assistance, contact [www.cisco.com/support](http://www.cisco.com/support).

Copyright 1989-2012 Trend Micro, Inc. All rights reserved. [Legal Notice](#) | [Privacy Policy](#) | [Contact Us](#)

**Remarque :** la page *Terminer l'activation* s'affiche. Cela confirme l'activation des services ProtectLink sur le périphérique. Pour modifier les licences ultérieurement, vous pouvez utiliser le nom d'utilisateur et le mot de passe obtenus lors de l'enregistrement pour modifier les paramètres.

Étape 6. Actualisez la page *ProtectLink* tant que le périphérique est toujours connecté à Internet. Les options ProtectLink s'affichent.

À propos de cette traduction

Cisco a traduit ce document en traduction automatisée vérifiée par une personne dans le cadre d'un service mondial permettant à nos utilisateurs d'obtenir le contenu d'assistance dans leur propre langue.

Il convient cependant de noter que même la meilleure traduction automatisée ne sera pas aussi précise que celle fournie par un traducteur professionnel.