



ReadMe for Cisco Unified Communications Manager Release 8.6(2a)SU3

Revision 1

Updated May 9, 2013

This ReadMe file discusses the following topics:

- [Introduction, page 2](#)
- [System Requirements, page 2](#)
- [Version and Description, page 2](#)
- [Important Notes, page 3](#)
- [Firmware Upgrade Issues, page 3](#)
- [Related Documentation, page 3](#)
- [Before You Begin, page 3](#)
- [Installation Instructions, page 4](#)
- [Reverting to a Previous Version, page 5](#)
- [Caveats, page 5](#)
- [Obtaining Documentation and Submitting a Service Request, page 25](#)



Note

To view the release notes for previous versions of Cisco Unified Communications Manager, choose the Cisco Unified Communications Manager version from the following URL:

http://www.cisco.com/en/US/products/sw/voicesw/ps556/prod_release_notes_list.html



Note

Please review all sections in this document pertaining to installation before you install this Service Update (SU). Failure to install this SU as described may result in inconsistent Cisco Unified Communications Manager behavior.

Before you install Cisco Unified Communications Manager, Cisco recommends that you review the [“Important Notes” section on page 3](#) for information about issues that may affect your system.



Americas Headquarters:

Cisco Systems, Inc., 170 West Tasman Drive, San Jose, CA 95134-1706 USA

Introduction

This 8.6(2a)SU3 ReadMe file contains important information about installation procedures and resolved caveats for Cisco Unified Communications Manager release 8.6(2a)SU3. This SU can be applied to Cisco Unified Communications Manager, Business Edition 5000 or 6000 and Cisco Unity Connection. It should not be installed on a Business Edition 3000 server.

System Requirements

The following sections comprise the system requirements for this release.

Server Support

Make sure that you install and configure this SU on a Cisco Media Convergence Server (MCS) or a Cisco-approved HP server configuration or a Cisco-approved IBM server configuration.

To find which servers support Cisco Unified CM Release 8.6(x), refer to the Cisco Unified Communications Manager Server Support Matrix at

http://www.cisco.com/en/US/prod/collateral/voicesw/ps6790/ps5748/ps378/prod_brochure0900aecd8062a4f9.html



Note

Make sure that the matrix shows that your server model supports Cisco Unified CM Release 8.6(x).

Uninterruptible Power Supply

Ensure that you connect each Unified CM node to an uninterruptible power supply (UPS) to provide backup power and protect your system.



Caution

Failure to connect the Cisco Unified Communication Manager nodes to a UPS may result in damage to physical media and require a new installation of Cisco Unified CM.

Version and Description

This SU is a cumulative update that incorporates all of the fixes and changes from Cisco Unified Communications Manager 8.6(2), 8.6(2a), 8.6(2a)SU1, and 8.6(2a)SU2, along with additional changes that are specific to this SU.



Note

You can only install this SU on Cisco Unified Communications Manager Release 6.1(4x), 6.1(5x), 7.1(3x), 7.1(5x), 8.0(1x), 8.0(2x), 8.0(3x), 8.5(1x), 8.6(1x), 8.6(2), 8.6(2a), 8.6(2a)SU1, 8.6(2a)SU2 or any 8.6(2)es from 8.6.2.21001-1 to 8.6.2.23069-1. Upgrades from 6x and 7x need to be requested via PUT (www.cisco.com/upgrade) to obtain the necessary license. This SU should not be installed on a Business Edition 3000 server.

See the Compatibility Matrix for further details:

http://www.cisco.com/en/US/docs/voice_ip_comm/cucm/compat/ccmcompmatr1.pdf

Important Notes

SUs do not impact system compatibility unless specifically stated.

Cisco provides the following guidance to help you successfully upgrade Cisco Unified Communications Manager software:

- To minimize call-processing interruptions during the upgrade process, register all devices to servers that are running the same version of Cisco Unified Communications Manager software. Make sure that you register all devices to the backup Cisco Unified Communications Manager server or to the primary Cisco Unified Communications Manager server, but not to both the backup and primary servers.

Warning for CSCtj50884

- This SU contains an update to the RTMT client that addresses a significant memory leak. You must upgrade the client version on any device that uses the RTMT client to completely resolve this issue. Please see the Bug Details of fix [CSCtj50884](#) for complete instructions on resolving this issue.

Firmware Upgrade Issues

For all SCCP and SIP firmware upgrades from firmware release versions earlier than 8.3(3) to version 8.5(2)SR1 or greater, you must first upgrade your firmware to version 8.5(2). Once you have upgraded to version 8.5(2), you can upgrade your IP Phone to version 8.5(2)SR1 or later. Refer to the *Firmware Versions in this Release* section of this document to determine the firmware load provided in this SU.

For additional details, Firmware Upgrade Instructions, and Firmware Download locations please see:

SCCP

http://www.cisco.com/en/US/docs/voice_ip_comm/cuipph/firmware/8_5_2/english/release/notes/7900_852SR1.html#wp57602

SIP

http://www.cisco.com/en/US/docs/voice_ip_comm/cuipph/firmware/8_5_2/english/release/notes/7900_852SR1.html#wp147343

Related Documentation

To view documentation that supports Cisco Unified CM Release 8.6(2), go to:

http://www.cisco.com/en/US/docs/voice_ip_comm/cucm/docguide/8_6_2/dg862a.html

Before You Begin

Before you upgrade the software version of Cisco Unified Communications Manager, verify your current software version.

To do that, open Cisco Unified Communications Manager Administration. The following information displays:

- Cisco Unified Communications Manager Administration System version

Installation Instructions

**Note**

Apply this SU to all of your Cisco Unified Communications Manager servers, beginning with the publisher server and TFTP server.

Refer to the “Upgrading to Unified CM 8.6(2a)” section of the *Release Notes for Cisco Unified Communications Manager Release 8.6(2a)* for detailed information about doing this upgrade:

http://www.cisco.com/en/US/docs/voice_ip_comm/cucm/rel_notes/8_6_2/cucm-rel_notes-862a.html#wp1944944

**Note**

Because the 8.6.2.23900-10 build is a non-bootable ISO, it proves useful only for upgrades. You cannot use it for new installations.

Release 8.6(2) is available in both restricted (which is the release type that has always been available from Cisco) and unrestricted versions of software to comply with import / export restrictions to various countries. The unrestricted version is available in limited markets. Please refer to the 8.6(2) Release Notes referenced above for a more detailed description.

**Caution**

For both restricted and unrestricted upgrades from an 8.5(x) or earlier release to an 8.6(x) release, a patch (COP file) must be applied prior to initiating the upgrade. Before you upgrade from compatible versions of Unified CM, install the COP file named `ciscocm.refresh_upgrade_v1.1.cop.sgn`. Please refer to the **Installing the COP File** section of the *Release Notes for Cisco Unified Communications Manager Release 8.6(2a)* referenced earlier in this document for detailed installation instructions and download location.

The file names and MD5 values you will use for this upgrade are:

- `UCSInstall_UCOS_8.6.2.23900-10.sgn.iso`

The **MD5** for the Restricted combined download is: `2c2661a8834d61d4971e6cf41207e174`

**Note**

Once installed, UNRST releases can never be converted or upgraded to releases which support full encryption capabilities

For the Unrestricted version:

- `UCSInstall_UCOS_UNRST_8.6.2.23900-10.sgn.iso`

The **MD5** for the Unrestricted combined download is: `a1f7b01f951d41178cad6b5c833e6f7d`

Reverting to a Previous Version



Note

Uninstall the SU on all servers in the cluster in the same order in which you performed the installation.

Refer to the “Reverting to a Previous Version” section of the *Cisco Unified Communications Manager Release Notes Release 8.6(2a)* for detailed instructions on “Reverting to a Previous Version.”

http://www.cisco.com/en/US/docs/voice_ip_comm/cucm/rel_notes/8_6_2/cucm-rel_notes-862a.html#wp2058677

Caveats

Caveats describe unexpected behavior on a Cisco Unified Communications server. The following sections contain lists and descriptions of resolved and open caveats in this release.

Resolved Caveats

Resolved Caveats for Cisco Unified Communications Manager Release 8.6(2a)SU3 describes possible unexpected behaviors in Cisco Unified Communications Manager Release 8.6(2), 8.6(2a), 8.6(2a)SU1 and 8.6(2a)SU2.

Resolved Caveats for Cisco Unified Communications Manager Release 8.6(2a)SU3

The following information comprises unexpected behavior that is addressed by this SU of Cisco Unified Communications Manager.

Resolved CUCM Caveats in 8.6(2a)SU3

[CSCug36887](#): 8.6(2) TFTP server taking long time to serve files after Change Notifica

[CSCuf65489](#): CCMCIP service responds with a 500 Internal Server

[CSCuf44112](#): CTIRequestTimer handling

[CSCuf24527](#): Forward all css not imported properly

[CSCue74059](#): 8.6 CUCM UDL not support fully effecting v.150 MER support

[CSCue04145](#): SIP Normalization scripts got scrambled during RU upgrade

[CSCtr78855](#): EN no longer valid after CFA to its associated RD

[CSCue97623](#): 9.3(3) SCCP/SIP loads for 6921/41/61/45 IP Phones (Part 2)

[CSCue93843](#): Gnutls Leakage of Timing Info when Decrypting TLS/SSL Records

[CSCue93809](#): OpenSSL Information Leakage and Null Pointer Vulnerabilities

[CSCue14149](#): /tmp/tftpcache/ missing causes tftp to core

[CSCud93944](#): Warning pop-up for RollBack Enterprise Parameter field should be modify

[CSCue90652](#): installdb cores during L2 upgrade caused by 7920 cop file

[CSCue73844](#): Unable to set dndOption for Jabber for iPad using 7.x AXL Schema

[CSCue66089](#): CCM Core on SIPcdpc During Recorded Call

[CSCue61604](#): BAT transactions goes to incomplete state

[CSCue38647](#): NullPointerException when Connector.close() is called more that once

[CSCub17830](#): Add support for 48/72 ports analog cards on ISR G2 platforms

[CSCub09472](#): NSS and NSPR Vulnerabilities for RHTSA-2012-1090-1 (CVE-2012-0441)
[CSCub06875](#): POPT RPM Vulnerabilities
[CSCty54598](#): RU appears to have failed due to failure to tar wrapped log file
[CSCts35174](#): RU 8.5(1) to 8.6(1) fails on 782xH3 when N/W Fault Tolerance enabled
[CSCtn53679](#): CUCM CTFTP lag in phone registration after config modification and reset
[CSCue82643](#): 9.3(3) SIP loads and support files for 8831 Conference IP Phones(Part 2)
[CSCue74302](#): 8.6(2a)su3 upgrade rules to prevent install over ineligible ES's
[CSCue70015](#): Phone line busy after the call comes via the hunt group - LineCdpc leak
[CSCue56392](#): CUCM cores in MeetMeConference when receiving SdLinkOOS signal.
[CSCue17376](#): Unable to pickup a call although users pressed pickup softkey
[CSCud92062](#): SNR/DVO Sometimes Works For Single Reg Dual-Mode in Multi-Node Setup
[CSCud80642](#): Device losing connection can lead to DVO/SNR failure with RESET required
[CSCud39624](#): DVO - client stuck connecting call when cant route properly, must RESET
[CSCud15176](#): Sometimes 183 Session Process does not come if placing DVOR call
[CSCtz91825](#): WebAdmin query optimization for User Device Association search
[CSCtz84000](#): Forwarded calls hairpinned over QSIG PRI to SCCP voicemail fail
[CSCtz35492](#): Certificate Monitor and revocation config back to default after restore
[CSCtw90744](#): DMMS process is stopped prematurely when there is no wifi registration
[CSCtw70211](#): UCM Nodes Core Dump due to Subscriber Memory Leak under SAF-QSIG Traffic
[CSCto57427](#): Cannot ping ipv6 addresses outside its own subnet from 8.6 UCM
[CSCuc74600](#): CUCM fails to reply to SIP Msg when using TCP/TLS and Host is a Hostname

Resolved Cisco Unity Connection Caveats in 8.6(2a)SU3

[CSCuf57021](#): UC 8.6(2) - New Templates Fill City and Department With ~^
[CSCua37939](#): Check System Configuration task detect an error for routing rules
[CSCue06459](#): UC single inbox w/ office 365 "An internal server error occurred. Try..
[CSCue32298](#): Unity Connection Server unable to answer calls due to high VVM usage
[CSCue92635](#): UC - Rewind Message by not obeying value set
[CSCue92920](#): UC - Transfers to Non Existent DNS via SIP Mislead With "Busy" Failure
[CSCue93988](#): In O365 calendaring not working via TUI using exchange 2013
[CSCuf25596](#): After hard delete from Exchange,message goes to web inbox's inbox folder
[CSCue50620](#): Unity Connection MBXSync coring
[CSCue43581](#): UC 9 - SELinux blocks "utils cuc networking dscp on" command
[CSCue29819](#): CUC Unable to playback voicemail received from VPIM user
[CSCud72204](#): Not handling CallerName in non-ASCII character set on UC v9.0
[CSCub88872](#): Unified Messaging Account Test Button gives incorrect Test Results
[CSCua60162](#): Directory Handler does not play all names
[CSCua48768](#): UC 8 - Bulk Edit Fails to Update Phone System for LDAP Enabled Users
[CSCua43294](#): UC 8 - Bulk Edit of "Inherit User's Extension" Fails if Alt. Ext. Exists
[CSCtz76434](#): Unity Connection Security Scan vulnerabilities
[CSCtz51822](#): Unity Connection - Fake Alarm appearing in Syslogs for MbxDb Full
[CSCtt44939](#): CuMixer Crash When Recording Codec set to GSM FR
[CSCue69077](#): Coredump is not created on CUC service crash
[CSCue38604](#): CUC 8.6 Hello String incomplete when "Relay" to Unix SMTP Smart Host
[CSCue37809](#): Deletion of Multiple Search Spaces is not reflected on remote node
[CSCue37320](#): DigNet - Sync not working after join.
[CSCue20267](#): Error message on connecting to Visual Voicemail for a few non-US locales

[CSCud93698](#) : UC Holiday Schedule not observing Call Handler Time Zone
[CSCud86584](#) : VMs generated by VMO lack Date field in header
[CSCud75831](#) : MBXSync cores due to DecryptPassword issue
[CSCua64733](#) : OpenAm is not working giving error like invalid username and password

Resolved CUCM Caveats in 8.6(2.23069-1); base ES for 8.6(2a)SU3

[CSCud05830](#) : MOH stops working intermitently - need restart IPVMS
[CSCue01003](#) : Intermittent Secure recording failure with cause 57 403 forbidden
[CSCue62283](#) : Cucm 8.6 is not responding to mgcp gateway during IPsec renegotiation
[CSCtw62173](#) : Kernel crash on ipvms - ipvms_cache_add_allocator
[CSCue69176](#) : Adding new endpoint model Cisco DX650
[CSCue67570](#) : 9.3(3) SIP loads and support files for 8831 Conference IP Phones
[CSCue63303](#) : Jabber for iPad to 9971 Has No Video
[CSCue60557](#) : Wrong CI sent to StationD from RSVP
[CSCue53751](#) : 9.1(1)/8.6(2) Support files for Cisco TelePresence models version TC6.1
[CSCue31750](#) : Unable to use Call Park On some servers after Primary shutdown
[CSCue29442](#) : 9.3(1)SR1 SCCP/SIP loads and support files for 6901/11 IP Phones
[CSCue29440](#) : 9.3(3) SCCP/SIP loads and support files for 6921/41/61/45 IP Phones
[CSCue06553](#) : DST/TZ data update with 2012j
[CSCue44728](#) : 1.4(4) loads and support files for 792X phones
[CSCue33973](#) : AXL Throttling can cause excessive queries for server replication status
[CSCud38377](#) : Call Forwrd sceanrio fails in interoperability between CUCM and HSI
[CSCtx25915](#) : CUCM 8.5.1 (SU3) 7835/45-I2 IBM Raid driver reverts back during L2
[CSCue12023](#) : Call Manager;Phone button template privilege escalation security problem
[CSCub12387](#) : JTAPI Throwing Exception for Basic Call
[CSCtz83878](#) : DTMF fails to be sent prior to a connect when EFA is enabled
[CSCuc66506](#) : Crafted DNS Data Can Cause a Lockup in BIND Named (CVE-2012-5166)
[CSCue23919](#) : Null conn in connectionList prevents removal of closed conns from list
[CSCud93702](#) : ESXi 5.1 Not Supported on UC Applications yet
[CSCty74444](#) : Stale reference to remote support account
[CSCuc34482](#) : Cimlistener core during disk consistency check -- 7835/45-I3
[CSCue09435](#) : License Manager does not log after RU to 8.6.2.22900-9 (FreeIM release)
[CSCud83278](#) : "Forward All CSS x" is not imported irregularly
[CSCud76724](#) : CTIManager core dump & memory leak due to CTIRP reset loop
[CSCuc69945](#) : BAT Scheduled job ends unexpectedly before configured Job End Time
[CSCud54258](#) : cucm is not populating reason header for CANCEL SIP message
[CSCud49047](#) : RTMT Option To Download Certificate Change Notification Service Logs
[CSCuc82081](#) : Cisco Certificate Change Notify Service Creates 30+ Pub DB Connections
[CSCty38752](#) : Serviceability code isImproperly Using a NULL pointer to detect an error
[CSCtr94400](#) : User login fails after LDAP bind timeout
[CSCua78747](#) : No-way audio experienced for SIP-to-SIP calls when MTP is invoked
[CSCtw50575](#) : no/one-way mediaSDP details not forwarded (eg MTP ORC ACK to SIP SDP)
[CSCud52854](#) : Coredump when AltGKInfoInd is triggerred
[CSCud22272](#) : UCM sends wrong cap for ReInvite during glare condition
[CSCud15338](#) : Call end 15 sec regardless of connectMGCP Facility prompts SIP media
[CSCud06250](#) : Conference reconnect over IPv6 SIP ICT between IPv6 and IPv4 fails
[CSCub84987](#) : Replication broken due to dbemapp and dbemweb sessions consuming memory

[CSCub67769](#): CTIManager coredump when ParkDN deleted
[CSCua71076](#): Failover of CUCM requires Gateway/Trunk to be reset for outbound calls
[CSCud68026](#): Incorrect reporting of media transport address fields in CDR
[CSCud26795](#): CallerID not being shown when Caller ID received in facility msg..
[CSCud09696](#): Update CSF Device Type to add Built-in-Bridge and Record Config Options
[CSCty47592](#): RTMT fails to display Critical Service panel in a UCS/MCS mixed cluster
[CSCud48650](#): Changes to maxConnections variables in prefs.xml should survive upgrade
[CSCud34186](#): Seeing weird behavior from the getPattern and getRoutePartition
[CSCud32173](#): Enhance - CUCM not responding to SIP session refresh INVITE for T.38 fax
[CSCud12501](#): New dbl2j.jar in VOS
[CSCud11654](#): When Active IPMA service is shut it doesn't failover to secondary
[CSCub28929](#): RTMT asks to accept certificates multiple times
[CSCua46569](#): Error, audispd, queue is full - dropping event
[CSCtx35559](#): RTPTA and TA are not populated correctly in AuConnectInfoInd
[CSCtx33341](#): H245 control channel TA is overwritten
[CSCtx17436](#): RTMT Client continues to prompt for certificates
[CSCud23035](#): DNA Calls DB Connector w/Incorrect DB User (DNA) - should be "dbdna"
[CSCud02271](#): Callback feature doesn't work on qsig link through MGCP gateway
[CSCuc97701](#): Process Leak in Device Mobility Code due to mFailedRoutingHash table
[CSCty26810](#): Receive dup ProviderDeviceRegisteredEvent after register CTI port
[CSCty20488](#): Throttle the number of connections to the database from ccmcip
[CSCud18522](#): Stale Pointer in SipHandler leads to Infinite Loop and CUCM Core
[CSCud17913](#): Missing rtpmap attribute for G.clear payload type in MDCX
[CSCud13612](#): Add RTMT alerts for Licensing Expiration tags for connection
[CSCuc30900](#): CCM 8.6 cores when the IP sec tunnel is established with MGCP gateway
[CSCub80236](#): Out of Memory error because of numerous AXL requests/returns
[CSCty34093](#): slow response during corporate directory searches from the phone
[CSCud17401](#): 1.4(3)SR1 loads and support files for 792X phones (Part 2)
[CSCuc98930](#): Dynamically generated SipMcuControl patterns inserted in NULL partition
[CSCuc38412](#): memory corruption after EpStreamStop() of Cisco Media Driver
[CSCub54349](#): CCM Service unexpectedly restarts upon receiving a RPID
[CSCtz08184](#): Integrate Cisco Jabber for Tablet COP version 10 into UCM
[CSCuc85098](#): iPhone ver120713 COP file
[CSCuc74689](#): CTI Manager core in handleDeviceCloseReq
[CSCuc63582](#): Stale Pointer in SipHandler leads to Infinite Loop and CUCM Core
[CSCuc58007](#): Wrong error message with HLOG when interworking with EMCC feature
[CSCub80084](#): Sync up Cisco Jabber Android COP ver24 to UCM
[CSCub02337](#): UC & CUCM 8.6 - Slow Admin Page Load on Subs Separated from Pub over WAN
[CSCua41259](#): CUCM not responding to SIP session refresh INVITE for T.38 faxes
[CSCty74946](#): SIP Profile timers need to apply to Jabber for iPad non-dual-mode device
[CSCtx42463](#): no unregistered and registered event if device not opened
[CSCtw88620](#): Call Back function may be failed if many "call back" softkey pressed
[CSCtw73409](#): CUCM includes diversion header when using called party redirect
[CSCuc46229](#): GLIBC String to Number Conversion Overflow Vulnerability
[CSCuc92625](#): Changes made with "BAT update line" feature don't affect some lines
[CSCuc80713](#): 1.4(3)SR1 loads and support files for 792X phones
[CSCuc80572](#): 9.3(2) SCCP/SIP loads and support files for 8941 & 8945 Phones
[CSCuc77757](#): 9.3(1) SR1 SCCP/SIP loads and support files for TNP 79xx IP Phones

[CSCuc73013](#) : 9.3(2) SIP loads and support files for 9971, 9951 and 8961 IP Phones
[CSCuc68452](#) : Unable to login to CAD on Primary node shutdown
[CSCuc29278](#) : RTMT Client always needs to be reinstalled after CUCM Upgrade
[CSCub75289](#) : DNA cores when doing phone analysis
[CSCts39191](#) : Get NPE on CallStateChangedEv
[CSCtr79913](#) : Media Negotiation Failure on EO SIP Trunk Call with Multiple SRTP Codec
[CSCuc78754](#) : Call-info SIP header needed to avoid mixed media ringback on SNR calls 2
[CSCuc65003](#) : Sudo Insecure Temporary File Use in RPM (RHBA-2012-1270-1)
[CSCuc44794](#) : Call-info SIP header needed to avoid mixed media ringback on SNR calls
[CSCub35890](#) : CPU DoS During Malformed UDP Packet Attack Against Port 2427
[CSCua18783](#) : Add option to CUP build script to specify alternate email addresses
[CSCuc63768](#) : Resuming SNR call fails if RD leg goes thru two trunks before connecting
[CSCuc49517](#) : Common Device Configuration always set to Standard Common Phone Profile
[CSCuc21995](#) : Incorrect calling number in received calls directory
[CSCub11333](#) : blocked upgrade of 862.22040-1->862.22900-5 corrupts inactive partition
[CSCuc16218](#) : BIND Resource Record Processing DoS Vulnerability (CVE-2012-4244)
[CSCuc22526](#) : LibXML Interger and Buffer Overflow Vulns (CVE-2012-2807/CVE-2011-3102)
[CSCuc20486](#) : Need to send last redirecting number as calling number for SNR
[CSCuc16779](#) : Route Partition is not updated in ConferenceParticipantInfo
[CSCuc14461](#) : Libxslt DoS, Buffer Overflow, and Info Leakage Vulnerabilities
[CSCub58794](#) : CTI Monitoring of Call Park Causes UCM Service Crashes During SdlLinkOOS
[CSCtz83318](#) : CUCM 7.1.5 - download of CTL files via HTTP not working
[CSCuc29672](#) : Full SIP URI displayed on 9951/9971 on service provider inbound call
[CSCub74932](#) : Restored fix for H.323 ICT call to SIP GW not receiving DTMF
[CSCty85404](#) : iphone/TCT's built as Remote Destinations unable to make inbound calls
[CSCub41613](#) : DHCP Zero Length Client Identifier Denial of Service (CVE-2012-3571)
[CSCuc12632](#) : Updating the GpickUp group on many lines fails for some lines
[CSCuc04738](#) : Annunciator message not played for SIP 410 Gone
[CSCuc02260](#) : 3rd-party SIP endpoint was not registered with UCM after WiFi roaming
[CSCub91034](#) : G.729 ptime error when using CUCM8.6 and MGCP
[CSCub82344](#) : GLIBC Buffer Overflow Vulnerabilities (CVE-2012-3480)
[CSCub79830](#) : cp-meVideo calls work as audio only due to delay in update on Video caps
[CSCtu02279](#) : Allowed characters mismatch for VG224 port between CCM and BAT .xlt file
[CSCts10778](#) : Denials thrown for security Password Recovery procedure
[CSCub34553](#) : After refresh upgrade, .iso file from /common/download/ is not deleted.
[CSCub17642](#) : SNMP DoS During UDP Malformed Packet Flood
[CSCtz04128](#) : localhost log file size can grow exponentially under certain load
[CSCtz01408](#) : ANN Port Leak- no audio played when PRACK disabled on ICT -CallQueueing
[CSCub94658](#) : Upgrade halts on 9.0.2 sync build
[CSCub48778](#) : Sudo Insecure Temporary File Use in RPM (CVE-2012-3440)
[CSCua19730](#) : Add Telepresence Support for Bandwidth Allocation Feature
[CSCub72167](#) : 9.0(1)/8.6(2) Support files for Cisco TelePresence models
[CSCub71163](#) : Orphaned MTP / CFB / MOH / ANN conference sessions with no rx/tx streams
[CSCub67519](#) : CUCM 8.6.2.22900-9 BULK update of Phones triggers java exception error.
[CSCub52470](#) : Send extra notify message to 3rd-party SIP endpoints when network glitch
[CSCub48609](#) : Cannot request device name with lower case letters
[CSCub10965](#) : GLIBC Arbitrary Code Execution Vulnerability for RHSA-2012;1097-1
[CSCua91582](#) : Audio Only option for phones Lock Icon

[CSCtr91719](#) : FTP for RTMT Scheduled Trace Collection Not Ending Packet with CRLF
[CSCub77254](#) : Calling Party not in CDR for calls inbound on MGCP controlled FXS/FXO
[CSCub18415](#) : CUCM IM&P 9.5 Label Move Innovation Proposal
[CSCtx01219](#) : SSO component restarts Tomcat
[CSCub33158](#) : Bind DNSSEC Vulnerability CVE-2012-3817
[CSCub42012](#) : When Connected Number IE is not populated, display dialed num on IP phone
[CSCtz35479](#) : Add Line Text Label option to Telepresence devices
[CSCub56734](#) : ipvmsd core file due to invalid format trace message
[CSCub34381](#) : QSIG protocol profile gets changed by CUCM in CT-Initiate error response
[CSCub34106](#) : Unable to auto-update IPMA Assistant Console after upgrade
[CSCub08259](#) : MGCP Gateway fails to do overlap sending when using primary-net5
[CSCub00939](#) : The call gets disconnected when the remote party is busy over the PSTN
[CSCub00243](#) : libstdc++ update needed for RHSA-2011-0025
[CSCua92010](#) : CUCM Subscriber core
[CSCua73936](#) : DPark fails due to SsJoinInd & SsDataInd release parking Race Condition
[CSCtz27133](#) : Failed to estb media connection to MTP ANN or CFB
[CSCtz08251](#) : SIP Message Data corruption cause core dump during load.
[CSCts06233](#) : ccm service cores in 862 when IPsec config protocol is set to any
[CSCub38715](#) : remove unneeded Tomcat Host Manager Application
[CSCua85519](#) : ciscortplib crashes with access violation error by race condition
[CSCua63985](#) : H323 Fast-Start Release Complete not disconnecting second leg properly
[CSCtz83937](#) : TFTP Certificate Mismatch btw DB and file system after DRS restore
[CSCtz57149](#) : SIP phone unable to send DTMF out MGCP w/ QSIG prior to Connect
[CSCty77802](#) : Terminal observer continues to receive events after it has been removed
[CSCty72866](#) : SIP From header does not cater to MGCP gateways with longer names
[CSCty64623](#) : Character limit in IP Phone Services "Service Name" Field
[CSCty18472](#) : Call to meetme number will log Unknown
[CSCtx66368](#) : User Facing Feature Data (UFF) is not preserved over L2 Upgrades
[CSCtx32290](#) : TSP misses Phone-State events during the phone is reset
[CSCtt94314](#) : Updating Placed Call History on SIP phone for cross-cluster call
[CSCtt08500](#) : CCMAAdmin Route Pattern Update Error when Route List/Gateway Removed
[CSCts80325](#) : Updating Placed Call History on SIP Phones for intra-cluster calls
[CSCub40850](#) : Call is not routed to destination thru ECC - follow up fix
[CSCub25618](#) : overlapping translation patterns causes issues for CTI in CfwAll
[CSCub11023](#) : Translation pattern not fully created over AXL interface
[CSCub02130](#) : CUCM g711 codec set incorrectly for g729 MGCP-SIP call with RSVP enabled
[CSCua84884](#) : H323--CM--SIP. Refer transfer from SIP device results in call drop.
[CSCua09290](#) : CLI "set password user security" did not set the correct apps password
[CSCtz92550](#) : Proxy TFTP enhancement to avoid CTL file searches to non-secure clusters
[CSCty65702](#) : Implement SSO robust disable command and Support SSO logs in RTMT
[CSCtx46132](#) : 'A Cisco DB' service hung in STARTING state after upgrade
[CSCtw64667](#) : Problem uninstalling a dialplan after upgrade
[CSCsz68286](#) : UCM Security Issue; Cookie Initialization and Attributes
[CSCub22278](#) : Increase CCD Learned Patterns upper limit from 20K to 100K
[CSCtz96078](#) : Adding Support for VG350 gateway in BAT
[CSCtz74532](#) : Memory leak in call stack call manager 8.6.20000-2
[CSCtz18126](#) : CTI Authentication fails for SSO tokens larger than 4096 bytes
[CSCty99442](#) : Gnutls Vulnerabilities (RHSA-2012-0428-1)

[CSCtx98976](#) : Update JDK to 1.6.0_31
[CSCtr64935](#) : RSYNC Update for RHSA-2011-0999-1
[CSCtq83354](#) : CTI Authentication fails for SSO tokens larger than 4096 bytes
[CSCtj43528](#) : FindAndList Gateway Template does not display the templates
[CSCCua90319](#) : Call Failure is seen when using Dual Mode Phone with MGCP GW
[CSCCua53272](#) : Python Vulnerabilities (CVE-2012-1150, CVE-2011-4940, CVE-2011-4944)
[CSCCua39041](#) : RTMT version not reported correctly in Build Load Info
[CSCCua34545](#) : Bind Vulnerabilities for DNS Service (CVE-2012-1667, CVE-2012-1033)
[CSCCua17013](#) : OpenSSL DTLS Vulnerability (RHSA-2012;0699-1)
[CSCCua07917](#) : Cluster will not advertise newly added route patterns via CCD/SAF
[CSCtz74477](#) : CUCM--slow memory Leak due to Power save plus alarms generation
[CSCty99421](#) : Glibc Vulnerabilities (RHSA-2012;0397-1)
[CSCty15013](#) : LibXML Vulnerability (RHSA-2012;0324-1)
[CSCtx45528](#) : pwd reset cli returns good but doesn't change password
[CSCtw80681](#) : Perl may be vulnerable to published vulnerabilities
[CSCtq30130](#) : PMR 04199 new csdk does not allow database connect.
[CSCte41494](#) : ETSGJ-CH; Extension mobility credentials stored in one of the log file.
[CSCtz29092](#) : MCU registration status stays as Unknown
[CSCCua84104](#) : Multiple H323 Gatekeeper configuration causes CCM service core dump
[CSCCua78828](#) : Incorrect reinvite handling by CUCM after previously receiving 488 msg
[CSCCua70597](#) : Race Condition in BuiltInBridge code
[CSCCua62209](#) : CUCM stops responding to SIP messages due to an incorrect transID
[CSCCua55511](#) : BAT Phones/Users - When adding an existing DN, some fields not changed
[CSCCua44645](#) : MGCP FXO CallerID missing when call is forwarded via CTI RP
[CSCtz41502](#) : CUCM Call Pickup visual notification missing
[CSCts30643](#) : Java Exception found in FindAndList Phone Page for DN
[CSCCua33814](#) : DRF start time drifts further each day
[CSCtz20987](#) : DST- Update CM to Olson TZ version 2012c
[CSCCua47930](#) : CUCM 8.6 drops call as fails parse QSIG Call-proc tunneled in SIP 183
[CSCtz50389](#) : TSP crashes
[CSCtz47276](#) : Wave Driver doesn't assign the default dynamic port range in Vista/7
[CSCtx96255](#) : WebAdmin query optimizations for BAT.
[CSCtw84714](#) : Call Queuing-Multicast Moh Timeout error
[CSCtu09935](#) : Secure icon not shown for secure conference call
[CSCCua36998](#) : Video M-line mangled -SAVP answer sent by CUCM to AVP offer from SBC
[CSCCua14268](#) : Call transfer (Blind/Consult) doesn't work for Video (CUVA) calls
[CSCCua12011](#) : Calling Party number is not seen in CDR report for Incoming Call
[CSCtz95738](#) : Phone-VPN-trust certs not backed up during a disaster recovery
[CSCty68640](#) : 9.3(1) SCCP/SIP loads and support files for 8941 & 8945 Phones
[CSCtx85340](#) : No video streaming on 8945(SCCP) phone - call transfer from Ex60 to E20
[CSCtx79632](#) : 9.3(1) SCCP/SIP loads and support files for 79xx series phones
[CSCtx79624](#) : 9.3(1) SIP loads and support files for 9971, 9951 and 8961 IP Phones
[CSCtx64261](#) : 9.3(1) SCCP/SIP loads and support files for 69xx IP Phones
[CSCCua19164](#) : CTI Manager does not return correct device handle
[CSCtz97475](#) : 9.2(4) phone loads and support files for Cius 4G & Wifi Phones
[CSCtz50729](#) : EMApp fails to connect to local EMSservice due to certificate mismatch
[CSCty94761](#) : BAT Export/Import Changes Values on CTI Route Point call forward all
[CSCtx84758](#) : Enhancement to make Keep Alive timer configurable for the Cius Phones

[CSCua27235](#): QED updates to VG350 Gateway

[CSCtz91877](#): Caller ID is no longer provided by CiscoTSP for parked external call

[CSCtz77067](#): SSO is not getting enabled and agent installation is not successful.

[CSCty01891](#): DRF Local agent aborts after communication to Publisher is lost

[CSCtu27583](#): Heavy use of Announcements causes CPU loop in IPVMS

[CSCua08595](#): CUCM MTP leak if Early media offered by far END

[CSCtz89191](#): Enablement of free IM/Presence for newly provisioned IM/Presence Users

[CSCtz37099](#): CLI Session Timeout missing during upgrade

[CSCua00864](#): CCM Core on SipLineStructFacade while call_remoteinuse

[CSCtz94655](#): Core on PolicyAndRSVPRegisterRes signal

[CSCtz70820](#): CmtempDbSpace_Used perfmon counter fails to report correctly

[CSCtz12797](#): Status of calls remain stuck and do not get updated

[CSCty80513](#): Attempt to launch RTMT fails with no warning after upgrade to restricted

[CSCtx40767](#): Call is not routed to destination thru ECC

[CSCts96145](#): no ringback on Eearly-offer enabled Q.SIG over SIP trunk tandem calls

[CSCtz89632](#): File support for build process for IM enhancement

[CSCtz84256](#): CTI unpark event is missing for park DNs

[CSCtz76809](#): CTI rehomeing doesnt work when LinkOOS received & Provider open pending

[CSCtz58882](#): Call leak when an MGCP device can not obtain a channel for non-QSIG PRI

[CSCtz47263](#): Core generated running call redirection by application call flows

[CSCty97023](#): CUCM 8.5.1.10000-26 QSIG facility in 183 not sent from stack to SIPCdpc

[CSCty29593](#): UCM Subscriber Node used as SME CORE dump under traffic.

[CSCtx84095](#): MTP/Xcoder resources getting hung because of inactive SDP

[CSCtz62088](#): CTIManager crash on on DeviceCloseNotify during EM Logout

[CSCty86050](#): Termination Boolean dtmf digit are discarded by IPVMS driver

[CSCtx03474](#): Intermittently after failover, some CTI RP or Ports failed to register

[CSCtw88054](#): CCM Standard Admin User able to elevate permission settings

[CSCtt21719](#): Call Forward All broken for E20 in CUCM 8.6.2

[CSCts72184](#): Speed dial BLF to PSTN number could trigger CCM memory leak

[CSCty13820](#): Kexec-Tools Vulnerabilities (RHSA-2012-0152-3)

[CSCtx76742](#): Webdialer should support "+" in the userid

[CSCtx30363](#): Update LibXML to Address Published Vuls per RHSA-2012-0017-1

[CSCts89659](#): Calling party number type and plan unknown on Mobile Connect Call

[CSCts53336](#): missed calls are still logged when unchecked "Log Missed Calls "

[CSCts29293](#): CCM core on HuntListCdr code while performing SendCcNotifyReq

[CSCtz51234](#): Checkin 9-2-4 Load for 6921/41/61 phones

[CSCtz42848](#): Incorrect BLF DCP number in Exported file when same DCP number is used

[CSCtz29527](#): PhoneSetDisplay displays error and causes a memory leak in the CiscoTSP

[CSCtz29142](#): UCS CUCM Media resources introduces jitter causing bad voice quality

[CSCtz28748](#): When logging into extension mobility gets Login unsuccessful Unknown 7

[CSCtz24262](#): CCM Core on SIP Line from invalid data in mLineInfo

[CSCty97691](#): RouteList unable to route calls.when trunk/GW runs on multiple nodes

[CSCty81435](#): x-cisco-mux sent to device that does not support the attribute

[CSCty51130](#): RL fails to pick local subscription when remote node goes OOS

[CSCtx28806](#): Active call gets stuck on sip phones that drop due to network loss

[CSCtw47969](#): UCM SIP 503 error - Cisco Jabber mobile client unable to register

[CSCtu08102](#): Service module support for VG350 gateways

[CSCtu07982](#): QED changes to add support for VG350 gateways and service modules

[CSCtz30396](#) : SCCP Phones Do Not Register With Certain Station KeepAlive Intervals
[CSCtz25519](#) : CR/LF in QED XML cause could not save device configuration
[CSCtz07716](#) : CTIManager triggered database updates severely delays replication setup
[CSCtz01499](#) : Got SQLException pop up when click on the "Remote Cluster ID" field
[CSCty91772](#) : jabber Mobility Identity call dropped when wlan connectivity lost
[CSCty75301](#) : CUCM 8.6CAPF doesn't recognize private key generated during CSR
[CSCty71445](#) : CUCM 8.5 MTP leak if Early media offered by far END
[CSCty58465](#) : Intermittent call drops when CVP transfers call to available agent
[CSCty51509](#) : Enable "Security by Default" for 8941 & 8945 Phones
[CSCty50190](#) : EM API fails to authenticate when the password of applID contains &
[CSCty43007](#) : Adding Live Desk Number and other settings for Telepresence Endpoints
[CSCty26928](#) : Adding/removing NTP changes licensing MAC warning missing
[CSCtx65886](#) : IOS requires CUCM to send SCCP PortClose msg to prevent MTP port leak
[CSCtx41471](#) : Enable new features for iPhone client
[CSCtw89219](#) : Call from CUPC to Tandberg EX90 drops when escalating to video
[CSCtt76455](#) : Failover to secondary CTI Manager fails if primary loses connectivity
[CSCtt00016](#) : Cause Codes are not preserved when call routed through RouteList
[CSCts30653](#) : Java Exception found in FindAndList Phone Page for DevicePool
[CSCts16568](#) : No Owner User ID in Phone Export on 8x
[CSCts01319](#) : Enable bulk unlock of the ITL File
[CSCty81696](#) : Cius video call to CIPC/CUVA video discontinue during docking/undocking
[CSCty36110](#) : CUCM 8.6 Tomcat OOM with "com.rsa.sslj.x.cu" suspect under high AXL Load
[CSCtw93153](#) : WebAdmin query optimization for phone search by Device Type
[CSCtl44970](#) : PMR 84047 Assert Failure read_recordunexpected log record type 11.50.
[CSCty81681](#) : 9.2(4) SIP loads and support files for 9971, 9951 and 8961 IP Phones
[CSCty74429](#) : Incorrect DSCP tagging for Video Calls
[CSCty72195](#) : UCM echos back IP for inactive answer for certain cases
[CSCty67720](#) : CTI handler leak in Callpark manager
[CSCty45199](#) : No install logs for RU failure during preboot phase on MCS7825H3
[CSCty22758](#) : CUCM not handle mid-call codec change well when "MTP required" checked
[CSCtx08945](#) : SQL injection in CUCM
[CSCtw71312](#) : Newly created Trigger can't be registered to CUCM at certain operation
[CSCtu33251](#) : Precedence call when IMSClient add 2nd participant to conferencecp-
[CSCts67352](#) : RTMT Alerts - Increase the Size of the "User-defined email text" Field
[CSCty75647](#) : Intercluster connectivity loss cause UCM sub nodes coredump
[CSCty71830](#) : Core generated due to SIP trunk issue
[CSCty69753](#) : Direct Call Park Number is not released under race condition
[CSCty67381](#) : Directed call park and assisted directed call park causes app crash
[CSCty64451](#) : CUCM Subscriber Node Core dump under SIP Trunk traffic.
[CSCty58884](#) : Un-Restricted version type is not detected during L2 upgrade.
[CSCty48978](#) : 9.2(3) phone loads and support files for Cius 4G & Wifi Phones
[CSCty04584](#) : Idle event not reported in hunt list RNA race scenario
[CSCtx43337](#) : CPU DoS During Malformed Packet Attack on Unused UDP Ports
[CSCtx08944](#) : Multiple critical XSS exists in Cisco unified communication manager
[CSCty83915](#) : Alerting when too many RTMT sessions attempts connect to CUCM
[CSCty77560](#) : Annunciator for SIP Conditions
[CSCty63127](#) : UCCX doesn't receive deviceUnregisteredEvent upon EM logout
[CSCty63105](#) : Incorrect recordType in the DeviceLineInfo right after an EM Login

[CSCty62699](#) : Server Hung at upgrade while deleting master rpm.
[CSCty54510](#) : No way audio when two phones try to answer a call from HuntList
[CSCty48382](#) : Recording fails on IP Phone when SCCP Dialer does a consult transfer.
[CSCty39354](#) : H323 Fast Start to SIP issue when inbound reINVITE SDP does not change
[CSCty26906](#) : TLS Handshake failure for SIP Trunk when symlink fails to be created
[CSCty26091](#) : UCCX consult transfer step to established meet-me conference fails
[CSCty07061](#) : SIPStack- should accept RR header received in 18x regardless of prack
[CSCtx95138](#) : UCCX consult transfer step to established meet-me conference fails
[CSCtx35002](#) : OLC Ack not received across H.323 ICT
[CSCtt11347](#) : CSA alarms raised for AXL hourly cron job
[CSCtt00105](#) : Users with IPCC ext showing as duplicate when running Sub Sync in CUPM
[CSCts66918](#) : CUCM sends calling number in SIP INVITE after a 503 service unavailable
[CSCts36950](#) : Conference should not happen and should fail due to geo-locations config
[CSCtr84752](#) : CallManager service core dump
[CSCtr82251](#) : CFNA triggered after direct transfer call is answered
[CSCti00625](#) : CallActiveEv intermittently sent instead of CiscoConsultCallActiveEv
[CSCsv50978](#) : Call Back "Dial" softkey do not work when speaker disabled
[CSCty62006](#) : CDR not populated with right Calling Party Num if From hdr contains FQDN
[CSCty44681](#) : Duplicate DTMF digits while using a Software conference bridge
[CSCtx84426](#) : cxn upgrade fails when upgrading from 8.5.x to 8.6.x - CCM DB full
[CSCtx75311](#) : Upgrading from 8.6 shows ?????? question marks when completed
[CSCtx44916](#) : CUCM RIS DC core dump due to timeout
[CSCtx22323](#) : Annunciator for SIP Conditions
[CSCtw82738](#) : Cimservr CORE because detected but not removed
[CSCtt17946](#) : Unable to run CDR reports after upgrade due to "Migration in progress"
[CSCts62013](#) : Memory Leak caused by RouteListCdr
[CSCty39288](#) : Location bandwidth leaked when call park is retrieved and call ends
[CSCty34252](#) : Not getting all the lines of RT device in dev caps.
[CSCty14880](#) : 720p lite call drop between P2P call
[CSCty04889](#) : SessionBW low bandwidth behavior for BFCP-enabled SIP trunk
[CSCtx96029](#) : Prevent SNRD/Mobile Device loop caused by DB/Change Notify
[CSCtx84918](#) : plain FAC showing up on SIP phone 8961 / 99xx
[CSCtx57665](#) : OpenSSL Vulnerability per RHSA-2012-0060-1
[CSCtx40171](#) : Hold fails to SBC when Media Streaming App Disabled
[CSCtx35461](#) : IOS - Dspfarm/Transcoder SCCP session gets hung for non supported codec
[CSCtx29110](#) : AXL Support for display Instance
[CSCtw94724](#) : Services deactivated after Refresh Upgrade to 8.6.2
[CSCtw94055](#) : Version checking and alerting when RTMT attempts connect to CUCM
[CSCtw84793](#) : CUCM strip off contact header in sip invite when forward reinvite to Ex60
[CSCtt45018](#) : Update JDK to Address Published Vulnerabilities
[CSCtt19490](#) : Incoming call from RD fails when Overlap receiving is enabled on MGCP
[CSCts62000](#) : EX60 (or EX90) calls fail to another EX60 (or EX90) over UCM SIP trunk
[CSCts00299](#) : Telepresence audio bandwidth modified to low value
[CSCtr70893](#) : SDP Build failure for application media with no floorctrl attr
[CSCtr60976](#) : Add-in callers cannot hear Codian devices after hold/resume
[CSCth95017](#) : Configurable parameter on how callingparty is displayed for hunt groups.
[CSCsh63057](#) : Missing ConferenceEnded when joining same call twice
[CSCty38921](#) : RTMT throws VMWareTools.log permission error when downloading upgrade lo

[CSCty23317](#) : AbbrDial With Incomplete Speed Dial Gives Reorder Tone
[CSCty22899](#) : Devices do not go in service after EM logout and CCM restart
[CSCtx98136](#) : Update GLIBC to Address Numerous Vulnerabilities (RHSA-2012-0126-1)
[CSCtx29696](#) : IPMASpeeddials get configured incorrectly in the CUCM DB
[CSCtw73590](#) : VSphere initiated shutdown or restart not logged to system-history.log
[CSCtw46813](#) : CUCM does not process inbound H245 OLC for tandem call
[CSCtu33310](#) : CUCM upgrade hangs on UCS during inactive master RPM deletion
[CSCtu26464](#) : CUCM Smart Call Home messages are missing in SCH History report
[CSCtu19859](#) : CTIManager trace wrong location on upgrade when /spare exist
[CSCtt41083](#) : Users cannot get deskphone mode to work
[CSCts76265](#) : Bulk Import - Route list member is Empty
[CSCts29266](#) : Movi Call only has one way video
[CSCtr15589](#) : idivert failed after nurd redirect call
[CSCty15458](#) : Unable to record voice for SIP calls
[CSCtx98146](#) : add ciscoSupportField to CSF Device for CUCM 7.1.5 through to CUCM 8.6.2
[CSCtx07128](#) : ccm service core after releaseBandwidth For MediaResource
[CSCtw80016](#) : H225D stopped after receiving DmResetDeviceReq two times within few mill
[CSCtw63038](#) : SNMP HostAgn Core. CUCM 8.5.1.12014-3
[CSCtw53886](#) : CUCM interpret the oRFR code incorrectly from SIP to SCCP
[CSCtu28672](#) : Support files for Telepresence models TX9000 and TX9200
[CSCtu04746](#) : settroubleshootd fast memory leak with SELinux context errors
[CSCtt39374](#) : ICT between two clusters with CVP involved, MSDAck not being sent
[CSCtt04590](#) : Qsig tunneling over SIP trunk fails for ISDN Alerting with no PI
[CSCts99665](#) : Authentication failure will cause provider open to fail with OutOfMemory
[CSCts96733](#) : unable to fork a call (remote destination) when UC client crashes or rej
[CSCts44873](#) : Cluster Manager may take a long time to authenticate subscribers
[CSCtr78325](#) : Call loop triggers CallManager (CCM) memory leak due to RouteListCdrC
[CSCtr59256](#) : QSIG Path replace fails after CUCM detects PRPropose collision
[CSCtx96816](#) : 3905 devpack test- "Softkey Template" is missed in CUCM 7.1.5 and 8.6.2
[CSCtx38318](#) : Failed to migrate records to tbl_generated_report table from 7.1.5.33900
[CSCtw63984](#) : CUCM 8.6 Tomcat OOM with "com.rsa.sslj.x.cu" suspect under high AXL Load
[CSCtt05524](#) : CTI Route Point or CTI Port remains unregistered after update or rename
[CSCts91620](#) : qed and MS change for 79xx Headset sidetone control development in 923
[CSCts47201](#) : Get NPE from deviceUnRegisterEvent
[CSCtj16922](#) : There is one way audio when mtp is inserted over SIP EO trunk
[CSCtx96613](#) : Mobile connect process leak and H.323 calls improperly disconnected
[CSCtx65207](#) : Route Pattern Flag doesn't take effect for a Unified Mobility call
[CSCtj73909](#) : Tomcat core during restore and java core during RU including RU COP
[CSCtx28033](#) : Support files for Cisco TelePresence SX20 and MX300 models
[CSCtw66529](#) : PIN Change Service needs to honor alphanumeric User ID service parameter
[CSCto80824](#) : RTMT throws VMWareTools.log permission error when downloading logs
[CSCtx75537](#) : Device does not unregister when application closes it
[CSCtx72618](#) : Device pack check in for Cisco 3905 9.2(2)
[CSCtx71084](#) : Device pack check in for Cisco ATA-187 9.2(3)
[CSCtx70059](#) : 9.2(3) SCCP/SIP loads and support files for 8941 & 8945 Phones
[CSCtx69548](#) : SELinux policy prevents source 'rm' from accessing ./services_tmp.conf
[CSCtx57751](#) : CTIManager Core on DeviceEventRouter
[CSCtx35686](#) : SELinux policy prevents CTIManager Authentication from DNS Query

[CSCtx28604](#) : Check 79xx 9.2(3) firmware into cm branches
[CSCtx27115](#) : Remote destination is displayed in connected state although masked
[CSCtx09925](#) : Device pack check in for Cisco IP phones 8961, 9951, 9971
[CSCtw90867](#) : Change to DP of device controlled by CTI user not propagated to CTIMgr
[CSCtw72937](#) : conference bridge DTMF method is changed from OOB only to OOB + RFC2833
[CSCtw56740](#) : No DTMF when UCM receives invite with fntp-101 before rtpmap-101 telepho
[CSCtu01360](#) : Partition of BLF Directed Call Park is not able to set by BAT
[CSCts56726](#) : CiscoProvTerminalUnRegisteredEv CiscoAddrRemovedEv failed after EM Login
[CSCts47497](#) : No event on EM on NonControlDevice after CCM Failback
[CSCtx05974](#) : H225D should allow empty bearer cap from Conference
[CSCtx04108](#) : Channels are marked as busy on cucm side.
[CSCtx04086](#) : Channels are marked as busy on cucm side
[CSCtx30744](#) : Location Leak causes unexpected call reject
[CSCtx15401](#) : Wrong bearer capabilities in call originated by sip video phone SPEECH
[CSCtx01289](#) : MGCP - Incoming NOTIFY message causing Call disconnects
[CSCts64005](#) : Kernel Panic in UCCX 8.0.2.11004-12
[CSCtx33094](#) : CUCM 8.6.1 auto registraion is not working
[CSCtx21804](#) : SDL OOS caused by MX offer that hangs trying to extract SIP SDP info
[CSCtw84678](#) : Redirected call does not honor calling party numbering plan and type
[CSCtw47561](#) : Device Search using Device Pool as filter results in SQLException Error
[CSCtw46639](#) : Detect Unified CM Connection Failure permanently overridden by device
[CSCts80956](#) : Call Manager not classifying video endpoints correctly based off H245
[CSCts22550](#) : Phone query by device pool shows incorrect records found
[CSCts19933](#) : Device search by device pool returns incorrect device status
[CSCtx11595](#) : Update KRB5 RPMs to Address Critical Vulnerability CVE-2011-4862
[CSCtw93269](#) : Subject Alternate Hostname does not work for CUCM 8.6
[CSCtw82594](#) : CCM Core after accessing null pointer for Station Keepalive Timer
[CSCtw66650](#) : AXL update of Pickup Group field for Hunt Pilot does not work
[CSCtu39495](#) : CUCM needs to be able to hide calling number when CLIR is set
[CSCtt95983](#) : CAPF certificate not backup'd/restored with DRF
[CSCtt26268](#) : Changing DN of supercopied phone does not default all line CSS values
[CSCtt05246](#) : BAT Export Configuration recurring schedule leaks Informix DB memory
[CSCts99246](#) : create OVA files for ESXi 5.0
[CSCtx08526](#) : IPMA- Spanish Locale - Speed-dials lost when client logs out and back in
[CSCtw70877](#) : DTMF failure to SIP trunk when calling from SNR remote destination
[CSCtu27653](#) : mobile connect fails after first successful call via AAR
[CSCts83446](#) : CUCM 8.6. Tomcat CSR does not get alternate hostname information from se
[CSCtw79059](#) : CTI Port not registering GetAvailWave() returned WAVELIST_NOT_ASSIGNED
[CSCtw53001](#) : One-way audio when one party leaves the conference.
[CSCtw52439](#) : ccmAgt vmSize is increasing when register/unregister phones
[CSCtw47566](#) : Outbound UPDATE not sent to URI specified in Contact Header
[CSCtu99282](#) : Update BIND to Address CVE-2011-4313 per RHSA-2011-1458-01
[CSCtu67390](#) : 7.1CUCM does not 200 OK/PRACK when in race condition with 200 OK/Invite
[CSCtt15145](#) : Mobility no ringback when the internal phone associated is unregistered
[CSCtw66721](#) : Crafted SDP message may cause crash or interoperability issue
[CSCtw73687](#) : Adding 5th Gen Cius WiFi device firmware version 9.2(2) to CUCCM
[CSCtw67186](#) : Phone Loses Registration to UCM But Appears Registered on Its Display
[CSCtw52265](#) : Incorrect default payload type set for G.Clear codec

[CSCtu19729](#): CAPF cores 26 times within 1 hours in Publisher
[CSCtt31692](#): secure status is sent to PSTN side for call coming from non-secure side
[CSCtt10761](#): add/updateRemoteDestinationProfile API not allow devpool uuid w/brackets
[CSCts58012](#): Add/Update Remote Destination Profile allows null in device pool
[CSCtu73538](#): Cisco Unified Communications Manager Skinny Client Control Protocol Vuln
[CSCtw64176](#): Adding 9.2(2) 5th gen phone firmware
[CSCtw59234](#): Check-in Cisco 7921, 7925, 7926 firmware 1.4(2) to CUCM
[CSCtw49338](#): Change service param int to bool for progress->disconnect translation
[CSCtw09624](#): CCM core when memory was no longer valid after the StationD stopped
[CSCtv09841](#): Checkin 9-2-2 phone FCS load for 6901/11/21/41/61/45(both SCCP and SIP)
[CSCtu92322](#): CiscoTerminal.getDeviceState() does not return current terminal status.
[CSCtu38296](#): CUCM need to set RCD info even for MGCP recvonly mode for sRTP calls
[CSCts86548](#): Removing phone results in incorrect phoneDevice ID removed from TSP
[CSCts69805](#): call drops when hold, because of the "handleMultipleCodeInAnswer"
[CSCtr86824](#): CalledParty stuck, if the disconnect happens in the middle of transfer
[CSCtu42152](#): Call failure with third party sip client if ! & SIP Domain name is used
[CSCtu34381](#): JTAPI connection clears CUCM settings
[CSCtt96292](#): PSTN phone is ringing for 8 sec after disconnecting the call
[CSCts89144](#): MGCP Retry Keepalive Handling - Restart Port should eventually stop
[CSCts64257](#): CLI does not accept 1 character label in domain name
[CSCts47952](#): CUCM8.5.1 MTP resource leak on SIP trunk
[CSCtq40657](#): Issue with QSIG over ICT MWI relay to ISDN PRI QSIG trunk failing
[CSCtu39388](#): UCM is not responding to OPTION Ping from VCS causing Trunk to go OOS.
[CSCtu39017](#): 9.2(2) SCCP/SIP loads and support files for 8941 & 8945 Phones
[CSCtu27381](#): CBTerm causes loop and CPU spike during Extension Mobility auto-logout
[CSCtu16466](#): Make BFCP configurable for CTS endpoints via QED
[CSCtu00209](#): Problem with answering the call by Cisco Jabber
[CSCts89285](#): Unexpected CallCtlConnDisconnectedEv when party drops from conference
[CSCts18909](#): No RFC-2833 DTMF signaled when events 0-15 aren't explicitly signaled
[CSCts10309](#): ITA+CAT;Mobile extension cannot be changed
[CSCts02791](#): Dependency records for call pickup group returns no results
[CSCtu22772](#): Checkin 9-2-2 QED for 6901/11/21/41//61/45
[CSCtt70472](#): Migration of data fails IF there is any record in 'tbl_generated_report'
[CSCts63030](#): Document Camera option is missing in CTS1300-47 and CTS1310-65
[CSCtt07767](#): Unacknowledged SIP UPDATE for an outbound call when glare occurs
[CSCts98692](#): Guard-Out Timer missing from FXO on 2900 gateways
[CSCtt87069](#): No audio provided to calling network Disconnect received with PI 8
[CSCtt39234](#): CPCA CIA Changes
[CSCtt10536](#): Cucm doesn't relay dtmf(sip notify) after call transfer
[CSCts60763](#): CUC is not interpreting Swedish (ISO-8859-1) 8bit
[CSCts45027](#): CUCM QED file commits into 7_x_x and 8_x_x for 88xVA-V
[CSCtr83193](#): RL fails after SDLLinkOOS with node on which trunk is registered
[CSCtr79907](#): ALL-LANG- CUCAdminTwo periods are in the end of a text.
[CSCtr15342](#): UC - Call the Sender option not announce for Unknown callers
[CSCtq34297](#): JPN- CUC- Field names are not localized on some status messages.
[CSCtt93790](#): No audio/dead air on CFA/CFNA to 3rd party voicemail
[CSCtt37428](#): convertToBindDN does not take place in case of pName containing Idaps//
[CSCtt34549](#): MTP session not released, if call fails to Primary Server in ICT

[CSCtt30291](#): Adding 9.2(2) 4th gen phone firmware and 9.2(2) QED changes to CUCM
[CSCtt27840](#): Webdialer 1st call failes when extension mobility on local node is down
[CSCtt22879](#): CCM core while utilizing Built-In-Bridge & Silent Monitor
[CSCtt15482](#): Different branch parameter in the Via header for same SIP Transaction
[CSCts82111](#): OnLine Help for 8.6(2) Not Visible on Latest Image.
[CSCtt18005](#): CM 8.6.2 Upgrade Failing Due to NTP Reachability
[CSCts79801](#): CUCM is running a ver of NSCD that may be vulnerable to published vulns
[CSCts60056](#): q735 namespace priority mapping broken with SIP-QSIG tunneling
[CSCts58289](#): Hunt group member unable to retrieve a call parked for the second time
[CSCts57160](#): Video conference call disconnects after enacting mobility
[CSCts03066](#): Agent greeting call failure during load with CCM861
[CSCtr64981](#): Updates for RHSA-2011-1005-1 and RHSA-2011-1073-1
[CSCtg92070](#): Add ability to set conference layout with Telepresence Adhoc MCU
[CSCtt01724](#): SIP Register not accepted by cucm when cucm hostname starts with digits
[CSCtt01052](#): DND Option can not be changed for IP Communicator
[CSCts96726](#): Call Transfer from 9971IP phones Fail
[CSCts46531](#): CLI "show open ports" needs to use option to prevent port name in output
[CSCts39201](#): Subscriber incorrectly indicates NumRegisteredDevices is exceeded
[CSCts23810](#): Unified CM does not forward ACK on tandem SIP to SIP call flow
[CSCts23319](#): After installing devpack all FCP options are not available
[CSCtr99347](#): BLF Presenc status is unknown across SIP Trunk for SIP end-points
[CSCtr78976](#): Secured Directory URL repopulates to default URL upon cucm reboot
[CSCtr64842](#): EM is logging out users before the auto logout timer expires
[CSCtt09033](#): Call Park error "No Park Number available"
[CSCtt05252](#): Adjust CallPark Audit Timer
[CSCts69270](#): CCX CTI ports may stuck in out-of-service state when UCM Upgrade/Restart
[CSCts65486](#): Updating Line Group causes some lines to be removed on sub
[CSCts32387](#): Switch Version fails after upgrade from 8.5.1.11900-21
[CSCtg94673](#): CUCM core dump when SIP phone deregisters during a call
[CSCts82966](#): Support "Lock Device During Audio Call" in Cius
[CSCts76540](#): Upgrade rules to prevent 862 Respins from installing over ES's
[CSCts62253](#): NSS and NSSPR Update for RHSA-2011-1282-1
[CSCts34379](#): CUCM portal may return "Log on failed"
[CSCts24630](#): CUCM does not forward busy tone when RD in PSTN returns busy across MGCP

Resolved Cisco Unity Connection Caveats in 8.6(2a)es62; base ES for 8.6(2a)SU3

[CSCtg91018](#): Upload of Customized Logon Banner fails
[CSCtr72791](#): Feature-ReqPerform Cross-Box Transfer On Call Forward to Voicemail
[CSCtr66655](#): Error message dispalyed on entering valid phone number
[CSCud24957](#): CUC 8.6.2 Bulk Edit Select All Button doesn't maintain original filter
[CSCud86537](#): Intro not played for forwarded secured message
[CSCud67131](#): No RTMT alerts in license expiration/violation for speechview Users
[CSCud20257](#): UC 8.6Cannot delete user from the webpage if limit search is COS
[CSCud00435](#): Not able to subscribe multiple event type in one CUNI subscription reqst
[CSCuc36589](#): CUC French locale - wrong translation in Visual Voicemail.
[CSCub79782](#): Menu entries too long in visual voicemail settings on 79X5 IP phones
[CSCuc56793](#): overwrittenb message in Pub is incorrect.

[CSCuc23414](#) : No RTMT Alert was generated for the license expiration warning
[CSCub86614](#) : VVM locale updation for RT phones
[CSCuc22800](#) : Enabling TLS on SIP Trunk between UC and CUCM leads to all ports busy
[CSCub84905](#) : New user template doesn't copy Message Action config
[CSCtz45445](#) : UC - Reports in Cluster Don't Reflect Proper Data Due to ReportDB Design
[CSCub63364](#) : AA Supervised Transfer to Meetme fails when invoking local SW CFB
[CSCtz67257](#) : CUNI notifications not sent for messages left during SBR
[CSCtx42950](#) : Core generated on Special Characters in Mail Subject Field
[CSCtz92935](#) : Autodiscovery should support concurrent MailboxSync threads.
[CSCub24377](#) : Visual voicemail cannot reply to calls from external callers
[CSCua88289](#) : API is not able to play audio file uploaded through CUTI for user
[CSCtz76475](#) : Unity Connection 8x ignores Stop Media Transmission coming from CUCM 8x
[CSCtz76269](#) : CPU hog while sending malformed UDP packets
[CSCty53266](#) : Msgs are receiving with delay while running load on 20K users.
[CSCua12209](#) : CUC migration, Platform Administrative Web Service should get activated
[CSCua00059](#) : Upgrade fail on SU releases when locales installed
[CSCua63049](#) : UC System Accounts expire after L2 Upgrade
[CSCtx83737](#) : Tomcat core observed on 8.6.2 ES13
[CSCua28575](#) : Update JDK to 1.6.0_31
[CSCtz55696](#) : eventservicesubscription table cleared by tomcat after reboot
[CSCua05063](#) : CUC 8.6(2)ES32-Unable to view Service management Page
[CSCtz95563](#) : Import All button Fail to import users from CUCM through AXL integration
[CSCty61699](#) : CUCimport users via CUCM returns zero if query request too large
[CSCtz29008](#) : NDR mail flood on configuring Out of Office Assitant
[CSCtj18105](#) : QEA; CUADMIN; DBCS is corrupted on User Message Activity Report.
[CSCtz57174](#) : Unity Connection Office 365 user templates missing "Service Capabilities
[CSCtz44627](#) : Unity connection Message Notification to Pager via TUI failing
[CSCtz93540](#) : Unified messaging account template missing MbxSync check-bo
[CSCtz32273](#) : Bulk Edit overwriting notification device field
[CSCts18127](#) : CUCA- certificate validation field missing on UMS page
[CSCtz61387](#) : Office365 Enhancement - change default user count per streaming thread
[CSCtz67753](#) : UC Direct Routing rule has issue with complex pattern with mutiple +
[CSCty85181](#) : Default Outdial Restriction Table is blocking the LDAP import of users
[CSCtq97369](#) : L2 upgrade 8.6.1.10000-26->8.6.1.10000-43 fails when locales installed
[CSCtz03307](#) : Upgrade fail on switchversion, if image is not loaded on both servers
[CSCtz44199](#) : Internal Software Error when recording greetings by phone in G.729a
[CSCtx01018](#) : Sametime Cisco VM/ CUPC. intermittent issue after perm. deleting VM
[CSCtx98015](#) : Digital Networking not working due to Digital Certificate Error
[CSCtx82397](#) : Office 365- Partner EWS URL/RTT/Request Id enhancement for O365
[CSCtz01067](#) : UC - Response to CUSP SIP OPTIONS Ping Erroneously Starts New TCP Conn.
[CSCtz00747](#) : incorrect calculation of jitter on G.722 calls
[CSCty46836](#) : CUCMBE 8.6 - UC Services Page Does Not Load After Admin User Name Change
[CSCty91526](#) : Office 365- Remove false errors from CuMbxSync log
[CSCtz31973](#) : Ews request printed is Null in case of StreamingSubscriptionRequest
[CSCtz31625](#) : CuMbxSync Cores while logging Autodiscovery diagnostics
[CSCtz19034](#) : UC 8.6(2) - Applying SIB UM Service to Users Marks All Msgs Unread
[CSCtx73576](#) : MWI doesn't turned off when message is read from Outlook SIB.
[CSCtz06132](#) : Autodiscovery-HTTP retry should be done only after http response 302/30

[CSCty54264](#) : After Upgrade ,Minimum password change interval default is not applied.

[CSCtx64076](#) : CO-RES Unity connection RU fails with no indications

[CSCts98388](#) : JETTY logs filling up root partition

[CSCty92204](#) : Expired password Users logging into WEB INBOX not notified to change pwd

[CSCtw50373](#) : Greetings Page needs more space betw Manage Greetings text and dropdown

[CSCts40400](#) : Pinging to Office 365 from Connection gives error in Test button

[CSCts12265](#) : Manual statistics still running while installation

[CSCtw98515](#) : UC - User does not show up as a Importable LDAP user after being deleted

[CSCtw80619](#) : Tomcat Crash

[CSCtu37485](#) : Hard deletes not honored when deleting from Outlook/Single Inbox

[CSCty64122](#) : trap call through VMO is not working when primary server is down

[CSCty57873](#) : SIB-on exchange, message moved to inbox subfolder gets deleted

[CSCtx42518](#) : CUNI- Subscription doesnt work on providing eventtype in request.

[CSCtx42500](#) : CUNI- Blank "Username" value results in error in subscription

[CSCtx42481](#) : CUNI- Blank "KeepAliveInterval" value results in error in subscription

[CSCts38146](#) : IMAP login fails when the password contains a backslash

[CSCtr63630](#) : Special chars in Display Name get NDR w/ENU text, garbled recips, uncaps

[CSCtw90439](#) : Unity Connection 8.x ports hung in attemp-sign-in

[CSCty05524](#) : UC 8.6.2.21009-1 - IMAP authentication failed when using LDAP directory

[CSCts21051](#) : Introduce new cli command to do a system health check preupgrade

[CSCto82536](#) : JPNUCWeb Inbox

[CSCto82544](#) : JPNUCMBCS user name is garbled on delivery notification.

[CSCtr54911](#) : ALL-LANG Inbox scrambling Display Names using advanced characters

[CSCtx67995](#) : RU from 8.5.1.12900-7 to 8.6(2a) fails at csp_RefreshFolderCounts()

[CSCtn78617](#) : TUI Conversation Message Count Enumeration should be Streamlined.

[CSCtt02014](#) : Unity Connection Upgrade checks "Use System Default Time Zone"

[CSCtw97101](#) : CUPI For Clients does not allow user added alt. ext. to be deleted.

[CSCtx27391](#) : Web based applications stop working after accessing Visual Voice mail

[CSCtx17088](#) : Sending voice mail failed through Web Inbox

[CSCtw78512](#) : CUC 8.5 unified messaging doesn't handle 2010 Exchange http 307 response

[CSCtw48736](#) : New JDK Version needed to Address Published Vulnerabilities

[CSCtq75677](#) : Mailbox quota taking 0 value in warning, send and Send/Receive Quota

[CSCtw49761](#) : Inbox slider gets IE error popups when a voice mail is highlighted

[CSCtx31456](#) : Failsafe observed while recording messag

[CSCtx00608](#) : CUC can't download CTL file when signaling preference on CUC set to be v6

[CSCtw88093](#) : Visual Voicemail in CUC 8.6 doesn't support +E164

[CSCtv22318](#) : BAT - cannot add User Template as a Distribution List member

[CSCtr73642](#) : Tomcat core at the Cisco Production site.

[CSCto94090](#) : cuc_er_sbspace meta-data full message

[CSCtu36143](#) : DST- Update CUC to Olson TZ version 2011h

[CSCtu21705](#) : Messages sent via API/TRaP stored in replicated folder

[CSCtu00812](#) : ConvMgr service dumps core due to SSL race condition

[CSCtw82039](#) : Getting System prompt as Voicemail while using the Supervise transfer

[CSCtw63233](#) : ALL-LANG- CUC- PCA- "About" window cannot be resized on IE.

[CSCtt21815](#) : ETSGJ-CH-CUC 8.6 Japanese option is not shown in System Default Language

[CSCts41146](#) : COMET subscriptions not cleaned up after tomcat service restart

[CSCtr58704](#) : TRAP failure - DB Pool Exhausted errors observed in REST API load run

[CSCtr53806](#) : TRAP Failure - No Trap calls gets through and getting to out of memory

[CSCtr53798](#) : TRAP Failure - CALL_DISCONNECTED errors observed in Grinder on TRAP loa
[CSCtu10118](#) : Unity ConnectionUnable to login to SA / IMS failure on upgrade
[CSCtw45220](#) : Secure IPv6 SIP call from CUCM fails with SSL error
[CSCtu28082](#) : BMs being sent to all vmus if recording is started, even if unaddressed
[CSCtt15340](#) : CUC breaks voicemail phone notification conversation
[CSCts49940](#) : Pub out of memory and CuMbxSync core on sub with load
[CSCtu27492](#) : Bulk Edit doesn't clean up some references
[CSCtu13113](#) : Tomcat core during the load run of 1000 VVM users
[CSCtt29323](#) : Subscription expires before expiry time due to Timezone calculations.
[CSCtt22097](#) : Voice mail size doubles when secure message is sent across digital nodes
[CSCtt12039](#) : Items (emails) dropped to Voicemail Outbox are HARD DELETED
[CSCtu32200](#) : Web InboxDeleting a message, plays it again.
[CSCtt21713](#) : UC 8.6.1.20000-1 - IMAP authentication failed when using LDAP directory
[CSCtr55114](#) : CPCA- CiscoIT - searching for users to add to privateDL takes 35 seconds
[CSCtt26472](#) : Cisco Unity Connection displays multiple "Extension" options in drop-do
[CSCtt22188](#) : Delay when accessing sub when pub is down
[CSCtu22092](#) : cpcsa Greetings page fails, MM applet problem
[CSCtq27478](#) : CUC 8.02 Notifier Exception generates too many errors
[CSCtr87537](#) : AA Call doesn't reach to VM if transferred Line is busy with other Call
[CSCtt11530](#) : Unable to get a list of users on a subscription
[CSCts52434](#) : Tomcat core found on subscriber during perf load in A/A
[CSCtr90951](#) : CUCMBE License information failed to generate in RTMT
[CSCts94906](#) : Unity Connection 8.5.1-CuCsMgr Diagnostic function is crashing
[CSCts01666](#) : CUMI Marking Read status Authentication Error and wrong return code
[CSCtr14827](#) : CUPI Validation in Notification Devecas
[CSCts58716](#) : "Null" Error in Import Users page in CUC when importing users using AXL
[CSCtk52978](#) : Delay in synchronization of SIB messages to Blackberry devices via BES
[CSCts28305](#) : UMS types not updated upon upgradation to Version 8.6.2.10000-76
[CSCts21141](#) : SIB-Re-enable Unified Messaging service, deleted message resync'd as new
[CSCts20300](#) : DL error in Diginet logs.
[CSCts04354](#) : InboxMessage download link not visible
[CSCts00519](#) : SIB VM moved out of/back into inbox folder not resync'd to CUC inbox
[CSCtr99813](#) : distorted message playback with g729 packet size 60
[CSCtr92721](#) : Potential message loss under heavy replication traffic with Smarthosts
[CSCtr88176](#) : Nuanceerrorcode when edited doing insertion instead of updation
[CSCtr87565](#) : Not able to create mailbox during load
[CSCtr73722](#) : "Hosted Exchange" ambiguous in unified messaging services8.6
[CSCtr67494](#) : Inbox- Play button missing on forwarded messages
[CSCtr66675](#) : Incorrect message duration shown for a message on Web Inbox
[CSCtr57540](#) : Inbox- Auto-complete recipients does not place cursor at end of line
[CSCtr57522](#) : Using next/previous selectors after refreshing displays incorrect page
[CSCtr57508](#) : Inbox- Buttons for Inbox, Deleted, and Sent are not rendered on page
[CSCtr57448](#) : User is incorrectly prompted with "No audio detected" error
[CSCtr50458](#) : CuMixer Core Dumps during SRTTP Decryption
[CSCtr48816](#) : Inbox- Chrome cannot playback messages via PC more than once
[CSCtr43963](#) : DN- Conflicting DL names can stop replication
[CSCtr01316](#) : StackOverflowError when doing screenshot
[CSCtr00153](#) : Getting failsafe instead of the record beep when attempting to leave msg

[CSCts54240](#) : French/German characters in Exchange Display cause Single Inbox issue
[CSCts49598](#) : SEC-MIN-INTV- Minimum password change interval default is not applied
[CSCts49106](#) : SMPP Port numbers only accepting 4 digit range
[CSCts44047](#) : DN- Replicator unable to sync delete user request to remote nodes
[CSCts42794](#) : SIB - Fea-req to have IP addr override in notif reg for BPOS-D

Open Caveats

Open Caveats for Cisco Unified Communications Manager Release 8.6(2a)SU3 describes a few of the possible unexpected behaviors still remaining in Cisco Unified Communications Manager Release 8.6(2a)SU3. For a complete list of open caveats please access the bug toolkit located at: <http://tools.cisco.com/Support/BugToolkit/>



Tip

For more information about an individual defect, click the associated Identifier in the to access the online record for that defect, including workarounds.

Open Caveats

[CSCuf93840](#) : 6901/6911 SR Phone loads are not reported correctly in builds
[CSCtw95413](#) : Critical BIOS Ver 2011.05.05 (6 Jul 2011) update HP ProLiant DL380 G6
[CSCty45858](#) : Failed Refresh Upgrade from 6.1(x) hangs during fall back
[CSCty42884](#) : cimserver core during shutdown on 782514
[CSCtt44392](#) : Increase log file size for informix in CAR
[CSCua79544](#) : Frequent CCM Process Cores Due to High Disk I/O
[CSCud80319](#) : RU upgrade gets stuck while upgrading from 803.24054-1 to 862.23061-1

Firmware / Device Loads

SUs contain firmware loads, however, Cisco recommends that you always download the latest firmware load from the Voice Software Download Center.

Phone Firmware

To download phone firmware, follow this procedure:

Step 1 Go <http://www.cisco.com/cisco/software/navigator.html?mdfid=278875240&i=rp>

Step 2 Select **IP Telephony** in the right most column

Step 3 Select **IP Phones** in the right most column

Step 4 Select the desired phone series in the right most column

Step 5 Select the desired phone model in the right most column

Step 6 From the options that display, select the desired software type for your deployment.

Device Packages

Firmware upgrades not explicitly addressed in the Phone Firmware section can be obtained via Dev Packs. To download Dev Packs for this release, follow this procedure:

Step 1 Go <http://www.cisco.com/cisco/software/navigator.html?mdfid=278875240&i=rp>

Step 2 Select **IP Telephony** in the right most column

Step 3 Select **Call Control** in the right most column

Step 4 Select **Cisco Unified Communications Manager** in the right most column

Step 5 Select **Cisco Unified Communications Manager Version 8.6** in the right most column

Step 6 From the options that display, select **Unified Communications Manager/CallManager Device Packages**

Step 7 From the options that display, select the desired release for your deployment.

Firmware Versions in this Release

Device type	Load name	Version
3905	3905.9-2-2-0	9.2(2.0)
3911_3951-sip	3911_3951-sip.8-1-4a	8.1(4.0)
6608	6608-4.0.0.32-mgcp	4.0(0.32)
6608cfb	6608cfb-4.0.0.03-sccp	4.0(0.3)
6608mtp	6608mtp-4.0.0.06-sccp	4.0(0.6)
6624	6624-4.0.0.13-mgcp	4.0(0.13)
6901_6911-sccp	6901_6911-sccp.9-3-1-SR1-3	9.3(1.0)
6901_6911-sip	6901_6911-sip.9-3-1-SR1-3	9.3(1.0)
6945-sccp	6945-sccp.9-3-3-2	9.3(3.2)
6945-sip	6945-sip.9-3-3-2	9.3(3.2)
69xx-sccp	69xx-sccp.9-3-3-2	9.3(3.2)
69xx-sip	69xx-sip.9-3-3-2	9.3(3.2)
7902	7902-8.0.2-sccp	8.0(2.0)
7905	7905-8.0.1.1-sip	8.0(1.1)
7905	7905-8.0.3-sccp	8.0(3.0)
7910	7910-5.0.7.0-sccp	5.0(7.0)
7911_7906-sccp	7911_7906-sccp.9-3-1SR1-1	9.3(1SR1.1)
7911_7906-sip	7911_7906-sip.9-3-1SR1-1	9.3(1SR1.1)
7912	7912-8.0.1.1-sip	8.0(1.1)
7912	7912-8.0.4-sccp	8.0(4.0)
7914-sccp	7914-sccp.5-0-4	5.0(4.0)
7915	7915.1-0-4-2	1.0(4.2)
7916	7916.1-0-4-2	1.0(4.2)
7920-sccp	7920-sccp.3-0-2	3.0(2.0)
7921-sccp	7921-sccp.1-4-4-3	1.4(4.3)
7925-sccp	7925-sccp.1-4-4-3	1.4(4.3)
7926-sccp	7926-sccp.1-4-4-3	1.4(4.3)
7931-sccp	7931-sccp.9-3-1SR1-1	9.3(1SR1.1)
7931-sip	7931-sip.9-3-1SR1-1	9.3(1SR1.1)
7935-sccp	7935-sccp.3-2-19	3.2(19.0)

7936-sccp	7936-sccp.3-3-21	3.3(21.0)
7937	7937-1-4-4-SCCP	1.4(4.0)
7940-7960	7940-7960-8.12.00-sip	8.12(00.0)
7940-7960-sccp	7940-7960-sccp.8-1-2	8.1(2.0)
7941_7961-sccp	7941_7961-sccp.9-3-1SR1-1	9.3(1SR1.1)
7941_7961-sip	7941_7961-sip.9-3-1SR1-1	9.3(1SR1.1)
7942_7962-sccp	7942_7962-sccp.9-3-1SR1-1	9.3(1SR1.1)
7942_7962-sip	7942_7962-sip.9-3-1SR1-1	9.3(1SR1.1)
7945_7965-sccp	7945_7965-sccp.9-3-1SR1-1	9.3(1SR1.1)
7945_7965-sip	7945_7965-sip.9-3-1SR1-1	9.3(1SR1.1)
7970_7971-sccp	7970_7971-sccp.9-3-1SR1-1	9.3(1SR1.1)
7970_7971-sip	7970_7971-sip.9-3-1SR1-1	9.3(1SR1.1)
7975-sccp	7975-sccp.9-3-1SR1-1	9.3(1SR1.1)
7975-sip	7975-sip.9-3-1SR1-1	9.3(1SR1.1)
7985	7985-4-1-7-0-sccp	4.1(7.0)
8941_8945-sccp	8941_8945-sccp.9-3-2-11	9.3(2.11)
8941_8945-sip	8941_8945-sip.9-3-2-12	9.3(2.12)
8961	8961.9-3-2-10	9.3(2.10)
9951	9951.9-3-2-10	9.3(2.10)
9971	9971.9-3-2-10	9.3(2.10)
ata	ata-3.2.4-sccp	3.2(4.0)
ata187	ata187.9-2-3-1	9.2(3.1)
cius	cius.9-2-4-45	9.2(4.45)
ciusSP	ciusSP.9-2-4-45	9.2(4.45)

Cisco Unity Connection RPMs

CCM Reference Build: 8.6.2.23900-10

Cisco Unity RPMs:

BuiltRPMsList

NRec-9.0-14.i386-rhel3.rpm
 NRec-en-US-9.0-0.i386-rhel3.rpm
 NSS-5.0.9-201001141015.i386-linux.rpm
 NuanceVersion-4.0.3.3-50.i386.rpm
 cuc-8.6.2ES69.23900-69.i386.rpm
 cuc-base-8.6.2ES69.23900-69.i386.rpm
 cuc-bin-8.6.2ES69.23900-69.i386.rpm
 cuc-etc-8.6.2ES69.23900-69.i386.rpm
 cuc-install-8.6.2ES69.23900-69.i386.rpm
 cuc-jetty-8.6.2ES69.23900-69.i386.rpm
 cuc-languagepack-enu-8.6.2ES69.23900-69.i386.rpm
 cuc-lib-ext-8.6.2ES69.23900-69.i386.rpm
 cuc-lib-jar-8.6.2ES69.23900-69.i386.rpm
 cuc-lib-so-8.6.2ES69.23900-69.i386.rpm
 cuc-links-8.6.2ES69.23900-69.i386.rpm
 cuc-productid-8.6.2ES69.23900-69.i386.rpm
 cuc-python-8.6.2ES69.23900-69.i386.rpm

cuc-python-site-8.6.2ES69.23900-69.i386.rpm
 cuc-selinux-8.6.2ES69.23900-69.i386.rpm
 cuc-share-8.6.2ES69.23900-69.i386.rpm
 nvn-American-English-en-US-Samantha-5.0.0-9133.i386.rpm
 nvn-api-5.0.2-10035.i386.rpm
 openssl097a-0.9.7a-9.el5_4.2.i386.rpm

Plug-In Report

 cm-taps-plugin-7.0.2.0-1.i386.rpm
 cm-axlsqlltoolkit-plugin-1.1.0.0-1.i386.rpm
 cm-tsp-plugin-8.6.2.9-0.i386.rpm
 cm-ctlc-plugin-6.0.0.1-1.i386.rpm
 cm-jtapi-plugin-8.6.2.23067-1.i386.rpm
 cm-rtmt-client-plugin-8.9.2.0-0.i386.rpm

TZDATA file

-----	Version
.platform-tzdata-2012j-1.el5.i386.rpm	2012-j

Obtaining Documentation and Submitting a Service Request

For information on obtaining documentation, submitting a service request, and gathering additional information, see the monthly *What's New in Cisco Product Documentation*, which also lists all new and revised Cisco technical documentation, at:

<http://www.cisco.com/en/US/docs/general/whatsnew/whatsnew.html>

Subscribe to the *What's New in Cisco Product Documentation* as a Really Simple Syndication (RSS) feed and set content to be delivered directly to your desktop using a reader application. The RSS feeds are a free service and Cisco currently supports RSS version 2.0.

Cisco and the Cisco Logo are trademarks of Cisco Systems, Inc. and/or its affiliates in the U.S. and other countries. A listing of Cisco's trademarks can be found at www.cisco.com/go/trademarks. Third party trademarks mentioned are the property of their respective owners. The use of the word partner does not imply a partnership relationship between Cisco and any other company. (1005R)

Any Internet Protocol (IP) addresses and phone numbers used in this document are not intended to be actual addresses and phone numbers. Any examples, command display output, network topology diagrams, and other figures included in the document are shown for illustrative purposes only. Any use of actual IP addresses or phone numbers in illustrative content is unintentional and coincidental.

© 2013 Cisco Systems, Inc. All rights reserved.

