

Set Home From the WebSphere Administrative Console

Document ID: 71567

Introduction

Prerequisites

Components Used

Conventions

Background Information

NetPro Discussion Forums – Featured Conversations

Related Information

Introduction

This document explains how users who run Cisco Unified Call Services, Universal Edition, on WebSphere can set the Audium Home JVM property to the location of their Audium Home directory with the WebSphere Administrative Console. Additionally, this document explains how users in general can set to Audium Home, without the use of WebSphere.

Prerequisites

Components Used

The information in this document is based on Cisco Unified Call Services, Universal Edition.

Conventions

Refer to Cisco Technical Tips Conventions for more information on document conventions.

Background Information

This document explains how users who run Cisco Unified Call Services, Universal Edition, on WebSphere can set the Home JVM property to the location of their Home directory with the WebSphere Administrative Console.

Symptoms: Cisco Unified Call Services needs to know the location of its data directory, called Audium Home. The developer wants to declare the location of this directory with a JVM variable in WebSphere.

Resolution: In order to declare the location of Audium Home from within the WebSphere Administrative Console, follow these steps:

1. Open the Administrative Console in a web browser, and log in.
2. Click **Servers**.
3. Click **Application Servers**.
4. Click the name of the server that runs Cisco Unified Call Services from the list that displays.
5. Scroll down and click **Process Definition**.
6. Scroll down and click **Java Virtual Machine**.

7. Scroll down and click **Custom Properties**.
8. Click **New**.
9. Set the name of the new property to **Home**. Set the value of the property to the location of your Audium Home directory. For example, on Windows the default location is c:\program files\Audium\CallServices.
10. Click **OK**.
11. Click the word **Save** in the message that displays on the top of the page:

Changes have been made to your local configuration.
Click **Save** to apply changes to the master configuration.

12. Click the **Save** button.

Note: Cisco Unified Call Services must be restarted for this change to take effect.

NetPro Discussion Forums – Featured Conversations

Networking Professionals Connection is a forum for networking professionals to share questions, suggestions, and information about networking solutions, products, and technologies. The featured links are some of the most recent conversations available in this technology.

NetPro Discussion Forums – Featured Conversations for Voice
Service Providers: Voice over IP
Voice & Video: Voice over IP
Voice & Video: IP Telephony
Voice & Video: IP Phone Services for End Users
Voice & Video: Unified Communications
Voice & Video: IP Phone Services for Developers
Voice & Video: General

Related Information

- [Technical Support & Documentation – Cisco Systems](#)

All contents are Copyright © 2006–2007 Cisco Systems, Inc. All rights reserved. Important Notices and Privacy Statement.

Updated: Jul 03, 2007

Document ID: 71567
