

## User Locales for Unified CM Auto-Register Phone Tool

Administrators can specify the languages for TAPs voice prompts by using the User Locales for Unified CM Auto-Register Phone Tool option. You can configure user prompts for Unified CM Auto-Register Phone Tool in several languages. Make sure that the Cisco Unified CallManager Locale Installer is installed on every Cisco Unified CallManager and Cisco CRS server in the cluster.

Using the locale installer ensures that you have the latest translated text, translated voice prompts, country-specific phone tones, and country-specific gateways tones that are available for the phones. For more information on the Cisco Unified CallManager Locale Installer, refer to the specific locale installer documentation.



**Note**

You have to select at least one user locale for Unified CM Auto-Register Phone Tool to work.

## Setting the User Locales for Unified CM Auto-Register Phone Tool

Use the following procedures to add or remove languages for Unified CM Auto-Register Phone Tool prompts:

- [Adding Languages for Unified CM Auto-Register Phone Tool Prompts, page 53-1](#)
- [Removing Languages for Unified CM Auto-Register Phone Tool Prompts, page 53-2](#)

## Adding Languages for Unified CM Auto-Register Phone Tool Prompts

To set the languages for Unified CM Auto-Register Phone Tool prompts, use the following procedure.

### Procedure

- Step 1** In the Cisco Unified CallManager Administration window, choose **Bulk Administration > Unified CM Auto-Register Phone Tool > User Locales for Unified CM Auto-Register Phone Tool**. The User Locales Configuration window displays.

- Step 2** In the User Locales list box, which is the list of languages that are installed on Cisco Unified CallManager, choose the languages that you want to use for user prompts. Click the arrow to move the chosen language to the Selected User Locales list box.
- You can choose as many languages as you need for user prompts and move them to the Selected User Locales list box.
- Step 3** After you have chosen the languages for user prompts, to create a job, click **Submit**.
- Step 4** Use the Job Scheduler option in the Bulk Administration main menu to schedule and/or activate this job. For more information on jobs, see the [Chapter 51, “Scheduling Jobs.”](#) For information on log files, see [“BAT Log Files” section on page 54-3.](#)
- 

#### Additional Topics

See the [“Related Topics” section on page 53-3.](#)

## Removing Languages for Unified CM Auto-Register Phone Tool Prompts

To remove the languages for Unified CM Auto-Register Phone Tool prompts, use the following procedure.

#### Procedure

- Step 1** Choose **Bulk Administration > Unified CM Auto-Register Phone Tool > User Locales for Unified CM Auto-Register Phone Tool**. The Select User Locales window displays. The User Locales Configuration window displays.
- Step 2** In the Selected User Locales list box, which is the list of languages that is chosen for user prompts, choose the language that you want to remove.
- Step 3** Click the arrow to move the chosen language to the User Locales list box.
- You can choose one or many languages from user prompts and move them to the User Locales list box.
- Step 4** Click **Submit**. A status message indicates that the update is complete.
- Step 5** To return to the Unified CM Auto-Register Phone Tool Options window, click **Back**.
- 

#### Additional Topics

See the [“Related Topics” section on page 53-3.](#)

## Unified CM Auto-Register Phone Tool Information for End Users

To configure your new phone, use this procedure.

#### Procedure

- Step 1** Plug the phone into a port.

The phone automatically registers and displays a number.



---

**Note** It takes around 20-25 seconds for downloading phone profile and making necessary updates in first node and directory.

---

- Step 2** Dial the CTI Route Point number provided by your system administrator and follow the prompts.
- Step 3** Dial the Unified CM Auto-Register Phone Tool extension that your system administrator provided.
- Step 4** A voice prompts you to choose the language that you want to use. Choose appropriately.
- Step 5** Dial your personal extension number, that your system administrator provided, followed by #.



---

**Note** You may be instructed to enter the complete telephone number (including area code).

---

- Step 6** To confirm, enter your personal extension number again, followed by #.  
You will receive confirmation prompt.
- Step 7** Hang up the phone.  
The phone resets and displays your extension number.
- 

If you experience any problems, contact your system administrator.

#### Additional Topics

See the [“Related Topics” section on page 53-3](#).

## Related Topics

- [Setting the User Locales for Unified CM Auto-Register Phone Tool, page 53-1](#)
- [Unified CM Auto-Register Phone Tool Information for End Users, page 53-2](#)
- [Installing Unified CM Auto-Register Phone Tool, page 52-4](#)
- [Uninstalling Unified CM Auto-Register Phone Tool, page 52-5](#)
- [Activating Unified CM Auto-Register Phone Tool Service, page 52-6](#)
- [Starting/Stopping/Restarting Unified CM Auto-Register Phone Tool, page 52-6](#)
- [Setting Unified CM Auto-Register Phone Tool Options, page 52-7](#)
- [Setting Secure Directory Numbers, page 52-8](#)

