



IP Phone Messenger Settings

Use IP Phone Messenger (IPPM) settings to configure the settings that apply to all IPPM users.

Configuring IPPM Settings

Follow this procedure to configure the IPPM settings.

Procedure

- Step 1** Choose **Application > IP Phone Messenger > Settings**.
The IP Phone Messenger Settings window displays.
- Step 2** Enter the appropriate settings as described in [Table 21-1](#).
- Step 3** To save the data, click the **Save** icon that displays in the tool bar in the upper, left corner of the window (or click the **Save** button that displays at the bottom of the window).

Table 21-1 IP Phone Messenger Configuration Settings

Field	Description
IPPM Application Status	This parameter toggles the application on and off.
Application Username	This parameter specifies the default application username.
Application Password	This parameter specifies the default application password.
Max Contact List Size	The parameter specifies the maximum size for a contact list. Range: 0–100 contacts
Max Instant Message History Size	This parameter specifies the maximum number of history messages. Range: 1–1000 messages
Subscription Timeout (seconds)	This parameter specifies the subscription timeout. Range: 100–86400 seconds
Publish Timeout (seconds)	This parameter specifies the publish timeout. Range: 300–86400 seconds

