

Configuring the Integrated Browser Home Page

- Step 1** Choose **View > Preferences**. The Preferences window appears.
- Step 2** Select the **Enable Integrated Browser** check box.
- Step 3** In the left pane, select the **Browser** node.
- Step 4** In the right pane, select a browser tab. Enter an URL in the Browser home page field and click **OK**.

Setting Preferences

- Step 1** Choose **View > Preferences**. The Preferences window appears.
- Step 2** In the left pane, select a node. The right pane displays that node's settings.
- Step 3** Change values as desired, then click **OK**.

Setting Up a Supervisor Work Flow

NOTE: "Skill group" is another term for "contact service queue".

- Step 1** Choose **Tools > Supervisor Work Flow Administrator**.
- Step 2** Click **Add**. The Add New Work Flow window appears.
- Step 3** Type a name, then click **OK**. The Skill Group Selection window appears.
- Step 4** Select a skill group from the Available Skill Groups list, then click the left arrow. Repeat if additional skill groups are desired. Click **OK** when done.
- Step 5** In the Supervisor Work Flow Setup window, complete the following steps.
 - a.** Select one or both of the Calls Waiting and Current Oldest check boxes.
 - b.** Set the upper and lower limits for the threshold(s) you selected.
 - c.** Add the actions to be triggered when the threshold(s) is/are crossed.
- Step 6** Click **OK** twice to enable the work flow and exit Work Flow Administrator.

Americas Headquarters
Cisco Systems, Inc.
170 West Tasman Drive
San Jose, CA 95134-1706
USA
<http://www.cisco.com>
Tel: 408 526-4000
800 553-NETS (6387)
Fax: 408 527-0883

Cisco and the Cisco Logo are trademarks of Cisco Systems, Inc. and/or its affiliates in the U.S. and other countries. A listing of Cisco's trademarks can be found at <http://www.cisco.com/go/trademarks>. Third party trademarks mentioned are the property of their respective owners. The use of the word partner does not imply a partnership relationship between Cisco and any other company. (1005R)
Any Internet Protocol (IP) addresses used in this document are not intended to be actual addresses. Any examples, command display output, and figures included in the document are shown for illustrative purposes only. Any use of actual IP addresses in illustrative content is unintentional and coincidental.
© 2010 Cisco Systems, Inc. All rights reserved.
© 2010 Calabrio, Inc. All rights reserved.



QUICK START GUIDE




Cisco Supervisor Desktop

Cisco Unified Contact Center Enterprise Release 9.0






- 1** Toolbar Buttons and Keyboard Shortcuts
- 2** Common Tasks

1 Toolbar Buttons and Keyboard Shortcuts



Refreshing the Data Display

Icon Name	Shortcut	Description
 Refresh	Ctrl+F	Refreshes the information in the data view pane.



Changing Agent State

Icon Name	Shortcut	Description
 Logout	Ctrl+L	Logs the selected agent out of the ACD.
 Ready	Ctrl+E	Changes the selected agent's state to Ready.
 Not Ready	Ctrl+N	Changes the selected agent's state to Not Ready.
 Work Ready	Ctrl+D	Changes the selected agent's state to Work Ready.
 Work Not Ready	Ctrl+Y	Changes the selected agent's state to Work Not Ready.



Call Handling

Icon Name	Shortcut	Description
 Barge-in	Ctrl+B	Enables you to join an agent's phone conversation.
 Intercept	Ctrl+I	Enables you to intercept a call while disconnecting the agent from the call.




Team Communication

Icon Name	Shortcut	Description
 Chat	Ctrl+J	Opens the Chat Selection window.
 Team Message	Ctrl+X	Opens the Team Message window.

Recording

Icon Name	Shortcut	Description
 Start Record	Ctrl+R	(Enhanced/Premium only). Starts recording the selected call.
 Stop Record	Ctrl+S	(Enhanced/Premium only). Stops recording the selected call.

Voice Monitoring

Icon Name	Shortcut	Description
 Start Voice Monitor	Ctrl+A	Starts monitoring the selected agent.
 Stop Voice Monitor	Ctrl+P	Stops monitoring the selected agent.
 Voice monitor volume	Ctrl+V	Opens a volume slider control.

2 Common Tasks

Sending Chat Messages

- Step 1** On the toolbar, click **Chat**. The Chat Selection window opens.
- Step 2** Select the names of one or more people, then choose **Actions > Chat**.
- Step 3** In the Chat Session window, type your message. To make your message pop on the recipient's screen, select the **High** priority check box.
- Step 4** Click **Send** or press **Enter**.

Sending Team Messages

- Step 1** Select a team, then click **Team Message**.
- Step 2** Type a message or select one of the last 10 messages that you sent.
- Step 3** If desired, enter a different expiration time. The default is 30 minutes. (To stop a message before it expires, click **Stop**.)
- Step 4** Click **Start**, then **Close**. All agents on your team who are running Agent Desktop will receive the message, even if they are not logged into the ACD.

Reviewing and Archiving Recordings

- Step 1** Choose **Tools > Recorded Files**. The Supervisor Record Viewer window appears.
- Step 2** Select the day that has the recordings you want to review or archive. To display recordings saved for 30 days, click **Extended Lifetime**.
- Step 3** Select a recording, then choose one of the following operations.
 - To review the recording, click **Play**.
 - To tag the recording for extended archiving, click **Set Extended Lifetime**. The recording will be saved for 30 days.

Pushing a Web Page to an Agent

- Step 1** Select the agent to whom you want to push a page from the Agent tree.
- Step 2** Choose **Intervention > Coach by Pushing a Page**.
- Step 3** Type or select a URL, then click **Push**.