



APPENDIX **A**

Provisioning Default Values for Maximum Calls and Busy Trigger Attributes

Maximum Calls and Busy Trigger are Line provisioning attributes that Provisioning Manager sets with default values based on the phone type. [Table A-1](#) lists the default values that Provisioning Manager sets for each phone type.

Table A-1 *Default Settings for Maximum Calls and Busy Trigger Provisioning Attributes*

Product	Maximum Calls	Busy Trigger
Analog Phones	1	1
CTI Port	4	2
Cisco 3905	2	2
Cisco 6901	2	2
Cisco 6911	2	2
Cisco 6921	2	1
Cisco 6941	2	1
Cisco 6945	2	1
Cisco 6961	2	1
Cisco 7902	2	2
Cisco 7905	4	2
Cisco 7905 (SIP)	2	2
Cisco 7906	4	2
Cisco 7906 (SIP)	4	2
Cisco 7910	2	2
Cisco 7911	4	2
Cisco 7911 (SIP)	4	2
Cisco 7912	4	2
Cisco 7912 (SIP)	2	2
Cisco 7920	2	2
Cisco 7921	4	2

Table A-1 Default Settings for Maximum Calls and Busy Trigger Provisioning Attributes (continued)

Product	Maximum Calls	Busy Trigger
Cisco 7925	4	2
Cisco 7926 G	4	2
Cisco 7931	1	1
Cisco 7935	2	1
Cisco 7936	2	1
Cisco 7937	6	2
Cisco 7940	4	2
Cisco 7940 (SIP)	2	2
Cisco 7941	4	2
Cisco 7941 (SIP)	4	2
Cisco 7941G-GE	4	2
Cisco 7941G-GE (SIP)	4	2
Cisco 7942	4	2
Cisco 7942 (SIP)	4	2
Cisco 7945	4	2
Cisco 7945 (SIP)	4	2
Cisco 7960	4	2
Cisco 7960 (SIP)	2	2
Cisco 7961	4	2
Cisco 7961 (SIP)	4	2
Cisco 7961G-GE	4	2
Cisco 7961G-GE (SIP)	4	2
Cisco 7962	4	2
Cisco 7962 (SIP)	4	2
Cisco 7965	4	2
Cisco 7965 (SIP)	4	2
Cisco 7970	4	2
Cisco 7970 (SIP)	4	2
Cisco 7971	4	2
Cisco 7971 (SIP)	4	2
Cisco 7975	4	2
Cisco 7975 (SIP)	4	2
Cisco 7985	4	2
Cisco 8941	3	2
Cisco 8945	3	2
Cisco 8961(SIP)	4	2

Table A-1 Default Settings for Maximum Calls and Busy Trigger Provisioning Attributes (continued)

Product	Maximum Calls	Busy Trigger
Cisco 9951(SIP)	4	2
Cisco 9971 (SIP)	4	2
Cisco IP Communicator	4	2
Cisco IP Communicator (SIP)	4	2
Cisco ATA-186	2	2
Cisco ATA-187	2	2
Cisco Dual Mode for Android	3	2
Cisco Cius	4	2
Cisco E20	5	2
Cisco 12-S	2	2
Cisco 12-SP	2	2
Cisco 12- SP+	2	2
Cisco 30-SP+	2	1
Cisco Dual Mode for iPhone	3	2
Cisco Unified Client Services Framework	6	2
Cisco Unified Personal Communicator	6	2
Cisco 30-VIP	2	1
Nokia S60 ¹	3	2
Remote Destination Profile	2	2
Third-party SIP device (advanced)	2	2
Third-party SIP device (basic)	2	2

1. After upgrade new phones like Nokia and iPhone cannot be ordered by default. You must associate these new phone types to the appropriate user types.

