



## Uninstalling the Plug-in 1.0(4) and Higher

---

This chapter includes the following sections:

- [Uninstalling the Cisco UCS Manager Plug-in, page 1](#)

## Uninstalling the Cisco UCS Manager Plug-in

For vRealize Orchestrator 7.x, you can disable the plug-in from the **vRealize Orchestrator Control Center** page. However, this does not remove the plug-in file from the file system.

If you want to disable the plug-in, click the **Plug-ins** tab, uncheck the **UCS Manager plug-in** check box, and click **Apply Changes**.

### Before You Begin

You must have admin permissions to log in to the machine on which the vRealize Orchestrator server is installed.

## Procedure

- 
- Step 1** Log in to the Orchestrator appliance through any SSH client and navigate to the path `/var/lib/vco/app-server`.
- Step 2** Delete the plug-in.dar file from the following path `plugins > ucsmplugin_x_x_x_x.dar`, where `x_x_x_x` is the version number.
- Step 3** Open the configuration file from the `- conf > plugins > _VSOPuginInstallationVersion.xml` path, and if the line `<entry key="UCSM">x.x.x.x</entry>` exists in the file, delete it. The `x.x.x.x` is the version number. Save and close the file after change.
- Step 4** Log in to the vRealize Orchestrator client.
- Step 5** From the drop-down list, select **Design** on the top left edge of the client.
- Step 6** Click the **Workflows** view.
- Step 7** Expand **Cisco UCS Manager Workflows > Configuration > Remove a UCS Domain Instance**.
- Step 8** Right-click **Remove a UCS Domain Instance** and select **Start Workflow**.
- Step 9** From the list of installed UCS domain instances, select the instance which you want to remove, and click **Submit**.
- Step 10** Click the **Packages** view. Right-click the package **com.cisco.ucs.mgr** and select **Delete**.
- Step 11** On the confirmation dialog box, click **Delete Package**.
- Step 12** To delete an element with the content, follow these steps:
- Expand **Tool > User Preferences**.
  - Check the **Delete non empty folder permitted** check box.
  - From the **Workflows** view, right-click the **UCS Manager** folder and click **Delete**.
  - Click the **Actions** view. Right-click the modules which you want to remove and click **Delete**.
- Step 13** Restart the plug-in.  
To restart, follow these steps:
- Log in to vRealize Orchestrator Control Center.
  - Click the **Startup Options** tab, and click **Restart**.
-