

# **Create Default Service Profile**

- Overview of service profile, on page 1
- Create default service profile, on page 2

## **Overview of service profile**

Figure 1: Service profiles workflow



**1.** Create UC services.

- 2. Associate the UC Service with the Service Profile.
- 3. Associate the User with the Service Profile.

## **Create default service profile**

Create a service profile to add the UC services.

#### Procedure

Step 1	Open the <b>Cisco Unified CM Administration</b> interface.	
Step 2	Select User Management > User Settings > Service Profile. The Find and List Service Profiles window opens.	
Step 3	Select Add New. The Service Profile Configuration window opens.	
Step 4	Enter a name for the service profile in the Name field.	
Step 5	Select <b>Make this the default service profile for the system</b> if you want the service profile to be the default for the cluster.	
	Note	On Cisco Unified Communications Manager release 9.x only, users who have IM only capabilities must use the default service profile. For this reason, select <b>Use Default</b> .

### Step 6 Select Save.

#### What to do next

Create the UC services for your deployment.