



# Nnrf\_NFManagement

---

The Nnrf\_NFManagement service allows a Network Function instance in the serving PLMN to register, update or deregister its profile in the NRF.

It also allows an NF to subscribe to be notified of newly registered NF instances along with their NF services.

The NF profile consists of NF instance parameters. It also consists of different services parameters exposed by the NF Instance.

**Reference:** 3GPP TS 29.510 version 15.1.0 Release 15

- [OpenAPI, on page 1](#)
- [Info, on page 1](#)
- [Servers, on page 1](#)
- [Security, on page 2](#)
- [Paths, on page 2](#)
- [Components, on page 10](#)
- [External Docs, on page 28](#)

## OpenAPI

OpenAPI Version: 3.0.0

## Info

**Version:** '1.0.0'  
**Title:** 'NRF NFManagement Service'  
**Description:** 'NRF NFManagement Service'

## Servers

**URL:** '{apiRoot}/nnrf-nfm/v1'  
**Variables:**  
    **API Root:**

**Default:** https://example.com

**Description:** apiRoot as defined in subclause subclause 4.4 of 3GPP TS 29.501

## Security

```
- {}
- oAuth2ClientCredentials:
  - nnrf-nfm
```

## Paths

### /nf-instances

#### get:

**Summary:** Retrieves a collection of NF Instances

**Operation ID:** GetNFInstances

#### Tags:

- NF Instances (Store)

#### Parameters:

- **Name:** nf-type

**In:** query

**Description:** Type of NF

**Required/Optional:** false

#### Schema:

**Reference:** '#/components/schemas/NFType'

- **Name:** limit

**In:** query

**Description:** How many items to return at one time

**Required/Optional:** false

#### Schema:

**Type:** integer

#### Responses:

'200':

**Description:** Expected response to a valid request

#### Content:

**application/3gppHal+json:**

#### Schema:

**Type:** object

#### Properties:

**\_links:**

**Type:** object

**Description:** 'List of the URI of NF instances. It has two members whose names are item and self. The item one contains an array of URIs.'

#### additionalProperties:

**Reference:**

```
'TS29571_CommonData.yaml#/components/schemas/LinksValueSchema'
  minProperties: 1
  '400':
    Reference: 'TS29571_CommonData.yaml#/components/responses/400'
  '403':
    Reference: 'TS29571_CommonData.yaml#/components/responses/403'
  '404':
    Reference: 'TS29571_CommonData.yaml#/components/responses/404'
  '411':
    Reference: 'TS29571_CommonData.yaml#/components/responses/411'
  '413':
    Reference: 'TS29571_CommonData.yaml#/components/responses/413'
  '415':
    Reference: 'TS29571_CommonData.yaml#/components/responses/415'
  '500':
    Reference: 'TS29571_CommonData.yaml#/components/responses/500'
  '501':
    Reference: 'TS29571_CommonData.yaml#/components/responses/501'
  '503':
    Reference: 'TS29571_CommonData.yaml#/components/responses/503'
  Default:
    Reference: 'TS29571_CommonData.yaml#/components/responses/default'
```

## /nf-instances/{nfInstanceId}

**get:****Summary:** Read the profile of a given NF Instance**Operation ID:** GetNFInstance**Tags:**

- NF Instance ID (Document)

**Parameters:**- **Name:** nfInstanceId**In:** path**Description:** Unique ID of the NF Instance**Required/Optional:** true**Schema:****Reference:** 'TS29571\_CommonData.yaml#/components/schemas/NfInstanceId'**Responses:**

'200':

**Description:** Expected response to a valid request**Content:****Application/JSON:****Schema:****Reference:** '#/components/schemas/NFProfile'

'400':

**Reference:** 'TS29571\_CommonData.yaml#/components/responses/400'

'403':

```

    Reference: 'TS29571_CommonData.yaml#/components/responses/403'
  '404':
    Reference: 'TS29571_CommonData.yaml#/components/responses/404'
  '411':
    Reference: 'TS29571_CommonData.yaml#/components/responses/411'
  '413':
    Reference: 'TS29571_CommonData.yaml#/components/responses/413'
  '415':
    Reference: 'TS29571_CommonData.yaml#/components/responses/415'
  '500':
    Reference: 'TS29571_CommonData.yaml#/components/responses/500'
  '501':
    Reference: 'TS29571_CommonData.yaml#/components/responses/501'
  '503':
    Reference: 'TS29571_CommonData.yaml#/components/responses/503'
  Default:
    Reference: 'TS29571_CommonData.yaml#/components/responses/default'
put:
  Summary: Register a new NF Instance
  Operation ID: RegisterNFInstance

  Tags:
    - NF Instance ID (Document)

  Parameters:
    - Name: nfInstanceId
      In: path
      Required/Optional: true
      Description: Unique ID of the NF Instance to register
      Schema:
        Reference: 'TS29571_CommonData.yaml#/components/schemas/NfInstanceId'
  Request Body:
    Content:
      Application/JSON:
        Schema:
          Reference: '#/components/schemas/NFProfile'
      Required/Optional: true

  Responses:
    '200':
      Description: OK (Profile Replacement)
      Content:
        Application/JSON:
          Schema:
            Reference: '#/components/schemas/NFProfile'
    '201':
      Description: Expected response to a valid request
      Content:
        Application/JSON:
          Schema:
            Reference: '#/components/schemas/NFProfile'
  Headers:

```

**Location:**  
**description:** 'Contains the URI of the newly created resource, according to the structure: {apiRoot}/nnrf-nfm/v1/nf-instances/{nfInstanceId}'  
**Required/Optional:** true  
**Schema:**  
**Type:** string

'400':  
**Reference:** 'TS29571\_CommonData.yaml#/components/responses/400'

'403':  
**Reference:** 'TS29571\_CommonData.yaml#/components/responses/403'

'404':  
**Reference:** 'TS29571\_CommonData.yaml#/components/responses/404'

'411':  
**Reference:** 'TS29571\_CommonData.yaml#/components/responses/411'

'413':  
**Reference:** 'TS29571\_CommonData.yaml#/components/responses/413'

'415':  
**Reference:** 'TS29571\_CommonData.yaml#/components/responses/415'

'500':  
**Reference:** 'TS29571\_CommonData.yaml#/components/responses/500'

'501':  
**Reference:** 'TS29571\_CommonData.yaml#/components/responses/501'

'503':  
**Reference:** 'TS29571\_CommonData.yaml#/components/responses/503'

**Default:**  
**Reference:** 'TS29571\_CommonData.yaml#/components/responses/default'

**patch:**  
**Summary:** Update NF Instance profile  
**Operation ID:** UpdateNFInstance

**Tags:**  
- NF Instance ID (Document)

**Parameters:**  
- **Name:** nfInstanceId  
**In:** path  
**Required/Optional:** true  
**Description:** Unique ID of the NF Instance to update  
**Schema:**  
**Reference:** 'TS29571\_CommonData.yaml#/components/schemas/NfInstanceId'

**Request Body:**  
**Content:**  
**application/json-patch+json:**  
**Schema:**  
**Type:** array  
**Items:**  
**Reference:** 'TS29571\_CommonData.yaml#/components/schemas/PatchItem'  
**Min Items:** 1  
**Required/Optional:** true

**Responses:**  
'200':

```

Description: Expected response to a valid request
Content:
  Application/JSON:
    Schema:
      Reference: '#/components/schemas/NFProfile'
'204':
  Description: Expected response with empty body
'400':
  Reference: 'TS29571_CommonData.yaml#/components/responses/400'
'403':
  Reference: 'TS29571_CommonData.yaml#/components/responses/403'
'404':
  Reference: 'TS29571_CommonData.yaml#/components/responses/404'
'411':
  Reference: 'TS29571_CommonData.yaml#/components/responses/411'
'413':
  Reference: 'TS29571_CommonData.yaml#/components/responses/413'
'415':
  Reference: 'TS29571_CommonData.yaml#/components/responses/415'
'500':
  Reference: 'TS29571_CommonData.yaml#/components/responses/500'
'501':
  Reference: 'TS29571_CommonData.yaml#/components/responses/501'
'503':
  Reference: 'TS29571_CommonData.yaml#/components/responses/503'
Default:
  Reference: 'TS29571_CommonData.yaml#/components/responses/default'
delete:
Summary: Deregisters a given NF Instance
Operation ID: DeregisterNFInstance

Tags:
  - NF Instance ID (Document)

Parameters:
  - Name: nfInstanceId
    In: path
    Required/Optional: true
    Description: Unique ID of the NF Instance to deregister
    Schema:
      Reference: 'TS29571_CommonData.yaml#/components/schemas/NfInstanceId'

Responses:
  '204':
    Description: Expected response to a successful deregistration

```

## /subscriptions

```

Method: Post
Summary: Create a new subscription
Operation ID: CreateSubscription

```

```

Tags:
  - Subscriptions (Collection)
Request Body:
  Content:
    Application/JSON:
      Schema:
        Reference: '#/components/schemas/SubscriptionData'
      Required/Optional: true

Responses:
  '201':
    Description: Expected response to a valid request
    Content:
      Application/JSON:
        Schema:
          Reference: '#/components/schemas/SubscriptionData'
    Headers:
      Location:
        description: 'Contains the URI of the newly created resource,
        according to the structure: {apiRoot}/nnrf-nfm/v1/subscriptions/{subscriptionId}'
        Required/Optional: true
        Schema:
          Type: string
  '400':
    Reference: 'TS29571_CommonData.yaml#/components/responses/400'
  '403':
    Reference: 'TS29571_CommonData.yaml#/components/responses/403'
  '404':
    Reference: 'TS29571_CommonData.yaml#/components/responses/404'
  '411':
    Reference: 'TS29571_CommonData.yaml#/components/responses/411'
  '413':
    Reference: 'TS29571_CommonData.yaml#/components/responses/413'
  '415':
    Reference: 'TS29571_CommonData.yaml#/components/responses/415'
  '500':
    Reference: 'TS29571_CommonData.yaml#/components/responses/500'
  '501':
    Reference: 'TS29571_CommonData.yaml#/components/responses/501'
  '503':
    Reference: 'TS29571_CommonData.yaml#/components/responses/503'
  Default:
    Reference: 'TS29571_CommonData.yaml#/components/responses/default'

Callbacks:
  onNFStatusEvent:
    '{$request.body#/nfStatusNotificationUri}':
      Method: Post
      Request Body:
        Description: Notification Payload
        Content:
          Application/JSON:

```

**Schema:****Reference:** '#/components/schemas/NotificationData'**Responses:****'204':****Description:** Expected response to a successful callback processing**'400':****Reference:** 'TS29571\_CommonData.yaml#/components/responses/400'**'403':****Reference:** 'TS29571\_CommonData.yaml#/components/responses/403'**'404':****Reference:** 'TS29571\_CommonData.yaml#/components/responses/404'**'411':****Reference:** 'TS29571\_CommonData.yaml#/components/responses/411'**'413':****Reference:** 'TS29571\_CommonData.yaml#/components/responses/413'**'415':****Reference:** 'TS29571\_CommonData.yaml#/components/responses/415'**'500':****Reference:** 'TS29571\_CommonData.yaml#/components/responses/500'**'501':****Reference:** 'TS29571\_CommonData.yaml#/components/responses/501'**'503':****Reference:** 'TS29571\_CommonData.yaml#/components/responses/503'**Default:****Reference:** 'TS29571\_CommonData.yaml#/components/responses/default'

## /subscriptions/{subscriptionID}

**patch:****Summary:** Updates a subscription**Operation ID:** UpdateSubscription**Tags:**

- Subscription ID (Document)

**Parameters:**- **Name:** subscriptionID**In:** path**Required/Optional:** true**Description:** Unique ID of the subscription to update**Schema:****Type:** string**pattern:** '^([0-9]{5,6}-)?[^-]+\$'**Request Body:****Content:****application/json-patch+json:****Schema:****Type:** array**Items:****Reference:** 'TS29571\_CommonData.yaml#/components/schemas/PatchItem'



**Required/Optional:** true

**Responses:**

'200':

**Description:** Expected response to a valid request

**Content:**

**Application/JSON:**

**Schema:**

**Reference:** '#/components/schemas/SubscriptionData'

'204':

**Description:** No Content

'400':

**Reference:** 'TS29571\_CommonData.yaml#/components/responses/400'

'403':

**Reference:** 'TS29571\_CommonData.yaml#/components/responses/403'

'404':

**Reference:** 'TS29571\_CommonData.yaml#/components/responses/404'

'411':

**Reference:** 'TS29571\_CommonData.yaml#/components/responses/411'

'413':

**Reference:** 'TS29571\_CommonData.yaml#/components/responses/413'

'415':

**Reference:** 'TS29571\_CommonData.yaml#/components/responses/415'

'500':

**Reference:** 'TS29571\_CommonData.yaml#/components/responses/500'

'501':

**Reference:** 'TS29571\_CommonData.yaml#/components/responses/501'

'503':

**Reference:** 'TS29571\_CommonData.yaml#/components/responses/503'

**Default:**

**Reference:** 'TS29571\_CommonData.yaml#/components/responses/default'

**delete:**

**Summary:** Deletes a subscription

**Operation ID:** RemoveSubscription

**Tags:**

- Subscription ID (Document)

**Parameters:**

- **Name:** subscriptionID

**In:** path

**Required/Optional:** true

**Description:** Unique ID of the subscription to remove

**Schema:**

**Type:** string

**pattern:** '^([0-9]{5,6}-)?[^-]+\$'

**Responses:**

'204':

**Description:** Expected response to a successful subscription removal

'400':

**Reference:** 'TS29571\_CommonData.yaml#/components/responses/400'

```

'403':
  Reference: 'TS29571_CommonData.yaml#/components/responses/403'
'404':
  Reference: 'TS29571_CommonData.yaml#/components/responses/404'
'411':
  Reference: 'TS29571_CommonData.yaml#/components/responses/411'
'413':
  Reference: 'TS29571_CommonData.yaml#/components/responses/413'
'415':
  Reference: 'TS29571_CommonData.yaml#/components/responses/415'
'500':
  Reference: 'TS29571_CommonData.yaml#/components/responses/500'
'501':
  Reference: 'TS29571_CommonData.yaml#/components/responses/501'
'503':
  Reference: 'TS29571_CommonData.yaml#/components/responses/503'
Default:
  Reference: 'TS29571_CommonData.yaml#/components/responses/default'

```

## Components

```

securitySchemes:
  OAuth2ClientCredentials:
    Type: oauth2
    Flows:
      clientCredentials:
        tokenUrl: '/oauth2/token'
        scopes:
          nnrf-nfm: Access to the Nnrf_NFManagement API

schemas:
  NFProfile:
    Type: object
    Required:
      - nfInstanceId
      - nfType
      - nfStatus
    anyOf:
      - required: [ fqdn ]
      - required: [ ipv4Addresses ]
      - required: [ ipv6Addresses ]
    Properties:
      nfInstanceId:
        Reference: 'TS29571_CommonData.yaml#/components/schemas/NfInstanceId'
      nfType:
        Reference: '#/components/schemas/NFType'
      nfStatus:
        Reference: '#/components/schemas/NFStatus'
      heartBeatTimer:
        Type: integer

```

```
plmnList:
  Type: array
  Items:
    Reference: 'TS29571_CommonData.yaml#/components/schemas/PlmnId'
  minItems: 1
sNssais:
  Type: array
  Items:
    Reference: 'TS29571_CommonData.yaml#/components/schemas/Snssai'
  minItems: 1
nsiList:
  Type: array
  Items:
    Type: string
  minItems: 1
fqdn:
  Reference: '#/components/schemas/Fqdn'
interPlmnFqdn:
  Reference: '#/components/schemas/Fqdn'
ipv4Addresses:
  Type: array
  Items:
    Reference: 'TS29571_CommonData.yaml#/components/schemas/Ipv4Addr'
  minItems: 1
ipv6Addresses:
  Type: array
  Items:
    Reference: 'TS29571_CommonData.yaml#/components/schemas/Ipv6Addr'
  minItems: 1
allowedPlmns:
  Type: array
  Items:
    Reference: 'TS29571_CommonData.yaml#/components/schemas/PlmnId'
  minItems: 1
allowedNfTypes:
  Type: array
  Items:
    Reference: '#/components/schemas/NFType'
  minItems: 1
allowedNfDomains:
  Type: array
  Items:
    Type: string
  minItems: 1
allowedNssais:
  Type: array
  Items:
    Reference: 'TS29571_CommonData.yaml#/components/schemas/Snssai'
  minItems: 1
priority:
  Type: integer
```

```

    Minimum: 0
    Maximum: 65535
  capacity:
    Type: integer
    Minimum: 0
    Maximum: 65535
  load:
    Type: integer
    Minimum: 0
    Maximum: 100
  locality:
    Type: string
  udrInfo:
    Reference: '#/components/schemas/UdrInfo'
  udmInfo:
    Reference: '#/components/schemas/UdmInfo'
  ausfInfo:
    Reference: '#/components/schemas/AusfInfo'
  amfInfo:
    Reference: '#/components/schemas/AmfInfo'
  smfInfo:
    Reference: '#/components/schemas/SmfInfo'
  upfInfo:
    Reference: '#/components/schemas/UpfInfo'
  pcfInfo:
    Reference: '#/components/schemas/PcfInfo'
  bsfInfo:
    Reference: '#/components/schemas/BsfInfo'
  chfInfo:
    Reference: '#/components/schemas/ChfInfo'
  nrfInfo:
    Reference: '#/components/schemas/NrfInfo'
  customInfo:
    Type: object
  recoveryTime:
    Reference: 'TS29571_CommonData.yaml#/components/schemas/DateTime'
  nfServicePersistence:
    Type: boolean
    Default: false
  nfServices:
    Type: array
    Items:
      Reference: '#/components/schemas/NFService'
    minItems: 1
  NFService:
    Type: object
  Required:
    - serviceInstanceId
    - serviceName
    - versions
    - scheme
    - nfServiceStatus

```

```
Properties:
  serviceInstanceId:
    Type: string
  serviceName:
    Reference: '#/components/schemas/ServiceName'
  versions:
    Type: array
    Items:
      Reference: '#/components/schemas/NFServiceVersion'
    minItems: 1
  scheme:
    Reference: 'TS29571_CommonData.yaml#/components/schemas/UriScheme'
  nfServiceStatus:
    Reference: '#/components/schemas/NFServiceStatus'
  fqdn:
    Reference: '#/components/schemas/Fqdn'
  interPlmnFqdn:
    Reference: '#/components/schemas/Fqdn'
  ipEndPoints:
    Type: array
    Items:
      Reference: '#/components/schemas/IpEndPoint'
    minItems: 1
  apiPrefix:
    Type: string
  defaultNotificationSubscriptions:
    Type: array
    Items:
      Reference: '#/components/schemas/DefaultNotificationSubscription'
    minItems: 1
  allowedPlmns:
    Type: array
    Items:
      Reference: 'TS29571_CommonData.yaml#/components/schemas/PlmnId'
    minItems: 1
  allowedNfTypes:
    Type: array
    Items:
      Reference: '#/components/schemas/NFType'
    minItems: 1
  allowedNfDomains:
    Type: array
    Items:
      Type: string
    minItems: 1
  allowedNssais:
    Type: array
    Items:
      Reference: 'TS29571_CommonData.yaml#/components/schemas/Snssai'
    minItems: 1
  priority:
```

```

    Type: integer
    Minimum: 0
    Maximum: 65535
capacity:
    Type: integer
    Minimum: 0
    Maximum: 65535
load:
    Type: integer
    Minimum: 0
    Maximum: 100
recoveryTime:
    Reference: 'TS29571_CommonData.yaml#/components/schemas/DateTime'
chfServiceInfo:
    Reference: '#/components/schemas/ChfServiceInfo'
supportedFeatures:
    Reference: 'TS29571_CommonData.yaml#/components/schemas/SupportedFeatures'
NFType:
anyOf:
  - type: string
    enum:
    - NRF
    - UDM
    - AMF
    - SMF
    - AUSF
    - NEF
    - PCF
    - SMSF
    - NSSF
    - UDR
    - LMF
    - GMLC
    - 5G_EIR
    - SEPP
    - UPF
    - N3IWF
    - AF
    - UDSE
    - BSF
    - CHF
    - NWDAF
  - type: string
Fqdn:
Type: string
IpEndPoint:
Type: object
Properties:
  ipv4Address:
    Reference: 'TS29571_CommonData.yaml#/components/schemas/Ipv4Addr'
  ipv6Address:
    Reference: 'TS29571_CommonData.yaml#/components/schemas/Ipv6Addr'
  transport:
    Reference: '#/components/schemas/TransportProtocol'
  port:
    Type: integer

```

```

    Minimum: 0
    Maximum: 65535
SubscriptionData:
  Type: object
  Required:
    - nfStatusNotificationUri
    - subscriptionId
  Properties:
    nfStatusNotificationUri:
      Type: string
    subscrCond:
      oneOf:
        - $ref: '#/components/schemas/NfInstanceIdCond'
        - $ref: '#/components/schemas/NfTypeCond'
        - $ref: '#/components/schemas/ServiceNameCond'
        - $ref: '#/components/schemas/AmfCond'
        - $ref: '#/components/schemas/GuamiListCond'
        - $ref: '#/components/schemas/NetworkSliceCond'
        - $ref: '#/components/schemas/NfGroupCond'
    subscriptionId:
      Type: string
      Pattern: '^[0-9]{5,6}-)?[^-]+$'
      readOnly: true
    validityTime:
      Reference: 'TS29571_CommonData.yaml#/components/schemas/DateTime'
    reqNotifEvents:
      Type: array
      Items:
        Reference: '#/components/schemas/NotificationEventType'
      minItems: 1
    plmnId:
      Reference: 'TS29571_CommonData.yaml#/components/schemas/PlmnId'
    notifCondition:
      Reference: '#/components/schemas/NotifCondition'
    reqNfType:
      Reference: '#/components/schemas/NFType'
    reqNfFqdn:
      Reference: '#/components/schemas/Fqdn'
NfInstanceIdCond:
  Type: object
  Required:
    - nfInstanceId
  Properties:
    nfInstanceId:
      Reference: 'TS29571_CommonData.yaml#/components/schemas/NfInstanceId'
NfTypeCond:
  Type: object
  Required:
    - nfType
  Properties:
    nfType:
      Reference: '#/components/schemas/NFType'
ServiceNameCond:
  Type: object

```

```

Required:
  - serviceName
Properties:
  serviceName:
    Reference: '#/components/schemas/ServiceName'
AmfCond:
Type: object
anyOf:
  - required: [ amfSetId ]
  - required: [ amfRegionId ]
Properties:
  amfSetId:
    Type: string
  amfRegionId:
    Type: string
GuamiListCond:
Type: object
Required:
  - guamiList
Properties:
  guamiList:
    Type: array
    Items:
      Reference: 'TS29571_CommonData.yaml#/components/schemas/Guami'
NetworkSliceCond:
Type: object
Required:
  - snssaiList
Properties:
  snssaiList:
    Type: array
    Items:
      Reference: 'TS29571_CommonData.yaml#/components/schemas/Snssai'
  nsiList:
    Type: array
    Items:
      Type: string
NfGroupCond:
Type: object
Required:
  - nfType
  - nfGroupId
Properties:
  nfType:
    Type: string
    enum:
      - UDM
      - AUSF
      - UDR
  nfGroupId:
    Reference: 'TS29571_CommonData.yaml#/components/schemas/NfGroupId'
NotifCondition:
Type: object

```



```

not:
  Required: [ monitoredAttributes, unmonitoredAttributes ]
Properties:
  monitoredAttributes:
    Type: array
    Items:
      Type: string
    minItems: 1
  unmonitoredAttributes:
    Type: array
    Items:
      Type: string
    minItems: 1
UdrInfo:
  Type: object
Properties:
  groupId:
    Reference: 'TS29571_CommonData.yaml#/components/schemas/NfGroupId'
  supiRanges:
    Type: array
    Items:
      Reference: '#/components/schemas/SupiRange'
    minItems: 1
  gpsiRanges:
    Type: array
    Items:
      Reference: '#/components/schemas/IdentityRange'
    minItems: 1
  externalGroupIdentifiersRanges:
    Type: array
    Items:
      Reference: '#/components/schemas/IdentityRange'
    minItems: 1
  supportedDataSets:
    Type: array
    Items:
      Reference: '#/components/schemas/DataSetId'
    minItems: 1
SupiRange:
  Type: object
Properties:
  start:
    Type: string
    Pattern: '^[0-9]+$'
  end:
    Type: string
    Pattern: '^[0-9]+$'
  Pattern:
    Type: string
IdentityRange:
  Type: object

```

```

Properties:
  start:
    Type: string
    Pattern: '^[0-9]+$'
  end:
    Type: string
    Pattern: '^[0-9]+$'
  Pattern:
    Type: string
DataSetId:
  anyOf:
    - type: string
    enum:
      - SUBSCRIPTION
      - POLICY
      - EXPOSURE
      - APPLICATION
    - type: string
UdmInfo:
  Type: object
  Properties:
    groupId:
      Reference: 'TS29571_CommonData.yaml#/components/schemas/NfGroupId'
    supiRanges:
      Type: array
      Items:
        Reference: '#/components/schemas/SupiRange'
      minItems: 1
    gpsiRanges:
      Type: array
      Items:
        Reference: '#/components/schemas/IdentityRange'
      minItems: 1
    externalGroupIdentifiersRanges:
      Type: array
      Items:
        Reference: '#/components/schemas/IdentityRange'
      minItems: 1
    routingIndicators:
      Type: array
      Items:
        Type: string
        Pattern: '^[0-9]{1,4}$'
      minItems: 1
AusfInfo:
  Type: object
  Properties:
    groupId:
      Reference: 'TS29571_CommonData.yaml#/components/schemas/NfGroupId'
    supiRanges:
      Type: array
      Items:
        Reference: '#/components/schemas/SupiRange'

```

```

        minItems: 1
    routingIndicators:
        Type: array
        Items:
            Type: string
            Pattern: '^[0-9]{1,4}$'
        minItems: 1
AmfInfo:
    Type: object
    Required:
        - amfSetId
        - amfRegionId
        - guamiList
    Properties:
        amfSetId:
            Type: string
        amfRegionId:
            Type: string
        guamiList:
            Type: array
            Items:
                Reference: 'TS29571_CommonData.yaml#/components/schemas/Guami'
            minItems: 1
        taiList:
            Type: array
            Items:
                Reference: 'TS29571_CommonData.yaml#/components/schemas/Tai'
            minItems: 1
        taiRangeList:
            Type: array
            Items:
                Reference: '#/components/schemas/TaiRange'
            minItems: 1
        backupInfoAmfFailure:
            Type: array
            Items:
                Reference: 'TS29571_CommonData.yaml#/components/schemas/Guami'
            minItems: 1
        backupInfoAmfRemoval:
            Type: array
            Items:
                Reference: 'TS29571_CommonData.yaml#/components/schemas/Guami'
            minItems: 1
        n2InterfaceAmfInfo:
            Reference: '#/components/schemas/N2InterfaceAmfInfo'
SmfInfo:
    Type: object
    Required:
        - sNssaiSmfInfoList
    Properties:
        sNssaiSmfInfoList:
            Type: array

```

```

    Items:
      Reference: '#/components/schemas/SnssaiSmfInfoItem'
    minItems: 1
  taiList:
    Type: array
    Items:
      Reference: 'TS29571_CommonData.yaml#/components/schemas/Tai'
    minItems: 1
  taiRangeList:
    Type: array
    Items:
      Reference: '#/components/schemas/TaiRange'
    minItems: 1
  pgwFqdn:
    Reference: '#/components/schemas/Fqdn'
  accessType:
    Type: array
    Items:
      Reference: 'TS29571_CommonData.yaml#/components/schemas/AccessType'
    minItems: 1
SnssaiSmfInfoItem:
  Type: object
  Required:
    - sNssai
    - dnnSmfInfoList
  Properties:
    sNssai:
      Reference: 'TS29571_CommonData.yaml#/components/schemas/Snssai'
    dnnSmfInfoList:
      Type: array
      Items:
        Reference: '#/components/schemas/DnnSmfInfoItem'
      minItems: 1
DnnSmfInfoItem:
  Type: object
  Required:
    - dnn
  Properties:
    dnn:
      Reference: 'TS29571_CommonData.yaml#/components/schemas/Dnn'
UpfInfo:
  Type: object
  Required:
    - sNssaiUpfInfoList
  Properties:
    sNssaiUpfInfoList:
      Type: array
      Items:
        Reference: '#/components/schemas/SnssaiUpfInfoItem'
      minItems: 1
    smfServingArea:
      Type: array

```

```

    Items:
      Type: string
    minItems: 1
  interfaceUpfInfoList:
    Type: array
    Items:
      Reference: '#/components/schemas/InterfaceUpfInfoItem'
    minItems: 1
  iwkEpsInd:
    Type: boolean
    Default: false
  SnsaiUpfInfoItem:
    Type: object
    Required:
      - sNssai
      - dnnUpfInfoList
    Properties:
      sNssai:
        Reference: 'TS29571_CommonData.yaml#/components/schemas/Snsai'
      dnnUpfInfoList:
        Type: array
        Items:
          Reference: '#/components/schemas/DnnUpfInfoItem'
        minItems: 1
  DnnUpfInfoItem:
    Type: object
    Required:
      - dnn
    Properties:
      dnn:
        Reference: 'TS29571_CommonData.yaml#/components/schemas/Dnn'
      dnaiList:
        Type: array
        Items:
          Reference: 'TS29571_CommonData.yaml#/components/schemas/Dnai'
        minItems: 1
  InterfaceUpfInfoItem:
    Type: object
    Required:
      - interfaceType
    Properties:
      interfaceType:
        Reference: '#/components/schemas/UPInterfaceType'
      ipv4EndpointAddresses:
        Type: array
        Items:
          Reference: 'TS29571_CommonData.yaml#/components/schemas/Ipv4Addr'
        minItems: 1
      ipv6EndpointAddresses:
        Type: array
        Items:
          Reference: 'TS29571_CommonData.yaml#/components/schemas/Ipv6Addr'

```

```

    minItems: 1
    endpointFqdn:
      Reference: '#/components/schemas/Fqdn'
    networkInstance:
      Type: string
  UPInterfaceType:
    anyOf:
      - type: string
        enum:
          - N3
          - N6
          - N9
      - type: string
  PcfInfo:
    Type: object
    Properties:
      dnnList:
        Type: array
        Items:
          Reference: 'TS29571_CommonData.yaml#/components/schemas/Dnn'
          minItems: 1
      supiRanges:
        Type: array
        Items:
          Reference: '#/components/schemas/SupiRange'
          minItems: 1
      rxDiamHost:
        Reference: 'TS29571_CommonData.yaml#/components/schemas/DiameterIdentity'
      rxDiamRealm:
        Reference: 'TS29571_CommonData.yaml#/components/schemas/DiameterIdentity'
  BsfInfo:
    Type: object
    Properties:
      dnnList:
        Type: array
        Items:
          Reference: 'TS29571_CommonData.yaml#/components/schemas/Dnn'
          minItems: 1
      ipDomainList:
        Type: array
        Items:
          Type: string
          minItems: 1
      ipv4AddressRanges:
        Type: array
        Items:
          Reference: '#/components/schemas/Ipv4AddressRange'
          minItems: 1
      ipv6PrefixRanges:
        Type: array
        Items:
          Reference: '#/components/schemas/Ipv6PrefixRange'

```

```

    minItems: 1
ChfInfo:
  Type: object
  Properties:
    supiRangeList:
      Type: array
      Items:
        Reference: '#/components/schemas/SupiRange'
      minItems: 1
    gpsiRangeList:
      Type: array
      Items:
        Reference: '#/components/schemas/IdentityRange'
      minItems: 1
    plmnRangeList:
      Type: array
      Items:
        Reference: '#/components/schemas/PlmnRange'
      minItems: 1
Ipv4AddressRange:
  Type: object
  Properties:
    start:
      Reference: 'TS29571_CommonData.yaml#/components/schemas/Ipv4Addr'
    end:
      Reference: 'TS29571_CommonData.yaml#/components/schemas/Ipv4Addr'
Ipv6PrefixRange:
  Type: object
  Properties:
    start:
      Reference: 'TS29571_CommonData.yaml#/components/schemas/Ipv6Prefix'
    end:
      Reference: 'TS29571_CommonData.yaml#/components/schemas/Ipv6Prefix'
DefaultNotificationSubscription:
  Type: object
  Required:
    - notificationType
    - callbackUri
  Properties:
    notificationType:
      Reference: '#/components/schemas/NotificationType'
    callbackUri:
      Reference: 'TS29571_CommonData.yaml#/components/schemas/Uri'
    n1MessageClass:
      Reference: 'TS29518_Namf_Communication.yaml#/components/schemas/N1MessageClass'
    n2InformationClass:
      Reference: 'TS29518_Namf_Communication.yaml#/components/schemas/N2InformationClass'

NotificationType:
  anyOf:
    - type: string
    enum:

```

```

- N1_MESSAGES
- N2_INFORMATION
- LOCATION_NOTIFICATION
- DATA_REMOVAL_NOTIFICATION
- DATA_CHANGE_NOTIFICATION
- type: string
TransportProtocol:
  anyOf:
    - type: string
      enum:
        - TCP
    - type: string
NotificationEventType:
  anyOf:
    - type: string
      enum:
        - NF_REGISTERED
        - NF_DEREGISTERED
        - NF_PROFILE_CHANGED
    - type: string
NotificationData:
  Type: object
  Required:
    - event
    - nfInstanceUri
  allOf:
    - anyOf:
      - not:
          Properties:
            event:
              Type: string
              enum:
                - NF_PROFILE_CHANGED
            - oneOf:
              - required: [ nfProfile ]
              - required: [ profileChanges ]
    - anyOf:
      - not:
          Properties:
            event:
              Type: string
              enum:
                - NF_REGISTERED
            - required: [ nfProfile ]
  Properties:
    event:
      Reference: '#/components/schemas/NotificationEventType'
    nfInstanceUri:
      Reference: 'TS29571_CommonData.yaml#/components/schemas/Uri'
    nfProfile:
      allOf:
        - $ref: '#/components/schemas/NFProfile'
        - not:
            Required: [ interPlmnFqdn ]
      - properties:
          nfServices:
            Type: array

```



```

    Items:
      allOf:
        - $ref: '#/components/schemas/NFService'
        - not:
            Required: [ interPlmnFqdn ]
        - not:
            Required: [ allowedPlmns ]
        - not:
            Required: [ allowedNfTypes ]
        - not:
            Required: [ allowedNfDomains ]
        - not:
            Required: [ allowedNssais ]
  profileChanges:
    Type: array
    Items:
      Reference: 'TS29571_CommonData.yaml#/components/schemas/ChangeItem'
    minItems: 1
  NFStatus:
    anyOf:
      - type: string
        enum:
          - REGISTERED
          - SUSPENDED
      - type: string
  NFServiceVersion:
    Type: object
    Required:
      - apiVersionInUri
      - apiFullVersion
    Properties:
      apiVersionInUri:
        Type: string
      apiFullVersion:
        Type: string
      expiry:
        Reference: 'TS29571_CommonData.yaml#/components/schemas/DateTime'
  ServiceName:
    anyOf:
      - type: string
        enum:
          - nnrf-nfm
          - nnrf-disc
          - nudm-sdm
          - nudm-uecm
          - nudm-ueau
          - nudm-ee
          - nudm-pp
          - namf-comm
          - namf-evts
          - namf-mt
          - namf-loc
          - nsmf-pdusession
          - nsmf-event-exposure
          - nausf-auth
          - nausf-sorprotection
          - nnef-pfdmanagement

```

```

- npcf-am-policy-control
- npcf-smpolicycontrol
- npcf-policyauthorization
- npcf-bdtpolicycontrol
- npcf-eventexposure
- npcf-ue-policy-control
- nsmsf-sms
- nnsf-nssselection
- nnsf-nssaiavailability
- nudr-dr
- nlmf-loc
- n5g-eir-eic
- nbsf-management
- nchf-spendinglimitcontrol
- nchf-convergedcharging
- nnwdaf-eventssubscription
- nnwdaf-analyticsinfo
- type: string

```

**N2InterfaceAmfInfo:**

**Type:** object

**Properties:**

**ipv4EndpointAddress:**

**Type:** array

**Items:**

**Reference:** 'TS29571\_CommonData.yaml#/components/schemas/Ipv4Addr'

**minItems:** 1

**ipv6EndpointAddress:**

**Type:** array

**Items:**

**Reference:** 'TS29571\_CommonData.yaml#/components/schemas/Ipv6Addr'

**minItems:** 1

**amfName:**

**Reference:** 'TS29571\_CommonData.yaml#/components/schemas/AmfName'

**NFServiceStatus:**

**anyOf:**

- type: string
- enum:**
  - REGISTERED
  - SUSPENDED
- type: string

**TaiRange:**

**Type:** object

**Required:**

- plmnId
- tacRangeList

**Properties:**

**plmnId:**

**Reference:** 'TS29571\_CommonData.yaml#/components/schemas/PlmnId'

**tacRangeList:**

**Type:** array

**Items:**

**Reference:** '#/components/schemas/TacRange'

**minItems:** 1

**TacRange:**

**Type:** object

**Properties:**

```

    start:
      Type: string
      Pattern: '^[A-Za-f0-9]{4}|[A-Za-f0-9]{6}$'
    end:
      Type: string
      Pattern: '^[A-Za-f0-9]{4}|[A-Za-f0-9]{6}$'
    Pattern:
      Type: string
  ChfServiceInfo:
    Type: object
    not:
      Required: [ primaryChfServiceInstance, secondaryChfServiceInstance ]
    Properties:
      primaryChfServiceInstance:
        Type: string
      secondaryChfServiceInstance:
        Type: string
  PlmnRange:
    Type: object
    Properties:
      start:
        Type: string
        Pattern: '^[0-9]{3}[0-9]{2,3}$'
      end:
        Type: string
        Pattern: '^[0-9]{3}[0-9]{2,3}$'
      Pattern:
        Type: string
  NrfInfo:
    Type: object
    Properties:
      servedUdrInfo:
        Type: object
        additionalProperties:
          Reference: '#/components/schemas/UdrInfo'
        minProperties: 1
      servedUdmInfo:
        Type: object
        additionalProperties:
          Reference: '#/components/schemas/UdmInfo'
        minProperties: 1
      servedAusfInfo:
        Type: object
        additionalProperties:
          Reference: '#/components/schemas/AusfInfo'
        minProperties: 1
      servedAmfInfo:
        Type: object
        additionalProperties:
          Reference: '#/components/schemas/AmfInfo'
        minProperties: 1

```

```
servedSmfInfo:
  Type: object
  additionalProperties:
    Reference: '#/components/schemas/SmfInfo'
  minProperties: 1
servedUpfInfo:
  Type: object
  additionalProperties:
    Reference: '#/components/schemas/UpfInfo'
  minProperties: 1
servedPcfInfo:
  Type: object
  additionalProperties:
    Reference: '#/components/schemas/PcfInfo'
  minProperties: 1
servedBsfInfo:
  Type: object
  additionalProperties:
    Reference: '#/components/schemas/BsfInfo'
  minProperties: 1
servedChfInfo:
  Type: object
  additionalProperties:
    Reference: '#/components/schemas/ChfInfo'
  minProperties: 1
```

## External Docs

**Description:** 3GPP TS 29.510 V15.2.0; 5G System; Network Function Repository Services; Stage 3

**URL:** '[http://www.3gpp.org/ftp/Specs/archive/29\\_series/29.510/](http://www.3gpp.org/ftp/Specs/archive/29_series/29.510/)'